

kilobaud

August 1981
USA \$2.95/DM 9.80

MICROCOMPUTING

T.M.

DESKTOP COMPUTING™


Six Unique Apple-cations



Increase Diskette Storage Eightfold ☐ Can You Top the Epson MX-80? ☐
The Sorcerer Speaks ☐ How to Maximize Profits ☐ Build a Videographic
System ☐ Coping with an Analog World ☐ TRS-80 Missile Launcher

Now! Color for Your...

SYSTEM-50




Introducing COLORAMA-50™ Percom's SS-50 Bus Color VDG

**Introductory
Price
\$219.95**

Featuring...

- **Eleven display formats** including 8-color semigraphics, 4-color graphics, 2-color high density graphics and 2-color alphanumerics.
Moreover, two- and four-color displays may be switched between primary and complementary color sets under software control or from the keyboard.
Full graphic resolutions range from 64 x 64 picture elements to 256 x 192 picture elements.
- **Instant display control:** The COLORAMA-50™ is memory mapped; your MPU has direct, instant access to display RAM and display control registers.
- **Low-cost Modulator Option for Color TV Interface:** The COLORAMA-50™ provides for installation of an inexpensive RF modulator such as Radio Shack PN 277-122 for operation using a color TV.



SS-50 Bus Department Store

Nobody supports the
SS-50 bus like Percom:

- ✓ SS-50 Bus/Single-Board Computers with I/O ports & memory
- ✓ Static and Dynamic RAM cards — memory expansion kits
- ✓ LFD-400/800 1-, 2- and 3-drive mini-disk systems
- ✓ Color and monochrome memory-mapped display controllers
- ✓ Extendable 7-slot SS-50 bus motherboards
- ✓ Versatile prototyping boards: SS-50 and SS-30 bus
- ✓ Field-proven software: monitors, operating systems, drivers, editors, assemblers, debuggers and HLLs.

- **Mix in Sound:** With the optional modulator installed, you can complement your colorful displays with software-controlled audio.
- **Extended Addressing:** The COLORAMA-50™ is compatible with the SS-50A bus and the extended-address SS-50C bus. Map the board into any of the sixteen 64-Kbyte banks of the 1-Mbyte SS-50C address space. The COLORAMA-50™ card "defaults" to the first (lowest) bank for the SS-50A bus.
- **Cassette I/O Option:** Add a few inexpensive components to the on-card circuitry provided and use an audio cassette for program/data storage.
- **Provision for On-Card Firmware:** Put your display operating system, cassette control program, etc. right on the COLORAMA-50™ card in a 2516 (5-volt 2716) EPROM. Resides in the top 2-Kbyte of the card memory space.
- **Operating Software:** Included in the comprehensive users manual is a listing of a display operating system and cassette controller that may be implemented as a callable subroutine function from BASIC or existing operating systems. The programs are optionally available in a plug-in ROM for just \$69.95.

System Requirements

The COLORAMA-50™ is pin- and outline-compatible with the Percom System-50™ bus, the SS-50A (SS-50) bus and the SS-50C bus. The composite video-sync signal output will directly drive a color (or BW) video monitor. The output may be modulated for operation with a standard (NTSC) TV set. A modulator is not included. The COLORAMA-50™ card occupies 8-Kbytes of memory in the upper half of a 64-Kbyte memory space. Included on-card is 1-Kbyte of display RAM which will accommodate alphanumeric displays, semigraphic displays and two low-density full-graphic displays. For the higher density graphic displays, additional display RAM is required. The optional RAM ICs may be installed on the card.

For quality Percom SS-50 bus products, see your nearby authorized Percom dealer. To order direct, call **toll-free, 1-800-527-1592**. Prices and specifications subject to change without notice. Prices do not include shipping and handling.

PERCOM DATA COMPANY, INC.
211 N. KIRBY GARLAND, TEXAS 75042
(214) 272-3421



™ trademark of Percom Data Company, Inc.

Most small system users think all micro-computers are created equal. And they're right. If you want performance, convenience, styling, high technology and reliability (and who doesn't?) your micro usually has a price tag that looks more like a mini. It seems big performance always means big bucks. But not so with the SuperBrain!

Standard SuperBrain features include: twin double-density 5 $\frac{1}{4}$ " drives which boast nearly 350,000 bytes of disk storage — expandable to 10 megabytes. A full 64K of dynamic RAM. A CP/M* Disk Operating System to insure compatibility to literally hundreds of application packages presently available. And, a 12" non-glare, 24 line by 80 column screen.

You'll also get a full ASCII keyboard with an 18 key numeric pad and individual cursor control keys. Twin RS232C serial ports for fast and easy connection to a modem or printer. Dual Z80 processors which operate at 4 MHz to insure lightning-fast program execution. And the list goes on! Feature after feature after feature.

Better yet, the SuperBrain boasts modular design to make servicing a snap. A common screwdriver is about the only service tool you'll ever need. And with the money you'll save on purchasing and maintaining the SuperBrain, you could almost buy another one. For under \$3,500, it is truly one of the most remarkable microcomputers available anywhere.

Whether your application is small business, scientific, educational or just word processing, the SuperBrain is certainly an exciting solution to the small computer problem. And since you can easily expand it, you'll probably never outgrow it.

Call or write us today for a complimentary copy of our "SuperBrain Buyer's Guide." We'll show you how you can get big system performance without having to spend big bucks.

**INTERTEC
DATA
SYSTEMS.**

2300 Broad River Rd. Columbia, SC 29210
(803) 798-9100 TWX: 810-666-2115

SUPERBRAIN™



MICROCOMPUTING

PUBLISHER/EDITOR

Wayne Green

EXECUTIVE VICE PRESIDENT

Sherry Smythe

EDITORIAL MANAGER

Jeff DeTray

PUBLICATIONS MANAGER

Edward Ferman

MANAGING EDITOR

Dennis Brisson

ASSISTANT MANAGING EDITOR

Susan Gross

COPY EDITOR

Eric Maloney

TECHNICAL EDITOR

Harold Nelson

EDITORIAL ASSISTANT

Lise Markus

Linda Stephenson

Betty Thayer

ADMINISTRATIVE ASSISTANTS

Pat Graham, Nancy Noyd

ASSOCIATE EDITORS

Robert Baker, Ken Barbier, Frank Derfler, Jr.,
Rod Hallen, Peter Stark, Sherm Wantz

PRODUCTION MANAGER/PUBLICATIONS

Nancy Salmon

ASSISTANT PRODUCTION MANAGER

Michael Murphy

ART DIRECTOR

Diana Shonk

ADVERTISING GRAPHICS

Robert Drew, Bruce Hedin, Steve Baldwin,
Jane Preston

PRODUCTION DEPARTMENT

Joan Ahern, Fiona Davies, Linda Drew, Bob
Dukette, Sandra Dukette, Gary Graham,
Kenneth Jackson, Ross Kenyon, Theresa
Ostebo, Dianne Ritson, Deborah Stone,
Susan Symonds, Thomas Villeneuve, Judi
Wimberly, Donna Wohlfarth

PHOTOGRAPHY

William Heydolph, Terrie Anderson,
Bill Suttentfield

TYPESETTING

Sara Bedell, Michele DesRochers, Stephen
Jewett, Luann Keddy, Mary Kinzel, Barbara
Latti, Kelly Smith, Karen Stewart

CORPORATE CONTROLLER

Charles Garniss, Jr.

EXECUTIVE ASSISTANT

Leatrice O'Neil

ACCOUNTING MANAGER

Knud Keller

CIRCULATION MANAGER

Debra Boudrieau

CIRCULATION

Doris Day, Pauline Johnstone,
Dion Owens, designer

BULK SALES MANAGER

Ginnie Boudrieau

ASSISTANT TO THE PRESIDENT

Matthew Smith

ADVERTISING

603-924-7138

Kevin Rushalko, Mgr.
Louise Caron, Hal Stephens,
Marcia Stone

APPLE

- 84 The Shiny Apple** Harold Nelson
After an inauspicious beginning, the Apple III is finally on-line.
- 85 Apples Grow Well in Dallas** Tom Lukers
A favorable climate should produce a good crop for Apple.
- 87 To Tell the Truth** David Curtis
Don't lie to your Apple when this program's running.
- 90 Down by the River** R. Deininger, R. Miller, P. Capano
Use your Apple to monitor water quality.
- 94 Apple to Selectric for 83 Cents** Charles Behrens
The price for this interface can't be beat.
- 110 Apple BASIC Prettyprinter** Michael Keith
Don't be a slob when it comes to formatting BASIC listings.
- 116 Time for the Apple** David Goss
Simplify the task of adding timekeeping ability to your Apple.
- 128 The Ten Cent Fix** Don Lancaster
Let's you hear programs as you load the tape.


BUSINESS

- 130 Put Your Micro on Wall Street** Dex Hart
Keep your portfolio up to date. Part 2.
- 158 How to Maximize Profits** James Burns
With this TRS-80 program, you can get the most out of your resources.


TRS-80

HARDWARE PROJECTS

- 56 How to Cope with an Analog World** Theodore T. Tylaska
Build a successive approximation register for use in A/D converters.
- 60 Videographic** Joe Martinka
Build a complete video system with text processing and graphics capability.
- 151 Student-Proof Your Computer** Ken Reid
You sometimes need protection from over-inquisitive minds.



Page 84.



Page 48.

Contents: August 1981

Volume V
No. 8

REVIEWS

Frank Derfler **The Epson MX-80: A Tough Act to Follow** 48

This dot matrix printer sets a high standard of quality.

Sorcerer Peter Vernon **The Sorcerer Speaks** 146

The Cognivox lets your micro understand what you say and answer you back.

6800 Phil Hughes **TSC Extended BASIC** 154

Quick, bug-free and well worth the price.

SOFTWARE

TRS-80 Terry Sunday **TRS-80 Launchpad** 134

Micros give a lift to aerospace engineering and save time and money.

Atari William Colsher **An Atari Disassembler** 142

Plunging deep into the heart of the steaming ROM jungle.

PET R. B. Nottingham **What's the Difference?** 152

Spotting and correcting incorrect data.

TUTORIAL

Peter Stark **Firm Up Your Floppy with 800K** 36

Increases the capacity of your five-inch diskette eightfold.

DEPARTMENTS

Publisher's Remarks-6 Dealer Directory-207

Micro Quiz-8 New Software-208

PET-pourri-10 Clubs-214

Computer Blackboard-18 Corrections-214

Dial-up Directory-20 Classifieds-215



As the Word Turns-28 Calendar-216

Micro-Scope-30 Book Reviews-219

Letters to the Editor-195 Perspectives-226

New Products-198

Page 60.



Page 134.

This month's cover:

What's a working microcomputer on a Florida beach doing on the cover of this month's issue? Have the editors of *Kilobaud Microcomputing* stayed out in the sun too long?

No, we aren't recommending that you pack your Apple II in with the suntan lotion, blankets and sand pail and shovel the next time you head for the beach.

This cover photo, which is a dramatic departure from the workstation setting where microcomputers are normally found, is the work of nationally known outdoor and wildlife photographer Ozzie Sweet. His credits include cover shots for such major publications as *Time*, *Newsweek* and *Look*. And while he has done covers for technical and scientific publications before, this marks the first time that he has worked with a computer as a model.

We think you'll agree that he brings a unique perspective to the world of computer photography. How better than in a seashore setting to illustrate the versatility of the Apple II "go-anywhere, do-anything" computer?

We commissioned Ozzie for this special Apple issue cover "between innings" of his tour this spring of the major league baseball training camps in Florida, where he was on assignment for Topps, the baseball cards people.

Besides being a talented photographer and creative artist, Ozzie is a prolific shutterbug. One magazine photo editor with whom he has worked described him as "the Henry Aaron and Babe Ruth of the magazine cover business."

Indeed, he has had over 1700 magazine covers published. We here at *Kilobaud Microcomputing* are pleased to be included among that number.

—The Editors

Kilobaud Microcomputing (ISSN 0192-4575) is published monthly by Wayne Green, Inc., 80 Pine St., Peterborough NH 03458. Subscription rates in U.S. are \$25 for one year and \$53 for three years. In Canada: \$27 for one year only, U.S. funds. Foreign subscriptions (surface mail)—\$35 for one year only, U.S. funds. Foreign air mail subscriptions —\$62 for one year only, U.S. funds. Canadian Distributor: Micron Distributing, 409 Queen St. West, Toronto, Ontario, Canada M5V 2A5. In Europe, contact: Monika Nedela, Markstr. 3, D-7778 Markdorf, W. Germany. South African Distributor: KB Microcomputing, PO Box 782815, Sandton, South Africa 2146. Australian Distributor: Electronic Concepts, Attention: Rudi Hoess, 55 Clarence Street, Sydney 2000, Australia. Second-class postage paid at Peterborough NH 03458 and at additional mailing offices. Phone: 603-924-3873. Entire contents copyright 1981 by Wayne Green, Inc. No part of this publication may be reprinted or otherwise reproduced without written permission from the publisher.

Are Shows Worth It?

Consider The Time And Expense

Show Hoopla

Having just managed to survive an intensive round of computer shows in the spring, I see more of them springing up—like mushrooms—this fall. Are these affairs really worth your trouble and expense to attend?

If you are a dedicated hobbyist and want to meet and talk with the people in the industry, I can see where you might get your five or ten dollars' worth at a show. Of course, you'll have to deal mostly with the smaller firms, since the big ones have pretty much been ignoring shows.

However, it is not likely that you'll see anything new. New equipment is no longer rushed into being for a show. Back when we had one big show a year, there might have been some justification for getting a new product ready a few weeks early so it could be shown at the show. Today, with dozens of shows a year, what's the difference?

Even the largest shows can't bring you the variety of merchandise you find advertised in one issue of *Microcomputing*.

Apple ran a series of small shows this last spring, and I assume this will continue if the enterprise was successful. Oddly enough, I've heard nothing from Apple, or from any of the exhibitors, about the success of the shows. The Boston Computer Society recently ran an independent Apple show in Boston. It was very small, but certainly successful, drawing a good crowd. The first independent TRS-80 show in New York was moderately successful, although lacking somewhat in crowds due, I surmise, to massively absent advertising and promotion.

The big show of the year was NCC in Chicago. This drew about 80,000, hundreds of whom were interested in microcomputers. This is a show for data processing people; no hobbyists or end users wanted. Many of the micro firms exhibit, in an attempt to overcome inferiority feelings, rather than for practical reasons.

You see, the maxi and even the mini people are so condescending about micros that many micro firms feel they have

to exhibit at NCC just to prove they are really in the business. The maxi crowd is not impressed by these "toy" merchants. Just as the Cadillac is America's answer to the inferiority complex, so NCC is the answer for our field.

What was really new at NCC this year? Little.

I also go to see the Consumer Electronics Show (CES) because sometimes in attendance are a few Japanese firms which seem confused about where to exhibit computers to reach the American market. Hitachi appeared this year, not sure what to do about the American market, yet afraid to lose out on it.

The Japanese Dilemma

With IBM due to show their new microcomputer soon—and similar threats from DEC, Digital Group and other mini-computer firms—the Japanese are beginning to panic. They have had some nice equipment available, but have not figured out how to get into the swing of the growth here. Apparently, they have not managed to find a consultant to explain to them how to enter the American market.

It is rapidly becoming much more expensive to get started here. Today it will cost about ten times as much as it would have a year ago to get going. By next year that entry fee may go up another order of magnitude. Soon it is going to tax the resources of even the enormous Japanese corporations to get a significant share of the US microcomputer market.

By the way, the rumors of IBM using the S-100 bus were just that . . . rumors. Using the S-100 would have been a very shrewd move. An even better move would have been TRS-80 compatibility.

The price of the Japanese indecision is high. There is no question that the American market for small computers is not only going to continue to grow, but also to escalate, eventually to behemoth proportions. The key to dominating the world market will lie in quantity production for the US market, which is developing first. Large-scale production means lower prices and faster development of

new technology, giving the firms in the US market a decided worldwide advantage. Whichever firms dominate the US market will probably come to dominate the European and Asian markets too, so the Japanese have a very serious problem.

The selling of consumer computers in the US is a new field and has baffled the Japanese so far. Much of the business is being done via Radio Shack stores, where they have no entry. Then comes the 2000 or so computer-specialty stores, many of which are underfinanced and difficult to deal with. A few tries have been made to sell via department stores, discount chains, office supply stores and so on, but the fact is that getting into the American consumer-computer market requires some very creative thinking, something we have not seen in abundance from Japan.

Complicating the sales problems for computer stores is the number of salesman hours to sell a system, and the similar number of hours required in after-the-sale handholding. Furthermore, there is the demand for instant service. Any business buying a computer soon finds that everything stops when the computer stops, so service is needed in minutes, not hours or days. This is a situation which has not yet been adequately tackled by any firm.

One of the reasons I'm interested in starting a "college" to train people in micros is the incredible need for people for our field. We need programmers, salesmen, technicians, advertising help, marketing help and so on. The need is desperate and growing as fast as sales. We could use a few thousand people with micro backgrounds to help the industry grow. We won't get the services we need unless we have some way of mass-training people. We are having to make do with poor service, which is costing more and more to buy.

Software firms have the same problem facing hardware firms—dealers interested in carrying the product, but without the cash to stock it and the facilities to sell it. This has seriously slowed the growth of software publishers, yet without this software, the sale of hardware is in-

AMAZING VALUES...

**HEAD
CLEANING KIT**

\$24⁹⁵

FOR 5 1/4" DRIVES

VERBATIM
**FD34-8000
DISKETTES**

\$43⁹⁵

BOX OF 10
SS, SS, DD

EPSON
**MX-80
MX-80FT**
—PRINTERS—
CALL FOR
PRICE

VERBATIM
**DATALIFE
DISKETTES**

\$26⁹⁵

BOX OF 10
SS, SS, 5 1/4"

**"OTHER
MYSTERIES"**
VOLUME I

\$19⁹⁵

CABLE
\$24⁹⁵

CONNECTS EPSON
PRINTER & TRS-80
MICRO

PLAIN JANETTM
Gold 5 1/4"
DISKETTES

\$25⁹⁵

SS, SS, DD
HUB RING

DISKETTE
FILE BOX
\$29⁹⁵

HOLDS 50-60
8" DISKS

PLAIN JANETTM
DISKETTES
\$21⁹⁵

BOX OF 10
SS, SS, 5 1/4"

**"OTHER
MYSTERIES"**
VOL. II or VOL. III

\$29⁹⁵

DISK DRIVE
**EXTENDER
CABLE**
\$9⁹⁵

FOR VISTA, MTI,
PERTEC, PERCOM
& OTHERS

TRI-STAR
**FLOPPY
SAVERTM**
HUB RING KIT
\$10⁹⁵

FOR 5 1/4"
DISKS

DISKETTE
FILE BOX
\$24⁹⁵

HOLDS 50-60
5 1/4" DISKS

FROM

M ETATRONICS
CORPORATION ✓ 161

RETAIL STORE
22297 EUCLID AVENUE
EUCLID, OHIO 44117
(EAST 222nd & EUCLID AVE.)

MOST ORDERS
SHIPPED WITHIN
ONE BUSINESS DAY



TO ORDER
CALL TOLL FREE
1-800-321-9390
IN OHIO, call
(216) 289-1210 (COLLECT)

OFFICES
26111 BRUSH AVENUE
EUCLID, OHIO 44132
(SEND MAIL ORDERS HERE)

TRS-80 is a trademark of the
Radio Shack Division of Tandy
Corporation. PLAIN JANE is a
Trademark of Meta Technologies
Corporation.

PRICES IN EFFECT
August 1, 1981 THRU
August 31, 1981,
Prices, Specifications,
and Offerings subject to change
without notice.

•Add \$3.00 for shipping & handling.
•\$3.00 EXTRA for C.O.D.
•Ohio residents add 6 1/2 % sales
tax.

© 1981 by Metatronics Corp.

evitably slowed. It's a Catch-22 situation.

Instant Software, which is one of the divisions of Wayne Green, Inc., could grow much faster if more people could be found to make things happen. I'm pressured every day with demands for more programmers, salesmen, marketing people, advertising people, promotions people, microcomputer technicians, digital audio technicians, typesetters, graphics artists, copywriters, documentation writers and so on. We could easily use 50 more people in Instant Software (though I don't know where we'd put that many!), and I'm sure we are not unusual in the industry. Most of the people I talk with are having the same problem.

In Plain English

One of the major problems facing computer stores in selling systems has been the language barrier. Something strange happens to computerists when they learn about computers—they lose all ability to communicate in plain language.

It is my thesis that there is a serious need for a magazine about computers which is written and edited in English, not computerese. This magazine will become a fact starting with the October 1981 premier issue. The idea is to make information on the uses of desktop com-

puters available to businessmen. The magazine will concentrate on success stories of business applications for our small computers.

By buying a couple more buildings and expanding the editorial offices of Wayne Green, Inc., we have made room for the staff of *Desktop Computing*. We are still looking for more help—space sales help, editing, writing, typesetting and so on.

Naturally we are looking for articles for *Desktop*. They should be double-spaced, generously margined and should be written with no computer buzzwords. You can do it. Readers will want to know what hardware and software systems really work, how long it takes to get on line, the costs, savings, benefits, problems and so on. We'll entertain some disaster reports too, but for the most part *Desktop* will be upbeat.

The businessman of today knows that he needs a computer, but doesn't know what to get or even how to find out. *Desktop* will bring him this information, all in plain language.

Readers of *Desktop* will want to know your successes with software, with accessories and with various systems. They'll want to know how to network computers so they can provide distributed processing, communications, bulletin boards and all of the lovely things our

micros can do. The magazine will not be restricted to micros, since the dividing line between them and low-end mini-computers is a fuzzy one at best. It will be aimed at the businessman—small and large—letting him know in English what is going on with computers.

I really need your help in getting articles, subscribers and advertising. In return, I think I will be able to help the whole computer industry to grow and surmount the cash and people problems now slowing it down. □

MICRO QUIZ

What Does This Program Do?

When the following program is executed, what will be printed? (If there are any embedded blanks in the string which is printed, replace each blank by the letter b with a slash through it: b.)

AS = "NECSL"

BS = left\$(right\$(AS,3),2)

CS = mid\$(AS,2,2)

BS = CS + BS

print BS

(answer on page 217)

Why Do Professionals Prefer

BECAUSE

- Unique software • Technical support • Quick delivery • Established company • Release 2 CP/M (some packages under UNIX and TRSDOS)
- Quality software • In-house expertise • Fast response • User orientation • Competitive prices • Customer service • Verbatim[®] media • Onyx hardware (CP/M and UNIX versions)



BECAUSE

Unique swift routing cybernetics response system gives you no-nonsense technical answers that save you time. Call: (714) 848-1922.



- NEW RM/COBOL[®] applications:
 - Order Entry/Inventory • Receivables • Payables • General Ledger • Financial Modeling • Client Accounting—and more on the way!
- NEW CBASIC2[®] applications:
 - REAP (Real Estate Acquisition Package).

Business
Medical
Real Estate
Computer Systems

Software from Cybernetics?

RM/COBOL—The new standard for microcomputer COBOL!! The only COBOL for CP/M (also on TRSDOS & UNIX) with alternate keys (multi-key ISAM), CRT screen handling, interactive debug, and the most useful Level 2 features. Compatible with RSCOBOL[®]—but runs faster.

Plus existing CBASIC2 packages:

- APH[®] (Automated Patient History)
- Osborne & Assoc.—Payroll • Payables/Receivables
- General Ledger
- NAD[®] (Name and Address)
- PMS (Property Management System)

Inquire for details

Trademarks of: Ryan-McFarland Corp., Compiler Systems, Inc., Digital Research, Bell Telephone Laboratories, Inc., Tandy Corp., Verbatim, Inc., Cybernetics, Inc., Structured Systems Group, Inc., Small Business Applications, Inc.

And system software packages:

- MAGIC WAND[®] Editing/Word Processing
- CBASIC2 Compiler BASIC
- QSOFT[®] Soft Merge Package



Distributed in U.K. by
Microcomputer Applications Ltd
11, Riverside Court, Caversham, Reading, England
TEL (0734) 470425

8041 Newman Ave., Suite 208
Huntington Beach, CA 92647
(714) 848-1922

I'm just finishing the update to my 144 page catalog and these are just a sample of the Rainbow of Applications we have for your Apple* Computer.

RAINBOW GAMES
CRIBBAGE - It's you against the Apple in one of the best two-handed card games which combines the luck of the draw with game strategy skill. Hi-Res cards and cribbage board. 48K Applesoft.

AIRCRAFT ID - Have fun while learning to identify over 40 Aircraft from WW I to the present. In Hi-Res graphics. 32K Applesoft. Disk \$19.95

From Apple Computer
DOS 3.3 KIT will increase the capacity of your diskette. You can still boot 3.2 programs. Includes manual, 16-sector PROMs for the disk interface, and utility disks. \$60.00
DOS TOOL KIT includes an Editor/Assembler with a relocating loader, Hi-Res Character Generator, Hi-Res Applesoft Programmer's Assistant. Requires 48 K, Applesoft Manuals and Disk. \$75.00

SUPER STELLER TREK (Rainbow)
A dramatic successor to the already popular "A stellar Trek." Tom Burlew has created Super Stellar Trek as a high-speed, Hi-Res, real-time action game that will challenge even the most skilled starship commander. Comes with a complete manual. Requires a 48K Apple, Applesoft in ROM, and DOS 3.2 / 3.3. Disk \$39.95

From On-Line Systems
HI-RES SOCCER - This is the only real-time action Soccer game for your Apple! All tackling, goal kicking, throwing, corner kicks etc. are shown in full Hi-Res graphics. Play against a friend or against the computer, fully animated players, 3 levels of play, scoreboard, both indoor and outdoor rules. Any 48K Apple... Any DOS... Disk \$29.95
HI-RES FOOTBALL - A fully animated, real-time action game. Any 48K Apple... Any DOS... Disk \$39.95

ARCADE-TYPE GAMES
From Sirius
SPACE EGGS... Any 48K Apple... Disk \$29.95
Any DOS... Disk \$29.95
PHANTOMS FIVE... Any 48K Apple... Disk \$29.95
Any DOS... Disk \$29.95
From Broderbund
Alien Rain (Apple Galaxian). Any 48K Apple... Disk \$24.95
Alien Typhoon (For Experts)... Any 48K Apple... Disk \$24.95
Any DOS... Disk \$24.95
Snoggle... Any 48K Apple... Disk \$24.95
Any DOS... Disk \$24.95
From Muse
ABM... 48K Applesoft... Disk \$24.95
Any DOS... Disk \$24.95



RAINBOW COMPUTING INC.

Our catalog contains many more products for your Apple computer. Please request a FREE catalog with any purchase. If you only want a copy of our catalog at this time, please send \$2.00 for shipping. Thank you.

 **apple computer inc.**

*Apple is the registered trademark of Apple Computer Inc.

Open Tues - Fri

Mail Order Dept. No. KB11 • 19517 Business Center Dr. • Northridge, CA 91324 • Phone orders only (Need Mastercard or Visa)
U.S.A. (except Calif.) (800) 423-5441 • Calif. and Foreign (213) 349-0300 • For information or technical questions (213) 349-5560
Add \$2.50 U.S./\$10.00 Foreign for shipping • Calif. residents add 6% sales tax.

Commodore Colors NCC

Introduces New 8032, Micro-Mainframe

Unfortunately, I couldn't make it to NCC in Chicago last May, but I did receive several new product announcements from Commodore. For those that haven't heard, a few new goodies are on the way that should create quite a stir. Pricing and availability were to have been announced at NCC, so watch for further details.


A Color 8032!

First of all, Commodore has announced a color version of their 80-column 8032 system. The new color 8032 has a high-resolution, direct drive RGB (red, green, blue) color monitor. It is supposed to provide a crisp, easy-to-read display in both text and graphics modes.

Normally, the color 8032 system displays green characters on a black background, just like the regular 8032. Using the control key, the user can then display information on the screen using a variety of foreground and background color combinations. You can even use reverse field with colors for highlighting. Color displays can be generated character-by-character, either directly by the user, or under program control from within a single print statement.

In all, there are eight colors (black, blue, green, cyan, red, magenta, yellow and white) available for the background color and foreground display. This gives you 64 possible combinations in each of the three character modes (text, graphics and plot). In the graphics mode there's a 160 x 100 point resolution for creating a high-resolution display.

You should be able to run all software developed for the standard CBM 8032 on the color version without modification. Fortunately, the standard CBM version 4.0 BASIC interpreter remains un-



Commodore's new CBM 8032 color microcomputer.

changed. However, the new color system contains an enhanced 32K Screen Edit ROM to provide the color handling capability. If a program uses any Screen Edit routines, it may need some work to run on the new color system.

Micro-Mainframe

The other new system from Commodore is their Micro-Mainframe. This is a new-generation computer that combines the power and languages available on mainframe systems with the low cost of microcomputers. Applications developed on the Micro-Mainframe can be transmitted to a mainframe system and executed without modification.


The new computer is based on the standard CBM 8032 with the familiar 12-inch green phosphor display, 73-key typewriter-style keyboard, and full cursor controls. However, the Micro-Main-

frame is a pseudo 16-bit 6809-based system with 36K ROM, 96K user RAM and 2K screen RAM (134K total). The system supports all current CBM peripherals except the C2N cassette recorder. Additionally, a new communication facility has been included to support standard RS-232C interfaces with speeds up to 9600 baud. All files are stored in true ASCII format for communication and compatibility with mainframe systems.

An extensive software package for the new system has been developed by Waterloo Computing Systems Limited to meet the requirements of the University of Waterloo in Waterloo, Ontario, Canada. This portable software is particularly suited to microcomputers, but identical versions are available on medium- and large-scale systems. Thus, a user is not limited by the capacity of the micro; the identical program will run without modification on many of the largest and fastest

Address correspondence to Robert W. Baker, 15 Windsor Drive, Atco, NJ 08004.

"WORDSWORTH,^{T.M.} TAKE A LETTER!"



**THE FIRST SUPER-SIMPLE LETTER QUALITY WORD PROCESSOR IN
THE WORLD THAT CAN SIT NEXT TO YOUR SECRETARY—
FOR LESS THAN \$5,000.**

"WordsworthTM" removes the fear and loathing many people have about things called "computers" and "word processing." Because Wordsworth just sits at a desk and does what he's told. With unique new, simplified software, it can tell its typist what to do—step by simple step—to perform even the most complicated tasks.

It can not only "take a letter," but it can revise it, customize it in millions of ways (quite literally), personalize it, print it on your letterhead or business form so you can't tell it from hand-typed . . . in short, everything but put it in an envelope.

Moreover, it can perform all sorts of mundane business functions,

like general ledgers and accounting reports, using easily available industry-compatible CP/MTM software.

Installation? Plug it in. (Cable supplied.)

Size? Bigger than a breadbox—but not by much. It's about half as big, or less, than systems that can't do half as much. Definitely desktop—a sub-compact 20" by 40".

Service? Available everywhere.

Price? About \$4,995. Complete and ready to go.

For the name of your nearest dealer—and a free hands-on demonstration—just pick up the nearest telephone.

TOLL-FREE 1-800-343-6833.

In Massachusetts, call collect (617) 828-8150. Telex 951-624.

LEADING EDGE.TM

✓ 355

Leading Edge Products, Inc., 225 Turnpike Street, Canton, Massachusetts 02021

DEALERS: For immediate delivery from the Leading Edge Inventory BankTM on "Wordsworth" and other of the industry's most popular products, just give us a call.

systems available.

The software package consists of interpreters for various languages, an editor, an operating system (supervisor) and an assembly-language development system. The four language interpreters include Waterloo microBASIC, microPascal, microFORTRAN and microAPL. COBOL is not yet available, but is under development. These language interpreters have been designed specifically for teaching computer programming. Their design emphasizes good error diagnosis and debugging capabilities which are useful in educational and other program development environments.

Waterloo microBASIC includes ANSI Minimal BASIC, with certain minor exceptions, and several extensions. Such things as structured programming control, long names for variables, sequential and relative file capabilities, integer arithmetic, debugging facilities and convenient program entry and editing facilities have all been included.

Waterloo microPascal is an extensive implementation of Pascal, corresponding very closely to draft proposals being produced by the ISO Pascal Committee. The ISO draft language is a refinement of the language originally defined by Wirth, varying only in minor aspects. This implementation includes sophisticated features such as text file support, pointer variables and multidimensioned arrays. A significant feature of Waterloo microPascal is its powerful interactive debugging facility.

Waterloo microFORTRAN is a special dialect designed for teaching purposes. It has many of the characteristics and much of the flavor of normal FORTRAN, but varies significantly from established standards for that language. It has many of the important characteristics of the WATFIV-S compiler, which is widely used on IBM computers, plus some features from the new FORTRAN-77 definition. It supports subroutines and functions, multidimensioned arrays, extended character string manipulation, structured programming control and file I/O. In addition, the interpreter provides a powerful interactive debugging facility.

Waterloo microAPL is intended to be a complete and faithful implementation of the IBM/ACM standard for APL with respect to the syntax and semantics of APL statements, operators and primitive functions. I/O forms and defined functions. System commands, system variables and system functions are those consistent with a single-user environment. There are no significant design limitations on the rank or shape of arrays or name length. The shared variable processor is omitted. Extensions include system functions supporting files of APL arrays. APL equivalents of BASIC features PEEK, POKE and SYS are also included.

A text editor known as Waterloo micro-

EDITOR, which is suitable for creating and maintaining both program and source data files, is included. It is a traditional line-oriented text editor with powerful text searching and substitution commands, including global change. Full-screen support and special function keys allow text to be altered, inserted and deleted on the screen without entering commands. Facilities for repeating and editing previously issued commands further enhance the usability of the editor.



Commodore's new Micro-Mainframe combines the power and languages available on mainframe systems with the low cost of microcomputers.

Disk-oriented assembler and linker programs, the Waterloo 6809 Assembler and Linker, are included to support development of general-purpose Motorola 6809 machine-language programs. The Assembler supports syntax and directives for Motorola 6809 assembly language and includes powerful macro capabilities. In addition, the Assembler supports pseudo op codes for structured programming control, long names (labels) and the ability to include definitions from separate files. The Assembler produces both listings and relocatable object files.

The Linker allows the combination of an arbitrary number of relocatable object files to produce an absolute loadable and executable program file. Since it is disk-oriented, the Linker is capable of building programs which are larger than the RAM work space available. The Linker supports building of programs in segments or banks for operation in bank-switched RAM memory, as well as building of programs for operating in normal RAM memory.

The Waterloo microSUPERVISOR is an operating system designed for single-user microcomputer environments. It includes a monitor, library and serial line communication support. The Monitor program supports loading of Linker-produced program files into bank-switched RAM memory or normal RAM memory. It also provides facilities which are useful for debugging machine-language programs. There are commands to display

or alter RAM memory and 6809 registers, using full-screen features for ease of use. In addition, another command permits disassembly of 6809 instructions into assembly-language mnemonics.

A library of functions and procedures is supplied for general use by other programs included in the software package. The Library includes support functions for input/output operations to the keyboard, screen and peripheral devices. Other elements of the library provide floating-point arithmetic, fundamental trigonometric functions and several general-purpose utility functions.

A Serial Line Setup program is included which provides selection of programmable characteristics, such as baud rate. The program includes support for establishing communication with a host computer, through a serial line, for accessing the host's files or peripheral devices.

Reference manuals, textbooks and instructor's guides are available for each software component of the system. The system was on display at the NCC show, but deliveries are not scheduled till the end of the year.

New Software

Several new software packages were also announced at NCC. Wordcraft 80 is Commodore's new word processor package for the 80-column systems. It is entirely different from the familiar Word Pro programs, but provides similar results. With Wordcraft you can display text in the exact form that it will be printed. Text can be easily edited and the format immediately verified on the display, without printing the document. In addition, page layouts of up to 117 characters wide by 98 lines deep can be accommodated by the automatic scrolling of text on the screen. Large documents are divided into chapters, with one chapter at a time held in the computer's memory.

During text entry Wordcraft will not break words when the right-hand margin is reached; the entire word is moved to the next line. Text editing is accomplished by a few simple keystrokes. Standard features include character, word and paragraph deletion or insertion plus block movement of text from one area to another. This word processor supports character string search and replacement within a chapter on the first of all occurrences. Wordcraft also handles tabs, decimal tabs, multiple levels of indentation and automatic centering. Tabs and margins can be changed anywhere throughout the text without disturbing the previous settings. Half-line printer movement for subscripts and superscripts is also supported from within the text.

Separate paragraphs or sections of text can be easily merged to form finished documents. Name and address files, or any information, can be merged into a standard form letter and then printed. The entire process is automatic once the

Most people just sell disks. I sell you a complete system, and then I help you make it work.

It's called support, and it's a rare commodity in the microcomputer world.

It's also one big reason why they call my programs "the standard of the industry."

I'm Irwin Taranto, the one who changed the TRS-80* into a serious business computer. When you buy my TRS-80 systems (or, for that matter, one of my own computers that says "Taranto" on it), you buy me.

You buy my experience in making TRS-80 systems work in thousands of businesses around the world.

You buy the corrections, modifications and upgrades I constantly make on my TRS-80 systems.

And you buy my telephone number. You see, most of those thousand businesses needed a little help getting their systems up and going, and they called. We answered all their questions, and talked them through their problems. Every time the questions got really tough or really unusual, I'd answer them myself, on the phone, right then and there. I still do.

That pays off in two ways. It makes sure you get your systems working. It also alerts me to any little operating inefficiencies I might have designed into my systems. If there are any general business programs anywhere in the world, of any kind, that are checked out any better than my TRS-80 systems, I'd like to know about them.



I turned the TRS-80 into a serious computer.

The Model I, II and III business systems.

So far, I have six systems for the Model I, at \$99 each:

Accounts Payable	General Ledger
Accounts Receivable	Payroll
Invoicing	Inventory Control

For the Cash Journal option on the General Ledger, add \$50.

I also have six systems for the Model II:

General Ledger/Cash Journal	\$ 299
Accounts Payable/Purchase Order	349
Open Accounts Receivable/Invoicing	349
Additional for Sales Analysis	100
Balance Forward Accounts Receivable	399
Payroll, without Job Costing	299
Additional for Job Costing	100
Inventory Control	399

For the Model III, we offer expanded versions of the six Model I systems, at \$199 each.

Just call the number below and I'll send you any or all of the Model I or Model III systems by return mail. If you call about the Model II, I send you a questionnaire before I'll send you any systems. That lets me individualize the programs to your specific applications.

Why I call them "systems," not "programs."

There's a one-word answer: interaction. Each of the three sets of programs links to the General Ledger, and wherever it's useful, they cross-link to each other. For instance, "Sales Analysis" figures in a salesman's commission rate, so it links to "Payroll." Since it computes profitability within product categories, it links to "Invoicing."

That's what a system is. And that's one big difference between the Taranto TRS-80 business systems and somebody else's collection of business program disks.

If you like, I'll sell you the hardware, too.

I offer the TRS-80, Model II, along with selected peripherals. If you buy the computer from me, you get some extra advantages — hardware that's absolutely tailored to the programs, plus even more hand-holding from Taranto & Associates. The equipment won't cost you any more.

I can sell you a truly serious, completely supported, thoroughly proven business computer system for as little as \$8000, hardware and software both.

There's nothing else like it in the market. Believe me, it's a far cry from that collection of program disks they're selling down the street.

Taranto
& ASSOCIATES, INC.

The Total System Store.™

121 Paul Drive, San Rafael CA 94903.
Outside California, toll free (800) 227-2868. In California, (415) 472-2670.
Authorized dealers throughout America.

*A trademark of the Tandy Corporation

files and form are set up.

Any properly interfaced letter-quality printer can be used with Wordcraft 80, and proportional spacing is supported. Single sheet stationery or continuous forms can be used. You can specify a single page, chapter or whole document for printing. At print time you can also specify underlining or heavy printing for those text areas so defined. With certain printer interfaces, background printing is allowed. This means that you can be working on one document while another is being printed.

Headers and trailers can be placed on each page and changed from chapter to chapter. They can even be specified in book fashion, alternating for left and right-hand pages. Page numbering is automatic and the system keeps track of all pages, even when a new chapter is added or inserted into a document.

Included with Wordcraft 80 is a special link program that lets the user incorporate VisiCalc data into a Wordcraft document. This data can then be edited like a standard document.

Wordcraft 80 is supplied with a comprehensive user's manual, a set of training cards and a pocket reference guide. The program can store about 350 pages of normal text on one standard 8050 disk drive. Alternately, a Commodore 4040

disk can be used. Retail price for Wordcraft 80 is listed at \$395.

Another new software package from Commodore is a Dow Jones Portfolio Management System (PMS). This package provides the serious private or professional investor immediate access to pricing and financial information available through the facilities of the Dow Jones News Retrieval Service and additionally functions as an accounting and control system for security portfolios.

The system allows maintenance of stock portfolios, automatic valuation of positions in the portfolio, retrieval of current and historical quotes and displaying and printing of news stories from the previous 90 days. This data is available for over 6000 stocks and selected news categories in the Dow Jones databases. Media General Financial Services, a price, dividend and fundamental financial database, can also be accessed with this system.

PMS features easy-to-use screen data entry for buys, sells and cash transactions. A complete year-to-date transaction audit trail and portfolio summary report are standard. The system provides a graphics display of historical prices and a printed copy of news stories, historical prices and the graphic displays.

This software package will run on any 32K PET/CBM system (2001, 4032, 8032). A Commodore 4040 or 8050 disk and a modem are also required, while a 4022 printer is supported for optional printing. Retail price for this package is \$149.95.

The last software package announced, Legal Time Accounting, manages the business side of a law firm, thus allowing lawyers to concentrate on their primary task. Specifically, LTA keeps track of client files, matter (case) files and associated log entries, which represent services performed for individual matters. LTA automatically posts log entries to the appropriate matter and prints individualized statements according to nine criteria. A number of options are provided to effectively use this information, once entered into the system. You can easily produce a list of clients or matters.

Client matter inquiry allows viewing all open log entries for a particular matter. A number of statistics and activity reports can be produced, including aging reports by both lawyer and firm. A utility section lets you set up fee and activity codes as well as perform normal house-keeping functions (such as disk backups).

LTA was designed to be easy to use, even for those with little or no computer experience. Additionally, the system closely follows the procedures used in a typical law firm. LTA handles about 500 active clients, 1500 matters and 2500 open log entries. It was designed for firms with up to ten lawyers. The program runs on the CBM 8032 with an 8050 disk, and

will support a 4022 (or similar) printer. Retail price is \$595.

VIGIL

Here's a new and very interesting software package for the PET/CBM from Abacus Software. Once I glanced through the documentation, I just couldn't wait to try it out. VIGIL stands for Video Interactive Game Interpretive Language. It's an easy-to-learn graphics and game language that lets you quickly create interactive applications. The language is patterned after the CHIP-8 game language available on the RCA COSMAC VIP computer, but has much greater capabilities. The VIGIL interpreter executes game programs and performs video graphics at much higher speeds than normally obtainable with BASIC.

VIGIL programs are entered and modified using the standard BASIC text editor built into the PET, the same way as programming in BASIC. If you have a printer, you can even list VIGIL programs just like normal BASIC programs. VIGIL was designed to read the BASIC text editor output stored in memory as its programs, just like PET/CBM BASIC. However, because of this, a little caution must be used in writing VIGIL program statements so BASIC keywords are not accidentally created where you don't want them.

There are more than 60 commands to manipulate graphics on the screen with 80x50 plot positions on a 40-column system. It is very easy to display and move patterns based on screen coordinates. Also, testing for pattern collisions or hits is easy. For most games, you can define standard graphics figures and display them anywhere on the screen with one simple command. Two registers are used to indicate the screen position where the pattern will appear. To move the pattern you simply issue the same command to erase the existing pattern, modify the registers containing the display coordinates, then issue the command again to display the pattern in the new screen position.

VIGIL commands consist of BASIC keywords and single-letter or character operands. One or more operands identify the data or internal registers to be used by the command. There are 26 internal registers, most of which can be used as desired for counters, pointers, etc. Besides graphics support, commands are also included for arithmetic, logical and random functions, accessing PET memory and loading and executing machine-language subroutines.

Two timers are available under program control. Input commands can read the full keyboard or a 4x4 portion of the numeric keyboard. The parallel user port can read joysticks or other attached devices. VIGIL can also create audio tones via the standard user port connection. Pitch and duration of the tone are pro-



HOT AUGUST BUYS!

Disk Based System: Apple II or Apple II Plus with 48k RAM installed, Disk II with controller, DOS 3.3 \$1869

THE SOURCE® FREE! Buy the D.C. Hayes Micromodem II® for \$379.95 and we'll give you The Source (\$100 value) Free!

EPSON MX-70 \$399

Mountain Computer CPS® new interface card \$199.95

SMARTERM® 80-column board \$299

CALL TOLL FREE

(800) 621-5802

ERICKSON
COMMUNICATIONS
Chicago, IL 60630
5456 North Milwaukee Ave.
(312) 631-5181 (within Illinois)

gram-controlled and operate simultaneously with screen action.

The preliminary copy I received was very nicely done with good documentation. The final package will offer cassette versions for the three different ROM sets as well as a diskette version. Also, the final manual is supposed to be a 50-page printed booklet. Included with each package are nine sample programs that really help in illustrating how to use VIGIL for various types of games. VIGIL will sell for \$35 in USA and Canada, \$40 elsewhere.

For more information, write Abacus Software, PO Box 7211, Grand Rapids, MI 49510. This should really be of interest if you enjoy writing game programs or using graphics. You'll probably never want to program another game in BASIC after trying VIGIL.

Kingston KRK-2

In recent months a number of new products for the PET/CBM have been entering the US from Europe and other parts of the globe. One new hardware addition is the KRK-2 module from Kingston Computers Limited in England. The module is really three devices in one: a keyboard reset, full keyboard repeat and a keyboard clicker. Actually, there is even a fourth feature—provisions for sound generation. All features are provided by a single hardware module but operate independently.


Basically, the KRK-2 package consists of a small printed circuit board that connects between the PET main logic board and the keyboard cable. There are no modifications to be made to the PET itself. Instead, a rather unique concept is used where one IC is removed from its socket and then reinserted with a small, flexible, printed circuit pad between the IC and the socket. The other end of the printed pad then connects to the KRK-2 board. This effectively breaks several connections to the IC and routes them through the logic on the KRK-2 board.

Other cables from the module connect to the second cassette port for power and to a small speaker that is mounted inside the PET. All connectors have color-coded stickers to aid in matching the correct cables.

New features added by the small module include the RESET function, which is activated by holding down the RUN/STOP and = keys at the same time. The PET will return to the machine-language monitor and can be returned to BASIC by the X command. The reset function is a BASIC "warm" start as previously documented in various newsletters and articles. It does not destroy your program in memory.

After the reset, you have two options: restart your program from scratch or attempt to continue. To restart, simply enter a CLR command followed by RUN. Details on how to reset the microproces-

What can you honestly expect from an interactive data terminal that costs only \$369?*



Well, to begin with, color graphics.

RCA's VP-3301 has unique color-locking circuitry that gives you sharp, jitter-free color graphics and rainbow-free characters.

Plus much more: Microprocessor control. Resident and programmable character set. Reverse video. State-of-the-art LSI video control. 20 and 40 character formats. RS232C and 20 mA current loop. Six baud rates. Eight data formats. ASCII encoding. Light-touch flexible-membrane key switches for reliability and long life. CMOS circuitry and a spill-proof, dust-proof keyboard for hostile environments.

The VP-3301 can be used with a 525-line color or monochrome monitor or a standard TV set through an RF modulator.** It serves a wide variety of industrial, educational, business and individual applications including communication with time sharing and data base networks such as those provided by Dow Jones News/Retrieval Service, CompuServe and Source.

All this—for the low price of \$369. And it's made by RCA. So get the whole story about the surprising VP-3301 today. Write RCA MicroComputer Marketing, New Holland Avenue, Lancaster, PA 17604. Order toll-free: 800-233-0094.

**Model VP-3303 with built-in RF modulator—\$389.

*Suggested user price. Monitor and modem not included.

RCA

MICROMAIL HAS WHAT YOUR SYSTEM NEEDS.



TELEVIDEO 910


\$599.00

912	\$699.00
920	\$749.00
950	\$995.00

DIABLO 630

\$1959.00

1640 RO	\$2269.00
1640 KSR	\$2499.00
1650 RO	\$2599.00
1650 KSR	\$2599.00




DEC LA34 DA

\$899.00



TELETYPE 43 PF(TTL)

\$975.00



ANADIX

DP 9500	\$1299.00
DP 9501	\$1299.00
DP 9000	\$1199.00
DP 9001	\$1199.00

TEXAS INSTRUMENTS

810/2	\$1549.00
810/2 PKG (U/L, VFC, CP)	\$1679.00

SOROC

IQ 120	\$689.00
IQ 140	\$1099.00
IQ 135	\$849.00

DEC

VT 100	\$1650.00
DEC LA 34AA	\$1050.00

C. ITOH

CIT 101	\$1625.00
---------	-----------

NEC

5510	\$2395.00
5530	\$2395.00

To Order: Send check to MICROMAIL, P.O. Box 3297, Santa Ana, CA 92703. Personal or company checks require two weeks to clear. Visa/MasterCard accepted. C.O.D. requires a 15% deposit. **Handling:** Add 3% to orders less than \$750, 2% to orders \$751 - \$2,000, 1% to orders over \$2,000. NOTE: Handling charges are waived on orders pre-paid in advance by check. **Shipping:** We ship FREIGHT COLLECT via UPS or Motor Freight. Air and Express delivery is available.

MICROMAIL

P.O. Box 3297
Santa Ana, CA 92703
Phone: 714/731-4338
TWX: 910 595 1146

sor stack and attempt to continue a program are given in the documentation.

The repeat key function is available from the time the PET is first powered on when the KRK-2 module is installed. There is nothing you have to do to enable the function; just hold down any key till it repeats. The hardware even provides two adjustments to tailor the repeat speed and sensitivity to your particular taste. The repeat is set up before delivery at a reasonably gentle pace so you can enjoy the repeat function and yet maintain contact with the cursor.

Bear in mind that you must compromise between something that's ideal for joystick-type games but useless for normal typing and something ideal for typing but boring and slow for games. The time delay between holding down a key and the start of the repeat action is two seconds maximum.

The key click function can only be activated after a POKE 59456,247 is entered. Thereafter, the feature can be enabled by holding down the RUN/STOP and < keys at the same time. It is disabled by holding the RUN/STOP and the space bar. Once enabled, a simple click sound verifies each keystroke for much nicer touch typing.

There are three ways of creating noise and/or music under program control with the KRK-2 module. The simplest is to repeatedly POKE the cassette port at location 59456. This is a far cry from "music," but can prove useful.

The second method is by direct control of the MICE TRO music generator. A listing of a very simple program to accomplish this is included in the documentation. The form of each note created by the music generator is determined by three parameters poked in memory prior to calling the routine via an SYS command. Two of the parameters determine the pitch, while the third determines the length of the note (up to four seconds).

The last method of producing music is by using the complete MICE TRO program that is included with the KRK-2 package. This program provides all the interface and control for the simple machine-language program provided in the manual. It implements an entire language for creating, editing, playing and saving music pieces.

Remember that the methods of generating sound via the KRK-2 module are not compatible with programs with sound written in the US. Most PET owners use the CB2 line on the user port to generate sound with an external speaker and/or amplifier.

As with other products I've seen from Kingston, the documentation is excellent and the product is first class. The complete KRK-2 package is \$119.50 and is available from Microtek, Inc., 9514 Chesapeake Drive, San Diego, CA 92123. If you are only interested in the keyboard repeat, a KRK-1 module is available for \$39.95. □



TYPE-'N-TALK™ IS T.N.T.

The exciting text-to-speech synthesizer that has every computer talking.

- **Unlimited vocabulary**
- **Built-in text-to-speech algorithm**
- **70 to 100 bits-per-second speech synthesizer**

Type-'N-Talk™, an important technological advance from Votrax, enables your computer to talk to you simply and clearly — with an unlimited vocabulary. You can enjoy the many features of Type-'N-Talk™, the new text-to-speech synthesizer, for just \$375.00.

You operate Type-'N-Talk™ by simply typing English text and a talk command. Your typewritten words are automatically translated into electronic speech by the system's microprocessor-based text-to-speech algorithm.

The endless uses of speech synthesis.

Type-'N-Talk™ adds a whole new world of speaking roles to your computer. You can program verbal reminders to prompt you through a complex routine and make your computer announce events. In teaching, the computer with Type-'N-Talk™ can actually tell students when they're right or wrong — even praise a correct answer. And of course, Type-'N-Talk™ is great fun for computer games. Your games come to life with spoken threats of danger, reminders, and praise. Now all computers can speak. Make yours one of the first.

Text-to-speech is easy.

English text is automatically translated into electronically synthesized speech with Type-'N-Talk™ ASCII code from your computer's keyboard is fed to Type-'N-Talk™ through an RS 232C interface to generate synthesized speech. Just enter English text and hear the verbal

response (electronic speech) through your audio loud speaker. For example: simply type the ASCII characters representing "h-e-l-l-o" to generate the spoken word "hello."

TYPE-'N-TALK™ has its own memory.

Type-'N-Talk™ has its own built-in microprocessor and a 750 character buffer to hold the words you've typed. Even the smallest computer can execute programs and speak simultaneously. Type-'N-Talk™ doesn't have to use your host computer's memory, or tie it up with time-consuming text translation.

Data switching capability allows for ONLINE usage.

Place Type-'N-Talk™ between a computer or modem and a terminal. Type-'N-Talk™ can speak all data sent to the terminal while online with a computer. Information randomly accessed from a data base can be verbalized. Using the Type-'N-Talk™ data switching capability, the unit can be "de-selected" while data is sent to the terminal and vice-versa — permitting speech and visual data to be independently sent on a single data channel.

Selectable features make interfacing versatile.

Type-'N-Talk™ can be interfaced in several ways using special control characters. Connect it directly to a computer's serial interface. Then a terminal, line printer, or additional Type-'N-Talk™ units can be connected to the first Type-'N-Talk™, eliminating the need for additional RS-232C ports on your computer.

Using unit assignment codes, multiple Type-'N-Talk™ units can be daisy-chained. Unit addressing codes allow independent control of Type-'N-Talk™ units and your printer.

Look what you get for \$375.00. TYPE-'N-TALK™ comes with:

- Text-to-speech algorithm
- A one-watt audio amplifier
- SC-01 speech synthesizer chip (data rate: 70 to 100 bits per second)
- 750 character buffer
- Data switching capability
- Selectable data modes for versatile interfacing
- Baud rate (75-9600)
- Data echo of ASCII characters
- Phoneme access modes
- RS 232C interface
- Complete programming and installation instructions

The Votrax Type-'N-Talk™ is one of the easiest-to-program speech synthesizers on the market. It uses the least amount of memory and it gives you the most flexible vocabulary available anywhere.

Order now. Toll free.

Call the toll-free number below to order or request additional information. MasterCard or Visa accepted. Charge to your credit card or send a check for \$375.00 plus \$4.00 delivery. Add 4% sales tax in Michigan.

1-800-521-1350.

Dealer Inquiries Invited

Votrax ✓ 200

Distributed by Votrax
A Votrax Company — Dept. RT
500 Stephenson Highway, Troy, MI 48064
(313) 588-0341

Type-'N-Talk™ is covered by a limited warranty. Write Votrax for a free copy.

Educators' Recess

Something For Everyone In Minnesota

You're Not Alone

The spectrum of educational computer applications is already quite large. At one end are those who resist all forms of computer support for a variety of personal reasons. At the other end are teachers making daily use of Logo in the elementary classroom. And there are many educators at every definable level between these extremes. This article is a collection of personal observations on the current state of the microcomputer explosion and its impact on the precollege educational community.

Last May I attended the annual meeting of American Educational Data Systems (AEDS). As an organization, AEDS' interest is all educational applications of computer technology. While the organization was once completely dominated by those interested primarily in administrative applications, the organization now focuses on the use of computers in instruction.

The 1981 annual meeting was held in Minneapolis, which is the home of the Minnesota Educational Computing Consortium (MECC). MECC (2520 Broadway Drive, St. Paul, MN 55113) produces some of today's best instructional software. It was featured in the March 1981 issue of *Creative Computing*, which provided a comprehensive picture of the organization and much of its available software.

The AEDS annual meeting was excellent, with several significant sections for anyone interested in instructional applications of the computer. The content of the meeting overshadowed the inconvenience of an older hotel with overcrowded and overheated meeting rooms. A participant at this meeting almost had to be impressed by the diversity of attendees' backgrounds and job titles. I spoke with superintendents, assistant superintendents, business managers, curriculum coordinators, directors of computer services, department heads, elementary and secondary teachers and even mem-

bers of state education departments.

This diversity of job titles was exceeded by the diversity of experience with and knowledge of the various aspects of computer-supported instruction. I met several old friends who've been working with computers and kids for over 15 years. I met several others who still have serious doubts about ever allowing computers to be a part of their instructional programs. And you could find attendees with every level of computer-related experience and nearly every level of personal educational philosophy in between. No matter what your title and no matter what your background, you were not alone at the AEDS convention.

The AEDS meeting program met the needs of virtually everyone—and that was no small feat. In one section the audience was shown the printed output of a program written by a fifth grader. The presenter was very proud that under her guidance this rather clever student was able to produce a picture of a rocket ship and the printed countdown from 10 to 1. Audience reaction ranged from, "Wow, that's amazing—and he was only in fifth grade," to the sound of pencils breaking between clenched teeth as those with a little more experience fought to remain polite and not interrupt the presentation of an enthusiastic teacher.

I nearly chipped a tooth while biting my pen during this presentation, as I've had the experience of having some of my own programs reviewed and then ranked with others evaluated by the same reviewer. Not being selected as the author of the best program was no surprise, but discovering that the "best" program had been written by a fourth grader—a fact the reviewer still doesn't know—was more than a little humbling.

As more and more students are given free access to general-purpose computers, I suggest most of us shall be both pleased and astonished with the result. When a student is given a sophisticated intellectual tool, he can undertake

sophisticated intellectual activities once thought to be the nearly exclusive domain of those more experienced and more educated.

Another presenter showed us how Logo can be used when working with elementary school children. As you can probably guess, audience reaction ranged from, "I've seen the salvation of education," to "that guy must be nuts." The audience included those who have long awaited the commercial availability of Logo and those who never before heard the word and had no concept of its implications for education.

Certainly the best case for Logo is made in Seymour Papert's *Mindstorms: Children, Computers and Powerful Ideas*, Basic Books, New York, 1980. I consider this to be the most important book published for educators in several years, and suggest it as required reading for all teachers and administrators. Papert does not accept the idea that computers should be used to help us better teach those subjects we are already teaching. His text addresses the issue that computer availability has significantly altered that which should be contained in a basic education. Computers should change what we teach, not just how we teach. Do read this book.

At least one presenter made the case for the difficulty of writing educationally sound software. Why are these presentations always given by someone who works for a company who wants to sell software to the education market? For those who continue to resist the use of microcomputers in education, you are well advised to look for presentations on the high cost of software development. You are almost certain to see statistics that suggest writing a program will require a school district referendum to

Walter Koetke, Putnam/Northern Westchester BOCES, Yorktown Heights, NY 10598.

allow a new bond issue so the program can be paid for after only a few years of hardship.

If you resist the use of microcomputers in education, be sure you do not attend presentations such as that made by CUE (Computer Using Educators). This user group offers hundreds of tested, evaluated, teacher-developed programs for virtually nothing. They will trade you their disk full of programs for your single original program or sell you any of their many disks for \$10 each. Efforts such as theirs deserve applause and support, and I hope similar cooperatives will be established elsewhere. You can obtain additional information about CUE by writing them in care of Don McKell, Independence High School, 1776 Education Park Drive, San Jose, CA 95133.

If AEDS were to give an award for bravery, my nomination would be the presenter of a section that defended the recent acquisition of a mainframe time-sharing system rather than microcomputers for an instructional environment. Certainly there are a few advantages inherent in the larger system, but there are also a surprisingly large number of disadvantages. Most important, however, is the need for educators to not view microcomputers or time-sharing systems as an either/or choice. The days of doing everything with one computer or accessing computing facilities in only one way were once very real, but they are now no more than a page in the history of computing.

Earl Joseph, a futurist with Sperry-Univac, gave presentations that were both very enlightening and more than a little frightening. Be sure to hear this man should you ever see his name on a program. As he speaks of the latest technological developments permitting the production of "teachers on a chip" and then "schools on a wafer," he has to have the best view in the house as he can see the faces of the audience. Some of the audience appear to be in shock, some search desperately for a flaw in his reasoning, some see new hope for the future and eagerly take notes, and some just cross their fingers and count the years until their retirement.

While his scenarios mean many different things to the audience, I hear him describing the world in which today's elementary and even secondary students must not just survive, but in which they must compete, make a living and raise a family. Their environment will be quite different from ours, and extraordinarily different from that which exists in our schools. I hear Earl Joseph and I hear a plea that we educate today's students so they are able to deal with the very different world that will be their future.

AEDS also included several presentations on the administrative applications of computers. As with topics on instructional computing, you could easily find the full range of opinions being present-

ed. There were several who advocated that microcomputers can do nearly all administrative tasks, and there were a few suggesting that the microcomputer is inappropriate for any but the most trivial administrative support.

Noteworthy was the fact that all presenters who spoke of microcomputers spoke of very small hardware configurations—those that could be purchased for \$3000 or less. Notably absent were discussions of applications being developed for machines in the \$6000 to \$10,000 range. I find this peculiar, for some of the machines in this price range are capable of doing all of the administrative processing for any school district containing less than 10,000 pupils.

Vendor displays at the AEDS meeting were, as is often the case, more interesting between the booths than in front of them. Most striking was the fact that there was no new hardware and only one piece of new software displayed at the meeting. Also notable was the absence of any mid- to upper-priced microcomputer configurations.

The single new piece of software displayed was Texas Instruments' Logo package. Although prototypes have been occasionally seen for some time, the Logo package is finally available to all of us. I consider this a major step forward in the application of computer technology to instruction, and certainly a feather in the cap of TI as they've taken a nontrivial monetary risk in supporting this step. The generally poor reviews of the TI 99/4 microcomputer are well known and well founded. However, if you accept the premise that the price of a microcomputer can be justified by a single significant application, then the TI 99/4 should find many new homes as a Logo machine. When used exclusively as a Logo machine with students, virtually all of the objections on which the poor reviews were based become invalid.

Perhaps my own career in education gives me a distorted view of the importance of preparation and homework, but I find it increasingly difficult to be polite to vendors who have no idea whatsoever about the status, purpose or even mechanics of using their companies' products. The vendor displays at AEDS were typical in this regard. While I readily acknowledge the presence of some well-informed, helpful vendors, I was told, "I don't know how to load a disk," "Don't ask me, I never saw this program before," "I don't know anything about the books we sell either," "The company never tells us anything," "If the catalog says so I guess it's true" and other similar bits of nonsense far too often. Considering the high cost of booth space, salaries and expenses that the vendors must support, they really ought to make the additional effort to put some knowledge behind the smile that greets you when you see their display.

Keynote Speech

Lou Wangberg, the Lieutenant Governor of Minnesota, was the keynote speaker at the AEDS convention. He delineated several problems and promises of computers in education from a position of understanding. He certainly left the audience wishing that their own state and local politicians could be as well informed and supportive. Little wonder that Minnesota leads the country in the application of computers to instruction.

Wangberg's presentation developed the idea that one of the three characteristics unique to our country is the concept that all children have a right to education rather than reserving education as a privilege for some. Education has also been our country's "great leveler" in that we treat some skills as essential for all citizens. He expressed some concern that computers will "mess-up" this minimum right by being provided for some but not all students. He then discussed the necessity of providing all students with access to computers as part of their public school instruction.

This concern for the haves and have-nots regarding access to computers is certainly a valid one, and one that others have discussed using different scenarios. The small business without computer support is not likely to survive in a world where the competition has computer support. Homes with computer access will provide a different learning, employment and recreational environment to family members than is possible for those without such access. While I share the concern for the have-nots in education and enthusiastically support providing all students with access to computers for instruction, I suggest we must be aware of yet another situation with unclear social consequences.

When nearly all students do gain access to computers, the individualization then possible will highlight the differences between students. The very bright students will proceed at a pace that far exceeds what they can now do. If true individualization of instruction is possible, then providing such instruction will enhance and strengthen the differences between individuals rather than reduce them, as has been the tradition of public education. I suggest this possibility as neither advocate nor opponent, but as one concerned with the social implications of the result.

The AEDS annual meeting did indeed have something for everyone. You weren't alone no matter what your perspective or experience. You could find others in similar situations, and presentations aimed directly at you. The 1982 AEDS annual meeting is in Orlando, Florida, on May 10-14. For more information about this meeting or AEDS, write them at 1201 16th Street NW, Washington, DC 20036. □

A Modem With Smarts

DataComm Represented At NCC

Disconnect that modem and put down that phone! This month, you and I are going to visit the National Computer Conference in Chicago. While we're there, we're going to see the newest things in data communications, including the revolutionary Hayes Stack Smartmodem, a way to make our terminals talk and a device to connect 16 remote users to a TRS-80 Model II over telephone lines.

The Scene

McCormick Place is a huge convention hall on Chicago's lakefront. The wind is always blowing, but even without the wind, the place was a storm of activity. The floor displays took up three large halls. The displays included music, singers, movies and lots of color, hardware, talking and walking. It was impossible to see the whole show in one day, even if

you stopped for only a moment at every interesting display.

The NCC display floor combines the microcomputer industry and the big computer industry and ignores the difference. Apple and Atari were just down the aisle from Xerox and IBM. Judging from the offerings of both the micro and maxi manufacturers, it is going to become harder and harder to tell the difference. The micro people are coming on strong with hard disks and networking systems, and the maxi folks are marketing desktop work stations with specifications that include dual minifloppies, 64K of memory and compatibility with the CP/M operating system.

Companies represented include Apple and Cromemco, both with interesting displays. The Atari booth was always crowded. They had many people from the Atari product and development staff demonstrating the Atari 800 in many different uses.


Ohio Scientific announced its new integrated business network, IBS-NET, which is a distributed processing network that can interconnect most of OSI's computer systems. Future plans call for the IBS-NET to interface with other local networks such as Ethernet.



The IF-800 from OKI Electric Industry Company is an integrated system with a beautiful color display, full keyboard and Z-80A able to run under CP/M. The standard system includes the double-sided double-density drives, color monitor and an 80-column printer with graphics capability. Options include a ROM cartridge interface and a light pen. The total system, fully loaded, will retail for about \$8000.



The C. Itoh X-100 breaks the pattern by using an M6809 CPU. C. Itoh was particularly interested in finding U.S. distributors who would use their system in special applications. This company has been successful with a low-price daisy-wheel printer. Their new bit-mapping graphics printer did a good job of taking a picture right off the screen.



The Hayes Stack Smartmodem shown alone on the left and with its matching clock on the right. This unique modem contains its own microprocessor and needs no special software or bus structure to perform automatic dialing and answering functions. Seems to be a lot of room in that clock cabinet!

We have acquired the rights to all TDL software (& hardware). TDL software has long had the reputation of being the best in the industry. Computer Design Labs will continue to maintain, evolve and add to this superior line of quality software.

— Carl Galletti and Roger Amidon, owners.

Software with Manual/Manual Alone

All of the software below is available on any of the following media for operation with a Z80 CPU using the CP/M* or similar type disk operating system (such as our own TPM*).

for TRS-80* CP/M (Model I or II)
for 8" CP/M (soft sectored single density)
for 5¼" CP/M (soft sectored single density)
for 5¼" North Star CP/M (single density)
for 5¼" North Star CP/M (double density)

BASIC I

A powerful and fast Z80 Basic interpreter with EDIT, RENUMBER, TRACE, PRINT USING, assembly language subroutine CALL, LOADGO for "chaining", COPY to move text, EXCHANGE, KILL, LINE INPUT, error intercept, sequential file handling in both ASCII and binary formats, and much, much more. It runs in a little over 12 K. An excellent choice for games since the precision was limited to 7 digits in order to make it one of the fastest around. \$49.95/\$15.

BASIC II

Basic I but with 12 digit precision to make its power available to the business world with only a slight sacrifice in speed. Still runs faster than most other Basics (even those with much less precision). \$99.95/\$15.

BUSINESS BASIC

The most powerful Basic for business applications. It adds to Basic II with random or sequential disk files in either fixed or variable record lengths, simultaneous access to multiple disk files, PRIVACY command to prohibit user access to source code, global editing, added math functions, and disk file maintenance capability without leaving Basic (list, rename, or delete). \$179.95/\$25.

ZEDIT

A character oriented text editor with 26 commands and "macro" capability for stringing multiple commands together. Included are a complete array of character move, add, delete, and display function. \$49.95/\$15.

ZTEL

Z80 Text Editing Language - Not just a text editor. Actually a language which allows you to edit text and also write, save, and recall programs which manipulate text. Commands include conditional branching, subroutine calls, iteration, block move, expression evaluation, and much more. Contains 36 value registers and 10 text registers. Be creative! Manipulate text with commands you write using Ztel. \$79.95/\$25.

TOP

A Z80 Text Output Processor which will do text formatting for manuals, documents, and other word processing jobs. Works with any text editor. Does justification, page numbering and headings, spacing, centering, and much more! \$79.95/\$25.

MACRO I

A macro assembler which will generate relocatable or absolute code for the 8080 or Z80 using standard Intel mnemonics plus TDL/Z80 extensions. Functions include 14 conditionals, 16 listing controls, 54 pseudops, 11 arithmetic/logical operations, local and global symbols, chaining files, linking capability with optional linker, and recursive/reiterative macros. This assembler is so powerful you'll think it is doing all the work for you. It actually makes assembly language programming much less of an effort and more creative. \$79.95/\$20.

MACRO II

Expands upon Macro I's linking capability (which is useful but somewhat limited) thereby being able to take full advantage of the optional Linker. Also a time and date function has been added and the listing capability improved. \$99.95/\$25.

LINKER

How many times have you written the same subroutine in each new program? Top notch professional programmers compile a library of these subroutines and use a Linker to tie them together at assembly time. Development time is thus drastically reduced and becomes comparable to writing in a high level language but with all the speed of assembly language. So, get the new CDL Linker and start writing programs in a fraction of the time it took before. Linker is compatible with Macro I & II as well as TDL/Xitan assemblers version 2.0 or later. \$79.95/\$20.

DEBUG I

Many programmers give up on writing in assembly language even though they know their programs would be faster and more powerful. To them assembly language seems difficult to understand and follow, as well as being a nightmare to debug. Well, not with proper tools like Debug I. With Debug I you can easily follow the flow of any Z80 or 8080 program. Trace the program one step at a time or 10 steps or whatever you like. At each step you will be able to see the instruction executed and what it did. If desired, modifications can then be made before continuing. It's all under your control. You can even skip displaying a subroutine call and up to seven breakpoints can be set during execution. Use of Debug I can pay for itself many times over by saving you valuable debugging time. \$79.95/\$20.

DEBUG II

This is an expanded debugger which has all of the features of Debug I plus many more. You can "trap" (i.e. trace a program until a set of register, flag, and/or memory conditions occur). Also, instructions may be entered and executed immediately. This makes it easy to learn new instructions by examining registers/memory before and after. And a RADIX function allows changing between ASCII, binary, decimal, hex, octal, signed decimal, or split octal. All these features and more add up to give you a very powerful development tool. Both Debug I and II must run on a Z80 but will debug both Z80 and 8080 code. \$99.95/\$20.

ZAPPLE

A Z80 executive and debug monitor. Capable of search, ASCII put and display, read and write to I/O ports, hex math, breakpoint, execute, move, fill, display, read and write in Intel or binary format tape, and more! on disk

APPLE

8080 version of Zapple

NEW! TPM now available for TRS-80 Model II!

TPM*

A NEW Z80 disk operation system! This is not CP/M*. It's better! You can still run any program which runs with CP/M* but unlike CP/M* this operating system was written specifically for the Z80* and takes full advantage of its extra powerful instruction set. In other words its not warmed over 8080 code! Available for TRS-80* (Model I or II), Tarbell, Xitan DDDC, SD Sales "VERSA-FLOPPY", North Star (SD&DD), and Digital (Micro) Systems. \$79.95/\$25.

SYSTEM MONITOR BOARD (SMB II)

A complete I/O board for S-100 systems. 2 serial ports, 2 parallel ports, 1200/2400 baud cassette tape interface, sockets for 2K of RAM, 3-2708/2716 EPROM's or ROM, jump on reset circuitry. Bare board \$49.95/\$20.

ROM FOR SMB II

2KX8 masked ROM of Zapple monitor. Includes source listing \$34.95/\$15.

PAYROLL (source code only)

The Osborne package. Requires C Basic 2.
5" disks \$124.95 (manual not included)
8" disks \$ 99.95 (manual not included)
Manual \$20.00

ACCOUNTS PAYABLE/RECEIVABLE (source code only)

By Osborne. Requires C Basic 2
5" disks \$124.95 (manual not included)
8" \$99.95 (manual not included)
Manual \$20.00

GENERAL LEDGER (source code only)

By Osborne. Requires C Basic 2
5" disks \$99.95 (manual not included)
8" disks \$99.95 (manual not included)
Manual \$20.00

C BASIC 2

Required for Osborne software. \$99.95/\$20.

SYSTEM/6

TPM with utilities, Basic I interpreter, Basic E compiler, Macro I assembler, Debug I debugger, and ZEDIT text editor.

Above purchased separately costs \$339.75

Special introductory offer: Only \$179.75 with coupon!!

\$160.

This Coupon is Worth
One Hundred And Sixty Dollars
Toward The Full Price Of The
SYSTEM/6 Package
System/6 with this coupon is only \$179.95.
This is a limited time offer.

\$160.00

ORDERING INFORMATION

Visa, Master Charge and C.O.D. O.K. To order call or write with the following information.

1. Name of Product (e.g. Macro I)
2. Media (e.g. 8" CP/M)
3. Price and method of payment (e.g. C.O.D.) include credit card info. if applicable.
4. Name, Address and Phone number.
5. For TPM orders only: Indicate if for TRS 80, Tarbell, Xitan DDDC, SD Sales (5¼" or 8"). ICOM (5¼" or 8"), North Star (single or double density) or Digital (Micro) Systems.
6. N.J. residents add 5% sales tax.

Manual cost applicable against price of subsequent software purchase in any item except for the Osborne software.

For information and tech queries call
609-599-2146

For phone orders ONLY call toll free

1-800-327-9191

Ext. 676

(Except Florida)

OEMS

Many CDL products are available for licensing to OEMs. Write to Carl Galletti with your requirements.

- * Z80 is a trademark of Zilog
 - * TRS-80 is a trademark for Radio Shack
 - * TPM is a trademark of Computer Design Labs. It is not CP/M*
 - * CP/M is a trademark of Digital Research
- Prices and specifications subject to change without notice.

DEALER INQUIRIES INVITED.

**COMPUTER
DESIGN
LABS**

342 Columbus Avenue
Trenton, N.J. 08629



Dominique Smith and Matthew Smith represented Instant Software, Microcomputing and 80 Microcomputing. By the way, in case you are one of those who "inspected" an Instant Software program from the rack and then just walked away with it, don't send it back as defective—you got just what you deserve. The display tapes are all blank.

North Star Computers drew a lot of interest with their multi-user system allowing up to five users to share the same system and hard disk. They also introduced an N Series of disk drives providing .82 megabytes of formatted storage per double-sided drive.

Impressions

Three things were apparent. First was the international nature of the show. Many of the attendees were from Germany, France or Japan. The aisles were a

babble of languages and sound. There were many Japanese exhibitors, most of whom had complete hardware systems, but needed distributors. This year and the next will certainly see the big Japanese marketing push, but the Japanese systems may bear many different nameplates when they hit the U.S. markets.

The second impression was that voice synthesis has come of age. Electronic voices were calling from several booths.

Finally, there will certainly be a little color in your life sometime soon. Color



Adam Osborne (left) was on hand to discuss his Osborne I system. This dual-drive \$1795 unit could blow the competition out of the water, or the small screen could make it fall flat. Initial evidence is that it will be a success. Osborne says he is backlogged with orders through at least the middle of 1982. A straw poll conducted while standing in various lines showed a lot of enthusiasm for the system. "even if you have to use a bigger monitor in some applications." The disk capacity (102K each) seemed small to some people, but most felt that even if they upgraded to higher capacity disks the system would still be very attractively priced.


displays were numerous on new systems, and lower-cost color printers seem to be emerging. The accompanying photos will give you many of the details of the displays, but this is a column on data communications, so let's see what the communicator can use.

Smartmodem

It all started with a company called D. C. Hayes making internal modems for Apple II and S-100 bus systems. They have changed their name to Hayes Microcomputer Products, Inc., but they still make the same integral modems. Now, they are launching a new product line of unique smart peripheral devices capable of interfacing with any computer system. The first ship of the line is the Smartmodem, and she's a beauty (see photo).

The Smartmodem is an RS-232C device. It is not a bus decoding or integral system. It does, however, provide all of the features of an integral modem (auto dial/answer, etc.) without unique software. In fact, the modem is so smart that the terminal can be completely dumb and still have automatic capability.

A small Z-8 microprocessor in the Smartmodem monitors the ASCII characters coming from the terminal (or microcomputer running a terminal program). It acts as a normal modem, converting the dc signals to audio tones at up to 300 bits per second (bps), until it recog-



Integral Data Systems demonstrated their very nice color printer. This device uses a multi-color ribbon which produces excellent quality. Release? "Maybe Christmas." Price? "Maybe \$2000, maybe a little more."



The Japanese companies had many systems on display. Often, they were looking for U.S. distributors for their products. Many U.S. system houses will probably market Japanese systems under their own names. NEC was pushing their PC-8000 series system, which features a full-color display, Z-80A 4 MHz CPU with CP/M compatibility and a very nice full-capability keyboard. Note the "IO Unit" expansion interface on the left.


nizes a string of characters pre-set in its memory. This command string can tell the Smartmodem to auto dial and auto answer, or to change such operational parameters as dialing speed, pulse or tone dialing, number of rings to answer

on, originate/answer mode and local echo. The modem will accept the command and send you back a prestored acknowledgement.

In normal operation, the Smartmodem comes up in an initial default mode which is determined by internal switches. You can command the modem to perform any of its functions directly from the keyboard. An easy way to do this would be to use the features of smart terminal programs such as OmniTerm, ASCII Express or Smart 80, which can prestore log-on codes of about 40 characters. These "macros" can be automatically sent by the selection of one or two keys and would be perfect for ordering the Smartmodem to auto dial.

Alternatively, a simple BASIC program could be used to shoot the desired characters out the RS-232C port. But I should emphasize that the Smartmodem can work with any dumb terminal. The commands can be quickly and easily entered from the keyboard.

The Smartmodem has a nice operating feature in the form of a built-in speaker, which lets you listen to the phone line. This is particularly useful during the dialing process so you can tell if you were not connected because of a busy signal or an unanswered ring. I usually leave a phone off the hook (with the microphone element removed) when using a direct-connection modem just so I can hear what's going on. I personally like to have the additional sense of hearing involved in the communications exchange—maybe that comes from 25 years of amateur radio operations.



The Digital Pathways SLC-11 voice synthesizer can store well over 300 complete words in ROM. The 6502 CPU and extensive operating system provides this "smart peripheral" with many options such as a list of different things to "say" to different people in response to one input. The activation of a fire sensor may cause the system to dial the fire department and give the address; it can then announce "Fire!" over the PA system while dialing the company president to tell him to "Get here quick!" The voice quality is excellent. The price is about \$2000.

I wonder, though, how much more in the way of smarts would be required for the Smartmodem to differentiate between a busy signal and a ring?

The Smartmodem is only the first of a line of unconventional peripheral devices. The photo shows a digital clock which mounts under the Smartmodem and interfaces with it. It hasn't been officially released yet and no one is saying what the interfaced system will do, but the cabinet is awfully big for just a clock. The Smartmodem should be reaching dealers right about now. The suggested retail price is \$279—not bad at all for such a unique and versatile device. Contact Hayes Microcomputer Products, Inc., at 5835 Peachtree Corners East, Norcross, GA 30092.

Talk to Me!

Several months ago, I wrote that the man-machine barrier must be broken.

I.E.E.E. 696

ads

S-100 BOARDS

6809 C.P.U. CARD

**PROM
PROGRAMMING CARD**

SOUND EFFECTS CARD

BREADBOARD CARD

& MORE

CALL OR WRITE:

**Ackerman
Digital Systems, Inc.
110 N. York Rd., Suite 208
Elmhurst, IL 60126 ✓261
(312) 530-8992**

SOFTWARE AUTHORS AND VENDORS

We are looking for programs of quality and usefulness for the TRS-80* Color Computer and Commodore VIC 20. Of particular interest are programs dealing with home finance and education. Please send documentation and/or sample to:

GENERAL VIDEOTEX CORPORATION
377 PUTNAM AVENUE
CAMBRIDGE, MASS. 02139 ✓392
(617) 491-3393

Publishers of the Kussmaul Encyclopedia™
"So simple even a grownup can use it."™

*TRS-80 is a trademark of Tandy Corp.
Encyclopedia is a trademark of
General Videotex Corporation.



The Votrax Type-'N-Talk is a versatile unit which reads aloud an ASCII string of characters. Words are defined as a string of characters separated by a space. A single letter or number bracketed by spaces will be pronounced by its name. An audio output on the back side of the unit is provided for feeding a more powerful amplifier. RS-232C and power are the only inputs. This smart peripheral device sells for \$345.

We have to develop terminal devices that are more user-friendly and less dependent on CRT displays and typing skills. The first cracks in the man-machine barrier have appeared. The NCC featured several voice synthesis and voice recognition systems.

The highest-quality speech came from a system produced by Digital Pathways (see photo); it had complete words stored in ROM for the use of the synthesizer. But at nearly \$2000 in single-unit quantities, this device is aimed at commercial uses (such as electronic banking).

The hit of the show was a small \$345 unit from Votrax called Type-'N-Talk (see photo). The name says it all. The Type-'N-Talk reads ASCII code coming from an RS-232C port and pronounces the English phonemes together to make words. The Type-'N-Talk needs no special program running in a computer. It has its own internal 6800 microprocessor and simply reads aloud the ASCII stream. It can be connected to any source of ASCII characters using RS-232C signaling. The price and ease of use make it almost a toy that you can keep around the computer room just to impress visitors if you do nothing else with it.

Of course, other things can be done with such an easy-to-use speech synthesizer. It is perfect for computer-assisted instruction. The verbal feedback it can provide in a training situation is unmatched by anything that can be easily put on a CRT. It has valuable uses for the blind, though some of these uses can be limited by the simple throughput speed of human speech.

The synthesizer operates from 70 to 100 bps. This roughly equals two words a second or 120 a minute (an average of five bytes per word). The unit has some buffering and can accept the data at any standard rate up to 9600 bps, but it can only pronounce it at about 120 words a minute. If you overload the 750 character buffer, you will simply lose the data.

This device could be used by the blind to read articles or mail from information utilities like The Source and CompuServe if the information utilities were instructed to transmit short "pages" (perhaps



Epson America took advantage of the show to introduce their new MX-100 printer, which is essentially an MX-80 with the capability of printing up to 233 columns wide in the compressed mode. It has both pressure feed and removable tractors and includes Epson's Grafrax II graphics package that gives high-resolution bit image graphics. Retail price is under \$995. A pressure feed version of the MX-80 was also on display. That's Chris Rutkowski, marketing manager of Epson, about to get his finger stuck in the printhead.



The folks at Personal Software kept the crowds happy with a constant demonstration of their VisiCalc and other "Visi-" software.

How's your love life?

A little dull around the edges?
Routine? Predictable? Boring? Maybe
all it needs is a little Interlude. Interlude is
the most stimulating computer game ever conceived.
It combines a computer interview, an innovative
programming concept, and a one-of-a-kind manual to
turn your love life into exciting, adventurous, delicious fun!

Interlude is: romantic...playful...outrageous...a fantasy. Interlude is: ■ A Bed of Roses (Interlude #1) ■ Mata Hari (Interlude #49) ■ The Chase (Interlude #7) ■ Rodeo! (Interlude #71) ■ The King and I (Interlude #60) ■ Some Enchanted Evening (Interlude #84) ■ Caveman Caper (Interlude #82) ■ From Here to Ecstasy (Interlude No. 30) ■ Satin Dreams (Interlude #72).

More than 100 Interludes are included in the program. Most are described in detail in the accompanying manual, but several surprise Interludes are buried in the program awaiting that very special time when your interview says you're ready. (When you learn secret Interlude #99, your love life may never again be the same!) Interlude can give you experiences you'll never forget. Are you ready for it?

InterludeTM
The Ultimate Experience. ✓ 235

INTERLUDE, Dept. KB, 10635 Richmond Avenue, Houston, Texas 77042. I'm really ready. Send my Interlude today.

Apple II (16K)*

- ☐ Cassette (\$18.95) ☐ Cassette (\$18.95)
☐ Diskette (\$21.95) ☐ Diskette (\$21.95)
☐ Diskette — Pascal or DOS 3.3 (\$21.95)

Add \$1.75 for shipping and handling.

☐ MASTERCARD

☐ VISA

All charge customers must sign here.

Account No. _____

Expiration date _____

MasterCard Bank Code _____

TRS-80 (Model 1, 16K)**

Poster

- ☐ 20"x 24" reproduction of
this ad without ad copy
(\$4.95—includes
shipping charges)

Available for immediate shipment.

Please enclose your check payable to INTERLUDE
or complete the charge information:

CHARGE CUSTOMERS: Order by phone toll-free! **1-800-231-5768 Ext. 306** (Texas: 1-800-392-2348 Ext. 306)

Name _____

Age _____

Address _____

City _____

State _____

Zip _____

*Apple II is a registered trademark of Apple Computers, Inc. **TRS-80 is a registered trademark of Radio Shack, a Tandy Co.



A communications multiplexer that can combine 16 phone lines to connect to and share the services of a TRS-80 Model II.

ten lines of 60 characters). A page is not transmitted until a carriage return acknowledges that the receiver is ready. This would, however, greatly slow down the rate of data exchange and greatly increase the connect time charges.

Alternatively, this device could be used to read information utility files if the data was downloaded at full speed, stored in local files by a smart terminal program and later retransmitted out the RS-232C port at a slower baud rate.

The Type-'N-Talk is beautifully set up to do this kind of modem-to-talker switching because it has a built-in extension of the RS-232C line. You do not have to change connectors or have two different RS-232C ports.

The quality and clarity of the Type-'N-Talk voice take a few minutes to get used to. The device has a frequency control which actually lets you fine-tune the pitch of the voice to your ear, and that

The quality and clarity of the Type-'N-Talk voice take a few minutes to get used to.

helps. After about three minutes of listening, I didn't miss a word. It is very much like listening to someone with an accent. The machine speaks phonetically, not colloquially. You get used to the rhythm and phrasing quickly, but you might not want to hit someone cold with it; say, over a telephone. It is not as good (or expensive) as the complete word synthesis systems used by the telephone company and banking services. But those systems are limited to about 300 words in ROM. Type-'N-Talk has no limitation. It can string together phonemes for anything you can type. Quite a machine! Phone Votrax at 1-800-521-1350 to order one.

Together?

The Hayes Stack Smartmodem and the Votrax Type-'N-Talk both represent a new breed of intelligent peripherals containing their own microprocessors and operating programs. They need no unique software to operate. I wonder if you put the two devices on line together, would the Smartmodem read its command string and reply back through the Type-'N-Talk. "By Your Command"? The modem could tell you when the phone was ringing ("One ringy-dingy, two ringy-dingy"). It could tell you when it had a carrier ("The tone! The tone!"). The list is endless. Mr. Hayes, there was a lot of room in that clock cabinet!

16 to 1

What was that big box sitting next to the TRS-80 in the above photo? Simple—it's a communications multiplexer.

A communications multiplexer is a device that combines many communications channels into one. Let's say, for instance, that you wanted to combine about 16 phone lines together so they could connect to and share the services of a TRS-80 Model II. Perhaps you wanted to set up a private information network for a company or development team, or groups of geographically separated farmers, doctors or librarians. Perhaps you were not happy with the one-at-a-time service most systems provide. You could then use a communications multiplexer to answer and combine as many as 16 phone lines into one.

The unit on display at NCC was an engineering model just fresh from the FCC certification labs, but a production unit should be appearing soon. You had better be serious though. The price for the 16-port unit was said to hover about \$8000. Oh, by the way, this kind of multitasking is very difficult to do if you don't have a hard disk.

Tell me

The world of microcomputer-based data communications systems is moving quickly. The power of its software and the quality of the hardware is maturing. If you market or manufacture hardware or software of interest to data communicators, let me know. Drop paper mail to PO Box 691, Herndon, VA 22070, and include a stamped envelope if you want a reply. Send electronic mail to TCB967 on The Source, 70003.455 on CompuServe, or to the AMRAD CBBS (703) 734-1387. □

A SHIRT-POCKET GUIDE

NEW!

✓ 146

ORDER OUR PRODUCT NO. 191

JUST \$2.00 POSTPAID (U.S.)

This handy, slim, 64-page reference contains a synopsis of each instruction available for the popular 6502 CPU. Mnemonics and machine codes in hexadecimal format are provided for each addressing mode. Appendices list the instruction set alphabetically by assembler mnemonics as well as numerically by machine code. A hexadecimal to decimal conversion chart is included. Additional information of value to programmers and designers is provided, including a chip pin-out diagram, basic timing information and diagrams of the basic chip architecture.

The 6502 INSTRUCTION HANDBOOK fits comfortably in a shirt or hip pocket.

It serves as a convenient reference for programmers, technicians and engineers. The guide may be obtained by mail for just \$2.00 postpaid in the United States. Order from: SCLEBI PUBLICATIONS, 20 Hurlbut Street, Elmwood, CT 06110

NAME (please print all information) _____

STREET ADDRESS _____

CITY _____ STATE _____ ZIP _____



Sony's 3-1/2-inch microfloppy drew a lot of attention. The 3-1/2-inch device can provide 435K of storage, but it isn't cheap.

HOOK 3 WINNERS



DOLPHIN


\$139.00

WINNER #1

data ed

\$159.00


WINNER #2




80 COLUMN
BLACK & WHITE
15 MHz

\$179.00

WINNER #3



P31
GREEN
PHOSPHOR
15 MHz



NEW
P31 GRAPHICS UNIT
RESOLUTION
1000+ LINES

**WATCH
THIS SPACE
FOR
COLOR
WINNER**

By **TECO**

**DEMAND THESE
UNITS FROM YOUR
DEALER!**

Data-Ed
18 Bridge Street
Salem, NH 03079
603-893-2047 (collect)

210

- _____ TM-12GX Monitors at \$179.00 plus 2.75 shipping
- _____ TM-12G Monitors at \$159.00 plus 2.75 shipping
- _____ TM-12 Monitors at \$139.00 plus 2.75 shipping

☐ Please send OEM information about your low cost custom fit smart printers.

- ☐ Check or Money Order enclosed
- ☐ C.O.D. Orders Accepted
- ☐ Bill my- ☐ VISA- ☐ Mastercharge

Card No. _____

Exp. Date _____ Bank No. _____

Signature _____



Name _____
Address _____
City, State, Zip _____

Name That Data Service

You Can't "Tele-text" Without a Scorecard

Videotex? Videotext? Viewdata? Teletext? The increased interest in information retrieval systems has caused some confusion as to what term refers to what service. The definitions are used somewhat interchangeably by many people,

but for the sake of clarity, *Microcomputing* has settled upon the following:

Videotext is a generic term that refers to the transmission of textual material via telephone lines or TV signals to your TV set or microcomputer. It thus encom-

passes both viewdata and teletext.

Videotex is commonly used in place of videotext, particularly in Canada, which recently hosted the Videotex '81 conference. But it also refers to a specific information retrieval system being marketed by Radio Shack. The full system consists of a TRS-80 Videotex terminal and Videotex software. (To show how confusing this can get, the October 1980 issue of Radio Shack's *TRS-80 Microcomputer News* refers to the software as Videotext in the headline and Videotex in the text.)

Teletext, according to the book *Videotext: The Coming Revolution in Home/Office Information Retrieval*, is "a one-way system, which piggybacks digital data on the normal television broadcast signal by inserting its messages in unused lines of the vertical interval." The user is able to call desired pages with a special control keypad.

Viewdata, says the same book, is an interactive system using the telephone lines and a modem. This shouldn't be confused with the Viewdata Corp. of America, which is a subsidiary of Knight-Ridder Corp.

* * * * *

A postscript to last month's comments on acronyms:

Keith Alexander of Detroit points out that many computerists are getting in the habit of capitalizing the language Ada, as in ADA. But Ada, like Pascal, is the name of a person, and is not an acronym. Ada Augusta Lovelace was a mathematician, and an associate of Charles Babbage, a 19th century inventor.

Alexander also says that the word spool, when referring to timesharing tasks, is an acronym for Simultaneous Peripheral Output On Line. It's a good example of an acronym falling into common use as a word.

* * * * *

In June, this column offered a simple formula by which business executives could name new products and companies. It consisted of two lists—26 pre-

```

10 'COMPNAME - PROGRAM TO INVENT COMPANY & PRODUCT NAMES
15 'BY JEROME S. MILLER, GRAND RAPIDS, MI 49505
20 'SUGGESTED BY ARTICLE IN KILOBAUD, JUNE '81, P. 24
25 'BASED ON ALIEN NAME PROG. PERS. COMP. MAG. 11/'79 P. 56
30 'THIS LISTING IS FOR TRS-80 MOD I TRSDOS 2.3
40 'DELETE LPRINTS IF YOU DON'T NEED HARDCOPY
100 DIMA$(26),B$(26)
110 A$(1)="COMPU";A$(2)="TELE";A$(3)="MULTI";A$(4)="DATA"
120 A$(5)="INTER";A$(6)="DIGI";A$(7)="AUTO";A$(8)="UNI"
130 A$(9)="VIDEO";A$(10)="INFO";A$(11)="SOFT";A$(12)="MEGA"
140 A$(13)="ASTRO";A$(14)="MICRO";A$(15)="OPTI";A$(16)="DYNA"
150 A$(17)="PLEXI";A$(18)="RAM";A$(19)="COM";A$(20)="TECHNO"
160 A$(21)="CON";A$(22)="FILE";A$(23)="INSTA";A$(24)="META"
170 A$(25)="ELECTRO";A$(26)="ALPHA"
200 B$(1)="DATA";B$(2)="SOFT";B$(3)="MICRO";B$(4)="RAM"
210 B$(5)="NET";B$(6)="COM";B$(7)="TYPE";B$(8)="TECH"
220 B$(9)="NATION";B$(10)="WRITER";B$(11)="GRAPHICS"
230 B$(12)="TEX";B$(13)="SERVE";B$(14)="FAX";B$(15)="TEL"
240 B$(16)="TRONIX";B$(17)="PLUS";B$(18)="CON";B$(19)="FILE"
250 B$(20)="FLEX";B$(21)="COMP";B$(22)="FLEX";B$(23)="VIDEO"
260 B$(24)="LINK";B$(25)="METRICS";B$(26)="CALC"
300 CLS:PRINTTAB(12);"<X> COMPANY & PRODUCT NAMES <X>"
305 LPRINTCHR$(32);LPRINTTAB(12);"<X> COMPANY & PRODUCT NAMES <X>"
310 PRINT
320 INPUT"HOW MANY NAMES DO YOU WANT";N
325 LPRINTCHR$(32);LPRINT"HOW MANY NAMES DO YOU WANT";N
330 CLS:PRINT"HERE ARE YOUR"N" NAMES";PRINT
335 LPRINTCHR$(32);LPRINT"HERE ARE YOUR"N" NAMES"
340 FOR I=1 TO N
350 GOSUB1000
360 X$(1)=A$(A) 'SELECT PREFIX
370 GOSUB1000
380 X$(2)=B$(B) 'SELECT SUFFIX
390 PRINT X$(1)+X$(2);LPRINT X$(1)+X$(2)
400 FORT=1TO100:NEXT
410 NEXT I
500 PRINT"TYPE 1 FOR NEW LIST; 2 TO EXIT"
510 Z$=INKEY$:Z=VAL(Z$)
520 ONZGOTO 300,540
530 GOTO 510
540 CLS:PRINT"464,"BYE BYE, COME BACK AGAIN!"
550 END
1000 A=RND(26);B=RND(26):RETURN

```

Listing 1.

fixes and 26 suffixes—which could be randomly combined to make 676 possible monikers. Well, Jerome S. Miller of Grand Rapids, MI, wrote a program for the TRS-80 Model I that does the pairing automatically. Listing 1 is the program, while Sample run 1 gives 40 of the possible combinations.

* * * * *

Is this what you really wanted to say department: Microcomputing author Mark Borgerson, who makes his home in Corvallis, OR, was looking through the software notes for Hewlett-Packard's HP-85 when he ran across this mind-twister.

"This particular note concerned problems which might occur when users tried to run certain application packs with other ROMs plugged into the system. It seems that the ROM packs compete for memory, resulting in an Out of Memory error. The software note explained the problem this way:

"The pacs were designed to operate in

a particular "typical configuration" so that more power could be built into each application. This trade-off in power versus flexible configuration was deliberately made to minimize the capabilities of our software for the most number of users."

"Somehow, I think the marketing people at Hewlett-Packard might object to the phrasing in that last sentence."

* * * * *

Punctuation is a boogeyman for many writers. Some have an almost complete aversion to it, while others toss punctuation marks around like grass seed. In this latter category are the comma fetishists, who can't march across a typed line without dropping two or three commas along the way. Reading their sentences is like climbing a tall ladder—by the time you reach the top, you're so exhausted that you're no longer interested in the view. Here's an example that recently crossed the *Microcomputing* desk:

"Quite simply, Grow is a BASIC language program, currently available to Apple II and Plus II and North Star users, that allows you to write, in plain English, and with only a few system commands, original, one-of-a-kind programs, which are contained in nodes, mini-programs themselves, linked together as needed to make up the entire program."

Is this any way to treat the comma? □

<*> COMPANY & PRODUCT NAMES <*>


HOW MANY NAMES DO YOU WANT 40

HERE ARE YOUR 40 NAMES



TECHNOFAX
TELETEL
PLEXIMETRICS
DATACOM
PLEXIRAM
DATACOMP
INSTATEL
AUTOFILE
DYNAMETRICS
PLEXISERVE
RAMLINK
COMSOFT
TELECOM
INSTAFAX
INFOTEL
CONTEX
DIGIVIDEO
ALPHA FAX
METALINK
INFOMETRICS
METAPLUS
TECHNOMETRICS
DATALINK
AUTOTECH
CONLINK
FILEFLEX
DYNASERVE
FILECALC
VIDEOLINK
MICRO RAM
RAM
INFOMATION
PLEXITEL
INSTASERVE
METATYPE
FILETECH
DYNAPLUS
FILETYPE
DYNAVIDEO
INSTAPLUS

Sample run 1.

MICROSETTE CASSETTES



**C-10 C-20
COMPUTER CASSETTES**



**C-60 C-90
AUDIO CASSETTES**

Microcassette, the undisputed industry leader in short cassettes for microcomputer applications also offers equally high grade audio cassettes at budget prices. Credit card buyers may phone (415) 968-1604.

LOOK AT OUR PRICES

Length	10 Pack	50 Pack
C-10	\$ 7.50	\$32.50
C-20	\$ 9.00	\$39.00
C-60	\$13.50	\$57.50
C-90	\$17.50	\$77.50

UPS shipment in Cont. USA incl.
We can not ship to P.O. Boxes

Length	Qty.	Price	Total
SUBTOTAL			
Calif. Cust. add Sales Tax			
TOTAL			

Check or money order enclosed ☐
Charge to: Visa ☐ Master Card ☐
Account No. _____
Expiration Date _____

SIGNATURE _____

KM

MICROSETTE CO.
475 Ellis Street
Mt. View, CA 94043

SIEMENS FLOPPY DISK SALE!

■ We are an OEM for SIEMENS disk drives, and have we got a deal for you! Floppy Disk Services is selling the latest and greatest disk drives direct to you at prices you can't find anywhere else. We buy in big quantities to set the best prices and pass that savings on to you.

■ Looking for 8" drives? The FDD-100-8 is the latest most updated model from SIEMENS. Single sided single or double density. These drives are built on tough chassis for years of trouble free use. They are rack mountable and Shugart compatible, both physically and electrically. Power requirements are simple just +24v and +5v, negative voltage not required. The motor is A.C. driven.

■ Need 5.25" drives? The FDD-100-5 is for you. These drives are 35 or 40 track models and like their big brothers are the latest models from SIEMENS. They work perfectly with the TRS-80 Mod 1 and are direct replacements for the drives used in Heath computers. Powered by just +12 and +5vdc.

ask about our 8" dual drive package for TRS-80 MOD II — \$995.00 for TWO drive system

FDD-100-8d. \$360.00 each

FDD-100-5b. \$250.00

power conn. set 8" \$3.50

Manuals (8" or 5.25") \$13.00

8" package requires some assembly.

All shipping via U.P.S. rates.

Prices & Specs subject to change. ✓ 191

Floppy Disk Services Inc.

C.N. 5212

Princeton, N.J. 08540

(609) 771-0374



Micro M. D.

Is There A Computer In the House?

Data for Health

An Apple software package that will make health information easily accessible to both doctors and their patients is being tested in several Montreal clinics.

Over a dozen programs will provide preventive and treatment information on such topics as chronic diseases and the side effects of medication and general health tips.

The package, developed by Dr. Michel Bourque of Montreal's Clinical Research Institute, is designed for a \$3000 Apple II with one disk drive and 48K memory. Bourque uses Applesoft BASIC with DOS 2.3, and has a numeric keyboard from Advanced Business Technology.

The programs, in a question/answer format, are for the "naive user," Bourque says. "We kept it very simple, so it can be used without training." The patient chooses a disk with the desired topic. The computer records the patient's questions, so the doctors can change the database according to demand. The computer can also question the user to help doctors develop demographic data.

The database has been compiled by five doctors at the institute's Hypertension Clinic, and at a research clinic headed by Dr. Robert Perrault of Montreal's Prevost Hospital.

Perrault is now testing programs that will provide sex education and contraceptive information for adolescent patients. The microcomputer is set up in a waiting room; Perrault hopes it will encourage patients to ask doctors further questions. The Hypertension Clinic is also using the micro, and its stress program is being tested throughout Quebec.

Another program, to help the chronically ill cope with the secondary effects of disease, will be tested in late fall, Perrault says. Three groups will be given diet and treatment advice: one with the microcomputer, another by a specialist and the third through biblio-therapy, or reading material. The hospital has few people for one-to-one counseling, Perrault says, and the computer should help to ease the pressure.

Though the system is suitable for both clinics and private practitioners, Bourque says it can also be used in such public places as shopping malls. Private physicians will find the system useful for after-hours business. And with additional software, it could even be converted to a computer bulletin board for doctors and researchers.

The \$100 operating disk and \$30 database are available from the institute's Computer and Biostatistics Research Centre, 110 Pine Ave. W., Montreal, PQ H2W 1R7.

**Contributed by Betty Thayer,
Microcomputing staff.**

Down on the Farm

The growing number of farmers using microcomputers has spawned a new newsletter—*Farm Computer News*.

The newsletter, spun off from Meredith Corp.'s *Successful Farming* magazine, made its debut in May, promising "all kinds of computer information of interest to farmers, farm managers and agribusiness people."

The idea for the magazine came after a survey showed that at least one percent of *Successful Farming's* 750,000 sub-

scribers own computers, with another 23 percent expecting to buy one within six years.

Most of those computers are TRS-80s, Apples and Commodores.

The first issue of *FCN* included an article on a users group called Agri-Cursors, a review of the Microsoft Z-80 card, a piece on information retrieval, tips for computer buying and the Computer Trade Mart.

Editors Chuck Sommers and Gary Vincent have an Apple II+ in the office. While they don't do any word processing on it, they use the Apple for reviewing programs and accessing outside databases.

"The unit we bought is very typical of what the farmer has," says Sommers. "This way we put ourselves in their position."

He adds that neither he nor Vincent is a "computer expert," although he has taken some computer courses at a local community college. But he says that this will let them walk through the same problems that their readers are experiencing.

While Radio Shack has actively pursued the agriculture market, Sommers says that Apple dealers "follow their sales more than Radio Shack."

"Radio Shack said basically, 'Here it is; take it or leave it,'" Sommers says. "They knew what we wanted and that we were very interested, but they didn't follow up on it."

Most farmers are using their computers for basic business management and accounting applications, Sommers says. The software is coming from a number of places: software houses, universities, independent consultants

and the farmers themselves. Except for financial needs, says Sommers, most farming applications are too specific for general off-the-shelf programs.

"VisiCalc has been adapted because there hasn't been anything else," he says. "It adapts well, but it is by no means the final answer."

Some farmers are using their micros to access such information databases as Agnet, which provides programs that farmers can use on their own systems. Other services, such as that of the Green Thumb project in Kentucky, offer information on such topics as market, the weather and pest control. But Sommers says that some kinks still have to be worked out before farmers make widespread use of these services.

"I know a farmer who's trying to use CompuServe, and is finding that it's not fast enough," he says. "He can get his information faster on the radio."

Subscriptions to Farm Computer News are \$40 per year. For more information, write to them at 1716 Locust, Des Moines, IA 50336.

Jerry Van Dyke, Where Are You?

You'll never have to look at your automobile's idiot lights again with Copilot, a microcomputer that monitors the car's systems and tells you over the radio when any of them are malfunctioning.

The soft, female voice—which should bring a rush of nostalgia to those who fondly remember Ann Southern and "My Mother the Car"—prompts you with such gentle hints as "Please remember your lights" and "Please remember your keys." It also lets you know when:

- The door is not closed tightly.
- You're almost out of gas.
- Your brakes are about to fail.
- Your oil pressure is low.
- The lights are left on after the engine is turned off.
- The engine is about to overheat.
- The keys are left in the ignition.
- The seat belts are left unfastened.
- The battery voltage is low.
- Diesel engines are not warmed up.

Copilot is the creation of Aristotle, Inc., owned by brothers John Aristotle and Dean Phillips. J. A. also goes by the alias The A-Bomb Kid—he's the Princeton University student of several years ago who made news by designing an atomic bomb from public documents. He's now 25, while his brother, an MIT graduate, is 23.

Dean says the Copilot is essentially a verbal set of idiot lights. The unit taps into the wires that run to the various lights and buzzers in the dash. Each unit, while not programmable by the owner, has what Phillips calls "a certain amount of learning ability," which lets the owner adapt it to his particular make of car.

With the exception of fuel, the critical levels at which Copilot responds are pre-

determined. The owner can adjust the computer to warn him or her of low fuel at anywhere from empty to half a tank. The voice will pipe up whether the radio is on or off.

Why a female voice? "It was a very conscious decision on our part," Phillips says. "The noise in a car tends to be low-frequency, and a male voice literally gets lost. Also, we felt that a female voice was more pleasing to hear."

Phillips says that Copilot is made to fit all cars. "If it comes out of Detroit and uses standard engine technology, it can use our system." It is also usable by trucks, buses and most other types of vehicles.

The company claims that Copilot is a first in the industry. Datsun has a model that talks, but, says Phillips, they use "what is literally a small record player." General Motors uses a microprocessor in some of its Cadillacs, but it does not have

The soft, female
voice prompts you
with such gentle
hints as "Please
remember your lights"
and "Please remember
your keys."

voice capability (see next article).

"Many automobile manufacturers didn't think that voice was possible for at least a couple of years, so they didn't bother with it," Phillips says.

By the way, if you're a hardware tinkerer thinking of buying one to modify for other uses, Phillips warns against it. The unit uses National Semiconductor's Digtalker DT1050 integrated circuit set, but uses special operating software and a custom-designed vocabulary.

The Digtalker kit is available commercially, and includes a vocabulary of 144 expressions. For a complete discussion of the kit, see Steve Ciarcia's article "Build a Low-Cost Speech-Synthesizer Interface," on page 46 of *Byte* magazine's June 1981 issue.

Copilot sells for \$199.95 plus \$4.50 for postage and handling. For more information, write Aristotle, Inc., Box 21, Norwalk, CT 06853. If you want to buy one, you need to include the make, model and year of your car.

Cadillac Blues

The microprocessor-controlled 1981

Cadillacs are beaching like suicidal whales, according to an article in *Electronic Engineering Times*.

In fact, some 100 Cadillac owners in 22 states have filed a class-action suit against General Motors, complaining of such problems as stalling in traffic, poor fuel economy, engine surges and indecisive shifting.

The Cadillac was introduced with much fanfare because of its unique 4-6-8 cylinder mechanism, which uses a microprocessor to find the right cylinder operation according to the driving circumstances.

An interesting feature of the microcomputer, says EET, is that it records whether the driver goes over 85 mph. The computer will also record whether the owner receives proper service within 30 miles of driving after the Check Engine light goes on.

Time for Beddy-Bytes

Homestead Computer Services, Ltd., of Winnipeg, Manitoba, has designed a computerized hospital bed monitoring system for Winnipeg's Seven Oaks Hospital.

Admissions/discharge/transfer (ADT) systems have often tied into large computers to keep track of patient bed use, but this is the first microcomputer-based bed monitoring system, says Homestead's president Sheldon Fulton.

The system's speed will let the hospital use its bed space more efficiently, saving both the hospital and Canadian taxpayers money.

The system, in use since Seven Oaks opened in January 1981, consists of a modified Vector Graphics microcomputer and five G.E. ADS terminals. Current patient-status information is stored on memory boards which have battery backup in case of power failure.

A terminal is located at nursing stations on each of the three floors where information can be quickly accessed and updated for that floor. Another terminal, centrally located at the admitting desk, can access and update information for the entire hospital. A fifth terminal, located in housekeeping, has display capabilities only.

Information provided by the computer includes bed status (occupied or empty), whether the room is for men or women, which wing of the hospital the room is in, when the room needs to be cleaned and when it's available for admission.

Florence Landygo, director of health records and information services at Seven Oaks, has found the system helpful and easy to use. Speed of information communication and reduced paper flow are two of the advantages of the new micro system. "By and large it does its job," Landygo says. Two modifications she recommends are inclusion of the patient's name with the other data dis-

played on the screen and printout capability.

Although it's too early to tell how much money Seven Oaks has saved through microcomputer-based bed monitoring, Homestead Computer Services is optimistic about the success of such systems. Says Fulton, "We're interested in seeing where we can go from here."

**Contributed by Lise Markus,
Microcomputing staff.**

Publications on Courseware

Several new publications focusing on courseware are out, or will soon be available.

School MicroWare Reviews will make its debut in July, and will feature reviews for some 100 instructional programs and packages. The publication, which will come out twice a year, will be organized by school department and subject. A rating of each software package will be accompanied by comments on documentation, instructions to users and the student-computer dialog. Each edition will also include an index to evaluations in other publications.

SMW Reviews will cost \$30 per edition. Subscribers to Dresden's other publication, the *School MicroWare Directory*, will receive it free if they submit evalua-

tions to *Reviews*. Nonsubscribers whose reviews are used will receive it for half-price.

Dresden Associates, Inc. is located at PO Box 246, Dresden, ME 04342. Call 207-737-4466 for an evaluation form and instructions.

The 1981 *Courseware Market Report*, published by Shotwell and Associates, is billed as "the first comprehensive reference book for all individuals, companies, and institutions preparing educational products for the computer software market."

The report includes statistics on hardware installations in educational institutions, a discussion of videodisk technology, a listing of hardware and courseware suppliers and a discussion of programming and authoring languages for developing educational software on microcomputers.

Price for the volume is \$175.

Shotwell and Associates is located at 44 Montgomery St., Suite 505, San Francisco, CA 94104.

Queue provides several directories of educational software. Their *IVA Educational Software* catalog is for the Apple, Atari and Compucolor, while the *IVB* catalog is for the PET and TRS-80. The *IVB* catalog also includes limited listings for the Sinclair, OSI and SOL micros. The catalogs are \$8.95 each.

Queue's address is 5 Chapel Hill Drive, Fairfield, CT 06432.

The National Council of Teachers of Mathematics has recently published a 30-page book entitled *Guidelines for Evaluating Computerized Instructional Materials*. The book, written for both experienced and novice programmers and users, discusses how to find promising materials without first buying them, how to evaluate the software and how to catalog it.

The book's forms and checklists are designed to be computerized for easy use, updating and retrieval.

The *Guidelines* are \$3.75, \$3 for NCTM members. The Council's address is 1906 Association Drive, Reston, VA 22091 (703-620-9840).

Help Solve a Murder

The quick summary read "Help Solve a Murder!", and many people accessing the Nobug Forum-80 Bulletin Board in Cleveland probably thought that it was from a frustrated game player fishing for clues to an adventure program. But if they retrieved the full message, they were in for a surprise: it was a call for help in tracking down equipment taken from a computer store during a robbery that resulted in the killing of the owners.

DR. DALEY OFFERS SOFTWARE FOR EVERYONE

DATA BASE

The data base package allows total user control over the contents of each entry in the file. Features user selectable record size from 5 to 242 characters per record, statistical and plotting package, output with WORDPRO files or printer. Includes full user definable output formatting. With optional indexing routine can produce a comprehensive index of a data set.

Index \$299.95
 99.95

For PET or CBM 2000 or 8000 series with 32K memory please specify your machine configuration.

MAIL LIST

This powerful mailing list package features a variety of options for producing labels. It includes user defined file structure and label format. Label format can list to the printer or to WORDPRO format files.

\$159.95

SOFTWARE LIBRARY

Hundreds of schools and individuals have purchased this package for use as an educational tool or just plain fun. It contains 50 (yes fifty!) programs. This ranges from our famous TREK 3 and horse race to fun learning programs for children to checkbook and a micro mail list program with lots in between. At about \$1.40 per program how can you miss?

Cassette \$69.95
Diskette 79.95
For APPLE II or PET

Charge to
your
MC/VISA



DR. DALEY'S SOFTWARE ✓34

425 Grove, Berrien Springs, Michigan 49103

Phone (616) 471-5514 Sunday-Thursday noon to 9 p.m. Eastern Time

The message reported how Henry and Laverne Rumberger, owners of the ABS Computer Services Store in Olympia, WA, were killed on Sunday, Feb. 22. It followed with a list of the equipment stolen, along with serial numbers. The equipment included an Apple III, three Apple IIs, a disk drive, a BMC monitor, a Sony TV, a Centronics 737 and an IDS Paper Tiger.

"If you discover any of these items, please contact the Olympia police department," the message concluded, along with the department's phone number.

Nobug operator Ray Furlong says that he read about the murders in a microcomputer magazine, and thought it was a good idea to put the information on his system. As far as he knows, it's the first time a system has been used for that kind of message.

The idea may be a precursor to more organized attempts to locate stolen equipment. According to a store owner in Seattle, WA, the Seattle-Puget Sound area has had a rash of burglaries during the last year. Dealers are considering forming a dealers association, one function of which would be to exchange information on hot hardware.

"Our service center sees a lot of equipment, and it would be very easy for us to match serial numbers as the stuff comes in," he says.

The "Help Solve a Murder!" message has been picked up from Nobug and put on at least one other system, the Medical Forum-80 BBS in Lansing, MI.

Ancestors on Disk

Genealogical Computing, a bimonthly newsletter for genealogists and computerists, begins publication this month.

The newsletter, put out by Data Transfer Associates, will include a directory of genealogy programs for micros, columns on how to computerize family research records and program reviews.

Editors Paul and Saralou Andereck operate the Family Historians' Forum, a free computer bulletin board system for genealogists. The Forum, which has been on-line since September of 1979, is used to exchange family research information.

Genealogical Computing costs \$12. DTA's address is 5102 Pommeroy Drive, Fairfax, VA 22032. Call 703-978-7561 from 6 PM to 6 AM on weekdays and noon to 6 AM on weekends and holidays to access the Forum.

Dow Jones for PETs

The Dow Jones Portfolio Management System, a software package designed for accessing its News/Retrieval Service, is

now available for Commodore microcomputers.

The system will run on Commodore's dual disk microcomputer, Model 2001-32K or Model 4032. Buyers will also receive a Dow Jones password and one hour of free introductory usage.


The system, developed by Micro Business Systems of Pine Brook, NJ, is for private and professional investors, letting them maintain multiple portfolios and continuously track, value, graph and research each one. It automatically retrieves price quotations (on a 15-minute delay basis) on some 6000 stocks and other securities from Dow Jones' computerized News/Retrieval Service.

Dow Jones News/Retrieval Service provides business news from Dow Jones' domestic and international news wires, *The Wall Street Journal* and *Barron's National Business and Financial Weekly*, plus company profiles and 10K extracts from Disclosure, Inc., Washington, DC; detailed corporate financial information from Media General Financial Services, Inc., Richmond, Va.; and a weekly economic survey of key economic and monetary indicators, with commentary and analysis, from Money Market Services, Inc., of San Francisco, CA. In addition, Free Text Search allows users to retrieve news stories as far back as June, 1979 by keyword search. □




PRESTO! A direct mail system

EPSON not only gives correspondence quality printing, but is an ideal label printer. Tell us about your computer. We'll furnish the printer, interfaces, cables, and the rest, so you will have an instant, low-priced, working system. We carry all accessories, printheads and ribbons.



EPSON MX-80
9x9 Head
80 Column



NEW EPSON MX-100
9x9 Head
233 Column
(Under \$1,000)



EPSON MX-70
5x7 Head
80 Column
(Under \$500)

**ASK FOR OUR
INSTANT DISCOUNT**
From Roy Hawthorne
Talk To Bill Tokar On
Applications

**CALL TOLL FREE
U.S.A.**
1-800-521-2764
MICHIGAN
1-800-482-8393

Remember:
We are open
8:30 AM to
6:00 PM EST
Monday - Friday



**No Credit
Card Penalty**

WRITE TO:
"The Stocking Source"
24069 Research Drive
Farmington Hills, MI
48024
313-474-6708 ✓ 288

TWELVE STRONG HEATH/ZENITH YOUR

Pick a strong partner

A computer purchase is the beginning of a long term partnership between you and the people you buy from. Your ongoing need for software and accessories requires a partner who will stand by you with a growing line of products. And nowhere will you find a more complete line of hardware, software and accessories than at your Heathkit Electronic Center. Here are twelve strong reasons to make Heath/Zenith your partner.

1. The All-In-One Computer

The heart of the Heath/Zenith line is the stand-alone 89 Computer. It's a complete system with built-in 5¼-inch floppy disk drive, professional keyboard and keypad, smart video terminal, two Z80 microprocessors, and two RS-232C serial I/O ports. It comes with 16K RAM, expandable to 64K.

2. Peripherals



These include the popular *Heath/Zenith 19 Smart Video Terminal*, loaded with professional features. And the *14 Line Printer*, priced as low as \$495. Other printer brands are on display, including high-speed, typewriter-quality printers.

3. Software

Word processing, includes reliable, easy-to-use Zenith Electronic Typing and powerful, full-featured WORDSTAR.

Small Business Programs, feature General Ledger and Inventory Control.

HUG, Heath Users' Group, offers members a library of over 500 low-cost programs for home, work or play.

4. Programming Languages



For your own custom programs, Microsoft languages are available in BASIC (compiler and interpreter), FORTRAN and COBOL.

5. Operating Systems

Three versatile systems give you the capability to perform your specific tasks.

CP/M by Digital Research makes your system compatible with thousands of popular CP/M programs.

UCSD P-System with Pascal is a complete program development and execution environment.

HDOS, Heath Disk Operating System gives you a sophisticated, flexible environment for program construction, storage and editing.

6. Utility Software

Expand the performance range of your computer with a broad selection of utility tools, including the best of *Digital Research* and the complete line of innovative *Softstuff* products.


7. Disk Systems

The 8-inch Heath/Zenith 47 Dual Disk System adds over 2 megabytes of storage to your




89 Computer. Diskettes are standard IBM 3740 format, double-sided, double-density.

The 5¼-inch 87 Dual Disk System adds 200K bytes of storage to your 89. Both disk systems feature read/write protection and easy plug-in adaptability.



8. Self-Study Courses

Learn at your own pace with *Programming Courses* that teach you to write and run your own programs in Assembly, BASIC, Pascal or COBOL.



A course on *Computer Concepts for Small Business* gives you the understanding to evaluate the ways a computer can benefit your business.

Personal Computing is a complete introduction to the fundamentals for the novice. Every Heathkit/Zenith course is professionally designed for easy, step-by-step learning.



All Heath/Zenith Computer Products are available completely assembled and tested for commercial use. Or in easy-to-build, money-saving kits.

✓ 236


REASONS TO MAKE COMPUTER PARTNER

9. Expansion Options

Communicate with the outside world through a *Three-port EIA RS-232C Serial Interface*.

Expand RAM to 64K with easy-to-install *expansion chips*.

10. Accessories



Your Heathkit Electronic Center has the latest in modems, black-and-white and color video monitors, computer furniture and a full line of supplies, accessories, books and parts.

11. Service

No one stands by you like Heath/Zenith. We help you get your system up and running smoothly. Service is available from trained technicians, over the phone or at one of 56 Heathkit Electronic Centers.



12. Value

Your money buys you more because Heath/Zenith prices are among the industry's most competitive. Make your own comparison and find out how much you can save.

Complete, integrated computer hardware and software, designed to serve you and to grow with you — that's what to look for in a strong partner. And with Heath/Zenith you get it all under one roof.

All at your Heathkit Electronic Center

Pick the store nearest you from the list at right. And stop in today for a demonstration of the Heath/Zenith 89 Computer System. If you can't get to a store, send \$1.00 for the latest Heathkit® Catalog and the new Zenith Data Systems Catalog of assembled commercial computers. Write to Heath Co., Dept. 351-804, Benton Harbor, MI 49022.

Visit Your Heathkit Electronic Center*

where Heath/Zenith Products are displayed, sold and serviced.

PHOENIX, AZ 2727 W. Indian School Rd. 602-279-6247	MISSION, KS 5960 Lamar Ave. 913-362-4486	CLEVELAND, OH 28100 Chagrin Blvd. 216-292-7553
ANAHEIM, CA 330 E. Ball Rd. 714-776-9420	LOUISVILLE, KY 12401 Shelbyville Rd. 502-245-7811	COLUMBUS, OH 2500 Morse Rd. 614-475-7200
CAMPBELL, CA 2350 S. Bascom Ave. 408-377-8920	KENNER, LA 1900 Veterans Memorial Hwy. 504-467-6321	TOLEDO, OH 48 S. Byrnes Rd. 419-537-1887
EL CERRITO, CA 6000 Potrero Ave. 415-236-8870	BALTIMORE, MD 1713 E. Joppa Rd. 301-661-4446	WOODLAWN, OH 10133 Springfield Pike 513-771-8850
LA MESA, CA 8363 Center Dr. 714-461-0110	ROCKVILLE, MD 5542 Nicholson Lane 301-881-5420	OKLAHOMA CITY, OK 2727 Northwest Expressway 405-848-7593
LOS ANGELES, CA 2309 S. Flower St. 213-749-0261	PEABODY, MA 242 Andover St. 617-531-9330	FRAZER, PA 630 Lancaster Pike (Rt. 30) 215-647-5555
POMONA, CA 1555 N. Orange Grove Ave. 714-623-3543	WELLESLEY, MA 165 Worcester Ave. 617-237-1510	PHILADELPHIA, PA 6318 Roosevelt Blvd. 215-288-0180
REDWOOD CITY, CA 2001 Middlefield Rd. 415-365-8155	DETROIT, MI 18645 W. Eight Mile Rd. 313-535-6480	PITTSBURGH, PA 3482 Wm. Penn Hwy. 412-824-3564
SACRAMENTO, CA 1860 Fulton Ave. 916-486-1575	E. DETROIT, MI 18149 E. Eight Mile Rd. 313-772-0416	WARWICK, RI 558 Greenwich Ave. 401-738-5150
WOODLAND HILLS, CA 22504 Ventura Blvd. 213-883-0531	HOPKINS, MN 101 Shady Oak Rd. 612-938-6371	DALLAS, TX 2715 Ross Ave. 214-826-4053
DENVER, CO 5940 W. 38th Ave. 303-422-3408	ST. PAUL, MN 1645 White Bear Ave. 612-778-1211	HOUSTON, TX 1704 W. Loop N. 713-869-5263
AVON, CT 395 W. Main St. (Rt. 44) 203-678-0323	BRIDGETON, MO 3794 McKelvey Rd. 314-291-1850	SAN ANTONIO, TX 7111 Blanco Road 512-341-8876
HIALEAH, FL 4705 W. 16th Ave. 305-823-2280	OMAHA, NE 9207 Maple St. 402-391-2071	MIDVALE, UT 58 East 7200 South 801-566-4626
PLANTATION, FL 7173 W. Broward Blvd. 305-791-7300	ASBURY PARK, NJ 1013 State Hwy. 35 201-775-1231	ALEXANDRIA, VA 6201 Richmond Hwy. 703-765-5515
TAMPA, FL 4019 W. Hillsborough Ave. 813-886-2541	FAIR LAWN, NJ 35-07 Broadway (Rt. 4) 201-791-6935	VIRGINIA BEACH, VA 1055 Independence Blvd. 804-460-0997
ATLANTA, GA 5285 Roswell Rd. 404-252-4341	AMHERST, NY 3476 Sheridan Dr. 716-835-3090	SEATTLE, WA 505 8th Ave. N. 206-682-2172
CHICAGO, IL 3462-66 W. Devon Ave. 312-583-3920	JERICHO, L.I. NY 15 Jericho Turnpike 516-334-8181	TUKWILA, WA 15439 53rd Ave. S. 206-246-5358
DOWNERS GROVE, IL 224 Ogden Ave. 312-852-1304	ROCHESTER, NY 937 Jefferson Rd. 716-424-2560	MILWAUKEE, WI 5215 W. Fond du Lac 414-873-8250
INDIANAPOLIS, IN 2112 E. 62nd St. 317-257-4321	N. WHITE PLAINS, NY 7 Reservoir Rd. 914-761-7690	

Prices and specifications subject to change without notice.

*Units of Veritechnology Electronics Corporation in the U.S.

HEATH/ZENITH

236

Your strong partner

Firm Up Your Floppy With 800K

By Peter A. Stark

It's quite possible to put 800 kilobytes of data on one five-inch mini-floppy diskette, thus rivalling the 1.2 megabytes or so that can be stored on an eight-inch diskette.

The trick is to use one of the newer disk drives such as the model 92 made by Micro Peripherals, Inc. (MPI), which provide twice the number of tracks per side, with two sides, and at double density. Since a normal five-inch diskette can hold slightly over 100K, this multiplies that number by eight for a total of about 800K.

Let's take a look at five-inch floppy disk drives in general, and then the MPI Model 92 in particular.

Floppy Fundamentals

The floppy diskette is a disk of plastic, five inches in diameter, which is coated on both sides with a magnetic oxide coating such as that used on recording tapes.

The disk is enclosed in a rectangular, stiff plastic envelope just a bit larger than the disk itself. The inside of the envelope is covered with a fiber material smooth enough that the disk can rotate within the envelope without being scratched.

In the center of the diskette is a round hole slightly over one inch in diameter; the plastic envelope in turn has a slightly larger hole in the center. When placed into a disk drive, the diskette is grabbed by a metal hub from one side, and a plastic expansion hub from the other; these

hubs are centered within the large hole in the center of the disk, and hold the diskette tightly so it can be turned. The disk drive has a small motor, usually operated from a +12 V dc power supply, which turns the metal hub and spindle via a plastic belt. In operation, the diskette turns at five revolutions per second (300 rpm).

The rotating speed must be held quite close to this value; most disk drives have a built-in regulator, possibly with a feedback tachometer on the spindle which helps keep the speed constant. There is usually a set of stroboscopic marks on a flywheel. These marks appear to stand still when viewed in a fluorescent light when the spindle is rotating at the correct speed. The motor speed regulator usually has an adjustment to allow slight changes in speed.

In hard-disk systems the motor is turned on continuously. This is not the case with floppy drives. In fact, most drive manufacturers specify that the motor should be turned off within a second or two after the last use of the drive for maximum life of both the drive and the diskette.

Though this is obviously a good idea, in practice it slows down operation, since there is always a delay of about one second from the time the motor is turned back on to the time the disk can safely be used. Since turning the motor on and off is done by the disk controller, many micro-

computer manufacturers leave the motor on for 15 to 30 seconds after each use; some manufacturers leave the motor on continuously.

Data is written on the disk or read back by a read-write head which touches the diskette. (Here is another difference between a floppy disk and a hard disk—in the hard disk the head rides above the disk, and [hopefully] never touches.) The head can reach the disk through a slotted hole in the outer jacket, about a half inch wide by about 1-1/8 inches long.

The head is mounted so it can slide in and out to reach different tracks. A track is a circular path around the disk; when the head is positioned over a track, the turning of the disk continuously rotates the same track under the head. That is, the track on a computer disk is not like the groove on a phonograph record since the groove keeps moving closer and closer to the center of the record as it turns; the disk track is a circle that does not spiral to the center.

The head itself is mounted on a carriage which slides in and out on two or three metal rods. The carriage, in turn, is moved in different ways by different manufacturers. The cheapest and most popular arrangement is to attach the carriage to a stepper motor through either a cam or metal

Peter A. Stark (PO Box 209, Mt. Kisco, NY 10549) writes extensively on 68xx systems for Microcomputing.

band so that the rotary motion of the motor shaft is translated into a straight-line motion of the head carriage.

The shaft of a stepper motor moves in steps in response to an electrical signal. This is quite different from the normal kinds of motors we are familiar with, whose shafts turn smoothly and continuously; the stepper motor turns in discrete steps or jerks. The amount of movement per electrical pulse depends on the mechanical motion of the motor and can be fairly well controlled. In general, the mechanical linkage between motor and head carriage is such that anywhere from one to four motor pulses are required to move the head exactly one track.

There is usually a microswitch mounted within the drive which closes a contact when the head is on track zero. The disk controller thus keeps track of where the head is by first moving the head all the way out until the track zero switch closes, and then keeping a count of pulses as the head is moved into inside tracks. If something else should move the head in the meantime, then the disk controller would think the head was on a different track from the one it is actually at. This is an important concept, and will show up again later.

Another way of moving the head carriage is by a voice coil actuator. This is a technique used more in standard eight-inch floppy drives as well as hard disks. Rather than move the carriage in discrete steps, the voice coil actuator is an electromagnet which can move the head in or out in one continuous motion. By use of a feedback loop and a servo system, this system controls carriage speed based on how far it has to move. If the carriage must move a large number of tracks, the voice coil system starts it moving very fast and gradually slows it down as it gets closer. The result is a very fast carriage movement.

Even in the stepper systems there is a large difference between drives. Table 1 shows some typical specifications for four important quantities: the disk motor startup time (the delay from the time the motor is started to the time when reading or writing can begin), the track-to-track movement time (for one track), the carriage settling time (the delay time after carriage motion stops to the time when it stops vibrating enough so it can be used) and the head load time (the de-

lay from the time the head is commanded to touch the disk to the time it stops bouncing up and down so it can be used). (See Table 1.)

In what is called single density, one track can hold about 2500 bytes, or about 20,000 bits. This amount of data is not, however, written or read all at once. Instead, the track is divided into from eight to 18 smaller segments called sectors, with each sector typically holding either 128 or 256 bytes, plus a few additional bytes which may be used for synchronization or identification of sector.

To be interchangeable between drives, the disk format must be standardized and sectors placed in a specific place on each track. For that reason, the disk drive must have a way of sensing how far the disk has turned from some specific reference point.

Near the large center hole of the diskette are one or more small holes which allow the drive and controller to sense disk rotation. These holes are called index holes; the drive has a small light-emitting diode and phototransistor which shines a light through this hole and produces a pulse output each time the disk turns to a position where light can shine through the index hole.

Every type of diskette has one such hole which marks the beginning of what is called sector 0. In a way, this is the beginning of a track, except, of course, for the fact that the track is continuous and does not really have a physical beginning or end. Using this as a starting point, the disk controller can count sectors to identify all the other sectors on the track.

This is, however, where there is a difference between so-called soft-sectored disks and hard-sectored disks. In a soft-sectored disk, there is only one index hole, at the beginning of sector 0. Before it can be used, such a disk must usually first be formatted.

When formatting, the controller steps the head to each new track, waits for the sector-0 hole to pass through the index sensor light beam, and then writes a series of blank sectors on the track. Each sector is pre-

ceded by a header which consists of a string of synchronization characters followed by a sector number. Since the rotation speed of the disk is very closely controlled, the controller and its program have no trouble placing each sector in its approximately correct spot on the track.

Since the entire process is software-controlled, there does not have to be any specific number of sectors per track, although from eight to 18 are generally used. Typical formats might be ten sectors of 256 bytes each, or 18 sectors of 128 bytes each.

Once a soft-sectored disk is formatted, many disk systems no longer use the index hole, except perhaps to sense whether a disk is inserted in the drive or not. Since each sector is numbered, it is only necessary to step the head to the specified track and read off the sector numbers as they go past the head until the correct sector arrives.

Hard-sectoring is quite different. Now, in addition to the one index hole which identifies the beginning of a track, there are either ten or 16 additional holes, evenly spaced around the disk, which identify the beginning of each sector. (The spacing between the holes is uneven, so the controller can recognize which of the holes is the one marking the beginning of the track.)

Note that there is no difference in drives—the same drive may be used for either soft- or hard-sectored disks. Only the disk controller and the diskettes themselves change.

Soft-sectoring has the advantage of being more flexible, since the size of the sectors can be varied to meet the need. Hard-sectoring, on the other hand, can be more efficient since sector timing is a bit less haphazard. It is also not necessary to number each sector, since the controller can use the index holes to find each sector on the track.

Soft-sectoring in mini-floppies is generally handled by a disk controller such as the 1771 or 1791. Hard-sectoring, on the other hand, is generally handled either with discrete cir-

Time Spec.	Shugart SA-400	Wango/Siemens 82	MPI 51/52
motor startup	1 sec	1 sec	1 sec
track-to-track	40 ms	30 ms	5 ms
carriage settling	10 ms	20 ms	15 ms
head load settling	75 ms	60 ms	35 ms

Table 1.


Big sale on K's!

16K...\$149.95

32K...\$199.95

48K...\$249.95

64K...\$299.95



New JAWS-IB

The Ultrabyte Memory Board

Due to the tremendous success of our JAWS I, we were able to make a special purchase of first-quality components at below-cost prices for JAWS-IB. And we are sharing our cost saving with you. But don't be surprised if the next time you see this ad the prices have gone up substantially. Better yet, order now, and get the best memory on the market at the best price on the market.

ONE CHIP DOES IT ALL

Jaws-IB is the Rolls-Royce of all the S100 dynamic boards. Its heart is Intel's single chip 64K dynamic RAM controller. Eliminates high-current logic parts... delay lines... massive heat sinks... unreliable trick circuits. JAWS-IB solves all these problems.

LOOK WHAT JAWS-IB OFFERS YOU

Hidden refresh... fast performance... low power consumption... latched data outputs... 200 NS 4116 RAM's... on-board crystal... RAM Jumper selectable on 8K boundaries... fully socketed... solder mask on both sides of board... phantom line... designed for 8080, 8085, and Z80 bus signals... works in Explorer, Sol, Horizon, as well as all other well-designed S100 computers.

10-DAY MONEY-BACK TRIAL: Try a fully wired and tested board for 10 days — then either keep it, return it for kit, or simply return it in working condition.

Continental U.S.A. Credit Card Buyers Outside Connecticut:

TO ORDER CALL TOLL FREE 800-243-7428

From Connecticut Or For Assistance:

(203) 354-9375

KB8

Please send the items checked below:

JAWS-IB kit:

- ☐ 16K...\$149.95*
- ☐ 32K...\$199.95*
- ☐ 48K...\$249.95*
- ☐ 64K...\$299.95*

JAWS-IB Fully Assembled, Wired & Tested:

- ☐ 16K...\$179.95*
- ☐ 32K...\$239.95*
- ☐ 48K...\$299.95*
- ☐ 64K...\$359.95*

☐ EXPANSION KIT, 16K RAM Module, to expand JAWS-IB in 16K blocks up to 64K. \$59.95

*All prices plus \$2 postage and insurance (\$4.00 Canada). Connecticut residents add sales tax.

Total enclosed: \$

☐ Personal Check ☐ Money Order or Cashier's Check
☐ VISA ☐ Master Card (Bank No.)

Acct. No. Exp. Date

Signature

Print Name

Address

City

State Zip

NETRONICS R&D Ltd.

333 Litchfield Road, New Milford, CT 06776

cuitry, or by using some circuitry plus a serial synchronous IC such as the S2350 USART.

There is one more sensor in most disk drives—the one which tests whether a diskette is write-protected. Five-inch diskettes have a small notch cut into the side, which is detected either by a microswitch or via another photoelectric sensor. If this notch is absent, or if it is covered by tape, the disk is write-protected and the drive will not write on it.

Compatibility

The oldest five-inch floppy drives were made by Shugart Associates. Floppies were originally intended as a program transfer medium for mini-computers, not as main storage in microcomputers. As a result, no one ever anticipated that the demand would be as large as it has become.

Shugart soon found itself unable to deliver all the drives that customers wanted, and hence other companies went to work and designed their own drives. Although each company made its drives slightly differently (for patent as well as other reasons), the external appearance as well as interfacing and mounting details were generally identical with the Shugart drives. Customers could thus switch to a different drive without having to redesign their products.

There are some exceptions to this (as in Micropolis drives, which have traditionally been designed differently), but in general it is quite possible to unplug a Shugart SA-400 drive from a system and simply replace it by a Wangco/Siemens model 82, a Pertec FD-200 or an MPI model 51. The drives are the same size, the

mounting screw holes are in the same place, and even the power and data connectors are the same.

There is also compatibility in the mechanical disk format. Not only do all these drives use the same disk, but they position their tracks in the same place on the disk, and maintain the same spacing between tracks. Thus, a disk written on one drive can—assuming the drives are properly adjusted—be read on another.

The tracks are normally spaced 1/48th of an inch apart; thus they are spaced at 48 tracks per inch (tpi). But the original Shugart disks had only 35 tracks, so that the distance between the outermost track and the innermost track is only about 3/4 of an inch. Since the oval slot through which the head reaches the disk is about 1-1/4 inches long, there is some extra room through which more tracks can be placed on the disk. Thus, most other disk drive manufacturers allow the head to go in for five more tracks, giving a total of 40 tracks.

(It appears, however, that BASF Flexy Disks, and perhaps others, have a shorter slot and cannot be used for 40 tracks.)

Though 40-track drives provide five more tracks than 35-track drives, the spacing between tracks and the positions of the first 35 tracks are identical. Thus, a 40-track drive can be used in a 35-track system and still be completely interchangeable.

Electrical Interface

Almost all five-inch floppy disk drives are advertised as being electrically Shugart-compatible. Since the same kind of connector is used in all, and since the logic signals almost always use the same pins in the connectors, there is true compatibility between them. (Except in one respect—an operating system designed to work with a drive which has fast head load time or fast carriage movement will not provide enough time for a slower drive.)

A five-inch drive connects to the system via two connectors and a single push-on-type ground lead.

A four-pin connector is used to bring power to the drive. A typical drive requires +5 V at about 0.5 amp, and +12 V at about 1 amp while running, and perhaps up to 1.8 amp when the motor is just starting.

The power connector needed is an AMP part number 1-480424-0 with four AMP 61473-1 or 60619-1 pins. It is most easily obtained as cat. no. 2480

Pin Function

2,4,6	Spare
8	Sector sensor
10	Drive select 1
12	Drive select 2
14	Drive select 3
16	Motor on
18	In/out step select
20	Step pulse
22	Write data
24	Write enable
26	Track 0 sensor
28	Write protect sensor
30	Read data
32	Spare
34	Spare

Table 2.

from Hobby World (HW) Electronics for \$1.99 each.

The data connection between the drive and its controller is normally done via a 34-wire flat cable with a 34-pin card-edge connector on the drive end of the cable. Suitable connectors are AMP part number 583717-5 or 3M Scotchflex 3463-001. These connectors crimp into the 34-conductor cable.

The other end of the cable usually attaches to its connector via another 34-pin card-edge connector, although sometimes a plug/socket connector is used, usually a 3M Scotchflex 3414-0000 or 3414-6000. (The matching connector for the controller board is then a 3M Scotchflex 3431-1002 right-angle connector or 3431-2002 straight connector.)

The 3M Electronic Products Division has sales offices in many U.S. cities, but the connectors are difficult to get because of minimum order requirements at their distributors; thus most computer users buy ready-made cables.

I have found two sources of these connectors, and the 34-wire cable, which are quite convenient:

Electrolabs (PO Box 6721, Stan-

ford, CA 94305, 800-227-8266) has the wire at 68 cents per foot, card-edge connectors at \$6.64, pin-type plugs at \$6.58 and sockets at \$4.47; the right angle pin-type plug for a controller board costs \$2.77.

Another source is the International Minicomputer Accessories Corp. (Inmac), which has offices in most large U.S. cities, including Los Angeles, Denver, Dallas, Chicago, Detroit, Washington, DC and Boston. Their current prices are as follows: no. 1603 cable is \$1.20 per foot, no. 1627 card-edge connector is \$7.20, no. 1653 pin-type socket connector is \$6.95 and the no. 1633 pin-type connector to a controller board is \$4.70.

(These connectors are similar to those used on eight-inch drives, except that eight-inch drives use 50-conductor cable and connectors.)

A special—and expensive—crimping tool is recommended for crimping the cable connectors onto the flat ribbon cable. A very large bench vise could also be used (small, portable vises will not do the job), but I have had luck with a drill-press vise. In any case, very careful assembly is required because the connector cannot be removed from the cable once

installed without damaging it.

Within the 34-conductor cable, the wires are numbered from 1 through 34, and all odd-numbered wires are used as ground. In other words, there is a ground wire separating each pair of adjacent data or control wires. On a card-edge or pin-type connector, however, all the odd-numbered pins appear on one side of the connector, while the even-numbered pins are on the other side. When the card-edge connector is plugged onto the edge of the board, all the grounds are on one side of the board, while the signal and control leads are on the other side.


Since card-edge connectors are seldom keyed, it is easy to plug the connector on the board backward, thereby shorting all the drive signal leads to the controller's ground and vice versa. This generally causes no damage (and is signalled by the fact that the drive motors run and don't stop), but should definitely be avoided.

Connector assignments are shown in Table 2.

(Note that some manufacturers refer to the first drive as drive 0, while others call it drive 1.)

All of these signals are normally

ROBOTS The Future Arrives



Intelligent machines are rapidly appearing in homes, automobiles, offices, and factories.

Affordable cameras, speech synthesizers, and even robot arms are now on the market. Such advances are giving microcomputers the power to see, hear, grasp objects, and to move around the room. Where can you learn about this technology? In **Robotics Age Magazine**, the journal of intelligent machines.

Robotics Age reports the experience of hobbyists building their own robots, the latest products from industry, and the most powerful techniques from research labs. The face of the world is changing. Join us as we enter the Robotics Age.

YES! I want to stay up-to-date on this fascinating new technology!

Name _____ Title _____

Company _____ Address _____

City _____ State/Province/Country _____ Postal Code _____

United States Canada Foreign

1 year (6 issues) \$15 \$17 \$19

2 years (12 issues) \$28 \$32 \$36

3 years (18 issues) \$39 \$45 \$51

*US Funds on US Bank

☐ Bill VISA ☐ MasterCard ☐ Bill me (N America only)

Card No. _____ Expires _____

Signature _____

Send to: **ROBOTICS AGE**, PO Box 512, Tujunga, California 91042

TEXAS COMPUTER SYSTEMS

Offers Lowest Prices on

TRS-80 COMPUTERS

Model II 64K
\$3349

Free with purchase:
1 Box of 10 Diskettes
a \$69 Value

Epson Printers
\$ Call

Model III 16K
\$849

Color Computer
4K Lev. I \$329

Radio Shack
Stereos, Radios
Discounted. Call for
discount on orders
over \$100.

Model III 32K
2 Disks \$2100

16K Ex. Basic
\$489

For fast, efficient service, we can air freight from Dallas to major a/p near you. Call for information.

• Payment: Money Order, Cashier's Check, Certified Check, Personal checks take 3 wks. VISA, MC, add 3%.

• Prices subject to change any time.
• No tax out-of-state. Texans add 5%.
• Delivery subject to availability.
• Shipping extra, quoted by phone.

TEXAS COMPUTER SYSTEMS ✓ 328

Box 951, Brady Texas 76825

Toll Free Number 800-351-1473

Texas Residents 915-597-0673

high (above +2.4 V) and go low (near ground) when on. For example, to select drive 1, the controller would bring line 10 low, while keeping the other drive select lines high.

In multidrive systems, all drives are connected in parallel across the same 34-wire cable; the customary method is to crimp several card-edge connectors on the cable, separated by six to ten inches, with each connector plugged into a drive. All the signals are shared except for the drive selects. (This explains why all motors go on and off together in multidrive systems—there is only one motor control line.)

There is a difference here between five-inch and eight-inch drives. Five-inch drives use dc motors, and contain circuitry to turn the motor on and off in response to the motor control signal on pin 16. Eight-inch drives use ac motors which run directly off the 115-V (or 230-V) power line, and do not have any power control circuit. The motors will either stay on continuously or else require another circuit board for motor control.

The line assignments shown in Table 2 only provide for three drives, whereas in many systems four drives are desired. Line 6 or 32 is often used as a fourth drive select line. Drives which provide a door-lock mechanism to prevent the door from being opened while the drive is being used may use line 4 for that purpose.

When all drives are off, all drive select lines are held high by the controller. To select a particular drive, the controller pulls its drive select line low. That enables that drive to respond to the other control lines, while all remaining drives on the system remain disabled (or deselected).

Fig. 1 shows the wiring of a shunt, which is found inside each drive. The shunt has a small DIP-IC-like body which is plugged into an IC socket right near the card-edge input connector. The shunt is essentially a series of jumpers which connect opposite pins on the IC socket together unless broken; there is a thin area in the center of each jumper intended to be broken. (I've found that an easier—and reversible—method is to unplug the shunt from its socket, and simply bend up the pins to be disconnected before plugging it back in.)

The D1, D2 and D3 shunts select whether this drive will be the first, second or third drive in a system (TRS-80 owners—read on, because

the TRS-80 does it slightly differently). For example, if the D1 shunt is left connected while D2 and D3 are broken, then this will be the first drive. Whenever drive select 1 goes low, the main drive select line inside the drive will therefore go low, and the drive will be selected. If D2 and D3 are broken, then nothing will happen here when the other drives are selected.

The HS and HM jumpers work together; one of them must always be installed while the other must be broken. These shunts control the head load solenoid. This is the solenoid which brings the disk up against the read/write head when reading or writing is about to be done. If the HS shunt is in place, then the head will load only when the drive is selected; if the HM shunt is in place the head will load as soon as the motor goes on. Either jumper could be used in a single-drive system. The HS shunt is usually used in multidrive systems because it results in less disk wear, and also in less likelihood of an accidental disk erasure in case of a hardware problem.

Systems using double head drives, however, often use the HM jumper even in multidrive systems. Although this increases the disk wear since the head is in continuous contact with the disk as long as the motor is turning, it reduces the severe disk wear which occurs when the two disk heads suddenly come together and clamp the disk between them. With the HM option, the heads only load as the motor goes on, not each time the

drive is selected.

The MX jumper leaves the drive always selected when in place. This would normally be used only in single-drive systems.

In most multidrive systems the drives are connected in parallel across the 34-pin cable, and each drive gets all three drive-select signals; the selection of drives is then done by breaking two out of the three jumpers in the shunt. This means, of course, that you have to open the drive cabinet and manipulate the shunt.

Right next to the shunt, in an adjacent IC socket, is a resistor network that contains pull-up resistors which act as loads on the signal lines coming from the controller. New drives always come with this resistor package installed, but in multidrive systems only one resistor pack should be used, in the drive which is connected farthest from the controller. Again, this means that you must open the drive cabinet and remove all but one of these packs when installing a system.

In the case of the TRS-80, Radio Shack apparently did not want customers poking around the inside of the disk cabinets, and so they made three changes. First, they added a short extender board to the drive to bring the 34-pin card-edge connector outside of the cabinet (normally it is inside). Second, they gave the first disk drive a different part number from add-on drives, and they always supply the first drive with the resistor pack in place, while the add-ons have it already removed. This is the only difference between the two types of drive, but it does eliminate the need to open the box at all.

Finally, they left all three drive-select jumpers in place on each drive (with D1, D2, and D3 all connected), and instead do the drive selection in the cable by physically yanking out the appropriate pins from the card-edge connector. For example, the connector for the first drive has pin 10 but no pin 12, 14 or 32. Thus, the drive-select 2 and 3 signals do not even get to the drive, and so the fact that all three drive-select jumpers in the shunt are still there makes no difference.

Since the TRS-80 can support up to four drives, pin 32 is generally used as the fourth drive select. Some drives have pin 32 wired for that use, while in others pin 32 is a spare, or is even used for another purpose. For




Fig. 1. The shunt.



Take Your Cue From Vista . . .

When it comes to Apples, take your cue from Vista's A800 Eight-Inch Floppy Disk Controller. The A800 offers a cost-efficient approach to software compatible disk memory expansion for your Apple II® computer. The A800 Controller enables Apple II users to access up to five megabytes of online storage through conventional disk operating (DOS) commands.

The Control and DMA Logic provides high speed (1 microsecond per byte) transfer of data from the disk drive directly to the Apple II memory without processor intervention. Plus, the Phase-Locked Loop Data Separator provides the ultimate in data reliability.

AND THERE'S MORE.

The controller is compatible with the most popular disk operating systems for the

It's a Sure Shot.


Apple II computer. It also interfaces to all Shugart/ANSI Standard Eight-Inch Floppy Disk Drives. The A800 provides complete IBM format compatibility in both single and double-density modes.

THE HOT SHOT AT A COOL PRICE.

The A800 is reasonably priced at \$595. A price you can't beat when you compare its quality and performance.

CALL YOUR SHOTS.

Vista offers you a complete line of peripheral equipment to maximize the capabilities of your Apple system including: High capacity Mini-floppy Disk Drives, the Vista Music Machine 9 and the Vista Model 150 Type Ahead Buffer. In addition, Vista offers a line of advanced components fully compatible with the TRS-80* and S-100 based computers.



Vista Computer
Company
1317 E. Edinger Avenue
Santa Ana, CA 92705
(714) 953-0523

Call Toll Free 800-854-8017

® Apple II is a registered trademark of Apple Computers, Inc.
* TRS-80 is a trademark of Radio Shack, A Tandy Co.

OSI (8K) APPLE TRS-80†



Computers & Gambling Products Magazine

PRESENTS:

PROBABILITY HANDICAPPING DEVICE 1 — A BASIC PROGRAM FOR: HORSE RACE HANDICAPPING!

This incredible program was written by a professional software consultant to TRW Space Systems. This is a complex program carefully human factored for easy use. It is a comprehensive horse racing system for spotting overlays in thoroughbred sprint races. Your computer will accurately predict the win probability and odds line for each horse based on your entries from the racing form. The next day overlaid horses can be spotted on the track tote board. The user's manual contains a complete explanation of overlay betting plus much more useful information. The appendix contains a detailed tab run of a 100 consecutive race system workout showing an amazing 50% return (\$1.50 returned for each \$1.00 flat wager.) Includes many features such as error correction, bubble sort, line printer output, automatic keyboard debounce, archiving, etc. The manual may be ordered separately for perusal for \$7.95 and credit.

CHALLENGER 1P, 2P, or 4P 8K VERSIONS Now Available!
Phd-1 User's manual and cassette for:

Apple II (16K), TRS-80 Level II (16K), Challenger (8K) ... 29.95
TRS-80 or APPLE DISK ... 34.95

BRAND NEW FROM SDL: WIN AT THE RACES. This thoroughbred handicapping algorithm is based on a currently popular book on thoroughbred multiple regression techniques. Both sprints and routes. All of the features of PHD-1 plus more. This program incorporates the best data entry technique we've ever seen.

32K TRS-80 or APPLE CASSETTE ... 34.95
32K TRS-80 or APPLE DISK ... 39.95

BOOKS:

Winning at the Races ... 21.95 + .75 P&H
Beating the Races with a Computer ... 14.95 + .75 P&H

Make checks payable to JOE COMPUTER DEPT K ✓ 247

22713 Ventura Blvd., Suite F, Woodland Hills, CA 91364

CA residents add 6 % sales tax.

PHONE ORDERS: 213-992-0514

*SEND \$2.00 TO PLACE YOUR NAME ON OUR MAILING LIST.

†TRS-80 is a registered trademark of Tandy Corporation.

MICRO-80™ CASSETTES— 100% ERROR-FREE



	12	24
LENGTH	PACK	PACK
C-10.....	69¢	59¢
C-20.....	89¢	79¢

- Fully Guaranteed!
- World's Finest Media
- Premium 5-Screw Construction
- Used by Software Firms Nationwide
- Dealer and Club Discounts Available
- Custom Storage Case, Add 19¢ Each
- Shipping Charges, Add \$1.50 ✓308

μ80™ MICRO-80™ INC.
K-2665 NO. BUSBY ROAD
OAK HARBOR, WA 98277

example, MPI model 51 drives use pin 32 to activate a side-select circuit (which is on the drive's printed circuit board, but not used). Thus, MPI 51 drives supplied for use with the TRS-80 usually have the trace to pin 32 cut, and a small wire jumper added to connect pin 32 to pin 14 or some other point in the drive-select circuit.

This is something which must be kept in mind if you switch either drives or cable between the TRS-80 and other computers.

Recording Method

To compensate for slightly different rotating speeds of the diskette, the signal written on the disk contains both data and clock pulses. Although the actual signal written on the disk is somewhat different, the read or write signal as it travels between the disk drive and its controller looks like that in Fig. 2.

Clock pulses spaced eight microseconds (μ s) apart are recorded continuously on the disk, with data pulses placed roughly halfway between clock pulses. When a 1 is being written, the controller inserts a data pulse between the clocks; for a 0 the controller omits the data pulse.

If the data is a long string of zeroes, then only the clock pulses will exist with a spacing of eight μ s. In a long string of ones, on the other hand, pulses appear every four μ s. This is the reason why this method is called FM encoding, since the frequency of the pulses (which is one divided by the spacing) is low for a zero, high for a one. (Except for the timing, this scheme is very similar to that used in a TRS-80 cassette recording. In a Level II TRS-80 system, the spacing between cassette clock pulses is 2000 μ s.)

Thus, disk data bits are spaced eight μ s apart for a total of 125K bits per second. A complete eight-bit byte, therefore, is written or read every 64 μ s.

Disk data is written serially, one bit at a time. Since a microprocessor is simply not fast enough to convert

data to or from serial format at eight μ s per bit, the conversion is always handled by external circuitry such as a 1771 disk controller or a USART.

This controller or USART, however, handles complete characters at a rate of one every 64 μ s. Most microprocessors are fast enough that they can move characters between the controller and main memory under program control as long as the program coding is carefully done and properly timed.

The data encoding described so far is the original recording and timing method, and is called normal or single density.

Double Density

In looking at Fig. 2 we see that every bit in single-density recording is accompanied by its own clock pulse. Hence the presence of the clock pulses effectively doubles the bit density of the disk—if we record 125,000 ones on the disk in one second, we are actually writing 250,000 pulses. Hence the disk drive as well as the diskette must be capable of handling pulses at a 250K bit per second rate.

If the clock pulses could be eliminated, then all of these 250K pulses could be used for data. This would double the data transfer rate, and would also double the storage capacity per disk.

This is the idea behind double density. Through a slightly revised encoding scheme called MFM (modified FM) or M2FM, the data and clock bits are combined, and therefore twice as much data can be stored. Since the effective data rate as far as the drive and diskette are concerned is unchanged, the same drive and disk can be used for double density as well as single—except for some very early disk drives (which are marginal performers), all floppy disk drives can be used with double density.

Note, though, that although double density doesn't affect the disk or drive, it does affect the computer. At double-density recording, the data bits are now only four μ s apart, and thus a complete byte is transmitted in 32 μ s instead of 64. At 64 μ s each character could be processed by the microprocessor; at 32 μ s there is much less time. Some processors, such as the 6809, are fast enough that with some very careful program coding, data can be moved to and from memory at that rate; but most com-




Fig. 2. FM data encoding.

mon processors are not.

Thus, with some double-density disks, data must go to and from memory without going through the processor; that is, the controller must be able to bypass the processor and access memory itself. Thus, a double-density controller is more expensive and more complex than a single-density one.

One technique for doing this is via DMA, or direct memory access. When DMA is being used, the main processor starts the controller and then disconnects itself from the computer buses. The controller takes over and controls the address and data buses, as well as read/write and other control lines, and does its own transferring of data.

In most systems, a data byte can be transferred to or from memory in under one us. Since data bytes are only transferred once every 32 us, there is plenty of time to do a DMA transfer. In a simple system, the microprocessor might relinquish the buses long enough to transfer an entire sector's worth of data to or from the controller, but this obviously wastes time. In more complex systems the controller generates interrupts when it needs the bus, and the processor releases the bus just long enough to transfer one byte.

Either way, though, system timing becomes very complex. If there are sources of other interrupts or if the computer is being used for time-critical work, then the overall operation of the DMA circuitry must be watched very carefully.

Thus, some of the most expensive double-density controllers use a different technique. Instead of using DMA access to the main memory, these controllers have their own memory on the controller board, just big enough to store data from one sector. When reading or writing on the disk, the controller transfers data between its own memory and the disk at high speed. But data transfer between the main computer memory and the controller's memory can be done by the processor itself, under program control, when convenient. Though this scheme appears to be slower because it involves double data transfer, in practice it avoids other difficulties, and so is just as good as direct DMA but much simpler.

(This may be a good place to compare standard eight-inch floppy recording with the five-inch floppy. In

the eight-inch floppy, the diskette rotates faster; the data bits also appear more often because the track diameter is larger, and thus there are more bits per track. As a result, the timing in single-density recording is half of that shown in Fig. 2—the clock bits are 4 us apart instead of eight. Thus, single-density must handle a byte every 32 us, while double-density recording handles a byte every 16 us. Thus eight-inch floppy controllers almost always use DMA or internal memory buffering on micro systems. This explains why five-inch controllers are so much cheaper. For example, a five-inch controller for a 6800 system can be purchased for under \$100, whereas an eight-inch controller costs several times as much.)

So we see that double-density recording doubles the number of bits per disk as well as doubles the data transfer rate.

Double-Sided Operation


Floppy diskettes are coated with oxide on both sides even though they are intended for single-sided operation. This is probably done for mechanical reasons—so the diskette doesn't warp—but it does mean that the back side of the floppy can also be used.

When the read/write head in a drive is touching the diskette, a pressure pad on the opposite side presses the diskette against the head. To allow the pressure pad access to the diskette, the diskette jacket has a slot on both sides. This again means that the disk can be used on both sides. (Note, however, that diskette manufacturers do not test the back side of diskettes, and so the back side may sometimes produce errors. Special double-sided diskettes are available at extra cost and are tested on both sides.)

There is still a problem, however. The index sensor hole is not located in a symmetrical location. That is, when the diskette is turned over in the drive, the sensor hole is in a different place. Thus, in a basic drive, it cannot be read.

Some disk drive manufacturers have solved that problem by installing two parallel index sensors, one for use when the disk is inserted correctly and the other when the disk is inserted backward. With these drives, sometimes called floppy drives, it is easy to write on either side of a disk. (A second write-protect sensor is also required, since the write-protect

COMPUCOVER®



COVER YOUR INVESTMENT

- Cloth Backed Naugahyde Vinyl
- Waterproof & Dustproof
- Longer Life
- Improved Reliability
- Two Decorator Colors—Saddle Tan and Black

APPLE COMPUTERS

Apple Ensemble-covers entire Apple II with 9" video & two stacked disk	\$15.95
Full Apple II.....	12.95
Apple II Keyboard.....	7.95
Apple II Disk.....	3.95
Apple II Disk (stacked-two disk).....	7.95
Apple III.....	14.95
TRS-80 MODEL I	
Keyboard.....	7.95
Cassette.....	4.95
Video Display.....	9.95
Package Offer.....	18.95

*NOTE—Add \$3.00 for Expansion Interface

TRS-80 5 1/4" Disk.....	\$4.95
Two Disk Cover (side by side).....	7.95
TRS-80 MODEL II	
Entire Unit.....	\$22.95
Keyboard Only.....	7.95
Three Disk Unit (8" Drives).....	18.95
TRS-80 MODEL III	
TRS-80 COLOR COMPUTER.....	9.95

Line Printer I.....	\$16.95
Line Printer II.....	9.95
Line Printer III.....	15.95
Line Printer IV.....	9.95
Line Printer VI.....	14.95
Daisy Wheel Printer II.....	16.95
Quick Printer I.....	9.95
Quick Printer II.....	5.95

CBM-PET COMPUTERS

CBM-Pet 2001-4001 series.....	\$12.95
CBM-Pet 8032.....	12.95
CBM-Pet 2040, 8050 Disk.....	12.95
CBM-Pet 2022, 4022 Printer.....	9.95
CBM-Pet 2023 Printer.....	7.95
ATARI 800.....	\$10.95
Atari 400.....	9.95
Atari 810 Disk.....	5.95
Atari 425 Printer.....	9.95

CROMEMCO SYSTEM THREE

Cromemco 3100, 3102 CRT.....	18.95
Cromemco 3779 Printer.....	16.95
Cromemco 3703, 3704 Printer.....	18.95
Cromemco 3355 Printer.....	15.95
SUPERBRAIN.....	\$19.95
Emulator.....	19.95
Intertube.....	19.95
Superstar.....	19.95

HEATH COMPANY

H-19, H-89 CRT.....	\$18.95
H-17, H-77 Disk.....	9.95
H-27, H-47 Disk.....	12.95
H-8, H-11 Computers.....	12.95
H-14 Printer.....	9.95
H-34, H-44K, H-44 RD.....	15.95
H-34, H-54.....	15.95

DIGITAL EQUIPMENT

Data System Terminal.....	\$19.95
Decscope Terminal.....	19.95
VT/78, VT/78 Terminal.....	19.95
VT-100 Terminal.....	16.95
Decprinter I.....	15.95
Decwriter II, III.....	18.95
Decwriter IV.....	15.95

OHIO SCIENTIFIC

Superboard II.....	\$12.95
CAP-DF, single case.....	14.95
CAP-DF, stacked.....	19.95
C2-single case.....	14.95
C2-stacked.....	19.95
C2-OEM, long case.....	19.95
C3-OEM, long case.....	19.95
C3-S1, single case.....	14.95
C3-S1, stacked.....	19.95

WANG COMPUTERS

CRT Terminal.....	\$18.95
2221 Printer.....	19.95
2221-W Printer.....	22.95
2231 Printer.....	19.95
2261 Printer.....	19.95

HEWLETT PACKARD

85, 83 Computer.....	\$14.95
7225A plotter.....	9.95
8290 IM disk.....	9.95
Plotter on disk outfit.....	12.95
Compucolor II Entire Unit.....	16.95
Compucolor II Keyboard.....	5.95
Vector Graphic MZ Computer.....	14.95
Vector Graphic Mindless Terminal.....	18.95

MINIMAX II TERMINAL

Minimax II doubledisk.....	9.95
North Star Horizon.....	14.95
Sorcerer.....	9.95
Texas Instruments 9914.....	9.95
Intercolor 3621.....	18.95
Poly Morphic System 8813 Computer.....	14.95
Poly Morphic Keyboard.....	7.95
Tano Outpost II.....	22.95
NEC Astra Computer.....	18.95
SOL 20 Computer.....	14.95
IMSAI 8080.....	14.95

CRT'S

Televideo TV 1912 or 920.....	\$14.95
Hazeltine (one size fits all).....	18.95
Soroc IQ 120.....	18.95
Adds Terminals 25, 100, 980, etc.....	19.95
ADM-3.....	14.95
Leedex Video 100.....	9.95
Leedex Video 100-80.....	12.95
NEC JB-1201 Monitor.....	9.95
Visual Tech 200.....	20.95
9 inch CRT.....	7.95
12 inch CRT.....	9.95

PRINTERS

Epson MX-80 and MX-70.....	9.95
CITON Starwriter.....	15.95
Okidata Microline 80.....	9.95
Base 2.....	9.95
MPI 88T.....	9.95
Diabolo 630.....	15.95
NEC Spinwriter with Keyboard.....	15.95
NEC Spinwriter without Keyboard.....	15.95
Diabolo with Keyboard.....	15.95
Diabolo without Keyboard.....	15.95
Xerox with Keyboard.....	15.95
Xerox without Keyboard.....	15.95
Qume Sprint III.....	14.95
Qume Sprint V with Keyboard.....	15.95
Qume Sprint V without Keyboard.....	15.95

TELETYPE 43

Teletype 43.....	12.95
ID5 440, 445, 480.....	12.95
Texas Instruments 800 Series.....	18.95
Trendcom 100 or 200.....	9.95
Centronics 101.....	19.95
700, 701, 702, 703, 704, 753.....	18.95
Centronics 779.....	16.95
Centronics P1, 730, 737.....	9.95
Comprint 912.....	12.95
Anadex DP8000.....	12.95
Xymec HY Q1000.....	12.95
Okidata 22, SL125, SL250.....	15.95

DISK DRIVES

Micropolis 1041, 1042, 1043, 1053.....	\$9.95
Vista Double Disk.....	9.95
Vista 5 1/4" Disk.....	6.95
Matchless 5 1/4" Disk.....	6.95
Lobo Double 8" Disk.....	9.95
Lobo 5 1/4" Disk, 14" long.....	6.95
Lobo 3, 2, 3, 3.....	3.95
MPI B51 or B52 Disk.....	4.95
Percom 5 1/4" Disk.....	4.95
IBM.....	write
DATA General.....	write
CPT.....	write

Send check or money order to
Include \$1.50 for postage and handling.
Overseas orders include \$4.00 postage.

DEALER INQUIRES INVITED

COMPUCOVER

P.O. Box 324 (Dept. A)
Mary Esther, FL 32569
Phone (904) 243-5793

✓90

Lowest Prices on Personal Computers




800™...\$789

ATARI® List \$1080

A NEW LOW PRICE!

ATARI® 400...\$359

hp HEWLETT PACKARD HP-85




\$2795

HP-85 Accessories

5 1/4" Dual Master Disc Drive List \$2500... \$2125
5 1/4" Single Master Disc Drive List \$1500... \$1275
HP 7225A Graphics Plotter List \$2050... \$1845
HP-85 16K Memory Module List \$395... \$355
HP-85 Application Pacs Standard List \$95... \$85
Serial (RS-232C) Interface Module List \$395... \$355
GPIO Interface Module List \$495... \$445

new HP-83 List \$2250
\$1895

NEW! HP-41CV with five times more memory



built in.
List \$325
\$249

HP-41C
List \$250
\$199

HP-32E Scientific w/Statistics — \$53.95
HP-33C Scientific Programmable — \$79.95
HP-34C Advanced Scientific Programmable — 123.95
HP-37E Business Calculator — \$49.95

Personal
Computer
Systems

609 Butternut Street
Syracuse, N.Y. 13208
(315) 475-6800

Prices do not include shipping by UPS. All prices and offers subject to change without notice.

notch is also in a different place now.) But even if dual sensors are not included, it is fairly simple to punch an extra set of holes in the diskette jacket—carefully!—to allow the single index sensor to check the index holes. Several suppliers are selling floppy kits for doing this; I have been doing it for years with a hand paper punch from a local stationery store.

Diskette manufacturers warn against the practice, however. As a diskette is used, the fiber layer inside collects dirt and dust and holds onto it. If the diskette is turned around, it now turns in the opposite direction, and hence much of this dirt and dust is released. They warn that this could result in increased disk and head wear as well as data errors.

The entire problem is alleviated with the new drives that provide two read/write heads, one on each side of the disk. Now either side of the disk can be written without turning the disk over. Not only does this double the storage per disk, but all the data on the disk is immediately usable. In other words, rather than appearing as two different disks, the disk can now be formatted as a single, large disk of double the capacity.

The idea of double-sided drives is fairly old, but until recently the drive manufacturers had trouble with the mechanical design. When the disk was clamped between two heads, it was often damaged by excessive pressure. In early designs, both heads were moved to and from the disk by the head load solenoid; most current designs leave one head in place and just move the other.

As far as the electrical interface is concerned, all of the leads on the 34-pin data connector remain the same except for one. Pin 32, which was formerly a spare, is now used to

select the side. When this pin is high, the drive uses the normal side of the disk; if pin 32 is low, it uses the reverse side. With this convention, if a double-sided drive is plugged into a single-sided controller, pin 32 will be unconnected and therefore allowed to go high. The drive will then use the normal side as if it was single-sided.

It's important, though, to watch out for drives which are wired to use pin 32 for a fourth drive select. If these are mixed with double head drives in one system, some modifications will be needed.

Double-Track Drives

In normal five-inch drives, track spacing is held at 48 tracks per inch, and the total number of tracks is either 35 or 40. (Compare this with 77 tracks on an eight-inch drive.)

Several manufacturers, however, make drives which use narrower tracks and place them closer together. For example, the MPI model 91 and 92 drives use spacing of 96 tracks per inch, and so have room for 80 tracks instead of 40. (The model 92 is double-sided, and so has a total of 160 tracks, 80 on each side.)

In these drives, track 0 is in the same place as track 0 on a normal drive; track 2 is located the same as track 1 in a normal drive, and so on. Hence the even-numbered tracks lie on top of normal, or single-track, track positions; the odd tracks are sandwiched between. Thus, a double-track drive can read a normal diskette assuming that the software is written to do double-track stepping. (But it cannot write in normal track spacing because its tracks are narrower and it does not fully erase previous data over the entire wide track width on previously used disks.)

Double-track drives are substantially more expensive than single-track drives because of much closer mechanical tolerances required. Since the tracks are narrower, it becomes much more important to maintain disk-to-drive alignment. This means that the disk must be centered on the spindle more accurately, and much closer attention must be paid to temperature compensation and alignment. Some users also have some reservations about long-term stability.

The MPI Model 92 Drive

I recently obtained an MPI Model 92 drive. This drive is capable of double-density, double-sided operation,




Fig. 3. Hardware side-select circuit. Diodes must be germanium junction diodes, not silicon.



THE NATIONAL COMPUTER SHOWS

HAVE WE GOT A PROGRAM FOR YOU IN '81 & '82

Attend the biggest public computer shows in the country. Each show has 100,000 square feet of display space featuring over 50 Million Dollars worth of software and hardware for business, industry, government, education, home and personal use.

You'll see computers costing \$150 to \$250,000 including mini and micro computers, software, graphics, data and word processing equipment, telecommunications, office machines, electronic typewriters, peripheral equipment, supplies and computer services.

All the major names are there including; IBM, Wang, DEC, Xerox, Burroughs, Data General, Qantel, Nixdorf, NEC, Radio Shack, Heathkit, Apple, RCA, Vector Graphic, and Commodore Pet. Plus, computerized video games, robots, computer art, electronic gadgetry, and computer music to entertain, enthrall and educate kids, spouses and people who don't know a program from a memory disk.

Don't miss the Coming Of The New Computers—Show Up For The Show that mixes business with pleasure. Admission is \$5 for adults and \$2 for children under 12 when accompanied by an adult.

Ticket Information

Send \$5 per person with the name of the show you will attend to National Computer Shows, 824 Boylston Street, Chestnut Hill, Mass. 02167. Tel. 617 739 2000. Tickets can also be purchased at the show.

THE MID-WEST COMPUTER SHOW

CHICAGO
McCormick Place
SCHOESSLING HALL
23rd & THE LAKE

THURS-SUN
SEPT 10-13, 1981

11AM TO 7PM WEEKDAYS
11AM TO 6PM WEEKENDS

THE MID-ATLANTIC COMPUTER SHOW

WASHINGTON, DC
DC Armory/Starplex
2001 E. CAPITAL ST. SE
(E CAP. ST. EXIT OFF I 295
-KENILWORTH FRWY)
ACROSS FROM RFK
STADIUM

THURS-SUN
SEPT 24-27, 1981

11AM TO 7PM WEEKDAYS
11AM TO 6PM WEEKENDS

THE NORTHEAST COMPUTER SHOW

BOSTON
Hynes Auditorium
PRUDENTIAL CENTER

THURS-SUN
OCT 15-18, 1981

11AM TO 7PM WEEKDAYS
11AM TO 6PM WEEKENDS

THE SOUTHEAST COMPUTER SHOW

ATLANTA
Atlanta Civic Center
395 PIEDMONT AVE NE AT
RALPH MCGILL BLVD

THURS-SUN
OCT 29-NOV 1, 1981

11AM TO 7PM WEEKDAYS
11AM TO 6PM WEEKENDS

THE SOUTHERN CALIFORNIA COMPUTER SHOW

LOS ANGELES
LA Convention Center
1201 SOUTH FIGUEROA

THURS-SUN
MAY 6-9, 1982

11AM TO 7PM WEEKDAYS
11AM TO 6PM WEEKENDS

and double-track spacing. Thus, it can hold eight times as much data on line as a standard single-density disk. At 160 tracks, with 20 256-byte sectors per track, this translates to 819,200 bytes of data per disk.

In actual use, though, total disk capacity is somewhat less than 819K for two reasons. First, soft-sectored disk systems require that each sector be preceded by some sync bytes and sector identification; this information takes up room and so the number of sectors per track is usually slightly less than 20; 18 is more common. Second, double-density systems generally use record track 0 in single-density mode. As a result, track 0 of all disks can be read on all systems, regardless of whether they are single or double density. Since track 0 contains information regarding the format of the rest of the disk, the disk operating system can then set itself to read the rest of the disk. Thus, though the theoretical capacity of such a disk is 819K bytes, in most cases the actual storage is somewhat under 800K.

The ultimate aim is to use it with a double-density controller; initially, though, I decided to test it at single

density with two existing controllers on my 6800 system.

The first job was to modify the existing operating system to allow the use of 80 tracks per side. This is a very system-specific job, and I won't describe that here.

The next job was to make use of the second side. One way is to add a side-select circuit to the controller, and modify the disk operating system to keep this output high on the first 80 tracks and low on the second 80 tracks. A much better way would be to keep alternate tracks on opposite sides of the disk, since this would minimize head carriage movement while reading a file.

Both of these tasks require quite a bit of work, as well as a good knowledge of the (usually undocumented) disk operating system. I therefore chose a slightly different approach.

Instead of the plug-in shunt inside the drive, I substituted a plug-in DIP header. This is an assembly which plugs into an IC socket and is usually used to allow simple connection of discrete components like resistors to a digital logic circuit.

On this header I put the circuit

shown in Fig. 3. The HS jumper is a wire, while the DS2 and DS3 jumpers are replaced by two germanium diodes. (Note: these diodes must be germanium junction diodes, not silicon. I used the base-emitter junctions of two old germanium transistors.) Finally, a short jumper from the DS3 diode's cathode was soldered to a tab connected to pin 32, the side select lead, of the 34-pin connector.

Using this circuit, the drive is selected as both drive 2 and drive 3, via the diodes. When either drive-select signal goes low, the diode pulls the drive's own select line low. (Germanium diodes must be used because they have the low-voltage drop needed to pull the output low enough. Silicon diodes don't work in this application.)


Thus, this one drive looks to the system as both drive 2 and drive 3. But when selected as drive 2, the side-select signal is high and so it uses the front side of the disk. When selected as drive 3, the side-select signal is low, and so it uses the back side of the disk.

Both sides of the disk are now us-

Desk Main/Frame Desk Main/Frame

LOW COST & ATTRACTIVE STYLING

- MAIN/FRAME INTEGRATED INTO FURNITURE QUALITY DESK
- ELECTRONICS PACKAGE SLIDE MOUNTED FOR EASY ACCESS
- SUPPORTS TWO 8" FLOPPY DRIVES FROM SEVERAL MANUFACTURERS (DRIVES NOT INCLUDED)
- 10 SLOT MOTHERBOARD INCLUDES CONNECTORS
- POWER SUPPLY FOR DRIVES AND CARDS
- DESK AND MAIN/FRAME AVAILABLE SEPARATELY
- MATCHING PRINTER DESK AVAILABLE




WRITE OR CALL FOR OUR BROCHURE WHICH INCLUDES OUR APPLICATION NOTE: 'BUILDING CHEAP COMPUTERS'

INTEGRAND ✓ 77

8474 Ave. 296 • Visalia, CA 93277 • (209) 733-9288
We accept BankAmericard/Visa and MasterCharge

Super Compuprism Color Graphics



For the S-100 Bus. 32K of on board memory allows a 288 H. x 192V. dot matrix, for a total of 55,296 pixels. Every pixel is programmable in any one of 16 colors or 16 grey levels completely independent of all other pixels in the matrix.

Compuprism Bare Board with documentation \$45, kit \$240, ass. and tested \$280. (16K Memory 144H. x 192V.)

Super Compuprism Bare Board with documentation \$50, kit \$350, ass. and tested \$395.

(32K Memory 288H. x 192V.)

Add \$15 to A & T price for 16 level grey scale. Add \$15 to A & T price for memory management port.

Compuprism software package, includes alphanumerics, point plot, line draw, and TRS-80* graphics simulation \$20 or FREE with A & T unit.

ALL COD ORDERS SHIPPED WITHIN 72 HOURS. 4MHz MOD FOR S.D. SYSTEMS. EXPANDORAM \$10.

**J.E.S. GRAPHICS, P.O. Box 2752
Tulsa, OK 74101, (918) 742-7104**

TRS-80* is a trademark of Tandy Corp.
SARGON II** is a trademark of Hayden Book Co.

✓ 180

Z-80 Users You Can Use TRS-80* Software

We offer an assembled hardware interface which we guarantee will load data from TRS-80* cassettes into any Z-80 based system. (Except sealed units.) The documentation explains how to patch the TRS-80* software to your system. In fact you can virtually change your Z-80 machine into a TRS-80* without making a single hardware change. The documentation also includes an example of patching SARGON II** into a Z-80 system.

The price is \$30 or FREE with the purchase of an assembled compuprism or super compuprism unit.

A-D, D-A Board

S-100 board provides 16 channels of analog to digital input and 8 channels of digital to analog output. With on board kluge area. Total cost of board and parts less than \$120. Bare board with documentation \$45.

able and on-line at the same time, except that they are seen by the system as separate drives. Though this does give the full capacity of the disk, this arrangement has one disadvantage—if both sides were seen as just part of one disk, a very large file (larger than one side) would automatically be split so it lies partially on each side. However, this scheme does not allow that.

Does It Work?

This connection was tied with two different controllers and operating systems, but on the same computer. In one case it worked; in the other, it did not.

To avoid wasteful head movement, most operating systems keep track of the last position of the head carriage on each drive. For example, if the system writes data on track 13 and then goes elsewhere to perform another operation, when it returns to the drive it assumes that the head is still on track 13. This is a reasonable assumption to make.

But when a double-sided drive is wired as two separate drives, both sides must be on the same track. Sup-

pose that the system moves drive 2 to track 13 and then does a read from track 30 of drive 3. Not knowing that this read has also moved the head on drive 2 to track 30, it now returns to drive 2 and expects its head to still be on track 13. But it's not, so we're in trouble.

One of my disk systems is soft-sectored and uses a 1771 controller. Since every sector on a soft-sectored disk is numbered, not just with the sector number, but also track number, then the 1771 controller immediately realizes that it's on the wrong track. It tries to re-read the sector a few times, but after two seconds or so does a seek back to track 0 and then back to the desired track. Thus there is a slight delay, but eventually it gets to the right track and reads or writes in the correct sector. The delay slows down operation, but is only present when alternate sides of the same disk are both used; if only one side is used continuously, then this problem does not appear.

My other disk system is hard-sectored. In this system, sectors need not be numbered (since the index holes are used to find the correct sector).

Thus, when the operating system switches from one side to other it has no way of knowing that the head has been moved from its earlier position. And so it reads or writes in the wrong place, a serious mistake.

There are, of course, several ways of getting around the problem (by, for example, forcing the drive to go to track 0 when changing sides, or by patching the disk operating system so that the same location is used to keep track of the head position of both drive 2 and drive 3). In the long run, however, this is not the real answer. The best method would be to do both the hardware and software conversion so that the double-sided drive appears as one big disk rather than two smaller ones. (That is ultimately going to be done when I get a new Gimix double-density controller for my 6809 system.)

In any case, though, having 800 kilobytes on a single five-inch disk is quite an accomplishment. Though not quite as good as the 1.2 million bytes possible on an eight-inch double-sided, double-density diskette, it is much more compact and much less expensive. ■

MBC SYSTEMS inc.

(203) 342-2747 TWX 710 4286345

COMPUTERS	HEWLETT-PACKARD	
	HP-85A.....	\$2795
	HP-83A.....	\$1990
	NORTH STAR	
	HRZ-2-32K-DD-FACTORY ASSEMBLED.....	\$2795
	HRZ-2-32K-QD-FACTORY ASSEMBLED.....	\$2995
	COMMODORE BUSINESS MACHINES	
	8032 (80) CHARACTER SCREEN.....	SCALL
	4032 (40) CHARACTER SCREEN.....	SCALL
	8050 DUAL DRIVE 1MEG STORAGE.....	SCALL
4040 DUAL DRIVE.....	SCALL	
CALL US FOR COMPLETE LINE		
INTERTEC SUPERBRAIN		
SUPERBRAIN 64K 2D.....	\$2890	
SUPERBRAIN 64K 2Q.....	\$3490	
ALTOS, APPLE, ATARI ETC. ALSO IN STOCK, CALL FOR PRICES!		
PRINTERS	DIABLO 630.....	\$2395
	NEC 5510 SERIAL OR 5530 PARALLEL.....	\$2595
	CITOH.....	\$1775
	ANADEX 9500 OR 9501.....	\$1490
	IDS PAPER TIGER 445G.....	\$520
	IDS PAPER TIGER 460G.....	\$1250
	IDS PAPER TIGER 560G 132 COL 5" PAPER.....	\$1395
	WE CARRY CENTRONICS COMPLETE LINE.....	SCALL
	EPSON MX-80FT FRICTION & TRACTOR.....	\$695
	EPSON MX-80.....	\$595
EPSON MX-70.....	\$425	
OKIDATA MICROLINE 80.....	\$499	
OKIDATA MICROLINE 82.....	\$690	
TERMINALS	TELEVIDEO MODEL 950.....	\$1075
	TELEVIDEO MODEL 920C.....	\$990
	HAZELTINE MODEL 1400.....	\$599
	HAZELTINE MODEL 1420.....	\$690
	INTERTUBE AND EMULATOR.....	\$775
	SOROC IQ 120.....	\$850
	SOROC IQ 135.....	\$899
	SINCE 1977 COMPLETE SALES AND SERVICE. VISA & MC OK!	
	PRICES ARE SUBJECT TO CHANGE. MOST ITEMS IN STOCK.	

Multi-Business Computer Systems

28 MARLBOROUGH ST. PORTLAND, CT 06480




PET* AIM*
KIM* TRS-80*

A/D D/A

Industrial quality data conversion boards (A/D and D/A) are available for **APPLE*, S-100, PET*, TRS-80*, AIM*, and KIM*** systems. Tecmar's new analog to digital converter series provides some of the most sophisticated and versatile analog data acquisition available for any computer. It supports options such as 12, 14, or 16 bit accuracy; 30, 40, 100, or 125 KHz conversion rates; variable ranges and gains; $\pm 250V$ of common mode voltage range; multiplexer expansion up to 256 channels; thermocouple cold junction compensation. In addition, the S-100 board contains a powerful timer/counter circuit which can start A/D conversion and can also be used independently for time of day, event counting, frequency shift keying and many other applications.

Apple* A/D Board	16 channel 12 bit	\$495
Apple* D/A and Parallel Output Board	2 channel 12 bit	\$295
S-100 A/D Timer - TOD - Counter Board	16 channel 12 bit	\$695
S-100 D/A Board	4 channel 12 bit	\$395

Apple* A/D & Timer Board Available 3rd Quarter



INC.

TECMAR, INC.
(216) 464-7410

23600 Mercantile Road • Cleveland, OH. 44122

The Epson MX-80: A Tough Act to Follow

By Frank J. Derfler

A home computer has many uses, but a lot of them are not really practical. For instance, I don't think anyone can honestly claim it is more convenient to keep recipes in a microcomputer than in a file box. But one of the most practical things you can do with a microcomputer is word processing. Most of us can see the value of being able to edit and cut and paste letters and other documents on a video screen before printing. The only drawback is the cost of a good letter-quality printer.

Three Approaches

There are essentially three ways to attack the printer problem. A high-quality high-speed printer will cost a minimum of \$2000, and could run over \$4000—that cost might be prohibitive. You might also require some unique software to fully exploit the power of an expensive printer. The quality, though, will be something to be proud of.

Surplus Printing Terminals

A middle-of-the-road approach involves using surplus printing terminals. The surplus terminals probably started life as input devices at car rental, airline or other remote locations serving large time-shared computer systems. These large systems usually did not use ASCII as a data alphabet, and they may not have used RS-232C as a signalling scheme. Many available systems have been


converted to RS-232C ASCII communications, but the quality of the conversion varies. These surplus printing terminals are usually based on an IBM Model 72 Selectric typewriter, so the print quality can be excellent and you can change typeballs.

On the positive side, surplus printing terminals offer moderate cost (\$600–\$1200) and high quality. On the negative side, the quality of conversions and mechanical refurbishing is inconsistent. The speed is limited to about 110 baud. The printing mechanism is a mechanical night-

mare for the uninitiated, although most local typewriter repair shops will recognize and repair the IBM mechanism once you persuade them to take a look at your unique beast. The cost of maintenance for the printing mechanism may be \$100 a year or more.

Dot Matrix

Until recently, the last choice of anyone doing word processing was a dot matrix printer. The only things dot matrix systems had going for them were price and convenience.



The Epson printers contain a microprocessor which controls all functions. The empty sockets in the center of the picture hold additional ROMs for the GRAFTRAX II graphics option. GRAFTRAX II provides a great deal of capability in addition to the TRS-80 graphics set. It gives the MX-80 a high density graphics mode and italics in all 12 print modes. The GRAFTRAX II option costs \$95 as a dealer installed retrofit and \$50 if it is installed at the factory. The optional RS-232C serial board and an IEEE-488 standard interface board are also available.

Frank J. Derfler, Jr. (PO Box 691, Herndon, VA 22070) is the author of the monthly Dial-up Directory column in Microcomputing.



Invasion Orion: Can You Defeat The Klaatu and Your Computer?

Look your computer straight in the eye, load in the new **Invasion Orion** and suddenly you are the Fleet Admiral, the Commander-In-Chief. And only you can stop the alien forces: the robotic Klaatu who have just invaded your Stellar Union space.

You command as many as nine starships; each ship spends energy on moving, on shielding itself, on firing its three weapon systems—destructor beams, missiles, torpedoes. There are 30 different types of starships—all armed with such a fantastic array as to intimidate the Klaatu.

But it isn't as easy as it seems. Your ships have only a limited amount of energy and you must decide how to allocate that energy to destroy the enemy.

Will your ship's armor be enough to stop the enemy's torpedo? Or should you divert energy from your beam to your shield? Move in for the kill on your weakened opponent and risk a beam attack? Or outrun the enemy? With each turn you take, your energy is replenished. Can you defeat the Klaatu? Or is your computer smarter than you are?

Invasion Orion is an EPYX game. Like all EPYX games, you will never get bored playing. Not in your or your computer's lifetime. Every game is different and fresh. Choose from three levels of skill: beginner, intermediate, expert. Ten fully tested scenarios, from one-on-one starship combat to full scale battle. Two programs: the first uses your pre-created scenarios to play the game; the second lets you create your own scenarios and design your own ships. A game that is infinitely expandable.

Yet so very easy to learn. With any of the ten scenarios, the computer takes care of all the details, no complex rules to

remember. The screen shows prompts for your battle orders. Just concentrate on your strategy for victory. Complete with superb graphics (if you have either an Apple or an Atari, you can enjoy color and sound!) and with battle manual, game program, scenario creation program, data files for your computer.

Invasion Orion. Another bug-free, easy-loading lifetime computer game from EPYX. With the unique EPYX lifetime warranty: If anything happens to your cassette or disk at any time and for any reason, send it back with just \$5.00 for shipping and handling and we will send you a brand new one.

(Of course, there is also our 30-day unconditional guarantee: if your EPYX game has any defect whatsoever within 30 days of purchase, return it to us or your dealer and we will replace it free. No questions asked.)

Visit your dealer now and pick up **Invasion Orion** in its good-looking, protective box with the best instruction book you've ever read. Now available on disk for the Apple II (48K RAM with Applesoft) and Radio Shack's TRS-80 (32K RAM). Or on cassette for the Atari (32K), TRS-80 (Level II, 16K), Apple (16K and Applesoft) and Pet (16K). Only \$24.95, disk or cassette.

If your dealer is out of stock and you can't wait, order directly from Automated Simulations. \$24.95 plus \$2.00 for shipping and handling (and sales tax if you are in California).

We guarantee you will be delighted with **Invasion Orion**. (If it is not exactly what you want, return it to us for full refund. Again, no questions asked.) Enclose your check. Or if you order by Visa or MasterCard, use our toll-free phones: In the United States: operator 861 (800) 824-7888; In California: operator 861 (800) 852-7777; In Hawaii and Alaska: operator 861 (800) 824-7919.

Order today. You and your computer deserve the fun.
AUTOMATED SIMULATIONS, INC. ✓55
Dept. 104, P.O. Box 4247
1988 Leghorn Street
Mountain View, CA 94040



FREE
with software purchase —
One year subscription to **InfoWorld**

DISCOUNT SOFTWARE

Ad #16

ULTIMATE SOFTWARE PLAN

✓ (New items or new prices)

✓ 250

We'll match any advertised price on any item that we carry. And if you find a lower price on what you bought within 30 days of buying it, just show us the ad and we'll refund the difference. It's that simple.

Combine our price protection with the availability of full professional support and our automatic update service and you have the Ultimate Software Plan.

It's a convenient, uncomplicated, logical way to get your software.

CP/M users: specify disk systems and formats. Most formats available.

CP/M *

ARTIFICIAL INTELLIGENCE
Medical(PAS-3).....\$849/\$40
Dental (PAS-3).....\$849/\$40

ASYST DESIGN
Prof Time Billing.....\$549/\$40
General Subroutine.....\$269/\$30
Application Utilities.....\$439/\$30

COMPLETE BUS. SYSTEMS
Creator.....\$269/\$25
Reporter.....\$169/\$20
Both.....\$399/\$45

COMPUTER CONTROL
Fabs (B-tree).....\$159/\$20
UltraSort II.....\$159/\$25

COMPUTER PATHWAYS
Pearl (level 1).....\$ 99/\$25
Pearl (level 2).....\$299/\$40
✓ Pearl (level 3).....\$549/\$50

DIGITAL RESEARCH
CP/M 2.2
NorthStar.....\$149/\$25
TRS-80 Model II (P+T).....\$159/\$35
Micropolis.....\$169/\$25
Cromemco.....\$189/\$25
PL/I-80.....\$459/\$35
BT-80.....\$179/\$25
Mac.....\$ 85/\$15
Sid.....\$ 65/\$15
✓ Z-Sid.....\$ 90/\$15
✓ Tex.....\$ 90/\$15
DeSpool.....\$ 50/\$10

D.M.A.
Ascorm.....\$149/\$15
DMA-DOS.....\$179/\$35
CBS.....\$369/\$45
Formula.....\$539/\$45

GRAHAM-DORIAN
General Ledger.....\$729/\$40
Acct Receivable.....\$729/\$40
Acct Payable.....\$729/\$40
Job Costing.....\$729/\$40
Payroll II.....\$729/\$40
Inventory II.....\$729/\$40
Payroll.....\$493/\$40
Inventory.....\$493/\$40
Cash Register.....\$493/\$40
Apartment Mgt.....\$493/\$40
Surveying.....\$729/\$40
Medical.....\$729/\$40
Dental.....\$729/\$40

MICRO-AP
S-Basic.....\$269/\$25
Selector IV.....\$469/\$35

MICRO DATA BASE SYSTEMS
HDBS.....\$269/\$35
MDBS.....\$795/\$40
DRS or QRS or RTL.....\$269/\$35
MDBS PKG.....\$1295/\$60

MICROPRO
WordStar.....\$319/\$60
Customization Notes.....\$ 89/\$na
Mail-Merge.....\$109/\$25
WordStar/Mail-Merge.....\$419/\$85
DataStar.....\$249/\$60
WordMaster.....\$119/\$40
SuperSort I.....\$199/\$40

MICROSOFT

Basic-80.....\$289/\$30
Basic Compiler.....\$329/\$30
Fortran-80.....\$349/\$30
Cobol-80.....\$574/\$30
M-Sort.....\$124/\$30
Macro-80.....\$144/\$20
Edit-80.....\$ 84/\$20
MuSimp/MuMath.....\$224/\$25
MuLisp-80.....\$174/\$20

ORGANIC SOFTWARE
TextWriter III.....\$111/\$20
DateBook II.....\$269/\$25
Milestone.....\$269/\$25

OSBORNE
General Ledger.....\$ 59/\$20
Acct Rec/Acct Pay.....\$ 59/\$20
Payroll w/Cost.....\$ 59/\$20
All 3.....\$129/\$60
All 3 + CBASIC-2.....\$199/\$75

PEACHTREE*
General Ledger.....\$399/\$40
Acct Receivable.....\$399/\$40
Acct Payable.....\$399/\$40
Payroll.....\$399/\$40
Inventory.....\$399/\$40
Surveyor.....\$399/\$40
Property Mgt.....\$799/\$40
CPA Client Write-up.....\$799/\$40
Mailing Address.....\$349/\$40

SOFTWARE WORKS
Adapt (CDOS to CP/M).....\$ 69/\$na
Ratfor.....\$ 86/\$na

SOHO GROUP
MatchMaker.....\$ 97/\$20
WorkSheet.....\$177/\$20

STRUCTURED SYSTEMS
GL or AR or AP or Pay.....\$599/\$40
Inventory Control.....\$599/\$40
Magic Worksheet.....\$219/\$40
Analyst.....\$199/\$25
Letterright.....\$179/\$25
QSort.....\$ 89/\$20

SUPERSOFT
Diagnostic I.....\$ 49/\$20
Diagnostic II.....\$ 84/\$20
Disk Doctor.....\$ 84/\$20
Forth (8080 or Z80).....\$149/\$25
Fortran.....\$219/\$30
Fortran w/Ratfor.....\$289/\$35
Other.....less 10%

TCS
GL or AR or AP or Pay.....\$ 79/\$25
All 4.....\$269/\$99

UNICORN
Mince.....\$ 99/\$25
Scribble.....\$ 99/\$25
Both.....\$189/\$50
Amethyst.....\$299/\$75

WHITESMITHS
"C" Compiler.....\$600/\$30
Pascal (incl "C").....\$850/\$45

"DATA BASE"
FMS-80.....\$649/\$45
dBASE II.....\$629/\$50
Condor.....\$599/\$30
Condor II.....\$899/\$50
Access/80.....\$749/\$50

"PASCAL"

Pascal/MT+.....\$429/\$30
Pascal/Z.....\$349/\$30
✓ Pascal/UCSD.....\$399/\$50
Pascal/M.....\$149/\$20

"WORD PROCESSING"
✓ WordSearch.....\$179/\$50
SpellGuard.....\$229/\$25
VTS/80.....\$259/\$65
Magic Wand.....\$289/\$45
Spell Binder.....\$349/\$45

"OTHER GOODIES"
The Last One.....\$549/\$95
SuperCalc.....\$269/\$50
Target.....\$189/\$30
BSTAM.....\$149/\$15
Tiny "C".....\$ 89/\$50
Tiny "C" Compiler.....\$229/\$50
CBASIC-2.....\$ 98/\$20
Nevada Cobol.....\$129/\$25
MicroStat.....\$224/\$20
Vedit.....\$105/\$15
ESQ-1.....\$1349/\$50
MiniModel.....\$449/\$50
StatPak.....\$449/\$40
Micro B+.....\$229/\$20
Raid.....\$224/\$35
String/80.....\$ 84/\$20
String/80 (source).....\$279/\$na

APPLE II *

INFO UNLIMITED
EasyWriter.....\$224
Datadex.....\$349
Other.....less 15%

MICROSOFT
Softcard (Z-80 CP/M).....\$259
Fortran.....\$179
Cobol.....\$499

MICROPRO
Wordstar.....\$269
MailMerge.....\$ 99
Wordstar/MailMerge.....\$349
SuperSort I.....\$159

PERSONAL SOFTWARE
Visicalc.....\$ 99
Visicalc II.....\$159
CCA Data Mgr.....\$ 84
Desktop/Plan II.....\$159
Visiterm.....\$129
Visidex.....\$159
Visiplot.....\$149
Visitrend/Visiplot.....\$229
Zork.....\$ 34

PEACHTREE*
General Ledger.....\$224/\$40
Acct Receivable.....\$224/\$40
Acct Payable.....\$224/\$40
Payroll.....\$224/\$40
Inventory.....\$224/\$40

"OTHER GOODIES"
✓ dBASE II.....\$329/\$50
VU #3 (use w/Visicalc).....\$ 49
SuperText II.....\$127
Data Factory.....\$129
DB Master.....\$184
OEM (complete
accting).....\$399
Charles Mann.....less 15%
STC.....less 15%

ORDERS ONLY—CALL TOLL FREE VISA • MASTERCARD

1-800-854-2003 ext. 823 • Calif. 1-800-522-1500 ext. 823

Overseas—add \$10 plus additional postage • Add \$2.50 postage and handling per each item • California residents add 6% sales tax • Allow 2 weeks on checks, C.O.D. ok • Prices subject to change without notice. All items subject to availability • ® — Mfgs. Trademark.

THE DISCOUNT SOFTWARE GROUP

6520 Selma Ave. Suite 309 • Los Angeles, Ca. 90028 • (213) 666-7677

Int'l TELEX 499-0032 BVHL Attn: DiscSoft • USA TELEX 194-634 BVHL Attn: DiscSoft • TWX 910-321-3597 BVHL Attn: DiscSoft

The appearance of the dot matrix characters was definitely a negative factor. It took a large lump of rationalization and some self-deception to convince yourself that people enjoyed reading letters prepared on a standard dot matrix printer—they didn't, and they still don't.

But several new dot matrix machines that provide good to superb print quality have recently hit the market. As usual, there are some trade-offs in cost vs quality. The best dot matrix machines cost as much as the daisywheel and thimble machines, but provide more flexibility in operation. However, the most popular machine has a low price, and a print quality suitable for personal letters and documents for other computer users. This kind of printer is exemplified by the Epson MX-80.

10,000 a Month

This trade-off is certainly popular. Chris Rutkowski, the marketing manager of Epson America, Inc., claims sales of 10,000 MX-80s a month. This figure seems to be limited only by the capacity of the Japanese manufacturer to make and ship the machines. User groups for this printer have spontaneously sprouted around the country—unique for a peripheral device! Let's take a look at this hot-selling printer and see what makes it so popular.

The Epson MX-80 has two major attributes: good print quality and low price. The other features (which the MX-80 shares with some other dot matrix machines) include small size, low weight, low noise, great operational flexibility and mechanical simplicity.

Too good to be true? It all depends on exactly what print quality you are willing to settle for.

Print Quality

Fig. 1 shows the quality and types of print available from the Epson MX-80. The machine uses a 9×9 dot matrix printhead for characters, and produces graphics in a 6×12 dot format. The lowercase characters have true descenders. The lowercase s probably shows the dots more clearly than any other character. Other lowercase rounded characters such as the a and e also show the dots, but not as clearly. The s is made up of 14 dots. In the double-strike mode, the paper is rolled up 1/216 inch and the character is printed again. The s is then made up of 28 dots slightly dis-

Various print styles are available on the **MX-80**. If different print styles are desired on one line or on one page, it is necessary to use BASIC PRINT statements to send the correct text and commands to the printer.

This is an example of double struck printing. It is a printing method which actually scrolls the paper vertically and then prints again to fill in the spaces between the dots. Some people like this mode, but others don't.

Double striking can be combined with another mode called **Emphasized Printing**.

A compressed mode is also available which gives 132 columns of print per line. This is very handy for some statistical programs which assume you have an 80 column printer. With the MX-80, **You DO!**

The EPSON MX-80 also has a graphics capability:

Fig. 1. Sample printout showing MX-80 print styles.

placed in the vertical axis. Some people find this print quality pleasing because it smooths out the dots; others claim it is fuzzier, and prefer the single-strike mode.

The different print styles are easy to use from BASIC, but they are much more difficult to mix on a single page when using a word-processing program. The most practical method of mixing print styles on one page is to write your document as BASIC "PRINT" statements. If you are using a word-processing program and want an entire page or document done in only one typeface, you must load BASIC, send an ASCII number out the I/O port to instruct the printer and then load your word-processing program. This could get a little cumbersome with tape-based systems. It isn't bad with disk systems, as long as you remember to save the document you have been working on before you go to BASIC.

Graphics

The printer contains a graphics set essentially the same as the one used in the TRS-80 Model I. When it does graphics it doesn't simply copy the screen—it reproduces the figures in its ROM, based on received ASCII codes. If you have a computer with no graphics set, the printer will still respond to the codes. If you have a more elaborate graphics capability, the printer will still only produce what is in its own ROM. If you have a TRS-80 Model I, what you see is what you get (see Fig. 2).

Connection

The Epson MX-80 is easy to interface with most computer systems. It plugs directly into the Centronics parallel port. However, the standard Radio Shack parallel printer cable will not allow separation of the carriage-return and line-feed signals. Epson says their special cable is needed

to separate these signals if the printer is to do underlining and other special printing.

If you don't need a separate CR and LF, the standard cable will work fine. This is a little hard to understand since each of these signals is a separate ASCII code, but the cables work as advertised. The Epson MX-80 prints bidirectionally at a nominal speed of 80 characters per second. A machine connected through a parallel port has no problem in printing along with a 300 baud input.

An optional RS-232C serial board is available for the printer. This interface is not quite so simple because it uses RS-232 pins 11 and 20 as clear-to-send lines. The Epson cannot hold or buffer serial data while it does a carriage return, line feed or form feed. If the computer does not stop transmitting, characters will be lost. When it needs some breathing room, the printer sets pins 11 and 20 to a low condition.

This kind of interface requires more complex driver software than most RS-232C ports commonly provide. Epson would probably have served the user better if they had included enough bytes of memory on the serial card to hold a few characters during mechanical operations. An IEEE-488 standard interface is also available for use with Commodore microcomputers.

Construction

The Epson MX-80 has held up well under heavy use. The power supply





Fig. 2. Screen dump showing the opening hand of Instant Software's Cribbage program.

We're
known
for our
fine print.



Epson.

The type you get out of most printers you wouldn't send to your maiden aunt, much less use for your *important* correspondence. And up to now, in order to get a dot matrix hardcopy you could really call correspondence quality, you had to spend on the high side of a thousand bucks.

Not any more.

The Epson MX-80 challenges any dot matrix printer anywhere to match our type at our price. Or even come close.


Our emphasized print mode gives you a tack-sharp, clean, easy-to-read face with true descenders—at a fraction of the price of daisy wheel printers. We give you a user-defined choice of twelve different weights and sizes of letters in 40, 80, 66 or 132 columns. We give you adjustable tractors so you can do anything from labels to memos to manuscripts. Fast and clean.

But if you think print quality is the only thing we have

to sell, you're wrong. The MX-80 may be the most revolutionary printer to come out in the past ten years.

For starters, it features the world's first *disposable* print head—after it's printed between 50 and 100-million characters, just throw it away. A new one costs less than \$30 and you can change it yourself with one hand. Plus, the MX-80 prints bidirectionally and 80 CPS with a logical seeking function to minimize print head travel time and maximize throughput. Finally—and this is the best part—you can buy an MX-80 right now for less than \$650.

And that's what we call a lot of fine print for the money.



EPSON
EPSON AMERICA, INC.

23844 Hawthorne Boulevard • Torrance, CA 90505 • (213) 378-2220

✓ 116

transformer (no wall transformer!) runs cool. The printer has passed the FCC certification test for rf radiation as a class B (home computer) device, so it should not significantly interfere with local television or radio receivers.

The printhead is easy to replace and costs about \$35. This is a fraction of the cost of printheads on competing dot matrix printers.

The tractor-feed mechanism is simple but effective. Perforated paper tears cleanly along the top cover, but it takes a little practice to manually roll the paper back down so the top of the next page is aligned with the printhead.

Documentation

The *MX-80 Printer User's Manual* is a witty book which provides over 100 pages of directions, hints and diagrams. David A. Lien is the author, and he has used a very readable style which encourages MX-80 users to get the most out of the system.

A separate service manual is also available—it is informative, but not as much fun to read. Most MX-80 owners would benefit from having the service manual around. It contains clear instructions and exploded-view mechanical diagrams. Several trips to the local dealer for simple lubrication or alignment can be avoided

through the use of the service manual.

Psychology

OK—this printer is reliable, easy to use and reasonably priced, but can it be used for real word processing? That question will raise an argument in many circles.

Chris Rutkowski claims that people will soon expect dot matrix and tractor-fed paper with little perforation marks around the edges. They will think you are inefficient and extravagant if you use single-fed sheets and high-priced printers. His vision of the future may be colored by his desire to keep his sales up, but it certainly is true that the print quality of the MX-80 is good enough for many uses.

If tractor-feed doesn't suit your needs, a newer version (the MX-80 F/T) is now available with a pressure-feed capability (for \$745). Don't confuse the MX-80 with its less capable brother, the MX-70. The 70's print face isn't nearly as pretty, and for some reason its operational reputation is not as good.

The MX-80 lists for \$645, but you can find it advertised here in *Microcomputing* for under \$500. At that price, you will have to judge if it is good enough to meet your word-processing needs. ■

Epson's Newest Printer


Epson has just added the 136-column MX-100 to its series of technologically-advanced dot matrix printers.

The MX-100's predecessor, the MX-80, is now the largest-selling 80-column dot matrix printer in the world.

The MX-100 uses dot matrices ranging from 9×9 to 18×18 to generate correspondence-quality printing in a total of 12 different character weights and sizes. The new printer also features Epson's Micro-Nine disposable printhead, and GRAFTRAX, a high resolution bit image graphics capability.

Because the printer accepts paper up to 15.5 inches wide, it is capable of printing up to 233 columns in the condensed print mode. It prints bidirectionally at 80 cps, with a logical seeking function to minimize printhead travel time and increase throughput. It comes standard with both a friction paper-feed platen and adjustable tractors on a removable tractor mechanism.

The MX-100 is currently available at a suggested retail price of \$995. For more information, contact Epson America, Inc., 23844 Hawthorne Boulevard, Torrance, CA 90505.



Epson's new MX-100 is a 136-column wide printer in the normal 10 character per inch mode. In the compressed mode of 16.5 characters per inch it can print 233 characters on paper up to 15.5 inches wide. It can handle both pin feed and cut sheets.

OHIO SCIENTIFIC

S-FORTH — a full implementation of Fig-FORTH including editor, virtual disk sub-system, and compatibility with OS65D-3 on 5¼" or 8" disk. \$34.95.

Source listing \$24.95.

Both for \$49.95.

TOUCH TYPING MADE EASY

— 15 lesson set teaches you to "touch type". Now also available for the C1P. 8K. \$19.95.

TITANIC QUEST — a real time search where you risk your remaining supplies to find the Titanic. 8K. \$6.95.

TEXT EDITOR — the best screen text editor available for OSI C4P, C8P disk systems. \$19.95.

Send for our FREE 14 page software and hardware catalog. Includes photos and complete descriptions of all game, utility, and business software.

Aurora Software Associates

P.O. Box 99553
Cleveland, Ohio 44199
(216) 221-6981



ADVENTURE INTERNATIONAL


TWO FULL DISKS
WORTH OF DATA!!



STONE OF SISYPHUS

APPLE 2 PLUS or APPLE 2 - 48K
with Applesoft in ROM 042-0100 \$29.95
WORKS ON 3.2 OR 3.3
Works on 1 or 2 drive systems

ALSO AVAILABLE FOR
TRS-80 32K DISK Model 1 012-0100 \$29.95



STONE OF SISYPHUS

SECOND IN THE MACES & MAGIC SERIES

MACES & MAGIC are fantasy adventures involving you and your computer. Armed only with your wits, a microcomputer, and the software provided, you can become the hero or the meal your destiny dictates. You create a character, equip him (or her) with suitable weapons and armor, and enter the dungeon in search of fame and fortune. Neither is particularly easy to obtain.

If you are successful in avoiding or conquering the various monsters, traps, enchantments and illusions set by our nefarious dungeon-masters, you may escape with riches and glory. Your name and deeds will be recorded for posterity in the records of the dungeon. More importantly, you'll be alive. You may then use the same character in his more experienced and wealthy form when you enter dungeons on later occasions.

The object of the whole exercise is not just to fight the monsters and collect treasure. You have to get out alive to enjoy it. In every dungeon there is at least one exit. It is possible to escape from each and every dungeon with a whole skin. We state that fact here because players often believe this not to be true. We really aren't out to get you. Not really.....

The Stone of Sisyphus carries you to the "thinking man's" dungeon. A subterranean world of monsters, magic, traps and treasures demands brains rather than luck to survive (of course, you might take along your mace just in case...). A compacted data structure makes it possible to run this fantasy on a single disk drive, though 2 full diskettes worth of data are supplied. Expanded use of free-form input puts your ingenuity to an even greater test. The responsiveness of the programs to the individual qualities of the character make this adventure frustratingly enjoyable for hundreds of hours before its secrets can be unlocked.

ADVENTURE 11 & 12 ARE HERE!

CALL OUR TOLL-FREE NUMBER FOR ORDERING INFORMATION!

PRO-PIX '81

PRO-FOOTBALL-PIX, or PRO-PIX, is the culmination of over five years of development and use of a utility program to track the progress of the 28 professional U. S. football teams during the regular 224-game (16 weeks and 14 games per week) season. **PRO-PIX** made its public debut in 1980 under a slightly different name after extensive testing and was very successful, receiving many plaudits from users, and requests for a 1981 version. **PRO-PIX** is basically an updated version for 1981, with several subtle changes in presentation format and modifications to make it usable with Model III. The prediction data has been modified slightly and information is included herein for updating the program for successive seasons. **PRO-PIX** is designed for use on a TRS-80 Model I or Model III computer with at least 16K of memory. It operates under either Level II Basic or DOS Basic, with data handling by either tape or disk.

Features of **PRO-PIX** may be summarized as follows:

- List **SCHEDULES** by team or week of interest.
- List **SCORES** of all games played, by team or week.
- List current **STANDINGS** in division.
- Show **PREDICTIONS** for games to be played, by team or week.
- **PRINT** any screen that displays data.
- **UPDATE** the program by entering weekly scores.
- Set up a new **SEASON**.



PRO-PIX '81

By Talley-Ho Software
APPLE and ATARI conversions by
Russ Wetmore

APPLE TAPE TO DISK 041-0127 \$19.95
ATARI 400/800 TAPE TO DISK 051-0127 \$19.95

ALSO AVAILABLE FOR
TRS-80 TAPE Model 1&3 010-0127 \$19.95
TRS-80 DISK Model 1 012-0127 \$24.95



A Division of Scott Adams, Inc.
Adventure International • Box 3435 • Longwood, FL 32750
CATALOG AND TOLL-FREE ORDER NUMBER: (800) 327-7172
IN FLORIDA (305) 862-6917
SHIPPING AND HANDLING CHARGES ARE EXTRA
PRICES ARE SUBJECT TO CHANGE WITHOUT NOTICE



WHAT IS IT?

Interactive Fiction is story-telling using a computer, so that you, the reader, can actually take part in the story instead of merely reading.

HOW DOES IT WORK?

The computer sets the scene with a fictional situation, which you can read from the CRT. Then, you become a character in the story: when it's your turn to speak you type in your response. The dialogue of the other characters and even the plot will depend on what you say.

IS IT A GAME?

No. In a game the situation is rigidly defined and you can select from only a limited number of responses. But in Interactive Fiction you can say anything you like to the other characters. (Of course if your response is too bizarre they may not understand you.)


His Majesty's Ship "Impetuous" — You are the Captain, Horatio Hornblower, back in the days when His Majesty's Navy ruled the seven seas. Pirates, plunder, fame and fortune await the intrepid captain. If you have ever enjoyed books about the sea, now is your chance to take the helm and find out what this life was really like.

FOURTH IN THE SERIES



INTERACTIVE FICTION

BY ROBERT LaFORE



The *Classic* game
you've heard
so much about!

APPLE 2 - 48K DISK
(Applesoft in ROM required)
His Majesty's Ship "Impetuous"
042-0077 \$19.95

ALSO AVAILABLE FOR
TRS-80 Model 1 32K DISK
His Majesty's Ship "Impetuous"
012-0077 \$19.95

HIS MAJESTY'S SHIP
"IMPETUOUS"

APPLE - ATARI

SOFTWARE DEALERS!!

If you aren't carrying the **Adventure International** line of products, then you're missing out on the fastest growing and most asked for programs in the industry today. We have over 150 quality products, with more being added every month. We offer our dealers support through national advertising, professional packaging and an established market. If you would like more information on joining our dealer family, call our toll-free number (800) 327-7172 and ask for a dealer representative.

If you own
an Apple,
Atari, TRS-80
or other desk-top
computer, then we have
the programs for you! Order
from your favorite software dealer
or call toll-free (800) 327-7172
today to order or for your free catalog.

SOFTWARE AUTHORS!!

Join the ranks of the leading writers in the industry by becoming an **Adventure International** author! We are looking for games (arcade, "Adventure"-style, simulation, role-playing) and outstanding utility packages for all of the major computers. Only the best will do! If you have a program which you feel would fit into our current catalog, then we invite you to submit it for review. Send a machine-readable copy, a description of any hardware needed, complete documentation and loading instructions to us in care of the **Software Review Board**. (Due to the tremendous number of programs we receive monthly, we can only return a submission if you include a stamped, self-addressed envelope.)

CATALOG & ORDERING
TOLL FREE HOT LINE (800) 327-7172

ai Adventure

INTERNATIONAL

393 A DIVISION OF SCOTT ADAMS, INC.

BOX 3435 • LONGWOOD, FL 32750
Call toll free for catalog (800) 327-7172

How to Cope With an Analog World

By Theodore T. Tylaska

Analog to digital converters (ADC) are absolute necessities whenever a digital computer is used to sense analog signals in real-world applications.

There are several ways to convert an analog voltage into an equivalent digital number. The successive approximation technique is the most popular, because it is a good compromise between speed and required hardware. The key control element in the successive approximation ADC is a medium-scale integration device called the successive approximation register (SAR).

This design for a four-bit SAR constructed from small-scale integrated circuits will help you better understand the operation of this important register. Support components are added so that an operational successive approximation ADC can be constructed. LED indicators and single-step switches are included in the design so that the operation of the SAR can be observed for each clock pulse.

Successive Approximation: An Overview

For an overview of the principles of the successive approximation ADC, study the block diagram in Fig. 1. Notice the ADC requires a digital to analog converter (DAC) plus other parts. Thus, the cost of an ADC is usually two to three times the cost of an equally accurate DAC itself. Successive approximation analog-to-digital conversion is a more time-consuming process than digital-to-analog conversion. The explanation of the SAR will clearly show that conversion time is a function of the number of bits of precision in the converter.

The A/D conversion process begins




Fig. 1. Block diagram of four-bit successive approximation A/D converter.




Fig. 2. Successively approximating an analog voltage.

upon receipt of a start conversion pulse. The successive approximation register sequentially turns on each weighted bit of the D/A converter to compare the voltage produced by that bit to the input voltage. The most significant bit (MSB), B3 of the D/A, is turned on first, and the output of the comparator is noted.

If the D/A output voltage is less than the analog input voltage, the MSB is left on in the successive ap-

proximation register; otherwise, the MSB is turned off in the SAR. The next MSB, B2, is turned on, and the summation of the voltages produced by B3 and B2 from the DAC is compared with the analog input voltage.

If, for example, the output of the DAC exceeds the value of the input voltage, then bit Q₂ is turned off in the SAR. The process continues until the least significant bit, B0, of the DAC is set, and a comparison is made between the input analog voltage to the ADC and the DAC output voltage. If the ADC has *n* bits of precision, there must be *n* comparisons made.

This method is also called a binary approximation technique, because at each stage of the conversion a comparison is made of one-half the remaining difference to determine whether that bit is required in the approximating voltage sum. Thus, the first step in the successive approximation process must determine if the input exceeds $V_{fs}/2$, where V_{fs} is the full-scale input voltage of the ADC. The second step determines if $V_{fs}/2^2$ is needed, and the *n*th stage determines if the weight of $V_{fs}/2^n$ is needed to approximate the input voltage. In general, *n* + 1 clock pulses are needed to perform the approximation. The first clock resets the SAR, and each succeeding clock determines the need for each successive bit.

An example of approximating a given voltage with a four-bit SAR feeding a DAC is shown in Fig. 2. The voltage to be approximated is 5.5 V. Assume the ADC full-scale output voltage is 8 V. The first approxima-

Address correspondence to Theodore T. Tylaska, RFD 1, Box 230, Mystic, CT 06355.

tion sets bit 3, whose weight is 4 V. The second clock cycle attempts to set bit 2 with a weight of 2 V, but the resultant sum from the DAC is 6 V, which exceeds 5.5 V. Thus, bit 2 gets

reset to a zero. At the third clock cycle, bit 1 is next turned on and the DAC adds 1 V to the sum which now totals to 4 + 1 = 5 V. Since this is less than 5.5 V, bit 1 remains set to 1. Bit 0

adds 1/2 V to the sum to exactly equal the 5.5 V so bit 0 remains set to 1. The resulting digital word is (1011)₂.

Now that the function to be performed by the successive approximation register has been examined, an implementation of the SAR can be surmised. If a four-bit SAR is being designed, the SAR must have some control method to selectively turn on or off each successive bit being tested. A four-bit shift register could fill the bill for control with a single "one" being shifted through the register. The presence of a "one" at a given stage of the shift register could signify that the corresponding bit in the SAR is being tested. The control circuit in Fig. 3 shows an arrangement for such a control shift register.

This register is implemented out of 74LS74 D-type flip-flops. The control register is started by an initialize pulse, which causes 1 to be directly set into the first stage flip-flop, IC1A, and 0 to be directly set in the other four stages of the register. The last flip-flop, IC3A in the register, is used to hold the conversion complete condition.





Fig. 3.




TRS-80 MODEL II 64K \$3500

PACKS ENOUGH DATA HANDLING POWER FOR MANY SMALL BUSINESSES.



TRS-80™ DISCOUNT


- ☐ NO OUT-OF-STATE TAX
- ☐ NO SHIPPING COSTS



TRS-80 MODEL III 32K-2 DISKS

\$2100

NEW PERSONAL COMPUTER... REAL-TIME CLOCK, SHARPER CRT IMAGES AND FASTER LOADING CASSETTES



TRS-80 COLOR COMPUTER OR VIDEO \$339 each

A LOW COST, COLOR COMPUTER FOR PERSONAL BUSINESS OR ENTERTAINMENT

CERTIFIED CHECKS
CASHIERS CHECKS
OR CREDIT CARDS



PERRY OIL & GAS INC.

137 NORTH MAIN STREET, PERRY, MICH. 48872

PHONE (517) 625-4161

WARRANTIES HONORED BY ALL RADIO SHACKS • T.M. TANDY CORP.




Fig. 4.

Conversion complete occurs when the "one" preset into the first flip-flop has shifted into the fifth flip-flop. The OR gate IC8 holds the conversion complete condition in IC3A in the presence of continuous control clocks. At this time the result of the conversion can be read out of the data register.

The data register is another set of four flip-flops which is used to hold the information as to whether or not each weighted bit of the DAC is needed to approximate the given input analog voltage. The data register is implemented by two 74LS76 J-K flip-flops as shown in Fig. 3. The initialize pulse sets bit 3 on, and turns off the remaining bits, B2, B1 and B0. Bit 3 is wired to the most significant bit of the DAC to generate the comparison voltage of $V_{fs}/2$.

The comparator output from IC11 feeds the AND gate IC6 to determine whether a clear signal should be applied to the K input of the flip-flop IC4A to reset it. If the comparator output shows that $V_{fs}/2$ is less than the unknown applied voltage V_{in} , then the comparator signal is low and flip-flop IC4A remains set with B3 high. During the next data clock pulse, bit 2 from flip-flop IC4B is turned on to supply $V_{fs}/4$ from the DAC output.

Again, a comparison is made between V_{in} and the DAC output caused by the weighted sum of bit 3 and bit 2. This process will continue until bit 0 is summed into the accumulated output voltage of the DAC. A set of LEDs is connected to the data register outputs as shown in Fig. 4.

Two Clock Phases

The SAR is controlled by two clock phases called the control clock and the data clock. The clock generator IC9 is a 74LS123 dual monostable. The two monostables are cross-coupled to produce a square wave of period 2.4 us with the specified timing components. Closing switch SW1 disables IC9B and prevents the generation of a continuous train of clock pulses. While SW1 is closed, moving SW2 from position A to B and then back to position A will generate a single control clock and a single data clock pulse. Thus, you can single-step the SAR and observe on the LEDs the setting and clearing of each of the data flip-flops, depending on the result of each voltage comparison.

The timing diagram in Fig. 5 shows

COMMODORE:

VIC-20 color computer	\$ 289
4016 PET, 16K	799
8032 CBM, 32K	1,249
8096 CBM, 96K	1,699
4031 single drive, 170K	559
4040 dual drive, 343K	1,059
8050 dual drive, 974K	1,469
4022 tractor printer	649

*available fall

ATARI:

400 computer, 16K	\$ 369
800 computer, 16K	749
810 single drive, 88K	469
815 dual drive, 320K	1,129
820 40 column printer	279
825 80 column printer	749
830 modem	149
850 interface module	159

PRINTERS & ACCESSORIES:

ANADIX DP9000/1	\$ 1,199
DP9500/1	1,299
BASE2 800B	649
CENTRONICS 737-1	749
C. ITOH STARWRITER, 25p.	1,439
STARWRITER, 45p.	1,849
NEC SPINWRITER, 5530p	2,399
OKIDATA MICROLINE 82	599
MICROLINE 83	899
MILOT, graphics plotter	1,139
AXLON 32K, ATARI ramcrum	189
MICROTEK 16K, for ATARI	89

EXIDY CLOSE-OUT:

SORCERER, 16K (limited quantities) 939



MicroComputer
arehouse

260

3620 La Habra Way
Sacramento, Ca. 95825
(916) 486-3678

Call or write for price list with comparable savings on a full line of microcomputer peripherals and accessories. Ask about our monthly system special! Master Charge/Visa welcome. We pay freight on prepaid orders. Allow 2 weeks for personal checks. Prices subject to change without notice.

TRS-80*

SAVE A BUNDLE

When you buy your
TRS-80™ equipment!

Use our toll free number to
check our price before you buy
a TRS-80™ . . . anywhere!

TRS-80 is a trademark of the Radio Shack Division of Tandy Corporation

Don't Delay. . Call Today



189

SALES COMPANY

1412 WEST FAIRFIELD DR.

P.O. BOX 8098 PENSACOLA FL 32505

904/438-6507

nationwide 1-800-874-1551

the rising edge of the control clock to be delayed from the falling edge of the data clock. This delay is implemented by resistor R3, capacitor C3 and IC10 to give a delay of 250 ns. Switch SW1 must be open and SW2 must be in the A position for the clock to free run. IC8 serves as a clock buffer.

The start circuit in Fig. 4 is implemented by two D-type flip-flops in package IC7. The start pulse is a rising edge, and it can be applied at any time. The timing diagram shows the start pulse setting flip-flop IC7A. At the next rising edge of the control clock, IC7B is set because its D input is 1. The initialize signal that sets the correct state in the control and data registers and also clears IC7A is generated. On the next control clock rising edge, IC7B goes to 0 and removes the initialize signal.

Control flip-flop CF1 remains high

during control clock period 2. Since B3 is set, the DAC is making a trial comparison with its output at $V_{fs}/2$. At the falling edge 2 of the data clock, the decision is made to keep B3 or to clear it. At the same time B2 is set because CF1 is applied to the J input of IC4B while its K input is 0.

At rising edge 3 of the control clock, CF1 is cleared and CF2 is set. This conditions the K input of B2 to give a clear signal or not, depending upon the result of the comparison of the DAC output with the input voltage V_{in} . At falling edge 3 of the data clock, the decision is made to keep B2 set or clear it, and at the same time to set B1.

At rising edge 4 control flip-flop CF2 is cleared and CF3 is set to condition data flip-flop B1. This process continues until all the bits are tested, at which time the conversion complete (CC) signal on IC3A comes true.

To have the converter operate continuously, simply wire the CC signal to the conversion start signal.

A complete ADC can be built by adding a DAC and a comparator to the successive approximation register. The DAC shown in Fig. 4 is an eight-bit National DAC 0800LCN, which is wired to use only four bits. Resistor R5 is chosen to be 6k, so that 2 mA of reference current flows into the $V_{ref}(+)$ pin. The selected reference current determines the maximum amount of current that can flow into the $I_0(-)$ pin. Thus, $I_0(-)$ of the DAC varies from 0 mA with a digital input code of $(1111)_2$ to 2 mA with a digital code of $(0000)_2$ placed on pins 5 through 8.

Resistor R4 is then chosen so that the voltage on pin 2, $I_0(-)$, varies from +5 V to -5 V. A 5k resistor will be needed as $2 \text{ mA} \times 5k$ equals the 10 V drop needed across R4. The code produced by the data register could be interpreted as straight binary for unipolar input voltages, or as offset binary for bipolar input voltages. The design in Fig. 4 will accept bipolar voltages of $\pm 5 \text{ V}$. By connecting $\overline{B3}$ instead of B3 to the MSB LED light, the successive approximation register generates two's complement code.

Conclusion

It is easy to see that additional bits could be accommodated by adding more control and data flip-flops with the rest of the circuit remaining the same. Try building this circuit, which is very practical and can convert as fast as the DAC output can settle. You will end up with a good understanding of how a successive approximation register operates. ■





Fig. 5. Timing diagram for successive approximation register.



The successive approximation register. Note the position of the components on the prototype.

Parts List

C1,C2	—100 pF mica
C3	—.001 capacitor
IC1,2,3,7	—74LS74
IC4,5	—74LS76
IC6	—74LS08
IC8	—74LS00
IC9	—74LS123
IC10	—74LS14
IC11	—LM 311
IC12	—National DAC 0800LCN
R1,R2	—20k ohm 1/4 W
R3	—100 ohm 1/4 W
R4,R5	—10k ohm trimpot
R6	—2.2k ohm 1/4 W
SW1	—SPST toggle switch
SW2	—SPDT toggle switch

Videographic

By Joe Martinka

My wife was studying for a college degree in French, and had to write several papers every semester. I had spent a delightful two years with a simple Heathkit terminal hooked up to my home computer, and decided it was time to provide her with one of its most valuable services: text editing and formatting. But first I needed upper/lowercase video display capability, something the old Heathkit terminal did not have.

I was willing to consider the easy

but costly option of buying a video display ready to go. But after scanning the microcomputing magazines, I soon realized that this option would be too expensive. Consider that I included as necessary specifications:

- Programmable special characters. An indispensable feature, since most of her text processing would be in French, and would require special accents and the like.

- Eighty characters per display row, 24 lines on screen, and a versatile 8

by 12 character matrix.

- Compatible with 4 MHz processors.

- Memory-mapped video for ease of screen update and programming.

- Programmable cursor control and reverse video capability.

- Graphics capability. To make the board useful for my own games and display needs, I had to be careful that limited hardware capabilities would not confine my imagination. I wanted good resolution—256 by 256 would do nicely for games, graphs and chart programs.

A reasonably priced commercial video board would satisfy only some of the above specifications. Some were tailored only to a certain processor, some were too slow and some had no graphics at all. I then decided to do what any true-blooded computer lover would do—build one myself. Thus, Videographic was born.

The advantages I gained by designing it were satisfying. I was able to accommodate my S-100 bus running a 4 MHz Z-80 microprocessor. See Photo 1. I could shift the entire mode of the video board from a character-oriented display to a full-graphics mode with a single input-output command. I used a new and exciting programmable video-display-controller integrated circuit, affording excellent versatility: as my needs change, I can change the mode of the display simply by reprogramming the video dis-



Photo 1. Overall view of the author's system. Involves a home-brew system boasting a 4 MHz Z-80A processor, 48K RAM, North Star disk system and the Videographic video interface. The large keyboard to the left houses a one-of-a-kind Selectric interface for hard-copy output. The Selectric typewriter itself is not shown.

Address correspondence to Joe Martinka, c/o Microcomputing.

play chip. Lastly, I made use of a spare Godbout Econoram 8K static memory board that reduced my costs even further.

Videographic's abilities are summarized in Table 1. It is easy to build this board, or one like it, emphasizing your own personal needs. The rest of this article will show you how.

Theory of Operation

As the block diagram in Fig. 1 indicates, Videographic is a relatively simple concept built around the Motorola MC6845 video chip. Originally designed for the 6800 and 6502 microprocessors, the MC6845 can be made to work with the faster Z-80A. The static RAM memory is shared between the 6845 and the host processor. The 6845 uses the memory continually as the source of information for TV screen updates, while the host processor can access the same memory as easily as it can regular memory. Hence the label: memory-mapped video.

While I use the Godbout board, there is plenty of room on the main board for your own memory chips (Photos 2 and 3). By using the popular 2114 static RAM chip, you can implement 8K memory using only one-eighth of the chips you see on the Godbout board. I used the extra

board because I already owned it. You could use existing memory, too. The changes you would have to make to the circuit are negligible. Choose the way that is easiest for you.

The video display chip, the Motorola MC6845, performs all the necessary video timing and refresh functions needed to produce a truly inexpensive high-density display. It can generate timing for almost any alphanumeric screen density, from 40×12 to 80×24 . It is powered by a single ± 5 V supply, offers hardware scrolling by character, line or page, as well as various cursor modes and light pen capability. The 6845 can address up to 16K of memory. (In Videographic, I make use of half that amount.)

The reader should obtain the technical notes on the 6845 from a local Motorola office before using the chip in his own application. A 20-page booklet is available describing the operation and programming considerations of the 6845. The versatility built into the video display processor is explained in detail, and is available from the address listed in Reference 1.

The 12.440 MHz clock provides the basic timing and "dot clock" for the entire display. The 12.440 MHz signal is used to clock the shift register that feeds dots to the video combiner circuit while in the character mode.

(One-half of that rate clocks the dots out in the graphics mode.) This dot clock frequency is divided by eight to provide the character clock, and is the signal that controls the transfer of characters between portions of Videographic.

A programmable 5-V $2K \times 8$ EPROM, the 2716, is used as the character generator. Using this chip, you can literally create your own character set. I created mine using an 8 by 12 grid on which I had placed pennies to form the style I liked, which included descenders and unusual French alphabets. (By squinting at the grid, you can imagine what the letter would look like on the screen.) Fig. 2 shows the dollar sign character being formed. The contents of my EPROM are shown in Listing 1. The characters at the left of the listing are only typewriter references and do not show the actual shape, as the typical character display in Photo 4 does.

You can avoid the hassle of EPROM programming your own custom characters if you can be satisfied with a factory-programmed character set. Unless you can obtain the use of a programmer, it would be significantly more economical to use popular chips such as the 6072 or the MCM66750, which are no more than one-chip ROMs. A 2716 EPROM or a




Fig. 1. Block diagram of the Videographic circuit based around the Motorola MC6845 video display controller.

**If you're looking for
the best prices
in the U.S.A. on**



TRS-80 MICROCOMPUTERS

We have consistently offered the TRS-80 line at **savings up to 20%**. You can save up to \$1500 by buying from Computer Discount of America.

ATARI® MICROCOMPUTERS



We have the full line of ATARI personal computers and systems.

Model II
26-4002 64K, 1 disc **\$3385.00**

Model III
26-1061 4K, Level I **\$ 610.00**
26-1062 16K, Level III **\$ 845.00**
26-1066 48K, Level II 2-drive/RS-232 **\$2115.00**

Color Computer
26-3001 4K **\$ 329.00**
26-3002 16K w/Ext. Basic **\$ 499.00**

EPSON
MX70 Printer **\$ 375.00**
MX80 Printer **\$ 485.00**
MX80FT Printer **\$ 639.00**

Our savings are as big on expansion interfaces, printers, diskettes, Apple Computers, OKIDATA Microliner, C-ITOH Starwriter, Lexicon Modems — everything for your computer.

We have the **largest inventory in the Northeast**, and most models are in stock, for immediate delivery. Our full price catalog or a price quote is as near as your phone.

**CALL TOLL FREE:
800-526-5313**

**Computer
Discount
of America**

COMPUTER DISCOUNT OF AMERICA, INC.
15 Marshall Hill Road, West Milford Mall
West Milford, New Jersey 07480
In New Jersey Call 201-728-8080

factory-programmed ROM will work equally well in the character generator spot with only minor socket-wiring changes.

At a given value of row count, the 6845 will put out the addresses of a series of 80 characters of refresh memory. Then it increments the row count and repeats the series of 80 addresses to the programmed total of 12 times, to paint all rows of the dots on the screen for the whole character line. Then the row count resets to zero and the process is repeated for the next line. You program the 6845 to output the vertical and horizontal sync pulses at any specified moment

in the timing so that the video chip will adapt to nearly any monitor or modified TV. This feature of the 6845 lets you center the display by merely changing one or two software bytes.

Videographic can reverse any character to black-on-white with bit 7—the most significant bit—set to 1. This feature can be used to highlight blocks of text, or create a screen that looks more like words on paper.

The 6845 accesses the shared memory through a multiplexer, which can be thought of as a 13-pole, two-position switch. The position of this switch is such that the memory is normally driven by this 6845 update


Listing 1. A hexadecimal dump of the EPROM character generator that I use in Videographic to produce a customized display in the character mode. The first two digits of the PROM address is conveniently the ASCII equivalent of the character.

VIDEO CHAR	PROM ADDR	Rows of character dots											
		0	1	2	3	4	5	6	7	8	9	10	11
CNTL-A	000	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-B	010	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-C	020	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-D	030	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-E	040	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-F	050	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-G	060	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-H	070	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-I	080	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-J	090	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-K	0A0	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-L	0B0	00	00	00	00	00	00	00	00	00	00	00	00
CNTL-M	0C0	00	00	00	00	00	00	00	00	00	00	00	00
	0D0	00	00	00	00	00	00	00	00	00	00	00	00
a	0E0	10	28	44	1E	22	42	42	46	3A	00	00	00
e	0F0	10	28	44	3C	42	42	7E	40	3E	00	00	00
f	100	10	28	44	30	10	10	10	10	10	00	00	00
o	110	10	28	44	3C	42	42	42	42	3C	00	00	00
u	120	10	28	44	42	42	42	42	42	3E	00	00	00
h	130	00	66	00	1E	22	42	42	46	3A	00	00	00
h	140	00	66	00	3C	42	42	7E	40	3E	00	00	00
i	150	00	66	00	30	10	10	10	10	10	00	00	00
o	160	00	66	00	3C	42	42	42	42	3C	00	00	00
u	170	00	66	00	42	42	42	42	42	3E	00	00	00
c	180	00	00	00	3C	42	40	40	42	3C	10	0C	18
\$	190	3C	24	3C	00	00	00	00	00	00	00	00	00
l	1A0	1C	20	40	20	1C	14	1C	80	40	40	38	00
l	1B0	00	00	00	00	00	00	00	00	00	00	00	00
e	1C0	60	18	04	3C	42	42	7E	40	3E	00	00	00
e	1D0	06	18	20	3C	42	42	7E	40	3E	00	00	00
u	1E0	60	18	04	1E	22	42	42	46	3A	00	00	00
u	1F0	60	18	04	42	42	42	42	42	3E	00	00	00
Space	200	00	00	00	00	00	00	00	00	00	00	00	00
!	210	00	10	10	10	10	10	10	10	10	00	00	00
"	220	28	28	00	00	00	00	00	00	00	00	00	00
#	230	00	28	28	FE	28	FE	28	28	00	00	00	00
\$	240	28	7E	A8	A8	7C	2A	2A	FC	28	00	00	00
%	250	00	42	E4	48	10	24	4E	84	00	00	00	00
&	260	70	88	88	50	20	52	8C	8C	72	00	00	00
'	270	18	08	10	00	00	00	00	00	00	00	00	00
(280	02	04	08	08	08	08	08	04	02	00	00	00
)	290	40	20	10	10	10	10	10	20	40	00	00	00
*	2A0	00	10	54	38	FE	38	54	10	00	00	00	00
+	2B0	00	00	10	10	7C	10	10	00	00	00	00	00
,	2C0	00	00	00	00	00	00	00	00	30	10	20	00
-	2D0	00	00	00	00	7C	00	00	00	00	00	00	00
.	2E0	00	00	00	00	00	00	00	00	30	00	00	00
/	2F0	00	02	04	08	10	20	40	80	00	00	00	00
0	300	38	44	86	8A	92	A2	C2	44	38	00	00	00
1	310	10	30	50	10	10	10	10	10	7C	00	00	00
2	320	7C	82	02	04	18	20	40	80	7E	00	00	00
3	330	7E	04	08	10	3C	02	02	82	7C	00	00	00
4	340	08	18	28	48	FE	08	08	08	08	00	00	00
5	350	FC	80	80	80	FC	02	02	82	7C	00	00	00
6	360	7C	82	80	80	FC	82	82	82	7C	00	00	00
7	370	7E	42	02	04	08	10	10	10	10	00	00	00
8	380	7C	82	82	82	7C	82	82	82	7C	00	00	00
9	390	7C	82	82	82	7E	02	02	82	7C	00	00	00
:	3A0	00	00	00	18	00	00	18	00	00	00	00	00
;	3B0	00	00	00	00	18	00	00	18	08	10	00	00
<	3C0	00	04	08	10	20	10	08	04	00	00	00	00

More

DOWN-TO-EARTH PRICES ON OUT-OF-THIS-WORLD PERSONAL COMPUTERS AND COMPONENTS.

Look at this!



Ohio Scientific Superboard II \$299

- It's the first complete computer system on a board.
- Superboard II uses the ultra powerful 6502 Microprocessor
- 8K Microsoft BASIC-in-ROM
- 4K static RAM on board, expandable to 8K
- Full 53-key keyboard, with upper and lower case. Plus user expandability.
- Video interface and audio cassette interface.

The Ohio Scientific Superboard II at \$299 — in today's economy — has got to be the best buy by far. It will entertain you with spectacular graphics made possible by its ultra high resolution graphics and super fast BASIC. It will help you in school or industry, as an ultra powerful scientific calculator. Advanced scientific functions and a built-in "immediate" mode allow you to solve complex problems without programming.

The Superboard II can be expanded economically, for business uses, or to remotely control your home appliances and security. Even communicate with other computers.

Read what's been written about Superboard II:

"We heartily recommend Superboard II for the beginner who wants to get into microcomputers with a minimum cost. A real computer with full expandability."

—POPULAR ELECTRONICS, MARCH 1979

"The Superboard II is an excellent choice for the personal computer enthusiast on a budget."

—BYTE, MAY 1979

Look at these easy hardware prices:

610 Board For use with Superboard II and Challenger 1P. 8K static RAM. Expandable to 24K or 32K system total. Accepts up to two mini-floppy disk drives. Requires +5V @ 4.5 amps.	\$ 298
Mini-Floppy Disk Drive Includes Ohio Scientific's PICO DOS software and connector cable. Compatible with 610 expander board. Requires +12V @ 1.5 amps and +5V @ 0.7 amps. [Power supply & cabinet not included.]	299
630 Board Contact us for important details.	229
AC-3P 12" combination black and white TV/video monitor.	159
4KP 4K RAM chip set.	79
PS-005 5V 4.5 amp power supply for Superboard II.	45
PS-003 12V power supply for mini-floppies.	45
RF Modulator Battery powered UHF Unit.	35
CS-900B Metal case for single floppy disk drive and power supply. [While stock lasts.]	49
AC-12P Wireless remote control system. Includes control console, two lamp modules and two appliance modules, for use with 630 board.	175
AC-17P Home security system. Includes console, fire detector, window protection devices and door unit for use with 630 board.	249
C1P Sams C1P Service manual	8
C4P Sams C4P Service manual	16
C3 Sams Challenger III manual	40
Ohio Scientific and independent suppliers offer hundreds of programs for the Superboard II, in cassette and mini-floppy form.	

Freight Policies All orders of \$100 or more are shipped freight prepaid. Orders of less than \$100 please add \$4.00 to cover shipping costs. Ohio residents add 5.5% Sales Tax.
Hours: Call Monday thru Friday.
8:00 AM to 5:00 PM E.D.T.
TOLL FREE: 1-800-321-5805

Guaranteed Shipment
Cleveland Consumer Computers & Components guarantees shipment of computer systems within 48 hours upon receipt of your order.
Our failure to ship within 48 hours entitles you to \$35 of software, FREE.

To Order: Or to get our free catalog **CALL 1-800-321-5805 TOLL FREE.** Charge your order to your **VISA** or **MASTER CHARGE** account. Ohio residents call: (216) 464-8047. Or write, including your check or money order, to the address listed below.



**CLEVELAND CONSUMER
COMPUTERS & COMPONENTS**

**P.O. Box 46627
Cleveland, Ohio 44146**

Order Form: CLEVELAND CONSUMER COMPUTERS & COMPONENTS P.O. Box 46627 Cleveland, Ohio 44146

- | | |
|--|---|
| <input type="checkbox"/> Superboard II \$299. | <input type="checkbox"/> RF Modulator \$35. |
| <input type="checkbox"/> 610 Board \$298. | <input type="checkbox"/> AC-3P 12" B/W Monitor \$159. |
| <input type="checkbox"/> Mini-Floppy Disk Drive \$299. | <input type="checkbox"/> C1P Sams Manual \$8. |

[Attach separate sheet for other items.]

NAME _____

ADDRESS: _____

CITY: _____ STATE: _____ ZIP: _____

PHONE: _____

Payment by: VISA _____ MASTER CHARGE _____ MONEY ORDER _____

Credit Card Account # _____

Expires _____ Interbank # [Master Charge] _____

TOTAL CHARGED OR ENCLOSED \$ _____ [Ohio Residents add 6.5% Sales Tax]

Orders of less than \$100, please add \$4.00 to cover shipping costs. Orders will be accepted from U.S. and Canada only. All prices quoted are U.S., date of publication, standard UPS shipping FOB the factory.

K

Listing 1 continued.

```

= 3D0 00 00 00 3C 00 3C 00 00 00 00 00 00 00 00 00 00 00
> 3E0 00 20 10 08 04 08 10 20 00 00 00 00 00 00 00 00 00
? 3F0 3C 42 42 04 08 10 10 00 10 00 00 00 00 00 00 00 00
@ 400 00 3C 42 9A AA AA 9C 40 3C 00 00 00 00 00 00 00 00
A 410 38 44 82 82 FE 82 82 82 82 00 00 00 00 00 00 00 00
B 420 FC 42 42 42 7E 42 42 42 FC 00 00 00 00 00 00 00 00
C 430 3C 82 80 80 80 80 80 80 7C 00 00 00 00 00 00 00 00
D 440 FC 42 42 42 42 42 42 42 FC 00 00 00 00 00 00 00 00
E 450 FE 80 80 80 F8 80 80 80 FE 00 00 00 00 00 00 00 00
F 460 FE 80 80 80 F8 80 80 80 80 00 00 00 00 00 00 00 00
G 470 7C 82 80 80 80 8E 82 82 7E 02 00 00 00 00 00 00 00
H 480 82 82 82 82 FE 82 82 82 82 00 00 00 00 00 00 00 00
I 490 7C 10 10 10 10 10 10 10 7C 00 00 00 00 00 00 00 00
J 4A0 3E 08 08 08 08 08 88 88 70 00 00 00 00 00 00 00 00
K 4B0 82 84 88 90 E0 90 88 84 82 00 00 00 00 00 00 00 00
L 4C0 80 80 80 80 80 80 80 80 FE 00 00 00 00 00 00 00 00
M 4D0 82 C6 AA 92 92 82 82 82 82 00 00 00 00 00 00 00 00
N 4E0 82 C2 A2 92 8A 86 82 82 82 00 00 00 00 00 00 00 00
O 4F0 7C 82 82 82 82 82 82 82 7C 00 00 00 00 00 00 00 00
P 500 FC 82 82 82 FC 80 80 80 80 00 00 00 00 00 00 00 00
Q 510 7C 82 82 82 82 82 8A 8A 8C 04 02 00 00 00 00 00 00
R 520 FC 82 82 82 FC 90 88 84 82 00 00 00 00 00 00 00 00
S 530 7C 82 80 40 38 04 02 82 7C 00 00 00 00 00 00 00 00
T 540 FE 92 10 10 10 10 10 10 10 00 00 00 00 00 00 00 00
U 550 82 82 82 82 82 82 82 82 7E 00 00 00 00 00 00 00 00
V 560 82 82 82 82 82 82 44 28 10 00 00 00 00 00 00 00 00
W 570 82 82 82 92 92 92 92 BA 44 00 00 00 00 00 00 00 00
X 580 82 82 44 28 10 28 44 82 82 00 00 00 00 00 00 00 00
Y 590 82 82 44 28 10 10 10 10 10 00 00 00 00 00 00 00 00
Z 5A0 FE 02 04 08 7C 20 40 80 FE 00 00 00 00 00 00 00 00
[ 5B0 3C 20 20 20 20 20 20 20 3C 00 00 00 00 00 00 00 00
\ 5C0 00 80 40 20 10 08 04 02 00 00 00 00 00 00 00 00
] 5D0 3C 04 04 04 04 04 04 04 3C 00 00 00 00 00 00 00 00
^ 5E0 00 10 38 54 10 10 10 10 10 00 00 00 00 00 00 00 00
_ 5F0 00 00 00 00 00 00 00 00 00 00 FE 00 00 00 00 00 00
a 600 FE 82 92 8A FE 8A 92 82 FE 00 00 00 00 00 00 00 00
b 610 00 00 00 1E 22 42 42 46 3A 00 00 00 00 00 00 00 00
c 620 40 40 40 58 64 42 42 62 5C 00 00 00 00 00 00 00 00
d 630 00 00 00 3C 42 40 40 42 3C 00 00 00 00 00 00 00 00
e 640 02 02 02 1A 26 42 42 46 3A 00 00 00 00 00 00 00 00
f 650 00 00 00 3C 42 42 7E 40 3E 00 00 00 00 00 00 00 00
g 660 0C 12 10 10 38 10 10 10 10 00 00 00 00 00 00 00 00
h 670 00 00 00 1A 26 42 42 46 3 02 42 3C 00 00 00 00 00 00
i 680 40 40 40 58 64 44 44 44 44 00 00 00 00 00 00 00 00
j 690 00 10 00 30 10 10 10 10 10 00 00 00 00 00 00 00 00
k 6A0 00 04 00 04 04 04 04 04 04 04 44 38 00 00 00 00 00
l 6B0 40 40 40 44 48 70 48 44 42 00 00 00 00 00 00 00 00
m 6C0 30 10 10 10 10 10 10 10 10 00 00 00 00 00 00 00 00
n 6D0 00 00 00 A4 DA 92 92 92 92 00 00 00 00 00 00 00 00
o 6E0 00 00 00 5C 62 42 42 42 42 00 00 00 00 00 00 00 00
p 6F0 00 00 00 3C 42 42 42 42 3C 00 00 00 00 00 00 00 00
q 700 00 00 00 58 64 42 42 62 5C 40 40 40 00 00 00 00 00
r 710 00 00 00 1A 26 42 42 46 3A 02 02 02 00 00 00 00 00
s 720 00 00 00 1C 52 60 40 40 40 00 00 00 00 00 00 00 00
t 730 00 00 00 3C 42 30 0C 42 3C 00 00 00 00 00 00 00 00
u 740 00 10 10 7C 10 10 10 12 0C 00 00 00 00 00 00 00 00
v 750 00 00 00 42 42 42 42 42 3E 00 00 00 00 00 00 00 00
w 760 00 00 00 44 44 44 44 28 10 00 00 00 00 00 00 00 00
x 770 00 00 00 82 82 92 92 92 8 00 00 00 00 00 00 00 00
y 780 00 00 00 42 24 18 18 24 42 00 00 00 00 00 00 00 00
z 790 00 00 00 44 44 44 44 4C 34 04 44 38 00 00 00 00 00
[ 7A0 00 00 00 7E 04 08 10 20 7E 00 00 00 00 00 00 00 00
\ 7B0 00 00 00 00 FF 00 00 00 00 00 00 00 00 00 00 00 00
] 7C0 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10
^ 7D0 00 00 00 00 00 00 00 00 00 FF 00 00 00 00 00 00 00
_ 7E0 FF FF FF FF FF FF FF FF FF FF FF FF FF FF FF FF
` 7F0 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00

```

address. When the control logic on the memory board sees that the processor is requesting a valid S-100 bus address, it generates the BDSEL signal. The multiplexer switches the address from the processor to the memory instead of the address normally supplied by the 6845.

The processor can then read or write to that location. The memory output is probably not correct for the display at that moment, so a segment of a different character is substituted for the correct one, producing a snow effect if extensive updates are being performed. The snow can be eliminated by allowing the processor to access the shared memory only when the display is in the blanking cycle




Fig. 3. Formation of a graphics mode character.

ROW	GRAPHIC FONT	BINARY	HEX	EPROM
0		00101000	= 28	THE ASCII CODE FOR
1		01111110	= 7E	\$ IS 24.
2		10101000	= A8	SO, IN EPROM ADDRESS
3		10101000	= A8	0240, PUT 28 (ROW 0)
4		01111110	= 7C	0241, PUT 7E (ROW 1)
5		00101010	= 2A	0242, PUT A8 (ROW 2)
6		00101010	= 2A	ETC. TO ↓
7		11111110	= FC	0449, PUT 00 (ROW 9)
8		00101000	= 28	044A, PUT 00 (ROW 10)
9		00000000	= 00	044B, PUT 00 (ROW 11)
10		00000000	= 00	
11		00000000	= 00	

↑ ALWAYS LEFT BLANK FOR CHARACTER TO CHARACTER SPACING

Fig. 2. Creating a character for your custom character generator. I used pennies to form the shape I wanted, then formed the eight-bit bytes across each row for a total of 12 bytes. The 6845 will call for this pattern row by row until the character is completely formed on the TV screen.

- 80 characters in 24 lines in the character mode. High-resolution 256 by 248 bits in the graphics mode.
- Custom-designed characters available in an 8 by 12 format. Seventh column blanked. User programmable in EPROM.
- Compatible with 4 MHz processors. Memory-mapped video. Requires 8K static RAM. (2K for character mode only.)
- Based on MC6845 Video-Display Generator. Easily programmed to support any screen format. Interfaces to host processor via I/O ports. Produces video signal to a monitor or modified television.
- Supported by high-level graphics subroutines to produce designs efficiently.
- Software driver recognizes:
 - ASCII characters, upper and lowercase
 - Control characters: line feed, carriage return, back space, bell
 - Cursor control codes (with scrolling capability): cursor up, down, right, left and home
- Light pen capability.

Table 1. Summary of the characteristics of the Videographic board.



if He'd used select[™] it wouldn't have taken seven days

Learn SELECT^{*} in just 90 minutes. A whole new word processing software concept that kicks the coded key habit and frees you from complicated instruction manuals. *SELECT* is fast. *SELECT* is logical. With single key mnemonics, you'll use dozens of commands that instantly access the rich capabilities of this system. There's nothing like it.

Simply hit "C" and you'll be ready to Create a document.

Key "I" and you'll be in the Insert mode.

Key "M" and Move entire blocks of text . . . and key dozens more.

That's all there is to it. You'll get all that word processing software promises . . . plus a few surprises.

SELECT with SUPERSPELL.^{*} The only microcomputer software with an integrated spelling dictionary. To proof your text all you do, of course, is to key "S". *SUPERSPELL* with its 10,000 word dictionary scans your text at computer speed then displays and corrects all your typing errors. You can increase *SUPERSPELL*'s word power and customize the dictionary by adding new words, one at a time. Ask to see it today at your local dealer.

SELECT with SUPERSPELL . . . just a little byte more.[™]



✓ 374

SELECT will run on any machine that uses CP/M or MP/M^{**} or its derivatives. It needs 40K of RAM and two disk drives. Special version now available for Radio Shack Mod II^{***} and Apple II^{****}.



^{*} SELECT and SUPERSPELL are trademarks of Select Information Systems Inc.

^{**} CP/M and MP/M are trademarks of Digital Research

^{***} A trademark of Tandy Corp.

^{****} A trademark of Apple Computer Inc.

919 Sir Francis Drake Boulevard • Kentfield, California 94904 • (415) 459-4003



Photos 2 and 3. The front and back views of the Videographic display board and its shared static RAM memory. This dependable board, called the Econoram II from Godbout was the author's first and only RAM memory. Now it easily serves as the memory-mapped video.

during the horizontal or vertical retrace, but I have not included the software in my design. (The blanking signal is available at bit zero on the status input port.)

A status flip-flop determines the current mode, character or graphic. This D-type flip-flop is accessed by a

processor output command. The graphics mode will alter the circuit operation slightly: the dot clock frequency is divided by two, and the character generator EPROM is bypassed by a two-to-one multiplexer. After reprogramming the 6845 for a 64-character by 124-line display

(which happens in milliseconds), you have a high-density graphic display.

As shown in Fig. 3, each dot on the screen matches to a bit in memory. A byte is split in a 4 x 2 matrix. The total screen density is a pleasing 256 dots across by 248 dots down, better than most ready-made microcomputers on



DIABLO 1620 \$1895

- Letter quality daisywheel printer
- Upper and lower case
- Forms tractor, print wheel, ribbon included
- ASCII serial interface with RS-232 cable
- Bidirectional printing
- Completely refurbished by national terminal distributor with 30 day warranty

PRINTERS			VIDEO MONITORS		
NEC 5510	\$2495	9" Sanyo B&W	\$169		
NEC 5530	2495	12" Sanyo B&W	289		
Diablo 630	2425	12" Sanyo w/green screen	299		
Centronics 730	675	13" Sanyo Color	495		
Centronics 737	799	9" Panasonic B&W	169		
		9" RCA B&W	169		

DISKETTES			3M		
5"SS,DD	10/2.40	50/2.35	5"SS,SD	10/2.80	50/2.70
5"DS,DD	10/3.95	50/3.90	8"SS,SD	10/2.90	50/2.80
5"SS,QD	10/2.90	50/2.85	8"SS,DD	10/3.50	50/3.40
8" SS, SD	10/3.05	50/3.00	8" DS, SD	10/4.50	50/4.40
8" SS, DD	10/3.35	50/3.30	8" DS, DD	10/4.50	50/4.40
8" DS, DD	10/4.15	50/4.10	Disk Flip 'N File Case 5"	22.95, 8"	27.95
Diskette Storage Pages 10/4.25			Disk Library Case 5"	2.05, 8"	2.80

3M HEAD CLEANING KIT

- Eliminate downtime
- Eliminate service calls
- Increase life of read-write heads
- Cleans in 30 seconds
- Removes dust, dirt, magnetic oxides

5 1/4" or 8" **\$19.50**

PAPER & LABELS

Greenbar 14 7/8 x 11	one part 3000 sheets	39.95
	two part 1300 sheets	45.95
White 9 1/2 x 11	one part 3500 sheets	29.95
	two part 1400 sheets	33.95
Labels 3 1/2 x 1 1/8	one across box of 5000	17.30
	two across box of 10,000	34.60

PRINT WHEELS			RIBBONS		
Mfr.	ea.	6+	Mfr.	ea.	Doz.
Diablo	8.25	7.50	Diablo	6.50	72.00
Qume	8.25	7.50	Qume	4.00	43.50
NEC	17.00	15.50	NEC	7.00	71.50

Call for quantity prices—Minimum \$1.75 shipping and handling. ✓ 63



DAVIS SYSTEMS INC.
2184 Meadowcliff Drive N.E., Atlanta, GA. 30345
(404) 634-2300








• AP104

comp case

• AP101	Apple II with Single Disk Drive	\$109
• AP102	Apple II with Double Disk Drives	119
• AP103	Apple II, 9 inch Monitor & Double Drives	129
• AP104	Apple ///, two additional Drives & Silentype	139
• AP105	12 inch monitor plus accessories	99
• RS201	TRS-80 Model I, Expansion Unit & Drives	109
• RS202	TRS-80 Monitor or TV set	84
• RS204	TRS-80 Model III	129
• RS205	Radio Shack Color Computer	89
• P401	Paper Tiger 440/445/460	99
• P402	Centronics 730/737 - Line Printer II/IV	89
• P403	Epson MX70 or MX80	89
• CC90	Matching Attaché Case	75

computer case company ✓ 320

5650 INDIAN. MOUND CT. COLUMBUS, OHIO 43213 (614) 868-9464

the market today. Photo 5 shows some sample designs. The software to create those dots is included later in this article, and can be used by both machine-language and higher-level programs.

6845 Interface to the Processor

As you already know, the characteristics of the video display are set by values stored in the 6845's internal registers by an initialization routine run by your processor. Nineteen registers in the 6845 can be accessed by means of the S-100 data bus. These registers and their characteristics are shown in Table 2.

Some of the registers are written only at system reset or character/graphic mode changes to establish display format. Others are updated periodically as part of normal operation (scrolling and cursor functions). Several fine discussions have appeared in *Microcomputing* and other magazines that explain the operation of the 6845 at length (see References).

For your system to access the 6845's





Photo 4. This picture, taken while in the character mode, shows a representative sample of the Video-graphic character set as programmed in the 2716 EPROM. You can change the shape of the characters as you desire, or create your own set. It was surprisingly easy—and fun—to invent the character set.

internal registers, you need to generate certain signals: Chip Select (\overline{CS}), Enable, Register Select (RS) and Read/

Write (R/\overline{W}). Your circuit must create these signals within the 6845 minimum timing specifications. I have

LOBO Add-On Disk Drive Subsystems For Apple, TRS-80, S-100 Based Computers



Expansion and enhanced capabilities are key words in achieving full utilization of your computer system. Our complete line of LOBO disk drive subsystems are the ideal, cost-effective way to provide the expansion capabilities you need to meet your system growth requirements. All of our subsystems are complete, thoroughly-tested, 100% burned-in, and feature a 1 year 100% parts/labor warranty.

APPLE

*Double Density Controller

3101	Minifloppy, \$399	31011 Minifloppy w/interface card \$489
8101CA	One SA800 in cabinet w/power, DDC* Controller, cable and manual \$1449	
8202CA	Two SA800 in cabinet w/power, DDC* Controller, cable and manual \$1889	
5101CA	One SA850 in cabinet w/power, DDC* Controller, cable and manual \$1759	
5202CA	Two SA850 in cabinet w/power, DDC* Controller, cable and manual \$2364	
LCA-22	Double Density Controller only \$599	

S-100 BASED COMPUTERS

MODEL NO.	DESCRIPTION
4101C	SA400 in cabinet w/power \$369
8212C	Two SA801 in cabinet w/power \$1329
5212C	Two SA851 in cabinet w/power \$1799

GENERAL

MODEL NO.	DESCRIPTION
8212C	Two SA801 in cabinet w/power \$1329
5212C	Two SA851 in cabinet w/power \$1799

TRS80

MODEL NO.	DESCRIPTION
4101C	SA400 in cabinet w/power \$369
8101C II	One SA800 in cabinet w/power for Mod. II \$909
8202C II	Two SA800 in cabinet w/power for Mod. II \$1349
LX80	Double-density expansion interface \$641
RS232	Dual Serial Port Option \$75



JR

INVENTORY CO.,
P.O. Box 185, Santa Ynez, Ca., 93460
(805) 688-8781






Photo 5. These are simple geometric designs drawn by Videographic while in the graphics mode. They show the flexibility of this nearly 8K bytes (63,488 bits) display. Software in Listing 2 will plot or unplot dots, as well as draw straight lines between any two points you specify in a calling program.

implemented a satisfactory interface with a 4 MHz bus operation as shown by the waveforms in Fig. 4. Note that the 6845 specifications are met. If your processor is slower than 4 MHz, you may be able to eliminate the wait states and the PRDY signal.

Table 2 shows that the address register is a five-bit write-only register used as an indirect or pointer register. Its contents are the address of one of the other 18 registers on the chip.

When RS is low, the address register itself is addressed. When RS is high, the register file pointed to be the address register is accessed. In other words, to write to any particular register file, two output cycles must occur; one to point to that register file, and the other to read/write data in it.

The RS line is connected to the system address line 0 (the least significant bit), so the two output ports to change a register file will have con-

secutive addresses. (In my design, I/O ports 70H and 71H.) The routines to initialize and maintain these registers are part of the software listing presented here.

I decoded two more addresses so that I could change the Videographic mode from character to graphics and back, as well as input the status of the light pen and blanking signals. All addresses are detailed in Table 3.

TV Monitor and Light Pen

I used the popular Leedex Video 100 as a monitor. It can be purchased from most mail-order outlets from \$129 to \$150. It is a good buy—it offers great bandwidth for the Videographic board and easy operation. If you intend to use an adapted TV receiver, it must have about a 6 MHz bandwidth to work without signal loss.

If you plan to use a TV with severe overscan, as most nonmonitor TV sets are designed to have, use a slightly faster clock rate. A 14 MHz clock will let you program the 6845 with the same page size, but give you more time for vertical and horizontal blanking so that you can correct for TV screen overscan. When changing the dot and character clock frequency, you will have to modify the register file data somewhat to account for the higher clock rate and maintain the same screen update timing.

Implementing the light pen hardware is easy. The +12 V I needed for the circuit came right from the power-on LED board in back of the monitor. The monitor offered a convenient spot to mount the components, and the front panel of the TV had two spots perfect for the miniature phone plug and sensitivity control. The signal is sent to the video board where it is buffered and used by the 6845 and the S-100 bus. Photos 6a and 6b show my version of the light pen components.

6845 RS	Register Number	Register File Name	Program Unit	# of Bits	Read ?	Write ?
0	—	Address Register	—	5	No	Yes
1	R0	Horizontal Total	Char.	8	No	Yes
1	R1	Horizontal Displayed	Char.	8	No	Yes
1	R2	H. Sync Position	Char.	8	No	Yes
1	R3	H. Sync Width	Char.	4	No	Yes
1	R4	Vertical Total	Row	7	No	Yes
1	R5	V. Total Adjust	Scan Ln.	5	No	Yes
1	R6	V. Displayed	Row	7	No	Yes
1	R7	V. Sync Position	Row	7	No	Yes
1	R8	Interlace Mode	—	2	No	Yes
1	R9	Max Scan Length Address	Scan Ln.	5	No	Yes
1	R10	Cursor Start	Scan Ln.	7**	No	Yes
1	R11	Cursor End	Scan Ln.	5	No	Yes
*1	R12	Start Address (H)	—	6	No	Yes
*1	R13	Start Address (L)	—	8	No	Yes
*1	R14	Cursor (H)	—	6	Yes	Yes
*1	R15	Cursor (L)	—	8	Yes	Yes
*1	R16	Light Pen (H)	—	6	Yes	No
*1	R17	Light Pen (L)	—	8	Yes	No

Table 2. The MC6845 internal register descriptions. The values marked by an asterisk may be updated during regular use. The position marked by two asterisks is explained at length in the text.

Input/Output Address	IC40 pin	Input Function	Output Function
60 (xx1000x0)	Y1	Not Used	Change to Graphic Mode
61 (xx1000x1)	Y2	Video Board Status	Change to Character Mode
70 (xx1100x0)	Y5	Not Used	6845 Register Select
71 (xx1100x1)	Y6	6845 Register Read	6845 Register Write

Table 3. Input and output addresses are decoded by IC40, a 74LS138. It is a 3 to 8 decoder. Videographic uses only its $\overline{Y1}$, $\overline{Y2}$, $\overline{Y5}$ and $\overline{Y6}$ outputs. The x's in the address are don't-cares, and are assumed to be {01----0-} in Videographic.

T/Maker II:TM it not only does more than VisiCalc,TM it does it on your computer.

VisiCalc is a fine aid for the computation of numerical problems. But it does have two major limitations: it is available only for a small number of systems, and its use is limited strictly to numbers, not words. To overcome these substantial limitations, Lifeboat Associates introduces T/Maker II.

Unlike VisiCalc, T/Maker II is designed to run on most small business computers with CP/M[®] or similar operating systems and a video terminal with cursor addressing capabilities. And soon there will be T/Maker II versions available for UNIX,TM RT-11TM and other systems.

Works with words as well as numbers. Like VisiCalc, T/Maker II reduces the manual tasks involved in computing and calculating financial documents. But since most business problems and reports involve words as well as numbers, T/Maker II also functions as a full-screen text editor for word processing.

T/Maker II is the most advanced aid for the analysis and presentation of numerical data and text material. In a matter of minutes, an entire document—including all edited text, all figures and all calculations—can be created, reviewed on your screen and reported in printed form.

T/Maker II turns your small business computer into a powerful, sophisticated and convenient tool. A tool that will save you money, time and energy, and eliminate the need for costly time-sharing.

With T/Maker II you can easily perform an unlimited number of analytical and reporting tasks which integrate numerical and text processing. You'll find T/Maker II perfect for such things as:

- Financial Statements
- Statistics
- Profitability Reports
- Revenue and Expense Analyses
- Portfolio Evaluations
- Price Lists
- Rate Structures
- Expense Accounts
- Cash Flow Projections
- Checking Account Reconciliations

...and much, much more.

Easy to learn and use. You don't have to be a programmer to operate T/Maker II. Just follow T/Maker II's easily understood and ordered instructions, set up your data in

As an example of what T/Maker II can do, see the chart below. The operator entered only the data shown in boldface. T/Maker II calculated and reported all the other values.

	1978	— Actual — 1979	1980	Growth Rate	Average	Total (000's)	1981	— Projected — 1982	1985
Item A	42,323	51,891	65,123	24.04	53,112	159.34	80,782	100,206	191,262
Item B	45,671	46,128	49,088	3.67	46,962	140.89	50,891	52,761	58,791
Total	87,994	98,019	114,211	13.93	100,075	300.22	131,673	152,966	250,053
% Item	48.10	52.94	57.02	8.88	52.69	158.1	61.35	65.51	76.49
% Item	51.90	47.06	42.98	-9.00	47.31	141.9	38.65	34.49	23.51
Total	100.00	100.00	100.00	—	100.00	300.0	100.00	100.00	100.00

rows and columns, define the relationships and T/Maker II will do the rest: it will perform the computations and formatting necessary to prepare your document. When you're finished you can analyze your report on your screen or store it on a diskette. Or, you can have the report printed with presentation quality.

And when any changes have to be made, simply enter the new figure or relationship and tell T/Maker II to adjust and recalculate all the new results.

Editing capabilities. As a full-screen editor for word processing, T/Maker II handles text up to 255 characters wide. It includes features like text formatting and justification, centered titles, a text buffer for block moves and repeated inserts, global search and replace commands for printing your letters, reports and documents. Wide documents are supported by horizontal scrolling.

Low cost. The cost of T/Maker II is only \$275 plus shipping and handling. Dollars well spent once you consider all the time, energy and money it can save. T/Maker II is brought to you exclusively and supported completely by Lifeboat Associates, world's largest computer software publisher. For more information send us the coupon below.

Mail coupon to: Lifeboat Associates, 2404
1651 Third Ave., NY, NY 10028. Or call (212) 860-0300.

☐ Please send me more information on T/Maker II.

☐ Please send me a free Lifeboat Catalog featuring over 200 programs, including integrated accounting and professional practice systems, office tools for bookkeepers and secretaries and sophisticated tools for programmers.

Name _____

Title _____


Company _____

Street _____

City _____

State _____ Zip _____

T/Maker II is a trademark of P. Roizen. Personal Software, Inc. UNIX is a trademark of Bell Laboratories. RT-11 is a trademark of Digital Equipment Corp. VisiCalc is a trademark of Digital Research, Inc.



LIFEBOAT WORLDWIDE offers you the world's largest library of software. Contact your nearest dealer or Lifeboat:

Lifeboat Associates
1651 Third Ave.
New York, N.Y. 10028
Tel: (212) 860-0300
Telex: 640693 (LBSOFT NYK)
TWX: 710-581-2524

Lifeboat Inc.
OK Bldg. 5F
1-2-8, Shiba-Daimon
Minato-ku, Tokyo, 105 Japan
Tel: 03-437-3901
Telex: 2422723 (ASRTYOJ)

Lifeboat Associates, Ltd.
PO Box 125
London WC2H 9LU, England
Tel: 01-836-9028
Telex: 893709 (LBSOFTG)

Lifeboat Associates GmbH
PO Box 168, Aegerstrasse 35
CH 6340 Baar, Switzerland
Tel: 042-31-2931
Telex: 865265 (MICO CH)

Intersoft GmbH
Schlossgartenweg 5
D-8045 Ismaning, W. Germany
Tel: 089-966-444
Telex: 5213643 (ISOFD)

Lifeboat Associates, SARL
10, Grande Rue Charles de Gaulle
92600 Asnieres, France
Tel: 1-733-08-04
Telex: 250303 (PUBLIC X PARIS)

Lifeboat Associates ✓59
Software with full support

You can construct your own light pen with an old pen cartridge and phototransistor. However, I elected to buy a light pen for \$20 from 3-G Company, Inc., Dept. KB, Route 3 Box 28A, Gaston, OR 97119. As it sees the electron beam when held close to the screen, the high signal at LPSTB on the 6845 will latch the current address of the character in file




Photo 6a. The front panel of the Leedex Video 100 modified for light pen use.




Photo 6b. The transistor interface that I designed to support the light pen feature fits easily on a small breadboard layout. One night's construction was all that was necessary to assemble it and mount it as you see in this picture. The +12 V I needed for the circuit was conveniently available from the power-on LED board nearby.

registers R16 and R17. The processor can then access these two registers to determine the location to which you

are pointing the light pen. The necessary software, although not exactly trivial, is straightforward and will not




Fig. 4. The processor interface waveforms. The circuitry was designed to avoid exceeding any of the 6845 timing specs. All specs are minimums and are shown in parentheses.





Fig. 5. These are the waveforms associated with the creation of a video character. SIG-A is derived so that the dot clock timing will have proper phase relationship to the SHIFT/LOAD signal when a reset pulse occurs.

MEMOREX

**SUPERB QUALITY AT
UNBEATABLE PRICES.
THAT'S MEMOREX
DISCS FROM PACIFIC
EXCHANGES**




**For Data Reliability—
Memorex
Flexible
Discs**

CALL FREE FOR PRICES & INFORMATION

(800)235-4137

In California (800) 592-5935 or (805) 543-1037



**PACIFIC
EXCHANGES** ✓172
100 Foothill Blvd.
San Luis Obispo, CA
93401

DEALER INQUIRIES INVITED



C.O.D.'s ACCEPTED

— Professional —
Real Estate Software
For Apple or TRS-80

Property Management System
(32K, 1 Disk Systems)

Features:

- Tenant Information
- Late Rent Reports
- YTD & Monthly Income
- Handles —
- Partial Payments
- Returned Checks
- Advance Payments
- Prints Receipts
- 5 Digit Expense Accounts
- Building Expense Report
- Vendor Expense Report
- Income Tax Report
- All Reports Can Be Printed
- Complete Documentation
- Easy Data Entry & Edit
- 200 Units per File

Price \$225.00

Real Estate Analysis Modules:
(Cassette or Disk)

- 1) Home Purchase Analysis
- 2) Tax Deferred Exchange
- 3) Construction Cost/Profit
- 4) Income Property Cashflow
- 5) APR Loan Analysis
- 6) Property Sales Analysis
- 7) Loan Amortization

\$35 Per Module



At Computer Stores Everywhere
Or Order COD Direct
(Cal Residents Add 6% Sales Tax)
(213) 372-9419

Dept. K 1116 F Eighth St. Manhattan Beach, CA 90266

CHEAP CHIPS . . . ARE NO BARGAIN
BUYING ADD-ON MEMORY?
GET THE BEST!!!

Memory failures cost you time and money. Japanese 16K RAM chips have a one-to-ten in-service failure ratio to U.S. chips—from a study by R. Anderson, Computer Div., Hewlett-Packard, reported in *The Economist*, 4-26-80.

We offer 4116 chips by Fujitsu, NEC, Hitachi, Toshiba and Mitsubishi . . . for most popular computers and expansion memory boards, including:

*Apple *All TRS-80's *New Pat *Heath H-89
*Superbrain *Expandoram *Many Others

4116 DYNAMIC RAMS THE BEST
200nsec Plastic \$27.70, Ceramic \$37.95
150nsec Plastic \$31.95, Ceramic \$41.95

STATIC RAMS
2114 450nsec \$3.30, 300nsec \$3.90; 2101 \$2.90.
EPROMS (450 nsec std; ask for hi-speed if required)
2708 \$4.80; 2716 5V+12V \$9.40; 2716 5V \$9.70;
2732 \$18.90.

We'll beat any legitimate price for comparable chips. Hi-volume users, dealers, or clubs, ask for quantity discounts. SHIPPING: to \$25, \$2; to \$50, \$1; over \$50, FREE. COD: +\$1.40.

DISCOUNTS ON TOTAL: over \$100, 5%; over \$200, 10%.

MINIS & MICROS INC. • 29486 Trailway
Agoura, CA. 91301 • (213) 342-4535
CA. residents add 6% sales tax ✓391

2 YEAR WARRANTY ★ CALL US ANYTIME

THE GREEN SCREEN THING

(The Green Thing is a custom design to fit your TRS-80. It mounts in seconds without any tools.)



AVAILABLE: For models I, II, and III as well as any standard 12 inch monitor.

List \$795

(Add \$1.00 for shipping & handling, and California residents add 6% sales tax.)

FEATURES:

- Improved image contrast
- Reduces eye fatigue
- Enhances screen legibility
- Decreases glare
- Gives system a professional look

ORDER NOW

24 HOUR

PH 408-946-1265



AVS

AUDIO - VIDEO
SYSTEMS ✓192

2485 Autumnvale Dr. San Jose, CA. 95132

be discussed further.

The Two-Character Delay

The sequence of character operations is as follows:

The 6845 presents a character address for the screen update to the memory. The memory after a set-up delay presents the character to the latch, IC34. The character in IC34 is then presented to the character generator, IC37, or to the graphics multiplexer, IC33, depending on the mode selection. The dots for the specified scan row of the character are then presented to the shift register, IC38,

and shifted out at the dot clock rate to produce the video signal. Fig. 5 shows the timing of this sequence for the character and the graphic modes.

Because of the set-up time delays in the memory, two characters are actually being processed at any one time—one character being accessed from the shared memory, and one character being output by the character generator or graphic multiplexer to the shift register. (Actually, the second character is one row of dots, not the whole character.) Thus, the two 6845 signals, cursor and display enable, must be delayed two character inter-




Fig. 6. The simple changes made to the 8K static RAM board. The intercepted signals were routed to the Videographic board over the ribbon cable.

vals by IC44 to accommodate this delay effect.

Cursor Generation

The cursor signal is true whenever the 6845 output address matches the internal value in the cursor address register pair (R14 and R15). This signal is processed in such a way with bit 7 of the incoming character byte (the bit that determines the black-on-

white status of the video) so that the 6845 cursor signal will always cause a reversal of the character.

The cursor can be programmed to underline, reverse the entire character, slow blink, fast blink or stay on steady. Registers R10 and R11 control the format of the cursor, and R14 and R15 control its position. The low-order five bits of R10 (bits 0 through 4) specify the scan row on which the





Fig. 7. The complete schematic for Videographic.



THE FASTEST, MOST POWERFUL HIGH-LEVEL LANGUAGE SYSTEM FOR THE APPLE

- * Runs six to sixty times faster than Basic
- * Programming capabilities well beyond Applesoft
- * Auxiliary Processor [AM9511] for fast Floating Point
- * High-speed, extended high resolution graphics
- * Software development time cut in half
- * Exceptionally compact, compiled code
- * Extensible, structured language to meet your needs
- * Requires 48K Apple II or II+, single Disk

Developed from an extended version of FORTH, microSPEED combines the benefits of compiled code and hardware arithmetic processing for maximum microcomputing performance

COMPLETE SYSTEM \$495.00
USER'S MANUAL ONLY 35.00


INFORMATION HOT LINE (301) 627-6650

applied analytics incorporated

5406 Roblee Dr. Upper Marlboro, Md. 20870

SUPERBRAIN

By INTERTEC



64K Double or Quad Density units available. Uses two Z-80 CPU's. Commercial-type terminal with 12" monitor. Dual double density minifloppies. Over 350 kilobytes of storage (twice that with quad density drives). Two serial RS232 ports, I/O ports standard. Expandable with optional S-100 interface. Comes with CP/MTM 2.2 operating system. MiniMicroMart can supply a wide range of CP/M development and application software.


w/64K Double Density, List \$3495 . . . \$2869
w/64K Quad Density, List \$3995. . . . \$3395



**hp HEWLETT
PACKARD HP-41CV**
\$259.
AVAILABLE NOW!



data systems
Z19 Video Terminal




**Limited
Time
\$799**

List \$995



**HEWLETT
PACKARD HP-85A**



**Desk-Top
Computer
List
\$3250
\$2749**

**HP-83
\$1895**

List \$2250

F.O.B. shipping point. All prices subject to change and all offers subject to withdrawal without notice. Advertised prices are for prepaid orders. Credit card and C.O.D. 2% higher. C.O.D. may require deposit.

— WRITE FOR FREE CATALOG — 304

MiniMicroMart

1618 James Street
Syracuse, NY 13203 (315) 422-4467

cursor is to start; the R11 specifies the scan row on which the cursor is to end. If R10 bits 0 through 4 are all equal to 0, and R11 is 11, the cursor will occupy lines 0 through 12, or the entire character. The character is reversed. If the value of 10 is stored in R10 bits 0 through 4, the cursor becomes a two-line underscore. This is what I prefer.

Bits 5 and 6 of R10 determine cursor blinking. If bit 5 is on and bit 6 is off, the cursor is not displayed at all. You can use this to blank the cursor for graphic display or other uses. If bit 6 is on, the cursor will blink. If bit 5 is off, the blink rate is about four

times a second. If bit 5 is on, the blink rate is two times per second.

The Memory Board

Fortunately, all the devices I needed to make Godbout's 8K Static Econoram II share memory with the Videographic could come on unused components right from the board. Fig. 6 shows the components I changed to interrupt the data and address signals, and produce the BDSEL and BDSEL for the video board to use. Since the 21L02 chips are arranged in 1K rows, the Godbout board decodes the addresses into eight row-enable signals. I cut those traces and routed




Fig. 7b.

those signals over the ribbon cable to IC30 and IC31.

These chips also get eight decoded row-enable signals from the 6845 address lines MA11, MA12 and MA13. Normally, 6845 row-enable signals get through until the Econoram is accessed by the processor. At that time, BDSEL goes low, and the Econoram row-enable signals are routed through IC30 and IC31 back through the ribbon cable to the memory chip-enable lines on the proper row.

To get the memory output, I merely tapped the data-out bus on the Econoram, and routed it over the ribbon ca-

ble to IC34, the eight-bit latch.

If you desire to use 2114 static RAMs on the Videographic board, you will have the advantage of lower power requirements and fewer memory chips, 16 instead of 64. (You also have the option to wire up only 2K as memory, but be aware that you will then have no graphics capability. However, a whole video display of characters with the minimum of two 2114s will be available to you. At \$6 apiece, low memory costs.)

Construction

Fig. 7 provides the complete sche-

matics for Videographic. As I noted in the block diagram, the 6845 is the central chip of the circuit. Photo 7 shows my prototype, and there is enough room left over for on-board memory, or expansion to a keyboard input interface. I used the excellent 8804 breadboard from Vector Electronics Company (12460 Gladstone Ave., Sylmar, CA 91342). The chips are labeled starting at IC30, merely because other hobby boards in my computer have already used the first 29 labels.

Wire-wrapping is the only means for a hobbyist to connect this system together. I used the Just Wrap tool (from OK Machine and Tool Corp., 3455 Conner St., Bronx, NY 10475) for point-to-point wire-wrapping; it is far superior to other alternatives when wire-wrapping on a large scale. Watch out though—no matter how much experience you've had, a small percentage of wrappings will always turn out bad. So double-checking with a circuit tester after wrapping is an absolute necessity.

Photo 8 shows the reverse side of the Videographic board. Note that the wires appear neat and taut.

This brings us to the actual construction. There is plenty of good advice in the magazines these days on how to construct an electronic project. (Don Lancaster's *TTL Cookbook* has a good set of tips.) I want to pass along some heartfelt rules that I have




Fig. 7c.

IC	Type	Pins
30	74LS157	16
31	74LS157	16
33	74LS157	16
34	74LS273	20
35	74S04	14
36	74LS241	20
37	2516 EPROM	24
38	74LS166	16
39	6845	40
40	74LS138	16
41	74LS74	14
42	74LS74	14
43	74LS93	14
44	74LS175	16
45	81LS97	20
46	74LS125	14
47	74LS74	14
48	74S86	14
50	47S11	14
51	74S05	14
52	81LS98	20
53	81LS97	20
54	74LS138	16
55	74LS09	14
56	74LS00	14

Fig. 7d. IC listing.




Photo 7. The complete Videographic video board is shown in this close-up component view. Note that there are plenty of despiking capacitors, and that there is enough room left on this prototype for onboard static memory if desired. The numbers on the chips correspond to the IC numbers used throughout this article.




Photo 8. The bottom, or wire-wrapped, side of the video terminal board. Neatness counts, and saves you hours of troubleshooting later. The video cable plugs into a socket that is exposed to the board. All high-frequency wire runs are kept as short as possible.

learned the hard way.

- Capacitors, capacitors, capacitors! Use plenty of them. I try to get almost one .1 uF disk capacitor per TTL chip. Keep the leads as short as possible. Put a 10 uF tantalum at the output of the regulator, and a 1 uF tantalum at the end of each chip row. Watch those polarities! This practice is especially important at the clock speeds in Videographic.

- It is impossible to avoid errors in wire-wrapping, so Xerox a copy of your schematic. Make the connection. Test it. Then mark it off with a colored pencil on the schematic. Sound easy? It is, if you want to avoid hours of headaches later. You'll be surprised at the number of connections you will do over. When the board is complete, test each line again and mark it off on the schematic. It saves hours.

- Use epoxy to cement the sockets to the board. Keep the fastest chips close together, and the 12 to 14 MHz wire runs as short as possible. Line up all the chips in one direction so that the 1 pins are always in the same corner. Make no exceptions.

- Wire all ground wires first, then all +5 V supply lines. Use many colors of wire to help later troubleshooting or modifications.

- Don't have wires too loose. Keep them close to the board, thereby close to the ground plane. Do all soldering before starting to wire-wrap.

- Power up the board before plugging in any chips to check the supply regulator performance. It makes sense to smoke-test the regulator first so one doesn't risk all the IC chips.

- This is the last bit of advice, and it is the hardest to live by. Document whatever wiring changes you make

on your schematic. Do not ever leave your project for the day without writing your changes down neatly.

If you have been meticulous, Videographic will start to work the first time you plug it in. (Remember, the 6845 will have to be programmed before it operates the way you want it to.)

Troubleshooting a system without good tools is almost impossible. Although a limited test circuit is built in (the actual display), you may have to use an oscilloscope to test further. Logic testers will help you to hunt down small problems. Use the waveforms in Fig. 5 to track the signals from the crystal oscillator to the various clocks. If those check out, verify proper operation of the memory (write and read to it), and the interface to the 6845 (run little software output loops while checking 6845 control signals). Kick yourself if you find that the bug turns out to be a wire-wrap error. You were warned. Photo 9 shows some of the growing pains while Videographic was being debugged.

Software Driver

Table 4 lists the available control codes to operate the driver. The Videographic software driver is contained in Listing 2. I have used my own assembler to create the listing, but most of the conventions found in commercial assemblers are present. The program is written in Z-80 object code starting at 1030 hex. It has four sections:

1. Routines for character loading and cursor control.
2. Subroutines for section 1 and




Fig. 8. The Motorola MC6845 pin-out. A prospective user of this chip should obtain a copy of its technical specs. See the article for details.

AUTOMATED EQUIPMENT INCORPORATED



18430 Ward, Fountain Valley, CA 92708

Call Toll-Free for latest low prices!

1-800-854-7635 Outside CA

714-963-1414 Inside CA

1-714-963-1414 Outside Cont. USA

Prices change daily to meet competition.



TERMINALS


TELEVIDEO 912 B.....	CALL
TELEVIDEO 912 C.....	CALL
TELEVIDEO 920 B.....	CALL
TELEVIDEO 920 C.....	CALL
SOROC IQ-120.....	675
ZENITH A-19.....	750
HAZELTINE 1500.....	995
TELEVIDEO 950.....	CALL



NORTHSTAR

HRZ-1D-32K.....	CALL
HRZ-2D-32K.....	CALL
HRZ-1Q-32K.....	CALL
HRZ-2Q-32K.....	CALL
ADDITIONAL 16K RAM.....	CALL
ADDITIONAL 32K RAM.....	CALL
HARD DISK SYSTEM.....	CALL

SPECIAL MEMORY CONFIGURATIONS
AVAILABLE, INCLUDING SYSTEMS GROUP.



PRINTERS

NEC 5510 (TRACT., RIB., THIM).....	2600
NEC 5515 (TRACT., RIB., THIM).....	2600
NEC 5520 (TRACT., RIB., THIM).....	2900
NEC 5530 (TRACT., RIB., THIM).....	2540
TI-810.....	1495
TI-820.....	1625
EPSON MX 80.....	CALL
EPSON MX 70.....	CALL
EPSON MX 100.....	CALL
ANADIX DP-9500/9501.....	CALL

VIP's customarily need top quality and service within stringent budgetary limits. naturally, they call A.E.I.

Item: A.E.I. tests virtually every* item sold, before shipping.


Item: A.E.I. initializes every piece of software, and makes a copy. If you have a problem, A.E.I. can check to locate the problem by using the in-house duplicate, saving you time.

Item: A.E.I. has in-house expertise on every item offered.

Item: A.E.I. prices are competitive with the lowest, no-service, no in-house expertise dealer.

40% OF ALL A.E.I. SALES ARE TO PUBLIC AND SEMI-PUBLIC INSTITUTIONS.

A partial list** of A.E.I. customers who purchased during the last quarter of 1980 includes: University of Nebraska, Univer-



sity of Virginia, U.S. Dept. of Interior, University of Kentucky, University of California, Massachusetts Institute of Technology, U.S. Air Force, Naval Air Development Center, Brown University, University of Oregon, University of Utah, Ohio State University, University of Southern California, California State Dept. of Water Resources, University of Michigan, and Princeton University.


In the private sector, an equal number of major national organizations purchased during the same period.

You can call A.E.I. too!

*With our normal fast shipping, we have time to test; expedited shipment may preclude testing.

**A.E.I. does not wish to imply that any of these fine organizations endorse A.E.I., merely that A.E.I. is proud to have them as customers.

VIP's Call A.E.I.



S.S.M.	KIT	ASM
CB2 Z80 CPU	\$200	\$265
VB1C VIDEO	140	190
VB2 VIDEO	155	210
VB3 VIDEO	375	440
IO4 INTERFACE	165	225
SB1 SYNTHESIZER	195	270

MEASUREMENT SYSTEMS MEMORY

DM3200 32K 4MHZ	480
DM6400 64K 4MHZ	595
DMB3200 32K 4MHZ BANK SELECT ..	630
DMB6400 64K 4MHZ BANK SELECT ..	745

**DYNABYTE SYSTEMS ALSO
AVAILABLE—CALL FOR THE
EXCITING NEWS ABOUT NEW
COMPETITIVE PRICING!**

**WE WILL TRY TO BEAT ANY
ADVERTISED PRICE.**


TERMS: All prices listed are cash discounted and subject to change. COD's are 2% additional. Universities and well-rated firms Net-10.

SHIPPING: ADDITIONAL IN ALL CASES.

TECHNICAL ASSISTANCE:
WE TRY TO HELP INTERFACE AND
TROUBLESHOOT—CALL (714) 963-1414.

Open Monday-Friday, 8:00 a.m.-5:00 p.m.

Dealer Inquiries Invited.



MORROW

DECISION 1 BASIC.....	\$1550
DISCUS-1 2 DRIVE	1550
DISCUS 2D 1 DRIVE	935
DISCUS 2D 2 DRIVE	1550
DISCUS 2+2 1 DRIVE	1250
DISCUS 2+2 2 DRIVE	2190
DISC JOCKEY 2D	350
DISCUS M26 HARD DISC	3925
ADDITIONAL HARD DISC	3685
DISCUS M10	2990

MISCELLANEOUS

NEC THIMBLES.....	\$16
NEC RIBBONS	7
RS232C CABLE 5'	20
RS 232 CABLE 10'	25
LEDEX MONITOR	145
NOVATION CAT	145

SOFTWARE

WORDSTAR	\$330
MAILMERGE	100
DATASAR	250
N.S. PASCAL	160
MAGIC WAND	290
C BASIC	100

GRAHAM-DORIAN

JOB COSTING	\$700
INVENTORY	475
CASH REG.	475
APARTMENT	475
MEDICAL	700

ADDITIONAL SOFTWARE DISCOUNTS WITH SYSTEM PURCHASE

DISCS—BOX OF 10

VERBATUM 5 1/4 1 SIDE	\$27
VERBATUM 5 1/4 2 SIDE	45
VERBATUM 8 1 SIDE	35
VERBATUM 8 2 SIDE	55
OTHERS	CALL
PLASTIC STORAGE BOXES	3

OUR SYSTEMS WORK!

All systems normally tested and configured in our repair facility before delivery. Service contracts available. Prompt repairs and warranties.




Photo 9. Troubleshooting a new circuit can be half the fun of construction. Here, the video logic is going through some growing pains.

outside program use.

3. Initialization routines for the character and graphics modes.

4. Routines for drawing and undrawing dots in the graphics mode. An algorithm to draw lines between

any two points on the screen is included to speed up the larger routines to improve overall speed.

A buffer area of 15 bytes must be set aside for the Videographic in a memory area. (I use BFF0 to BFFF.) I designed the software so only two bytes need to be altered to relocate this buffer area. That is why I make such extensive use of the IX register throughout the subroutines.

Actual memory displayed in the character mode is 80×24 characters, or 1920 bytes. The starting point in the 8K RAM could be anywhere, depending on the contents of the 6845 register files R12 and R13. Changing these two registers will scroll the screen for the user.

When in the 256×248 graphics mode, memory displayed is much more—64 times 124, or 7936 bytes. That is 63,488 bits of memory used, or 63,488 potential dots on the screen. R12 and R13 register files will stay at zero at all times in the graphics mode.

Scrolling

Scrolling is the management of a video display. The 6845 can scroll by



Mayday!

THE UNINTERRUPTIBLE POWER SUPPLY

... that keeps your computer on
when the power fails ...

Mayday protects the computer and disk system from power surges, sudden drops in voltage, or a complete disruption of power.

Most problems operators or programmers have are caused by voltage or current interruptions of the computer. There are 12 different Mayday UPS power supplies, one of which is specifically designed to handle your computer system from 50 watts up to over 600 watts.

Protect your time and investment. One power failure could well cost you the price of the Mayday. Prices start at \$240 for the 150 watt system. (Line surge voltage regulator protection is available at additional cost).

For more information, please call or write.

from...

244




Sun Research, Inc.

Box 210 New Durham, NH 03855
(603) 859-7110 TWX 510-297-4444

THE NEW LAREDO LS525. WHEN YOU'RE READY TO GET DOWN TO BUSINESS.

Laredo Systems, Inc. introduces the LS525 five megabyte rigid disk memory system for TRS80 Models I and III. Laredo's LS525 rounds up a Seagate ST506 Drive, LDOS Operating System by Logical Systems, and Laredo's own LSI

- On-board data separator, micro-code diagnostics and write-precompensation.
- Increased disk media reliability and data integrity with automatic defect block allocation and extended ID fields.
- Versatile CPU compatibility provided by separate host adaptor.



Introductory Offer To TRS80 Users.

Now through October 1, 1981 buy the LS525 for the OEM/dealer price of \$2990, a savings of \$760 off the usual suggested retail price of \$3750.


LDOS Operating System with manual and diskette available for \$149.

500 Series Controller into a single-board controller that emulates the famed IBM 3370 disk system, complete with:

- Improved read/write/seek access time through full block buffering and variably tuned interleave.

For more information about the LS525 Memory System and the LSI 500 Series Controller, contact:

Laredo Systems, Inc.
669 Giraudo Drive, San Jose, CA 95111
(408) 629-2283



laredo systems inc.

✓394

character, line or by page simply by starting its update cycle on a different memory address. The software presented here scrolls line by line. The

ASCII Code	Name	Function
07	Cntl-G	Rings the terminal bell.
08	Cntl-H	Backspace. (Cursor Left)
09	Cntl-I	Cursor up.
0A	Cntl-J	Line feed. (Cursor Down)
0B	Cntl-K	Cursor forward.
0C	Cntl-L	Cursor home (upper left corner).
0D	Cntl-M	Carriage return.

Table 4. Software driver commands.

Register	Function of Register	Characters 80 x 24	Graphics 256 x 248
R0	horizontal total	102 (66)	102 (66)
R1	horizontal columns displayed	80 (50)	64 (40)
R2	horizontal sync position	86 (56)	78 (4E)
R3	horizontal sync width	12 (0C)	9 (09)
R4	vertical total	24 (18)	127 (7F)
R5	vertical total adjustment	19 (13)	25 (19)
R6	vertical rows displayed	24 (18)	127 (7F)
R7	vertical sync position	24 (18)	125 (7D)
R8	interlace mode	0 (0)	0 (0)
R9	maximum scan line	11 (0B)	1 (01)
R10	cursor start	73 (49)	0 (0)
R11	cursor end	11 (0B)	0 (0)
R12 through R17	cursor and RAM start	0 (0)	0 (0)

Table 5. Appropriate MC6845 values to be stored in the internal registers for the character and graphics display formats. The values given are for a 12.440 MHz crystal dot clock. The decimal value is given, followed by the hexadecimal equivalent in parentheses. If you need a faster clock, some of these registers have to have different values. (For example: 14.138 MHz crystal, R0 must be set to 70 hex, R2 must be set to 5A hex character mode and 52 hex for graphics mode.)

principle is simply that new data is entered on the bottom line of the display. When the bottom line is full, the entire display is moved up one line. In the process, the top line, containing the oldest data, is scrolled off the screen. The display can be scrolled down as well as up, and the TV screen acts as a movable window. The driver program changes the update start address of the 6845 in increments of 80 (for the 80-character line width).

When the scrolling process completes several video pages and comes to the end of the memory-mapped 8K, a wrap-around occurs—the address 8192 is equivalent (at least from the point of view of the 6845) to the address 0. Thus, the wrap-around occurs automatically, even if it occurs in the middle of the screen.

Note, however, that the 6845 can address up to a full 16K of memory. I use only 13 bits of the 14-bit address. I leave the most significant bit of the 6845 address disconnected. But the cursor address register, light pen address register and the update address register are 14-bit registers. All 14 bits must match a displayed video character to expect proper operation. This fact, when overlooked, can cause problems when you are writing your own driver routines. Be especially wary when wrap-arounds occur in the middle of a page.

Conclusion

I hope Videographic will interest you as much as it did me. It is a complete video system, and will keep you busy for months with its many possibilities. ■

References

1. Motorola Advance Information Notes AD1-465, "MC6845 CRT Controller (CRTC)," Motorola Semiconductors, 3501 Ed Bluestein Blvd., Austin, TX 78721.
2. Hass, Bob, "Single Chip Video Controller," *Byte*, May 1979.
3. Beetem, John, "Vector Graphics for Raster Displays," *Byte*, October 1980.
4. Lancaster, D., *TV Typewriter Cookbook*, Indianapolis, IN: Howard W. Sams & Co., 1976.
5. Wierenga, Theron, "Construction of a Fourth-Generation Video Terminal," *Byte*, August 1980.
6. Knutson, Jeff, "A Video Graphics Primer," *Microcomputing*, November 1980.

Listing 2. The Videographic software driver. (Listing continues on page 163.)

```

0000      1 ORIG 0
0000    100 ;*****
0000    110 ;*** VIDEOGRAPHIC DRIVER SOFTWARE *****
0000    120 ;*****
0000    130 ;*** WRITTEN BY J.J. MARTINKA *****
0000    140 ;*** OCTOBER, 1980 *****
0000    150 ;*****
0000    160 ;
0000    170 ;THIS DRIVER FACILITATES THE USE OF THE VIDEO-
0000    180 ;GRAPHIC BOARD AS A CONSOLE DISPLAY DEVICE.
0000    190 ;IT IS PRESENTED AS FOUR SECTIONS:
0000    200 ; 1) THE ROUTINES CALLED FOR CHARACTER LOADING
0000    210 ; AND CURSOR CONTROL
0000    220 ; 2) SUB-ROUTINES USED BY SECTION 1) AND ARE
0000    230 ; ACCESSIBLE FOR OUTSIDE PROGRAM USE BY
0000    235 ; TEXT EDITORS OR OTHER PROGRAMS
0000    240 ; 3) THE INITIALIZATION ROUTINE NEEDED PRIOR TO
0000    250 ; 6845 VIDEO CHIP OPERATIONS
0000    260 ; 4) SHORT GRAPHICS ROUTINES
0000    270 ;
0000    280 ; NOTE: THIS PRESENTATION IS ASSEMBLED BY A HOME
0000    290 ; BREW ASSEMBLER, AND ITS OUTPUT IS FREE FORMAT.
0000    300 ; THE ONLY REAL DIFFERENCES FROM COMMERCIAL
0000    305 ; ASSEMBLERS ARE:
0000    310 ; -LABELS ARE ASSIGNED WITH THE COLON IN FRONT
0000    320 ; INSTEAD OF BEHIND. I.E. 20 :ECHO NOP
0000    330 ; -JP, JR, AND CALL INSTRUCTIONS THAT HAVE
0000    340 ; CONDITIONS ARE PRECEDED BY A PERIOD.
0000    350 ; I.E. CALL .NZ,ADDRESS JR .C,ADDRESS
0000    360 ;
0000    370 ;

```

More →

MICROPROCESSOR SUPPORT I.C.'S

WE GUARANTEE FACTORY PRIME PARTS

We are going to become the largest supplier of prime microprocessor support I.C.'S. We guarantee that our I.C.'S are purchased from manufacturer authorized distributors. This is the only way to deliver prime parts at the lowest possible prices. Our commitment is to offer the best price and the fastest delivery to our customer. We give many thanks to our valued customers who have helped us grow.

NEC 16Kx1 DYNAMIC RAM 200 N.S.

These are prime 4116's from one of the best MOS RAM manufacturers in the world.

4116 200ns
8 for \$25.00 32 for 96.00

8080A	CPU	4.95	2708	EPROM 1Kx8	4.50
8085A	CPU	8.95	2716	EPROM 2Kx8	7.00
8086	CPU	99.95	2732	EPROM 4Kx8	19.00
8088	CPU	44.95	4118	STATIC 1Kx8	15.00
Z-80	CPU	6.70	4164	200ns 64Kx1 Call	
Z-80A	CPU	7.25	Z80B	CPU	21.00

NEC 1Kx4 STATIC RAM 250 N.S.

These are prime low power static ram's NEC for the finest in MOS MEMORY.





2114L 250ns
8 for \$25.00 32 for \$96.00

Z80-P10	6.00	8755	49.95	4050	.69	4531	.99	74C925	6.95	74LS107	.45	74LS244	1.95
Z80A-P10	7.10	4000	.35	4051	1.10	4532	1.25	74LS00	.35	74LS109	.45	74LS245	4.95
Z80-CTC	6.00	4001	.35	4052	1.10	4539	.99	74LS01	.28	74LS112	.49	74LS247	1.10
Z80ACTC	7.10	4002	.35	4053	1.10	4543	1.99	74LS02	.28	74LS122	.55	74LS248	1.10
Z80-DMA	18.50	4006	1.39	4055	3.95	4553	3.50	74LS03	.28	74LS123	1.19	74LS249	1.69
Z80A-DMA	22.50	4007	.29	4056	2.95	4555	.75	74LS04	.39	74LS125	1.35	74LS251	1.79
Z80-S10/0	18.50	4008	1.39	4059	9.95	4556	.75	74LS05	.28	74LS126	.89	74LS253	.98
Z80A-S10/0	22.50	4009	.49	4060	1.39	4581	1.99	74LS08	.39	74LS132	.79	74LS257	.98
Z80-S10/1	18.50	4010	.49	4066	.75	4582	1.01	74LS09	.39	74LS136	.59	74LS258	.98
Z80A-S10/1	22.50	4011	.35	4068	.35	4584	.55	74LS10	.28	74LS138	.89	74LS259	2.95
Z80-S10/2	18.50	4012	.29	4069	.35	4585	.99	74LS11	.39	74LS139	.89	74LS260	.69
Z80A-S10/2	22.50	4013	.49	4070	.49	4702	9.95	74LS12	.39	74LS145	1.25	74LS261	2.49
3205	3.95	4014	1.39	4071	.35	74C00	.39	74LS13	.47	74LS148	1.49	74LS266	.59
3242	10.00	4015	1.15	4072	.35	74C02	.39	74LS14	1.25	74LS151	.79	74LS273	1.75
8155	11.25	4016	.59	4073	.35	74C04	.39	74LS15	.39	74LS153	.79	74LS275	4.40
8185	29.95	4017	1.19	4075	.35	74C08	.49	74LS20	.26	74LS155	1.19	74LS279	.59
8185-2	39.95	4018	.99	4076	1.29	74C10	.49	74LS21	.38	74LS156	.99	74LS283	1.10
8202	45.00	4019	.49	4078	.35	74C14	1.65	74LS22	.38	74LS157	.99	74LS290	1.29
8205	3.95	4020	1.19	4081	.35	74C20	.39	74LS26	.39	74LS158	.75	74LS293	1.95
8212	2.00	4021	1.19	4082	.35	74C30	.39	74LS27	.39	74LS160	.98	74LS295	1.10
8214	3.95	4022	1.15	4085	1.95	74C32	.99	74LS28	.39	74LS161	1.15	74LS298	1.29
8216	1.85	4023	.38	4086	.79	74C42	1.85	74LS30	.26	74LS162	.98	74LS324	1.75
8224	2.65	4024	.79	4093	.99	74C48	2.39	74LS32	.39	74LS163	.98	74LS347	1.95
8226	1.85	4025	.38	4099	2.25	74C73	.85	74LS37	.79	74LS164	1.19	74LS348	1.95
8228	5.00	4026	2.50	4104	1.99	74C74	.85	74LS38	.39	74LS165	.89	74LS352	1.65
8238	5.45	4027	.65	4501	.39	74C85	2.49	74LS42	.79	74LS166	2.49	74LS353	1.65
8243	4.65	4028	.85	4502	1.65	74C89	4.95	74LS47	.79	74LS170	1.99	74LS363	1.49
8251A	5.55	4029	1.29	4503	.69	74C90	1.85	74LS48	.79	74LS173	.89	74LS365	.99
8253	9.85	4030	.45	4505	8.95	74C93	1.85	74LS51	.26	74LS174	.99	74LS366	.99
8255A	5.40	4031	3.25	4506	.75	74C95	1.85	74LS54	.35	74LS175	.99	74LS367	.73
8255A-5	5.40	4032	2.15	4507	.95	74C107	1.19	74LS55	.35	74LS181	2.20	74LS368	.73
8257	9.25	4033	2.15	4508	3.95	74C151	2.49	74LS73	.45	74LS190	1.15	74LS373	2.75
8257-5	9.25	4034	3.25	4510	1.39	74C154	3.50	74LS74	.59	74LS191	1.15	74LS374	2.75
8259A	7.30	4035	.95	4511	1.39	74C157	2.10	74LS75	.68	74LS192	.98	74LS375	.69
8271	60.00	4037	1.95	4512	1.39	74C160	2.39	74LS76	.45	74LS193	.98	74LS377	1.95
8275	32.95	4040	1.29	4514	3.95	74C161	2.30	74LS78	.65	74LS194	1.15	74LS385	1.95
8279	10.80	4041	1.25	4515	3.95	74C163	2.39	74LS83	.99	74LS195	.95	74LS386	.65
8279-5	10.80	4042	.95	4516	1.69	74C164	2.39	74LS85	1.19	74LS196	.89	74LS390	1.95
8282	6.70	4043	.85	4519	.99	74C173	2.59	74LS86	.45	74LS197	.89	74LS393	1.95
8283	6.70	4044	.85	4520	1.39	74C174	2.75	74LS90	.75	74LS221	1.49	74LS395	1.70
8284	5.85	4046	1.75	4522	.99	74C175	2.75	74LS92	.75	74LS240	1.95	74LS399	2.95
8286	6.70	4047	1.25	4526	1.15	74C192	2.39	74LS93	.75	74LS241	1.90	74LS424	2.95
8287	6.70	4048	.99	4527	1.75	74C193	2.39	74LS95	.88	74LS242	1.95	74LS668	1.75
8288	25.40	4049	.69	4528	.99	74C195	2.39	74LS96	.98	74LS243	1.95	74LS670	2.29
8289	49.95												

MAIL ORDERS SHOULD BE SENT TO:
13400 Northup Way 22 Bellevue Washington 98005
Telephone Orders & Inquiries 1-800-426-2668
Minimum Order \$10.00 Add \$3.00 Shipping

HANLEY ENGINEERING ✓
(206) 643-0792
13400 NORTHUP WAY 22
BELLEVUE, WASHINGTON 98005

FOR THE FINEST IN MICROPROCESSOR SUPPORT I.C.'S



Four New Programs for Your TRS-80*

GEOGRAPHY EXPLORER: USA

The Geography Explorer: USA package is the most fascinating (and least painful) way of learning social studies that we've seen yet.

The program displays computer generated maps of the United States, its seven regions, and its individual states. The student then answers questions about the states of a given region. These questions may be in multiple choice recognition of fill-in format.

Geography Explorer has a unique TEACHER mode which allows the teacher or parent to choose multiple options of how the material is to be presented. This permits directed learning for the student.

The package is also just plain fun! When the student answers the questions correctly, there are a variety of graphic rewards that flash on the screen to provide immediate, positive reinforcement.

As a bonus, this educational package can use a compatible Light Pen! The union of sophisticated software with the speed and novelty of the Light Pen represents a milestone in Computer Assisted Instruction.

Order No. 0071RD (Model I, Level II 16K, E/I 16K + disk drive) \$49.95 DISK

RENUM/COMPRESS

RENUM/COMPRESS is a machine-language utility which adds two commands to TRS-80 Level II BASIC. Occupying the top 767 bytes of memory, the program allows you to renumber and/or compress any BASIC program. In renumbering, all GOTO and GOSUB commands are re-addressed to the new line numbers. With simultaneous renumbering and compression, all lines are renumbered, GOTO and GOSUB commands are re-addressed, and the entire BASIC program is reduced in size by elimination of all spaces not enclosed in quotes and all REM statements. This program allows you to expand your number-to-number intervals to accommodate insertion of new lines, and then to compress your program to free up additional memory.

Order No. 0133R \$14.95 TAPE

Instant Software™

PETERBOROUGH, N.H. 03458

A DIVISION OF WAYNE GREEN INC.

✓401

THE WORDSLINGER

At last... simplified word processing! The Wordslinger is an economical word processing program designed for the individual user or small business. The program has automatic formatting for letterhead stationary and envelope addressing. You can write and edit letters, reports, forms, even schoolwork!

One of the Wordslinger's major advantages is that you don't need disk drives or an expansion interface. The minimum system required is the TRS-80 Level II with 16K of RAM and appropriate printer (you may need an expansion interface if your printer can't operate with just a printer interface cable, such as Radio Shack's part #26-1411 or 26-1416).

Complete text editing is yours for the asking—just ask for the Wordslinger.

Order No. 0129R (Model I, Level II, 16K RAM) \$29.95 TAPE

PROGRAMMER'S PRIMER

There is a well known cliché, "One picture is worth a thousands words." That time tested message has served as the impetus for this program that demonstrates, for the novice programmer, the logic used in six common computer operations. The program is designed to function as a CAI device.

The six routines presented include Decimal to Hexadecimal Conversion (and vice-versa); Subscription of a Variable and Three Dimensional Array data storage operations; the For-Next-Loops demonstration of logical program flow; and the Bubble Sort sorting routine.

All of these routines are clearly presented with on-screen step-by-step instructions and are displayed with a sequence of the logic used to arrive at the desired goal. Several of the routines can be modified to suit individual needs.

Order No. 0245R (Model I, Level II 16K, Model III 16K) \$9.95 TAPE

To Order: See your local Instant Software dealer. If these programs are unavailable, order directly.

**Call Toll-Free
1-800-258-5473**

*A registered trademark of Tandy Corp.

KB BOOK NOOK

FOR TRS-80* OWNERS ONLY!

THE NEWEST PERIPHERAL FOR THE TRS-80*

The **Encyclopedia for the TRS-80***, published by Wayne Green Books, is a ten-volume reference work that is absolutely packed with programs and articles carefully selected to help you make the most of your microcomputer. The volumes of the Encyclopedia can be considered an extension of the documentation that came with the TRS-80*, offering a continual supply of information and ideas that will help you realize the full potential of your TRS-80*. Each volume contains material on programming techniques, business, games, tutorials, utilities, and interfacing.

Unlike conventional encyclopedias, the **Encyclopedia for the TRS-80*** will never become stale or out of date. That's because the volumes of the Encyclopedia are being issued one at a time, over a period of months. This means that each new volume will reflect the latest developments and discoveries, making this a living encyclopedia for TRS-80* users.

Here's a sample of what's included in Volume 1:

- Four Graphics Methods. Improved techniques for dealing with the TRS-80's low resolution graphics.
- TTY Interface. Build an interface, hookup a Teletype to a TRS-80.
- The President Decides. A thrilling simulation that lets you make decisions as if you were President of the United States.
- Measure Instructional Effectiveness. Many programs teach or tutor: this one helps determine the effectiveness of the lessons.
- The Invoice. A program for small businesses which produces custom invoices.
- Punch Out Your Disks. Double your disk storage in seven easy steps.

*TRS-80 is a trademark of the Radio Shack Division of Tandy Corp.

ORDERING INFORMATION

HARDCOVER SERIES			SOFTCOVER SERIES		
EN8101	VOL. 1	19.95	EN8081	VOL. 1	10.95
EN8102	VOL. 2	19.95	EN8082	VOL. 2	10.95

*Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to Kilobaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.

No C.O.D. orders accepted. All orders add \$1.00 handling. Please allow 4-6 weeks for delivery. Questions regarding your order? Please write to Customer Service at the above address.


PRICES SUBJECT TO CHANGE WITHOUT NOTICE

FOR TOLL FREE ORDERING CALL 1-800-258-5473

RONDURE COMPANY **the computer room**

2522 BUTLER/DALLAS, TX. 75235 ✓74
214-630-4621

GE TERMINET 300 PRINTER




Pin feed—9" paper

- 80 Print positions
 - Receive only
 - ASCII code
 - RS-232 interface
 - 30 CPS
 - Upper & lower case
 - Shipping wt. 75#
- Shipping containers \$15.00
(used)
(good working condition)

Will run on serial RS232 port of most micros including TRS-80. **SPECIAL \$295.00**

FLAT-PACK ACOUSTIC Modem Pickup



\$19⁵⁰

RS 232 CABLES—LIKE NEW

6' pins wired male/female— \$25.00	15' RS 232 male/male—\$20.00
8' RS 232 male/male—\$12.50	25' RS 232 male/male—\$22.50
	50' RS 232 male/male—\$45.00

CABLES MADE TO ORDER AVAILABLE

MICRO SWITCH KEYBOARD USED BUT LOOKS VERY NICE



ASC II **\$40.00**
(With Print)

USED FANS



Muffin—\$8.00
Sprite—\$6.00

ORDERING INFORMATION:

We ship the same day we receive a certified check or money order. Texas residents add 5% sales tax. Please call if you have a question. Write for our CATALOG of many parts, terminals, printers, etc. All items subject to availability. Your money returned if we are out of stock.

SHIPPING INFORMATION:


Modems: \$300 each; Key Boards \$350; Power Supply \$800. Larger items & Parts: Specify Freight or Air Freight Collect. Foreign Orders: Add appropriate freight or postage. We now take Master Charge and Visa orders. Specify full number, bank number and expiration date.



**USED
OMNITEK
Orig.
Only
\$75.00**

HOBBY ROBOTICS' Shoppers Mart

— For the SERIOUS Hobbyist —



**Hobby
Robotics
Directory**

**Amateur
Robotics
Designers
Newsletter**

ARD Newsletter.
Quarterly. Keeps
you abreast of
latest news,
perks up interest!
\$6.00

Complete RU-2 Manual!

Everything you need to build your own robot shown, detailed! Build from base up with Hobby Robotics' highly maneuverable 2-ft. per sec. super-traction base, extendable arms lift-rated at 15 lbs., grip-like hands. Manual only \$25.00, refundable with first purchase.

Hobby Robotics' Parts Supplier Directory. Chock-full of names, addresses, phone numbers you want for hard-to-find parts, systems, build-your-own-robot info. Only \$3.50. Get yours now!

HOBBY ROBOTICS ✓265

5070 Buford Highway
Norcross, Ga. 30071 404/448-0190
Please send items checked below:

- ☐ Qrt. Newsletter ☐ RU-2 Manual
☐ Parts Directory ☐ Robot Base

FREE ☐ Hobby Robotics' Catalog **FREE**

Total Enclosed \$_____ (includes shipping)

- ☐ Personal Check ☐ Cashiers Check/M.O.
☐ Mastercharge ☐ Bank Americard

Acct. # _____

Signature _____ Exp. _____

Name _____

Address _____

City _____

State _____ Zip _____



**HOBBY
ROBOTICS' ROBOT BASE**
Ready to roll!

ONLY \$495 (includes shipping)

The Shiny Apple

By Harold Nelson
Microcomputing Technical Editor

In the five years since two young men started building *microcomputers* in a garage in California, Apple Computer, Inc., has become, according to *The Wall Street Journal*, "one of the hottest high-technology companies to go public." Among computerists, it is also one of the microcomputer industry's most respected manufacturers. The Apple II itself is one of the chief reasons why—it's a sound computer, easily adapted to virtually any purpose. Also, Apple encourages independent producers to develop products for use with its computers, a philosophy that lets users easily modify their Apples when they need to.

Applefest '81

In spite of early difficulties with the new Apple III computer, consumer interest in, and enthusiasm for, Apple seems to be undiminished. June's highly successful Applefest '81 show (10,000 paid attendance), sponsored by the Apple/Boston group of the Boston Computer Society, underlined this point. Even though the temperature was close to 90 degrees, with the humidity

not far behind, both spirits and exhibitor sales were high. The show was not only well-supported by current and potential Apple owners; Apple Computer itself was well-represented. They provided a public hands-on room with about 20 Apple IIs, and offered free 45-minute "lessons" on 15 Apple IIIs. It wasn't easy to find a computer in either of these rooms that was not being used.

Apple III, Round 2

The Apple announced its Apple III well over a year ago (May 1980, to be specific). Orders were enthusiastically placed and received. Then the long wait began.

Prior to March of this year, only some 1000 Apple IIIs were delivered—many months behind the first scheduled delivery dates. The machines only became readily available this spring.

Soon after the first Apple IIIs were out, horror stories began to appear. These ranged from reports of minor problems to statements that the machine was a total failure and that Apple would not be able to reproduce its success with the Apple II. Rumors

began to circulate that the company itself was in trouble.

The Apple III had some very real problems, but it now appears that the doomsayers were a little hasty. Obviously, Apple released the Apple III prematurely. Phil Roybal, Apple's Product Marketing Manager, does not shy away from discussing these problems, which included:

- Intermittent difficulties with programmable random-access memory. Apple discovered that corrosion formed on memory board contacts after the computers were shipped. Coating these contacts with a protective lubricant at the factory has eliminated the problem.

- In shipment, ICs worked out of their sockets, a result of movement of the large motherboard and loose sockets. The solution was to use tighter sockets with a metal tab to hold the ICs in place.

- The tighter sockets did not seem to remedy the above problem. Actually, the new sockets caused new problems with similar symptoms to those caused by the loose sockets. The new sockets were so tight that



The Apple III features an 80-character, upper and lowercase display, up to 128K of memory, one built-in disk drive and the capacity for more. (Computer courtesy of Computer Town of Salem, NH)



Applefest '81 in Boston was hot, humid, crowded and a huge success.

pins were often bent when the ICs were installed. Apple didn't detect this at first, since the tabs tended to cover up the problem during factory testing. The final solution was to use the tighter sockets without the tabs. Now bent pins can be detected during factory inspection.

- The very fine-line PC board first used in the Apple III made it hard to detect slight solder bridges occurring during assembly. Apple has lessened this problem by using wider traces on the PC board and by improving quality-control measures.

Roybal also said that, since these corrections, "the backlog of orders has been filled and production is up to par." Dealers and users we contacted are now pleased with the Apple III's performance.

The only negative remark concerns the lack of software for the Apple III. Word Painter, Apple's word processor for the Apple III, is not on the market, even though it was promised months ago; this fact has frustrated several Apple III purchasers. The delay, says Apple, is because Word Painter was written in Pascal, and the Apple III version of UCSD Pascal is only now being readied for release.

Apple III Software

Two new Apple III word processors, available from independent producers, should therefore be welcomed by users, dealers and Apple itself. Rainbow Computing, Inc., (19517 Business Center Drive, Northridge, CA 91324) has released Write-On III (for a review of the Apple II versions of Write-On, see the June 1981 *Byte*, p. 186). Also, Type-Righter has been announced by Imagineering, Inc. (c/o Adcast Advertising, 405 S. Farwell, Suite #10, Eau Claire, WI 54701). If these word processors are any indication, the Apple III software vacuum should soon be filled.

Some Apple III purchasers have also had trouble using its Apple II emulation mode. In this mode, the Apple III will run software written for the Apple II. Problems with this mode are, for the most part, I/O-related. For example, an Apple II program written for printer output with a printer interface card in slot 2 will not run on the Apple III. The reason is simple. The Apple III has a built-in printer interface that is addressable as slot 7. If the Apple II software is designed to look for the printer in slot 2, it won't work. But the solution is also simple. Modify the Apple II software to send printer output to slot 7. Most emulation mode problems can be similarly solved.

Apple knows it has made mistakes with the Apple III, but believes that they are now corrected. Apple's chairman and cofounder Steve Jobs expressed unqualified confidence while at Applefest '81 that the Apple III is finally on-line.

But beyond discussing software being developed for the Apple III, both Jobs and Roybal are close-mouthed about future Apple products. The message is that they won't disclose anything about new products until they're certain that those products are ready. ■

Apples Grow Well in Dallas

By Tom Lukers



Independent consultant Philip Russell is shown here training office staff on the fine points of VisiCalc on an Apple III.

Apple is getting good reviews from dealers in the Dallas area, where Apple recently opened a new manufacturing plant.

Retailers and consultants are reporting steady sales and satisfied customers, and are happy with Apple's factory support and promotional efforts.

"It wasn't long before we saw that almost all of our income was from Apple sales," says one dealer. Another adds that Apple constitutes about 80 percent of his sales.

Many customers are from large companies with corporate headquarters in Dallas. They like Apples because they work well either as stand-alone systems or as terminals in a corporate network. Some executives use them at the office, others use them at home and some do both.

The Apple's friendliness is the key to its success so far, dealers say.

"Most people want a buttoned-down system," says one retailer. "They want to be able to walk up to it and use it. Let's face it: most people aren't programmers or hardware hobbyists. They don't care about this bus, that bus or any bus. They just want to use the computer."

The same dealer says that the Osborne I, despite its price and features, won't have a great impact on Apple sales.

"The Osborne I isn't a friendly system," he says. "Besides, the guy who buys an Osborne I probably wouldn't have bought an Apple, anyway."

Pam Inserra, vice president of the KA Computer Store, says that several re-

cent Apple promotional campaigns have given sales a shot in the arm.

For example, a recent Apple road show for dealers and the general public was extremely successful, she says, and was followed by an increase in sales. And the advertising campaign featuring Dick Cavett also helped the store.

"For a while, it was a regular occurrence for someone to walk through the door, saying, 'Dick Cavett sent me,'" she says.

People are not without their reservations. Independent consultant Philip Russell, for example, is critical of the lack of software support for the Apple III.

"As far as I'm concerned, the Apple II emulation mode is almost a failure, because of its inflexibility," he says. "I have even considered recommending to one of my clients that he go back to the Apple II because of this."

Compushop District Manager Richard Hartman warns that Apple could face some stiff competition if it isn't careful.

"Apple is by far our leading seller," he says. "But some really serious competition is looming on the horizon and Apple should be preparing for it. Atari sales are increasing every day. And Atari has the financial backing to give everyone a run for it." ■

Dr. Tom Lukers (PO Box 1949, 3625 Hendrick Drive, Plano, TX 75054, Micronet 70130,371) wrote the January 1981 cover story, "Assemble a Super Business System."

NEW

CENTRONICS 739 (RADIO SHACK LINE PRINTER IV)

With Graphics and Word Processing Print Quality




- 18 x 9 dot matrix; suitable for word processing • Underlining • proportional spacing • right margin justification • serif typeface • 80/100 CPS • 9 1/2" Pin Feed/Friction feed • Reverse Platen • 80/132 columns • Top of form

CENTRONICS 739-1 (Parallel) (List \$995) **\$ Call**
CENTRONICS 739-3 (Serial) (List \$1045) **\$ Call**

ANADEx

Dot Graphics, Wide Carriage




- 11 x 9 dot matrix; lower case descenders • Dot resolution graphics • Bidirectional, logic seeking • Up to 200 CPS • RS 232 Serial & Parallel • Forms control • X-ON/X-OFF • Up to 6 part copy.

ANADEx 9501 (List \$1650) **\$1350**

AXIOM

Dot Graphics, Low Price



- Dot addressable graphics • 70 CPS • 12 characters per inch • 80 columns • adjustable tractors • 3 part copies • Manufactured by Sieko • Parallel, RS232 serial, IEEE-488 interfaces available.

AXIOM GP-80M (List \$399) **\$349**

IDS PAPER TIGERS

Dot Resolution Graphics, quality print, speed



- 7 wire printhead (445); 9 wire printhead (460) with lower case descenders • Over 150 CPS • bi-directional, logic seeking (460) • 8 character sizes; 80-132 columns • Adjustable tractors • High-resolution dot graphics • Proportional spacing & text justification (460).

IDS 445G 7 wire printhead, graphics (List \$895) **\$ 750**
IDS 460G 9 wire printhead, graphics (List \$1394) **\$1150**
IDS 560G 9 wire, wide carriage, graphics (List \$1794) **\$1400**


CALL FOR FREE CATALOG

(800) 854-8275
CA, AK, HI (714) 630-3322

At Orange Micro, we try to fit the right printer to your application. Call our printer specialists for free consultation.

EPSON MX80/MX70

Low-Priced Professional Print Quality



- 9 x 9 dot matrix • Lower case descenders • 80 CPS • Bidirectional, Logic seeking • 40, 66, 80, 132 columns per line • 64 special graphic characters: TRS-80 Compatible • Forms handling • Multi-pass printing • Adjustable tractors

We also carry a full line of Epson Accessories.

EPSON MX80 (List \$645) **\$ Call**
EPSON MX 70 Dot graphics, 5 x 7 matrix (List \$450) **\$ Call**
EPSON MX100 wide carriage (List \$995) **\$ Call**
GRAPPLER™ Apple graphics parallel interface and cable **\$ 165**

MX80/70 FRICTION FEED KIT

Uses installable kit for single sheets. Easy 15 minute installation.

\$ 75

ANACOM

Low Cost, High Speed, Wide Carriage

- 9 x 9 dot matrix • Lower case descenders • Wide carriage • Adjustable tractors to 16" • 150 CPS, Bidirectional, Logic Seeking

ANACOM 150 (List \$1350) **\$ Call**

NEC SPINWRITER

High Speed Letter Quality

- 55 CPS • Typewriter quality • Bidirectional • Plotting • proportional spacing.

5510-5 RO, Serial, w/tractors (List \$2995) **\$2675**
5530-5 RO, Parallel, w/tractors (List \$2970) **\$2650**



QUANTITY PRICING AVAILABLE

TELEVIDEO CRT'S AT DISCOUNT PRICES!

TVI 910
TVI 912C
TVI 920C
TVI 950

Please Call Toll Free
Prices are too low to
advertise

PRINTERS

MALIBU 165 wide carriage, graphics, letter quality .. (List \$2495) **\$ 1975**
QUME 5/45 typewriter quality (List \$2905) **\$ 2559**
VISTA-C. ITOH Starwriter, letter quality (List \$1895) **\$ Call**

INTERFACE EQUIPMENT

EPSON ACCESSORIES **\$ Call**
ORANGE INTERFACE for Apple II parallel interface board & cable **\$ 110**
MICROTRONICS Atari parallel interface **\$ 69**
TRS-80 CABLES to keyboard or Exp. interface **\$ Call**
NOVATION D-CAT direct connect modem **\$ Call**

RETAIL PRINTER STORES:

3150 E. La Palma, #1, Anaheim, CA.
13604 Ventura Bl., Sherman Oaks, CA.
Store Hours: M-F 10-6 Sat. 10-4

Phone orders WELCOME; same day shipment. Free use of VISA & MASTERCARD. Personal checks require 2 weeks to clear. Manufacturer's warranty included on all equipment. Prices subject to revision.

Orange Micro, Inc.
3150 E. La Palma, Suite I
Anaheim, CA 92806

To Tell the Truth

By David B. Curtis

Can a computer replace Scotland Yard? How much stress do you feel when another Klingon enters your sector? Who ate the last piece of leftover mince pie? Who knows the answers to these questions?

The Apple II does, with the aid of this inexpensive and criminally simple way to connect it to a psychogalvanometer, or lie detector.

The skin surface of the human body carries small electrical currents, and has a measurable resistance. This resistance is lowered by tension, physical exertion and other factors, which may be the result of lying or another form of stress. Psychogalvanometers measure this varying resistance.

Radio Shack sells a lie detector unit (catalog number 28-182) for \$11.95. It includes two sensors that attach to two fingers of the subject's hand. The relative skin resistance tunes the frequency of an audio oscillator, which drives a speaker. When the subject's resistance goes down, the pitch of the generated tone goes up proportionally.

Because of the audio output, the Radio Shack lie detector is simple to interface to the Apple II. You connect the output of the oscillator to the cassette input of the Apple II, and use a small machine-language program to measure the frequency of the audio output of the lie detector.

Construction

Assemble the Radio Shack lie detector kit according to the instructions that come with it. The kit is very

simple; anyone who knows which end of a soldering iron to hold should have no trouble assembling it in less than an hour. Before proceeding to

Listing 1.

```
1000 *****
1010 *
1020 * LIE DETECTOR INTERFACE
1030 *
1040 * DATE THIS REVISION : 11-OCT-80
1050 *
1060 * ENTRY -
1070 * CALLED FROM APPLESOFT AS USR
1080 * FUNCTION
1090 *
1100 * INPUT - NONE
1110 *
1120 * OUTPUT -
1130 * RETURN VALUE FROM 0-255
1140 * REPRESENTING RELATIVE
1150 * SKIN RESISTANCE
1160 *
1170 *
1180 * TO USE -
1190 * APPLESOFT PROGRAM SHOULD
1200 * BRUN LIE DETECTOR INTERFACE
1210 * AS PART OF INITIALIZATION
1220 *
1230 * MEMORY USAGE -
1240 * $315 - $34E (INCLUSIVE)
1250 *
1260 *****
1270 *
1280 * INTERFACE EQUATES
1290 *
1300 USRVEC .EQ #A ;START OF APPLESOFT USR VECTOR
1310 FLOAT .EQ #E2F2 ;CHANGE INTEGER TO FLOATING POINT VALUE
1320 CASSIN .EQ #C060 ;CASSETTE INPUT ADDRESS
1330 *
1340 * SET START OF PROGRAM TO PAGE
1350 * $3 WHERE IT IS OUT OF THE WAY
1360 *
1370 .OR $315
1380 *
1390 * INITIAL ENTRY
1400 * - SET UP USR VECTOR AND RETURN
1410 *
1420 JMPOP .EQ #4C ;OP CODE FOR JMP
1430 INIT .EQ *
1440 LDA #JMPOP
1450 STA USRVEC
1460 LDA #ENTRY
1470 STA USRVEC+1
1480 LDA /ENTRY
1490 STA USRVEC+2
1500 RTS
1510 *
1520 * STORAGE ALLOCATION
1530 *
1540 I .DA *** ;INNER LOOP COUNTER
1550 J .DA *** ;OUTER LOOP COUNTER
1560 PULSES .DA *** ;NUMBER OF PULSES SEEN
1570 *
1580 * TIMING EQUATES
1590 * - LOOP FOR 16*255 TIMES
1600 *
1610 ISTART .EQ #FF
1620 JSTART .EQ #10
1630 *
```

```
0315- A9 4C
0317- 85 0A
0319- A9 25
031B- 85 0B
031D- A9 03
031F- 85 0C
0321- 60
```

```
0322- 00
0323- 00
0324- 00
```

More →

connect it to the Apple II, be sure that the lie detector operates properly in its unmodified form.

Modifying the lie detector for interfacing is simple. First, solder a miniature phono plug (the kind of plug that

fits the cassette-in jack) to one end of a piece of two-conductor wire. Run the other end through a hole in the

Listing 1 continued.

```

1640 * LIE DETECTOR READ
1650 * - ALL USER CALLS COME HERE
1660 *
1670 ENTRY .EQ *
0325- A9 00 1680 LDA #0 ;CLEAR PULSE COUNTER
0327- 8D 24 03 1690 STA PULSES
032A- A9 10 1700 LDA #JSTART ;INITIALIZE OUTER
032C- 8D 23 03 1710 STA J ; LOOP COUNT
1720 CNTLO .EQ * ;OUTER LOOP ENTRY
032F- A9 FF 1730 LDA #ISTART ;INITIALIZE INNER
0331- 8D 22 03 1740 STA I ; LOOP COUNT
1750 CNTLI .EQ * ;INNER LOOP ENTRY
0334- AD 60 C0 1760 LDA CASSIN ;TEST CASSETTE INPUT
0337- 10 03 1770 BPL NOPULS ;BRANCH IF NO PULSE
0339- EE 24 03 1780 INC PULSES ;COUNT PULSE SEEN
1790 NOPULS .EQ *
033C- CE 22 03 1800 DEC I
033F- D0 F3 1810 BNE CNTLI ;LOOP (INNER) WHILE I NOT ZERO
0341- CE 23 03 1820 DEC J
0344- D0 E9 1830 BNE CNTLO ;LOOP (OUTER) WHILE J NOT ZERO
1840 *
1850 * CONVERT PULSES TO FLOATING
1860 * POINT VALUE LIKE APPLESOFT
1870 * EXPECTS AND RETURN
1880 *
0346- A9 00 1890 LDA #0
0348- AC 24 03 1900 LDY PULSES
034B- 20 F2 E2 1910 JSR FLOAT
034E- 60 1920 RTS

```

SYMBOL TABLE

USRUEC 000A	FLOAT E2F2	CASSIN C060
JMPOP 004C	INIT 0315	I 0322
J 0323	PULSES 0324	ISTART 00FF
JSTART 0010	ENTRY 0325	CNTLO 032F
CNTLI 0334	NOPULS 033C	

>CALL-155


*315.34E

```

0315- A9 4C 85
0318- 0A A9 25 85 0B A9 03 85
0320- 0C 60 00 00 00 A9 00 8D
0328- 24 03 A9 10 8D 23 03 A9
0330- FF 8D 22 03 AD 60 C0 10
0338- 03 EE 24 03 CE 22 03 D0
0340- F3 CE 23 03 D0 E9 A9 00
0348- AC 24 03 20 F2 E2 60
*3D0G

```

Listing 2. A dump of the lie detector interface routine.



t_p = LENGTH OF PULSE (CONSTANT)

t_f = TIME BETWEEN PULSES (VARIED TO CHANGE PITCH)

Fig. 1. Lie detector audio output as seen by computer.

SAVE more than 50%



FOB Reston
Virginia
MasterCard, VISA
Check, MO, PO.

NEW! \$1995 USED in excellent condition
RO version only **RO \$995; KSR \$1495**

Rugged and well-constructed; available in **KSR** and **RO** versions; feature 96 ASCII (upper & lower case) **plus** 27 graphics characters in a 5X7 (optionally 5X9) dot matrix. Prints bidirectionally (logic seeking) at 180 char/sec on std pin feed paper (up to SIX part) in **red and black**. Tractors are adjustable from 3 to 15 inches; split platen versions also available. Electronic top of form/forms length control and six selectable character print densities (10, 12, and 17 cpi plus elongated in each). 1K buffer and 110-9600 Baud RS-232C interface is standard; additional buffer may be added and a Centronics-compatible parallel interface is available. Free-standing pedestal unit.

DSE ✓61
Digital Systems Engineering

12503 King's Lake Drive, Reston VA 22091 (703) 620-2994

ALSO AVAILABLE: New Centronics and Integral Data Systems printers at 15-20% below list; also, used printers of several makes. **Call for information!**

START YOUR OWN COMPUTER CO.

We have the manuals that tell you how.

HOW TO START YOUR OWN SYSTEMS HOUSE

\$36.

6th edition, March 1980

Written by the founder of a successful systems house, this fact-filled 220-page manual covers virtually all aspects of starting and operating a small systems company. It is abundant with useful, real-life samples: contracts, proposals, agreements and a complete business plan are included in full, and may be used immediately by the reader.

Proven, field-tested solutions to the many problems facing the small systems house are presented.

HOW TO BECOME A SUCCESSFUL COMPUTER CONSULTANT

\$28.

by Leslie Nelson, 2nd revised edition, Jan. 1981

Independent consultants are becoming a vitally important factor in the microcomputer field, filling the gap between the computer vendors and commercial/industrial users. The rewards of the consultant can be high: freedom, more satisfying work and doubled or tripled income. **HOW TO BECOME A SUCCESSFUL COMPUTER CONSULTANT** provides comprehensive background information and step-by-step directions for those interested to explore this lucrative field.

FREE-LANCE SOFTWARE MARKETING

\$30.

by B. J. Korites, 3rd edition, June 1980

Writing and selling computer programs as an independent is a business where • you can get started quickly, with little capital investment • you can do it full time or part time • the potential profits are almost limitless. Since the demand for computer software of all kinds is growing at an explosive rate, the conditions for the small entrepreneur are outstanding.

Send check, money order, VISA or Master Charge #. Publisher pays 4th class shipping. Add \$1.00 per book for UPS shipping. For faster shipment on credit card orders call (201) 783-6940.

ESSEX PUBLISHING CO. Dept. 1
285 Bloomfield Avenue • Caldwell, N.J. 07006

✓327

case of the lie detector, and solder one conductor to each side of the speaker.

Software Interface

The audio oscillator output (as seen by the computer) is a varying pulse signal like that shown in Fig. 1. The pulse is constant, and the pitch is varied by changing the time between pulses. The simplest method of find-

ing the relative pitch is to count the number of pulses in a given period. This is what the machine-language program in Listing 1 does. The routine is designed to be used as a USR function from Applesoft in the same way that PDL is used to read the game paddles. When called from BASIC, the routine will return a number from 0 to 255. Refer to Listing 1 for details of the routine's design.

To install the program in your system, first get into the monitor by typing CALL -155. The Apple II should beep and display the * prompt. Listing 2 is a dump of the interface routine. Type each line as shown in the dump, changing all dashes (-) to colons (:). To re-create the dump and check for entry errors, type 315.34E. When the program is entered correctly, type 3D0G to return to BASIC. From BASIC, type BSAVE LIE DETECTOR DRIVER,A\$315,L\$40 to save the routine to disk.

Listing 3 shows a sample Applesoft program using the lie detector. A red lie-meter bar, which varies with skin resistance, is displayed using low resolution graphics. ■

```

10 REM APPLESOFT PROGRAM TO DEMONSTRATE LIE DETECTOR INTERFACE
20 REM LAST REVISION 11-OCT-80
100 GOSUB 40000: REM INITIALIZE
110 REM SENSE-SCALE-DISPLAY LOOP
120 S = USR (<S>): REM READ RELEVANT STRESS
130 REM S IS PASSED TO USR BUT IS NOT USED
140 S = S / 6: IF S > 38 THEN S = 38: REM SCALE S TO FIT LOW RES SCREEN
150 REM PAINT METER BAR
160 COLOR= RED: HLINE 0,S AT L
170 COLOR= BLACK: HLINE S + 1.39 AT L
180 GOTO 120: REM REPEAT FOREVER
40000 REM INITIALIZATIONS
40010 D$ = CHR$ (<4>)
40020 REM LOAD THE INTERFACE ASSEMBLY CODE
40030 REM THE USR VECTOR IS SET UP AUTOMATICLY
40040 PRINT D$ + "BRUN LIE DETECTOR DRIVER"
40050 RED = 1: REM COLOR FOR METER BAR
40060 L = 20: REM LINE TO PLACE METER BAR
40070 GR : REM SET LOW-RES GRAPHIC MODE
40999 RETURN

```

Listing 3. A sample Applesoft program using the lie detector.

References

Apple II Reference Manual, Apple Computer, Inc., 10260 Bandley Drive, Cupertino, CA 95014

Applesoft II Programming Reference Manual, Apple Computer, Inc.

S-C Assembler II Disk Version 3.2 Reference Manual, S-C Software, PO Box 5537, Richardson, TX 75080

Select the write printer —

PRESTO!
Overnight your
computer becomes
a word processing,
data processing or
graphic system.

Under \$500



Okidata
Microline 80 — 7x9 Head,
80 Column, Low Price

The NEW OKIDATA line of bidirectional dot matrix printers — high quality with continuous duty 200-million character printheads. The NEW printers have correspondence quality with their new 9x9 dot matrix heads and have full forms control, serial and parallel interfaces, as well as many other features. The Microline 80 is a very reliable, low cost printer. All products are available from our stock at The Stocking Source along with the optional cables, interfaces and memory buffers.

NEW
Microline 82A — 9x9
Head, 80 Column,
120 CPS

NEW
Microline 83A — 9x9
Head, 136 Column,
120 CPS

NEW
Microline 84 — 9x9 Head,
136 Column, 200 CPS

NEW
Model 2350 — 9x9
Head, 136 Column,
350 CPS



ASK FOR OUR
INSTANT DISCOUNT
From Roy Hawthorne
Talk To Bill Tokar On
Applications

CALL TOLL FREE
U.S.A.
1-800-521-2764
MICHIGAN
1-800-482-8393

Remember:
We are open
8:30 AM to
6:00 PM EST
Monday — Friday



No Credit
Card Penalty

"The Stocking Source"
24069 Research Drive
Farmington Hills, MI
48024
313-474-6708 ✓ 296

Down by the River

By Rolf A. Deininger, Richard L. Miller
and Paul J. Capano



Photo 1. Martek water quality monitor and Apple microcomputer on a bridge over the Huron River in Ann Arbor, Michigan.

Automatic sensors used to monitor water quality will quickly gather much data. This gives you a great deal of flexibility: you can monitor a location over a period of time, a cross section of a river or different depths at a single location in a lake.

But large amounts of data can create significant handling problems. So instead of reading the data from the instruments, keypunching them and analyzing them later, we decided to use a microcomputer.

The advantage of this system is that data can be collected continuously and recorded in machine-readable form. No need to read the meters, write the values in notebooks and then keypunch them later for processing or storage. The data on the disk can be transferred to a larger computer system using the communications interface and a modem, and we do this routinely.

This small microcomputer system has extended our abilities to monitor water quality significantly and does it very cost-effectively.

The System

The computer is an Apple II, and the monitor is from Martek Instruments. Photo 1 shows the actual set-up, on a bridge over the Huron River in Ann Arbor. The monitor and display are on the top shelf; the Apple, amplifier, disk drive and cables are on the middle shelf; and the power supply is on the bottom shelf.

Photo 2 shows the actual sensors which are lowered into the water. From left to right are the oxygen sen-

Address correspondence to Rolf A. Deininger, Professor of Environmental Health, The University of Michigan, Ann Arbor, MI 48109.

sor, the temperature sensor, the conductivity sensor and the pH sensor. The unit also has a depth sensor, which was not used.

The power source for the Apple and the display is a 12-volt recreational-vehicle battery connected to a 100-watt power inverter (Radio Shack Cat. No. 22-31) which produces 110 V ac. Our Apple draws about 0.3 amps at 110 V, and increases to about 0.4 amps during disk operations. The Sanyo display draws a little less than 0.3 amps at 110 V. Due to inefficiencies in the inverter, the battery drain is about 7 amps at 12 V. For a few hours of operation, the battery shown is sufficient; for longer times you'll need a larger battery. (Occasional use of the display also reduces power requirements.)

The Martek water quality monitor continuously monitors the temperature, the dissolved oxygen, the pH and the conductivity of the river water and displays the values on the panel meters. At a recorder output, all four signals are continuously available and range from 0 to 500 mV. These signals are then amplified by a factor of about eight using four LM308NA operational amplifiers.

An analog/digital (A/D) converter (AI-02 from Interactive Structures, Inc., Bala Cynwyd, PA) outputs digital voltage readings. The voltages sampled by the system were calibrated using known water samples and calibration signals available on the Martek monitor. We've written a simple program that will check the sensors for a predetermined number of samples at given time intervals (see Listing 1).

The program in Listing 2 produces a printout of data stored on disk. Data gathered one afternoon, stored on disk and later printed at our office using this program is shown in the Sample run.

Program Notes

The program in Listing 1 actually begins at line 1000, which sets the base addresses for the A/D converter (in slot 7 of our Apple). Lines 1010 through 1040 set the amplification and conversion factors for the four channels. Statement 1090, together with 160, produces the approximately desired sampling interval.

Since the Martek has several ranges for measurement of dissolved oxygen and conductivity, statements 1140 through 1190 are needed to set the desired range for each. Statement

1230 activates a scrolling window. The program goes to line 50. Lines 60 through 100 cause the A/D converter to initiate a conversion, read the con-

verted values and round them to the first decimal place. Lines 110 through 150 print the data onto the monitor screen. ■

Listing 1. Computer program in APPLESOFT for operating the system.

```

1 LOAD WQ MONITOR
2 LIST

10 REM WATER QUALITY MONITORING SYSTEM
20 REM WRITTEN BY R A DEININGER MAY 80
30 DIM SR(600,4)
40 GOTO 1000
50 SN = SN + 1
60 FOR I = 1 TO 4
70 POKE AF1,I
80 R = PEEK(A) * 19.6 * CV(I) / AF(I)
90 SR(SN,I) = INT((R + .05) * 10) / 10
100 NEXT I
110 HTAB 3: PRINT SN;
120 HTAB 9: PRINT SR(SN,1);
130 HTAB 16: PRINT SR(SN,2);
140 HTAB 23: PRINT SR(SN,3);
150 HTAB 29: PRINT SR(SN,4)
160 FOR I = 1 TO DLAY: NEXT I
170 IF SN < NS THEN 50
180 IF SV$ = "N" GOTO 300
190 D$ = CHR$(4)
200 PRINT D$;"OPEN ";LOC$
210 PRINT D$;"WRITE ";LOC$
220 PRINT LOC$
230 PRINT NS
240 FOR I = 1 TO NS
250 PRINT SR(I,1): PRINT SR(I,2)
260 PRINT SR(I,3): PRINT SR(I,4)
270 NEXT I
280 PRINT D$;"CLOSE ";LOC$
300 HTAB 15: PRINT "...DONE..."
310 STOP

1000 A = - 14592:AF1 = A + 1: REM SLOT 7 ADDRESSES
1010 AF(1) = 7.91:AF(2) = 7.91
1020 AF(3) = 7.91:AF(4) = 8.0
1030 CV(1) = .0234:CV(2) = .0199
1040 CV(3) = .0756:CV(4) = .09
1050 PRINT "ENTER NAME OF SAMPLING STATION"
1060 INPUT LOC$
1070 PRINT "ENTER SAMPLING INTERVAL(SECS)"
1080 INPUT SECS
1090 DLAY = 700 * SECS
1100 PRINT "HOW MANY SAMPLES TO BE TAKEN"
1110 INPUT NS
1120 PRINT "SAVE THE DATA ON DISK(Y/N)"
1130 INPUT SV$
1140 PRINT "ENTER CONDUCTIVITY RANGE SELECTED"
1150 INPUT CR: IF CR > 100 OR CR < 2.5 THEN 1140
1160 CV(4) = CV(4) * CR / 50
1170 PRINT "ENTER DISS OXYGEN RANGE SELECTED"
1180 INPUT DR: IF DR > 20 OR DR < 2 THEN 1170
1190 CV(2) = CV(2) * DR / 10
1200 SN = 0: CALL - 936
1210 PRINT "LOCATION: ";LOC$: PRINT : PRINT
1220 PRINT "SAMPLE# PH DIS OX TEMP COND"
1230 POKE 34,4
1240 GOTO 50
1250 END

```

Listing 2. Program that produced the Sample run.

```

10 REM MARTEK DATA READER
11 DIM SR(600,4)
20 D$ = CHR$(4)
30 PRINT "ENTER NAME OF FILE"
40 INPUT FI$

```

More

SIEMENS DISK DRIVES

5 1/4" floppy with case and power supply.

One Drive	\$ 320
Two Drive	\$ 620
Three Drive	\$ 900
Four Drive	\$1195

8" with case and power supply.

One Drive	\$ 489
Two Drive	\$ 940
Three Drive	\$1400
Four Drive	\$1860

COMPUTER SALES & SERVICE

5819 Camp Bowie Blvd.
Fort Worth, TX 76107

817-731-7412 ✓ 346

12" BLACK & WHITE LOW COST VIDEO TERMINAL


Easily interfaced with Radio Shack TRS 80

\$140.00 LIST

Will sell 6 feet coaxial cable \$5.00

Texas residents add 5% sales tax.

Add \$6 for shipping and handling



One year
limited warranty

• Ideal for home, personal and business computer systems; surveillance monitors • 12" diagonal video monitor • Composite video input • Compatible with many computer systems • Solid-state circuitry for a stable & sharp picture • Video bandwidth—12 MHz \pm 3 dB • Input impedance—75 Ohms • Resolution—650 lines Minimum 1N Central 80% of CRT, 550 Lines Minimum beyond central 80% of CRT ref EIA RS-375 • Dimensions—11.375" high; 16.250" wide; 11.250" deep (exclude video input connector) • Weight—6.5 KG (14.3 lbs) net

Use Master Charge/Visa or send money order.

Micro Products Unlimited

P.O. Box 120005, Arlington, TX 76012


817/277-4198

Dealer inquiries welcome

✓ 335

MEMOREX FLEXIBLE DISCS

**WE WILL NOT BE UNDER-
SOLD!!** Call Free (800)235-4137
for prices and information. Dealer
inquiries invited and C.O.D.'s
accepted.



**PACIFIC
EXCHANGES**

100 Foothill Blvd.
San Luis Obispo, CA
93401. In Cal. call
(800)592-5935 or
(805)543-1037

✓ 172

Listing 2 continued.

```

50 PRINT D$;"OPEN ";FI$
60 PRINT D$;"READ ";FI$
70 INPUT LOC$
80 INPUT NS
90 FOR I = 1 TO NS
100 INPUT SR(I,1); INPUT SR(I,2)
110 INPUT SR(I,3); INPUT SR(I,4)
120 NEXT I
130 PRINT "LOCATION: ";LOC$
140 PRINT : PRINT
150 PRINT "SAMPLE# PH DIS OX TEMP COND"
160 FOR I = 1 TO NS
170 HTAB 3; PRINT I;
180 HTAB 9; PRINT SR(I,1);
190 HTAB 16; PRINT SR(I,2);
200 HTAB 23; PRINT SR(I,3);
210 HTAB 29; PRINT SR(I,4)
220 NEXT I
230 HTAB 15; PRINT "...DONE..."
240 END

```

JRUN

ENTER NAME OF FILE

?HURON RIVER BRIDGE (6/24/80-1PM)

LOCATION: HURON RIVER BRIDGE (6/24/80-1PM)

SAMPLE#	PH	DIS OX	TEMP	COND
1	8.3	8.1	21.8	56.2
2	8.3	8.1	21.8	56.2
3	8.3	8.1	21.8	56.2
4	8.3	8.1	21.8	56.2
5	8.3	8.1	21.8	56.2
6	8.3	8.1	21.8	56.2
7	8.3	8.1	21.8	56.2
8	8.3	8.1	21.8	56.2
9	8.3	8.1	21.8	56.2
10	8.3	8.1	21.8	56.2

...DONE...

Sample run.

TAR HEEL SOFTWARE SYSTEMS

"Affordable Software for Small Business"

PROUDLY ANNOUNCES

REAL ESTATE BOOKKEEPING SYSTEM

a disk-based fully-integrated system including cash journal, general journal, tenant ledger, landlord ledger, monthly landlord statements, balance sheet, P & L statement by profit centers, and more, all for \$150 postpaid. (North Carolina orders add 4% sales tax.) Free continuing update service included. Minimum hardware: TRS-80 Model I, 32K, 2 disk drives, line printer. Versions for TRS-80 Model II and III, Apple II and Commodore 2001 Series coming soon. Watch for announcement of other small business applications software in the months to come.



✓ 233

**TAR HEEL SOFTWARE
SYSTEMS, INC.**

536 S. LEXINGTON AVE. - P.O. BOX 340
BURLINGTON, NORTH CAROLINA 27215





Photo 2. Sensor assembly for dissolved oxygen, temperature, pH value and conductivity.

"NIBBLE[®] IS TERRIFIC" (For Your Apple)



NIBBLE IS: *The Reference for Apple computing!*

NIBBLE IS: One of the Fastest Growing new Magazines in the Personal Computing Field.

NIBBLE IS: Providing Comprehensive, Useful and Instructive Programs for the Home, Small Business, and Entertainment.

NIBBLE IS: A Reference to Graphics, Games, Systems Programming Tips, Product News and Reviews, Hardware Construction Projects, and a host of other features.

NIBBLE IS: A magazine suitable for both the Beginner and the Advanced Programmer.

Each issue of NIBBLE features significant new Programs of Commercial Quality. Here's what some of our Readers say:

- "Certainly the best magazine on the Apple II"
- "Programs remarkably easy to enter"
- "Stimulating and Informative; So much so that this is the first computer magazine I've subscribed to!"
- "Impressed with the quality and content."
- "NIBBLE IS TERRIFIC!"

In coming issues, look for:

- ☐ Stocks and Commodities Charting ☐ Assembly Language Programming Column
- ☐ Pascal Programming Column ☐ Data Base Programs for Home and Business
- ☐ Personal Investment Analysis ☐ Electronic Secretary for Time Management
- ☐ The GIZMO Business Simulation Game

And many many more!

NIBBLE is focused completely on the Apple Computer systems.

Buy NIBBLE through your local Apple Dealer or subscribe now with the coupon below.

Try a NIBBLE!

nibble

✓286

Box 325, Lincoln, MA. 01773 (617) 259-9710

I'll try nibble!

Enclosed is my \$17.50 (for one year).

(Outside U.S., see special rates on this page.)

☐ **check** ☐ **money order**

Your subscription will begin with the next issue published after receipt of your check/money order.

Name _____

Address _____

City _____

State _____ Zip _____

NOTE:

First Class or Air Mail is required for all APO, FPO and all foreign addresses with the following additional amounts.


Europe \$32.00; Mexico and Central America \$21.00; South America \$32.00; Middle East \$35.00; Africa: North \$32.00, Central \$43.00, South \$43.00; Far East, Australia \$43.00; Canada \$18.00; APO FPO \$7.50.

All payments must be in U.S. funds drawn on a U.S. bank.

© 1980 by MICRO-SPARC, INC. Lincoln, Mass. 01773. All rights reserved.


* Apple II is a registered trademark of Apple Computer Company.

Are you looking for...



When you subscribe to a magazine, you want to get REAL SOLID INFORMATION, not just a giant catalog of ads every month... and mostly the same ads, if you've noticed.

Kilobaud Microcomputing has the meat: feature articles written by the most knowledgeable people in the field, yet written for the relative newcomer to computing. *Kilobaud Microcomputing* has more articles than any other magazine in the field... by a wide margin... regardless of fatness. In 1980 *Kilobaud Microcomputing* published 409 articles... and that included a wealth of programs which you could use.




Compare that with 133 paltry articles in *Brand B*, the "Fat Albert" of the computer field. You can get far more from your computer if you can really understand it, which is where the simple articles in *Kilobaud Microcomputing* come in. You don't need a science degree to get through it like some magazines I could mention. The practical reviews of both hardware and software in *Kilobaud Microcomputing* can save you a bundle... far more than the cost of a subscription... even for life. The wealth of programs give you things you can do with your computer... again at a fraction of the cost of buying the same program over the counter. Further, the

articles on programs *help you learn* how to write and modify programs that you have to do yourself.

When you subscribe to a magazine, you want to pay for the information, not a bunch of ads. The advertisers are already paying for them so why should you? *Kilobaud Microcomputing* has been running around 40% advertising while *Brand B* has been running 60-70%, making fat issues, but with *little real information* for you.

You want to learn about computers as fast as you can. The editors of *Kilobaud Microcomputing* are under orders (pain of death or worse) to keep the material as simple as possible so new comers will be able to learn about computers as quickly as possible. *Kilobaud Microcomputing* covers all types of microcomputers, including (to some extent) the TRS-80 though this is covered overwhelmingly in *80 Microcomputing*, a sister publication.

At \$2.95 a copy, *Kilobaud Microcomputing* is the best information buy you'll find. At \$25 a year (you save \$10.40 off the newsstand price) you're investing in the most valuable library of microcomputing you can buy... 2,960 pages in 1980!




☐ So, please bill me \$25 for one year's subscription to *Kilobaud Microcomputing*.

Canadian \$27/1 year only, US funds.
Foreign \$35/1 year only, US funds.
Please allow 4-6 weeks for delivery.

name _____
street _____
city _____ state _____ zip _____

Kilobaud Microcomputing • Box 997 • Farmingdale NY 11737

is a division of



Peterborough NH 03458

318B7

Apple to Selectric for 83 Cents

By Charles Behrens

For 83 cents and some intriguing tinkering, your Apple can control any peripheral device with a serial input port. Of course, there are many interface cards on the market designed to do just this, but they usually cost several hundred dollars. Who needs that when every Apple already has what it takes!

PET, Atari, Ohio Scientific and other microcomputer owners should also take note: the technique can be applied to virtually any system. The program listings supplied here are written in 6502 assembly language and can be readily adapted.

To test my new hardware addition,

I wrote a short software routine to control an IBM Selectric typewriter/printer. It works beautifully.

The Apple II was designed for easy interface to the outside world. All of the proper signals for controlling peripherals were brought out to the Apple II's ports, and they are just aching to be harnessed. Here's how to take maximum advantage of what the folks at Apple have already provided.

Interface Construction

To create the interface, you must do four things:

- Write a software routine to translate the Apple's internal American

Standard Code for Information Interchange (ASCII) coded data from a parallel format to the proper serially-coded format that the Selectric can use.

- Output this serial data to a latched port on the game paddle I/O connector.

- Build a simple, one-transistor circuit to supply the needed transistor-transistor-logic (TTL) to RS-232C voltage conversions. (See reference 1 for background on steps 1 and 3.)

- Add +12 and -12 V supply voltages to the two unused pins on the game paddle connector.

The best reward is that the only costs are for a little one-transistor circuit. Not only that, but the little circuit fits inside a case like the one on the plug of the game paddle controllers. How convenient can you get!

Inside the Selectric

To understand the software, you must first understand the coding format that IBM designed into its printers.

The IBM Selectrics use a six-bit code. You might ask how this can be. Given that there are 128 unique characters in the seven-bit ASCII code, how can just six bits generate enough different symbols to represent all of the letters needed? It's an old trick that the inventors of the modern typewriter developed. They were faced with the dilemma: With the great number of characters used in



Photo 1. The author's system with Carterfone S15B Selectric I at left. Notice the "customized" paper dispenser from the local hardware store. (All photos by Michael La Pointe.)

Address correspondence to Charles Behrens, PO Box 233, Kingston, RI 02881.

CHARACTER	ASCII	CORR	BCD	EBCD					
NUL	80	7F	7F	7F	@	C0	70	82	82
SOH	81	7F	7F	7F	A	C1	79	23	23
STX	82	7F	7F	7F	B	C2	76	13	13
ETX	83	7F	7F	7F	C	C3	7A	73	73
EOT	84	FC	FC	FC	D	C4	2A	0B	0B
ENQ	85	7F	7F	7F	E	C5	4A	6B	6B
ACK	86	7F	7F	7F	F	C6	73	5B	5B
BELL	87	7F	7F	7F	G	C7	23	3B	3B
BACK SPACE	88	5D	5D	5D	H	C8	26	07	07
TAB	89	2F	2F	2F	I	C9	19	67	67
LINE FEED	8A	6E	6E	6E	J	CA	43	61	61
VERT. TAB	8B	7F	7F	7F	K	CB	1A	51	51
FF	8C	7F	7F	7F	L	CC	46	31	31
CAR. RET.	8D	6D	6D	6D	M	CD	61	49	49
SO	8E	7F	7F	7F	N	CE	52	29	29
SI	8F	7F	7F	7F	O	CF	45	19	19
DLE	90	7F	7F	7F	P	D0	0B	79	79
DC1	91	7F	7F	7F	Q	D1	5B	45	45
DC2	92	7F	7F	7F	R	D2	29	25	25
DC3	93	7F	7F	7F	S	D3	25	52	52
DC4	94	7F	7F	7F	T	D4	02	32	32
NAK	95	7F	7F	7F	U	D5	32	4A	4A
SYN	96	7F	7F	7F	V	D6	31	2A	2A
ETB	97	7F	7F	7F	W	D7	75	1A	1A
CAN	98	7F	7F	7F	X	D8	62	7A	7A
EM	99	7F	7F	7F	Y	D9	67	46	46
SUB	9A	7F	7F	7F	Z	DA	54	26	26
ESC	9B	7F	7F	7F	L. BRACK.	DB	7F	7F	7F
FS	9C	7F	7F	7F	B. SLASH	DC	7F	7F	7F
GS	9D	7F	7F	7F	R. BRACK.	DD	7F	7F	7F
RS	9E	7F	7F	7F	CIRCUMFLEX	DE	7F	7F	7F
US	9F	7F	7F	7F	—	DF	7F	01	01
SPACE	A0	40	40	40	SPACE	E0	40	40	40
!	A1	81	75	75	a	E1	F9	A3	A3
"	A2	49	38	34	b	E2	F6	93	93
#	A3	70	B4	B4	c	E3	FA	F3	F3
\$	A4	04	F5	F5	d	E4	AA	8B	8B
%	A5	08	68	68	e	E5	CA	EB	EB
&	A6	68	C3	C3	f	E6	F3	DB	DB
'	A7	C9	58	58	g	E7	A3	BB	BB
(A8	34	64	64	h	E8	A6	87	87
)	A9	64	54	54	i	E9	99	E7	E7
*	AA	38	04	04	j	EA	C3	E1	E1
+	AB	13	34	43	k	EB	9A	D1	D1
,	AC	3B	F6	F6	l	EC	C6	B1	B1
-	AD	B7	81	81	m	ED	E1	C9	C9
.	AE	51	B7	B7	n	EE	D2	A9	A9
/	AF	87	E2	E2	o	EF	C5	99	99
0	B0	E4	D4	D4	p	F0	8B	F9	F9
1	B1	C6	A0	A0	q	F1	DB	C5	C5
2	B2	90	90	90	r	F2	A9	A5	A5
3	B3	F0	F0	F0	s	F3	A5	D2	D2
4	B4	84	88	88	t	F4	82	B2	B2
5	B5	88	E8	E8	u	F5	B2	CA	CA
6	B6	D8	D8	D8	v	F6	B1	AA	AA
7	B7	E8	B8	B8	w	F7	F5	9A	9A
8	B8	B8	84	84	x	F8	E2	FA	FA
9	B9	B4	E4	E4	y	F9	E7	C6	C6
:	BA	6B	08	08	z	FA	D4	A6	A6
;	BB	EB	70	70	L. BRACE	FB	7F	7F	7F
<	BC	7F	7F	10		FC	7F	7F	7F
=	BD	93	20	20	R. BRACE	FD	7F	7F	7F
>	BE	7F	7F	38	WAVE	FE	7F	7F	7F
?	BF	07	62	62	RUB	FF	7F	7F	7F

Table 1. ASCII-to-Selectric conversion table. Any Selectric can support all three codes, depending on which type element is installed by the user (reference 1).

9580-	7F	7F	7F	7F	8B	7F	7F	7F
9588-	5D	2F	6E	7F	7F	6D	3E	7F
9590-	7F	7F	7F	7F	7F	7F	7F	7F
9598-	7F	7F	7F	7F	7F	7F	7F	7F
95A0-	40	75	34	B4	F5	68	C3	58
95A8-	64	54	04	43	F6	81	B7	E2
95B0-	D4	A0	90	F0	88	E8	D8	88
95B8-	84	E4	08	70	10	20	38	62
95C0-	82	23	13	73	0B	6B	5B	3B
95C8-	07	67	61	51	31	49	29	19
95D0-	79	45	25	52	32	4A	2A	1A
95D8-	7A	46	26	7F	7F	37	76	7F
95E0-	40	A3	93	F3	8B	EB	DB	BB
95E8-	87	E7	E1	D1	B1	C9	A9	99
95F0-	F9	C5	A5	D2	B2	CA	AA	9A
95F8-	FA	C6	A6	7F	7F	01	52	20

Table 2. This is the cross-reference table I am currently using with my Selectric typewriter/printer. I have adapted some of the characters for special uses, so this table does not exactly correspond with Table 1.

written print, how does one make an efficient keyboard for ten-fingered humans? As a solution, the shift key was invented. Suddenly only half as many separate keys were needed to create the entire character set. When the Teletype came along, the designers realized that the same trick could be used to speed up transmitted electronic information.

Naturally, when IBM Selectrics were outfitted as data terminals, the old dog used the same old trick. And it is this same trick that our program uses to generate any character desired. When the Selectric is to be sent an uppercase letter, a shift-up must precede it. Any letter sent from then on will be in uppercase until a shift-down code is transmitted. The software technique for doing this will be described shortly.

Next, you need to understand that IBM Selectrics use three different six-bit codes. The reason for this is that there are three different methods of configuring the letters on the type element. The style of type element installed in the machine determines which code is to be used. If the wrong code is transmitted to the Selectric, it will print nonsense. The codes used are extended binary-coded decimal (EBCD), binary-coded decimal (BCD) and correspondence code. (See Table 1.)

EBCD and BCD printheads are fine for utility printing, but if you need to do a great deal of word processing, then get a correspondence-code element. It offers a greater variety of character fonts (e.g., script, oversize, special characters, etc.). Conveniently, every style may be used on the same machine. It is not necessary to own separate typewriters; just different type elements.

By relying on a software method of controlling the Selectric, three differ-

ent look-up tables can be created to handle each style of code. This would be expensive to do with a hardware approach. But with software, you can load any of the codes separately. This offers the versatility of having all three while only tying up a minimal amount of memory space for one at a time.

Now that these points are understood, let's move into the workings of the software.

The Program

The 6502 assembly-language routine (see Listing 1) is used for translating the Apple's internal character data to the needed serial code (references 2 and 3). The program is short enough to fit in even a 16K Apple. This program will be called in every mode of the Apple's operation. Anything that can be displayed on the video screen can be printed. In other words, it may be used for word processing, BASIC program listings, monitor listings and even to obtain hard copies of program output.

The first duty of the program is to intercept the desired ASCII character before it is sent to the usual output routine in the Apple II's Monitor. Normally, this is the COUT1 routine at \$FDF0 (the "\$" sign indicates a hexadecimal number), used for displaying output on the video screen. When a character is to be output, the routine at \$FDFF named COUT reads the values at \$36 and \$37 to determine the address of the output routine. Because the output routine is indirectly called, it is easy to divert the program flow by substituting a new address. This is a technique called vectoring.

The routine listed here loads its own beginning address to locations \$36 and \$37, instead of the address for COUT1. In this way, COUT will vector to the printing routine when it tries to output a character. For convenience, the print routine branches to COUT1 after printing so that the character is also displayed on the video screen.

Once the printing routine has been called, its first step is to save all of the working registers in memory. This is so that everything will be intact when the routine returns from the call.

At the beginning of the routine, the accumulator contains the desired ASCII character. The code for this character is also stored separately in location \$FC of page zero for easy recall. Execution then proceeds into the

FORTH FOR/MATT™ SCREEN EDITOR

A MUST FOR THE SERIOUS FORTH PROGRAMMER

- All code is Forth-79 standard. Each line of code is fully explained and flow-charted (Forth style) for easy modification.
- This editor works just like the popular word processors on the market except it is written in high level forth and is confined to the 1024 byte boundary of a forth screen.
- There are over 20 different commands for cursor positioning, text modification, tabs, relocating lines, spreading lines, and moving lines to other screens.
- Insert mode is toggled on and off for midstream insertions and deletions. Text ahead of CP is moved right during insertion and left during deletion if insert mode is on.
- Column position is displayed at all times.
- Bomb proof — all unused control codes are trapped.
- Must be used with a CRT that has cursor addressing or with a memory mapped video.
- Send check or money order in the amount of \$50.00 and receive complete source code, flowcharts, documentation, and instructions for bringing up on your system.

KV33 CORPORATION
P.O. BOX 27246
TUCSON, AZ 85726
(602) 889-5722



✓ 289

ALPHA MICRO USERS: Be a whiz with Word Wizard™

Professional quality word processing at an affordable price. Word Wizard is in use worldwide.

Word Wizard makes you a whiz with a clearly written 110 page manual filled with examples and an on-line help facility is built into the editor.

Word Wizard detects and corrects spelling errors and typos with a 70,000 word on-line dictionary.

The screen editor has global search & replace, block move/copy, wraparound, file merge, and virtual memory to edit large documents.

Word Wizard does true proportional spacing, table of contents, bold printing, underlining, super- and subscripts, footnotes, tables, fancy running titles with page numbering (even in Roman numerals), centering, sorted index, form letters, automatic hyphenation using the dictionary, and MUCH MORE! \$599 and worth it!

Available on floppy, Hawk, and Phoenix disks (add \$100 for Hawk, \$350 for Phoenix, or supply your own). Send for free brochure or \$15 for complete 110 page manual. For personal service phone (408) 496-0855.

Word Wizard Division,
Toxen Computer Systems ✓118
950 Meridian Ave., Suite 34
San Jose, CA 95126 USA

THE NEW NEVADA COBOL!

**At \$149.95 you can't buy
a better COBOL or one
residing in less memory.**

Now with the new Nevada COBOL, you can use the programs developed by professional business programmers over the past twenty years to run the big IBM machines. And you can develop and tailor programs on your micro and run them on your micro or recompile and run them on any mainframe computer. What's more you can do it for about one-fifth the cost of comparable COBOL compiler systems.

Almost all the popular microcomputers work with the CP/M operating system we use including Apple, TRS-80, North Star, Superbrain, Cromemco and so on.

Check the features; you'll go Nevada COBOL.

A powerful subset of ANSI-74, Nevada COBOL requires a scant 16K of RAM. It's available on 8" CP/M standard single density or 5-1/4" diskettes. Price includes diskette and manual. Price for manual only, \$24.95.

Four COBOL applications packages available too.

Four COBOL applications packages are currently available. Each is priced at \$24.95 for the diskette. The 73 page manual covering all four applications costs an additional \$24.95. The manual carries complete COBOL source code listings and superior documentation.

Package #1 is the Budget Plan Report Generator. Here's an extraordinary time saver and planning aid for both start-up and well established businesses.

Package #2 is the Personal Financial Planner to give you some eye opening insights into your own personal spending habits.

Package #3 is Labels so you can print name and address labels.

Package #4 is Pre-COBOL for use as a pre-processor of COBOL source programs. A great programming aid.

Order today or write for complete details.

Phone (415) 751-1522 or address Ellis Computing, 600 41st Ave, San Francisco, CA 94121. Nevada Cobol is also available at Lifeboat Associates, Discount Software, Westico, Business Micro Products, Computer Information Exchange and other quality computer stores. Mastercard, Visa, C.O.D.s, or checks accepted. California orders please include sales tax.

CP/M, TRS-80 and IBM are TM's of Digital Research, Tandy Corp. and I.B.M. respectively.



ELLIS COMPUTING
SOFTWARE TECHNOLOGY

heart of the program.

A check is made to determine if a carriage return is to be output. If so, then three things must happen. First, the Carriage Return must be preceded with a Shift-Up command. Second, a carriage return character must be sent. Third, an extra long delay is needed to give time for the carriage to physically move back to the start of the next line before trying to print the next character.

The extra shift-up is needed to work properly with the word processor program, Apple Writer. Otherwise, the Selectric sometimes will not properly decode the carriage return character. Obviously word processing with Apple Writer is not the only use for the printer. During those other times, it is necessary to replace the extra shift-up character to a null character to prevent errors. Change the \$9C in location \$9DF7 of the program to a \$FF and you'll be all set.

The indexed addressing mode of the 6502 is invaluable for determining the properly cross-referenced Selectric code. Knowing that the ASCII

characters are represented by the values \$80 through \$FF, the ASCII-to-Selectric cross-referencing table is loaded into locations \$80 through \$FF of a page in memory immediately following the program. (See Table 2.) The page number containing the look-up table is then set as the base address of the indexed addressing instruction.

The value of the needed ASCII character is then loaded into the Y register. By adding the value of the Y register to the base address, the right code in the look-up table can be found with just one instruction! This value is then tucked away for safe-keeping in location \$FB of page zero.

Once the Selectric character code is obtained, the next step is to figure out whether it is an upper or lowercase letter. Not only that, but also whether or not the last letter sent was of the same case. This is done by comparing the most-significant bit (MSB) of the character code with the MSB in location \$FA. The MSB denotes the case of the letter, and location \$FA holds the case of the last letter sent.

If the new character is not of the

Listing 1. This 6502 assembly-language routine is the foundation of the Apple/Selectric interface described in this article. The same logic will also work with Atari, PET, Ohio Scientific and other 6502-based micros with only minor changes. Due to vectoring, it can be located in any convenient section of memory. Note: change location \$94F7 to \$FF when not using the Apple Writer word processor. (See text.)

94D4-	A9 E0	LDA	#\$E0	**PRINTER OUTPUT ROUTINE
94D6-	85 36	STA	\$36	LOAD \$94E0 AS VECTOR BRANCH FOR 'COUT'
94D8-	A9 94	LDA	#\$94	LOW BYTE IN \$36
94DA-	85 37	STA	\$37	HIGH BYTE IN #37
94DC-	20 51 A8	JSR	\$A851	SET D.O.S. VECTORS
94DF-	60	RTS		
94E0-	48	PHA		**SAVE-SAVE ALL REGISTERS
94E1-	08	PHP		
94E2-	86 FE	STX	#\$FE	
94E4-	84 FF	STY	#\$FF	
94E6-	20 F0 94	JSR	\$94F0	JUMP TO **BEGIN
94E9-	A6 FE	LDX	#\$FE	**RESTORE-RESTORE ALL REGISTERS
94EB-	A4 FF	LDY	#\$FF	
94ED-	28	PLP		
94EE-	68	PLA		
94EF-	60	RTS		RETURN TO CALLING PROGRAM
94F0-	85 FC	STA	#\$FC	**BEGIN-THE MAIN PROGRAM
94F2-	C9 8D	CMP	#\$8D	STORE THE ASCII CHARACTER IN \$FC
94F4-	D0 0C	BNE	\$9502	CHECK TO SEE IF IT IS A CARRIAGE RETURN
94F6-	A9 9C	LDA	#\$9C	IF NOT, BRANCH TO **LOOKUP
94F8-	20 27 95	JSR	\$9527	ELSE, OUTPUT A 'SHIFT UP'
94FB-	A9 ED	LDA	#\$ED	JUMP TO **SERIAL
94FD-	20 27 95	JSR	\$9527	THEN A CARRIAGE RETURN
9500-	F0 4B	BEQ	\$954D	JUMP TO **SERIAL
9502-	A8	TAY		**LOOKUP-CROSS REFERENCE ASCII TO SELECTRIC
9503-	B9 00 95	LDA	\$9500, Y	USE Y-REGISTER AS OFFSET WITHIN TABLE
9506-	85 FB	STA	#\$FB	LOAD FROM TABLE
9508-	29 80	AND	#\$80	STORE FOR SAFE KEEPING
950A-	C5 FA	CMP	#\$FA	
950C-	85 FA	STA	#\$FA	**CASE-CHECK CURRENT CASE AGAINST LAST
950E-	F0 0E	BEQ	\$951E	MASK OFF BITS 0-6
9510-	90 07	BCC	\$9519	CHECK M.S.B. AGAINST LAST CHARACTER SENT
**SHIFT DOWN-SEND A SHIFT DOWN				

More →

ANADEx • TI • APPLE • VERBATIM

More

The first step of the output subroutine is to mask the no longer needed MSB to a logic 1 for later use as the stop bit. Next, the program clears the carry bit of the 6502. This provides the needed start bit. The 0, now in the carry bit, is transferred to annuncia-

A vintage computer terminal, likely from the 1970s or 1980s. The screen displays a bar chart with approximately 15 vertical bars of varying heights. The chart is titled "RESEARCH" at the top and "INFORMATION" at the bottom. To the right of the screen is a control panel with several buttons and a small display. Below the screen is a keyboard. The entire unit is housed in a dark, rectangular casing.

\$599

(includes Disk Drive)

Fully compatible with Radio Shack's operating system TRSDOS.

- One, two, three, four drive configurations.
- 40 track and 80 track available
- 90 day warranty, 100% parts and labor
- Extended warranty available

Complete upgrade includes one mini-disk drive, power supply, controller, and mounting hardware. IMMEDIATE DELIVERY.

	OUR PRICE	RADIO SHACK	SAVINGS
Complete one drive kit	\$599.	\$849.	29%
Additional internal drive	265.	399.	34%
External drive	299.	499.	32%
80 track drive	add 120. ea	N/A	
16K memory (required to use drives)	49.	119.	59%

Model III 32K w/VR Data
two drive assembly

RS232 Adapter Board

WE DISCOUNT RADIO SHACK & OTHER COMPUTER PRODUCTS

To order call toll free (800) 345-8102, or (215) 461-5300 in PA.



\$299*

We've broken through the three hundred dollar barrier.

- Fully compatible with TRSDOS™
 - Fully compatible with RS Drives
 - Easy plug-in installation
 - Rigid extender board
 - 90 day warranty — 100% parts and labor
 - Extended warranty available — \$45/year
 - Choice of Tandon or MPI drives
- * Includes power supply, enclosure, single sided — 40tk drive and **EXTENDER BOARD**

1 sided 80tk - \$419	2 sided 40tk - \$419
2 sided 80tk - \$549	

Starwriter 25 (P)	1599.00
Centronics 739	\$750.00
MX80	\$485.00
Lexicon Modem	\$135.00

PRICES SUBJECT TO CHANGE WITHOUT NOTICE

PUBLISHED PRICE REFLECTS CASH DISCOUNT DEALERSHIPS AVAILABLE
VR Data, a manufacturer of innovative computer products, is known worldwide for quality dependability and prompt, personal service since 1972.



VR Data Corporation • 777 Henderson Boulevard • Folcroft, PA 19032

Listing 1 continued.

954A-	D0 F8	BNE	\$9544	LOOP BACK TO **OUTER
954C-	60	RTS		RETURN
954D-	A9 85	LDA	#\$85	**LONG DELAY-FOR CARRIAGE RETURN
954F-	85 FB	STA	\$FB	SET COUNTER
				STORE COUNTER IN \$FB
9551-	20 42 95	JSR	\$9542	**MACRO
9554-	C6 FB	DEC	\$FB	JUMP TO **DELAY
9556-	D0 F9	BNE	\$9551	DECREMENT COUNTER
				LOOP BACK TO **MACRO
9558-	A5 FC	LDA	\$FC	**VIDEO
955A-	48	PHA		RELOAD ORIGINAL ASCII CODE
955B-	29 F0	AND	#\$F0	SAVE IT ON THE STACK
				MASK OFF BITS 0-3
955D-	C9 C0	CMP	#\$C0	**UPPERCASE-ASCII CHARS. \$C0-\$DF
955F-	F0 04	BEQ	\$9565	IS IT CAPITAL A-O, ETC.?
9561-	C9 D0	CMP	#\$D0	BRANCH TO **INVERSE
9563-	D0 07	BNE	\$956C	IS IT CAPITAL P-Z, ETC.?
				BRANCH TO **LOWERCASE
9565-	68	PLA		**INVERSE-OUTPUT AN INVERSE CHARACTER
9566-	29 3F	AND	#\$3F	GET CHARACTER FROM STACK
9568-	20 F0 FD	JSR	\$FDF0	MASK OFF BITS 6 & 7
956B-	60	RTS		JUMP TO 'COUT1'
				RETURN TO **RESTORE
956C-	C9 E0	CMP	#\$E0	**LOWERCASE-ASCII CHARS. \$E0-\$FF
956E-	F0 04	BEQ	\$9574	IS IT SMALL A-O, ETC.?
9570-	C9 F0	CMP	#\$F0	BRANCH TO **NORMAL
9572-	D0 07	BNE	\$957B	IS IT SMALL P-Z, ETC.?
				BRANCH TO **SAME
9574-	68	PLA		**NORMAL-OUTPUT A NORMAL CHARACTER
9575-	29 DF	AND	#\$DF	GET CHARACTER FROM STACK
9577-	20 F0 FD	JSR	\$FDF0	MASK OUT BIT 5
957A-	60	RTS		JUMP TO 'COUT1'
				RETURN TO **RESTORE
957B-	68	PLA		**SAME-OUTPUT CHARACTER AS IS
957C-	20 F0 FD	JSR	\$FDF0	GET CHARACTER FROM STACK
957F-	60	RTS		JUMP TO 'COUT1'
				RETURN TO **RESTORE

tor 0 in the first cycle of the output subroutine loop, and is followed by a call to the 7.43 ms delay loop.


Next, the accumulator is right-shifted to place the first bit of the character code into the carry bit. The annunciator 0 output is then set or cleared to reflect the value of the carry bit. Again, the level is held for 7.43 ms. This cycle continues until all six bits of the character code, a seventh bit for parity checking, and the logic 1 MSB as a stop bit are transferred serially to the annunciator 0 port.

The exact timing of each delay is easily adjusted by changing the limits of the delay loops. Since the Apple II executes about one machine cycle per microsecond, the limits were determined by counting the number of machine cycles per loop and dividing this number into 7.43 ms. Bear in mind that if this were being timed by hardware, delicate timing circuits would have to be used. Again, because software can be easily changed, it can be much less trouble.

Only one more task is left for the annunciator port to have all of the proper data. That is to provide for an

THE BIGGEST NAME IN LITTLE COMPUTERS™

TRS-80® Model II—Your Best Buy
In a Business Microcomputer



UP
TO
15%
OFF!
on

TRS-80™ computers,
software and peripherals

Similar values on all merchandise

CALL COLLECT:

915-283-2920 ✓214

Van Horn Office Supply

701 W. Broadway -- P O Box 1060

Van Horn, Texas 79855

Dealer G055

Form F48 Provided

Standard Warranty on Merchandise

THE NATIONWIDE SUPERMARKET OF SOUND®



WP6502®

the finest word processor for

OHIO SCIENTIFIC

New Powerful Version 1.3

WP6502 is accepted as being the best word processor for OSI computers. That was version 1.2. Now there's Version 1.3! V1.3 is the ultra simple, professional and powerful version of WP6502. In addition to the exclusive features that made V1.2 the leader, V1.3 has built-in memory and disk tests, headers, true proportional justify, print from anywhere, super-simple editing, and on and on. On cassette and disk (65D or 65U). Priced from \$50 to \$250.


Get Our Brochures FREE!

We are not just word processing either! As the most reputable name in OSI software, Dwo has been constantly asked to release non-word processing software. Finally we have! Games, utilities and business applications that are absolutely the best (we guarantee it).

Dwo Quong Fok Lok Sow ✓87
23 East 20th Street
New York, NY 10003
(212) 673-6310




A-D & D-A CONVERTER



JBE one channel A-D & D-A Converter can be used with any system having parallel ports • Interfaces with JBE Parallel I/O Card • D-A conversion time — 5 μ s • A-D conversion time — 20 μ s • Uses JBE 5V power supply • Parallel inputs & outputs include 8 data bits, strobe lines & latches • Analog inputs & outputs are medium impedance 0 to 5 volt range.

79-287 ASSM. \$79.95
Bare Board \$39.95 Kit \$59.95


6502 MICROCOMPUTER



JBE's 4 1/2 x 3 1/4 dedicated controller features: • 1024 bytes RAM (two 2114s) • 2048 bytes EPROM (2716) • Uses one 6522 VIA (comp. doc. incl.) • Interfaces with JBE Solid State Switches & A-D & D-A Converter • Uses JBE 5V power supply • 2716 EPROM available separately (2716 can be programmed with an Apple II & JBE EPROM Programmer & Parallel Interface) • 50 pin connector included in kit & assm.

80-153 ASSM. \$110.95
Bare Board \$49.95 Kit \$ 89.95


SOLID STATE SWITCH



Your computer can control power to your printer, lights, stereo & any 120VAC appliances up to 720 watts (6 amps at 120VAC). Input 3 to 15VDC • 2-14MA TTL compatible • Isolation — 1500V • Non zero crossing • Comes in 1 or 4 channel version.


79-282-1 ASSM. \$13.95
Bare Board \$6.95 Kit \$10.95
79-282-4 ASSM. \$49.95
Bare Board \$24.95 Kit \$39.95

APPLE II DISPLAY BOARD



80-144 ASSM. \$49.95
Bare Board \$25.95 Kit \$42.95


Z80 MICROCOMPUTER



JBE's 4-1/8"x3-1/4" single board dedicated computer is designed for control functions. It features: • A Z80 Microprocessor software compatible with the Z80, 8080 & 8085 Microprocessors • Uses a Z80 PIO chip for I/O which has 2 independent 8 bit bidirectional peripheral interface ports with handshake & data transfer control • Uses one 2716 EPROM (2K) & two 2114 RAM memories (1K) • Single 5V power supply at 300MA req. • Clock frequency is 2MHz, RC controlled • Board comes with complete doc. • 50 pin connector is included • 2716 EPROM available separately.

80-280 ASSM. \$129.95
Bare Board \$49.95 Kit \$119.95

PRINTER INTERFACE



JBE Parallel Printer Interface interfaces your Apple II® to Centronics® compatible printers. This 3" x 4" board features: on board ROM compatible with Integer Basic, Applesoft® and Pascal® • Has one 8 bit parallel latched output port with selectable positive or negative strobe and one bit input selectable for Ready or Ready • Cable and Connectors available separately.

80-297 ASSM. \$79.95
 Kit \$69.95
4 ft. Std. Dip Jumpers 16 pin \$ 4.25
Champ Connector \$ 9.95

POWER SUPPLIES

• Use wall transformers for safety
• Protected against short circuit and thermal breakdown.

5 VOLT POWER SUPPLY

Rated at 5V 500MA • Operates JBE A-D & D-A Converter, Z80 & 6502 Microcomputers, 8085 & 8088 Microcomputers.

80-160 ASSM. \$20.95
Bare Board \$8.95 Kit \$16.95

± 12 VOLT POWER SUPPLY

Rated at ± 12V 120MA • Can be used as a single 24V power supply • Ideally suited to OP-AMP experiments.


80-161 ASSM. \$22.95
Bare Board \$8.95 Kit \$18.95

ICS

6502	\$9.95
6522	\$9.95
Z80 CPU	\$9.95
Z80 PIO	\$9.95
2716	\$14.95
2716 Programmed	\$19.95

• Has run-stop, single step switch • Has 16 address LEDs, 8 data LEDs & 1 RDY LED
• All lines are buffered.


6522 APPLE II INTERFACE



• Interfaces printers, synthesizers, keyboards, JBE A-D & D-A Converter & Solid State Switches • Has handshaking logic, two 6522 VIAs & a 74LS05 for timing • Inputs & outputs are TTL compatible.

79-295 ASSM. \$69.95
Bare Board \$39.95 Kit \$59.95

2716 EPROM PROGRAMMER



JBE 2716 EPROM Programmer was designed to program 5V 2716 EPROMS • It can also read 2716s. It interfaces to the Apple II using JBE Parallel I/O Card & four ribbon cable connectors • An LED indicates when power is being applied to the EPROM • A textool zero insertion force socket is used for the EPROM • Comes with complete doc. for writing and reading in the Apple II or Apple II+ • Cables available separately.

80-244 ASSM. \$49.95
Bare Board \$24.95 Kit \$39.95
2 Ft. Ribbon Cable \$ 4.25

BARE BOARDS

APPLE II EXTENDER BOARD

3 1/2" x 2 1/2". Price includes 50 pin Connector.

80-143 \$12.95

8085 3 CHIP SYSTEM

State-of-the-art system using an 8085, 8156 & either an 8355 or 8755 • Instruction set 100% upward compatible with 8080A.

Bare Board \$24.95

8088 5 CHIP SYSTEM

An 8086 family microcomputer system using an 8088 CPU, 8284, 8155, 8755A & an 8185.

Bare Board \$29.95

CRT CONTROLLER

This intelligent CRT Controller uses an 8085A CPU & an 8275 Integrated CRT Controller. It features: • 25 lines (80 Char./line) • 5x7 dot matrix • Upper & lower case • two 2716s (controller & char. generator) • serial interface RS232 & TTL • baud rates of 110, 150, 300, 600, 1200, 2400, 4800 & 9600 • keyboard scanning system • unencoded keyboard is req'd • uses +5V & ± 12V power supplies • Doc. includes program listing & composite video circuit.

Bare Board only (Doc. incl.) \$39.95
Programmed 2716s each \$19.95



JOHN BELL ENGINEERING, INC.

ALL PRODUCTS ARE AVAILABLE FROM JOHN BELL ENGINEERING • P.O. BOX 338
REDWOOD CITY, CA 94064 • ADD SALES TAX IN CALIFORNIA • ADD 5% SHIPPING & HANDLING

(415) 367-1137

10% OUTSIDE U.S.A.

MC

VISA




Photo 2. The 83-cent circuit before final assembly. The DIP socket was wire-wrapped to the pins below and the case glued shut.




Photo 3. Main circuit board with peripherals connected. Plug game paddles and the new RS-232C output into game paddle socket (upper right).


extra long delay if a carriage return character is sent. Another delay loop is used to call the 7.43 ms loop several times to provide a sufficient pause.

At this point in the processing, the routine could return directly to COUT1. However, with a little more attention to details, I added a subroutine to return inverse video characters if uppercase letters were printed.

This is done by masking the normal video mode ASCII codes. With lower-case letters bits 4-7 were masked to allow them to be displayed in normal video. The other characters are output without change. As this is the same technique many word processor programs employ, it is especially convenient for proofreading during printout.

The program in Listing 1 locates the routine at a convenient place in memory of a 48K disk system. By setting the HIMEM limit to just below its starting address, it is protected from most BASIC applications.

However, there may be some systems in which it would be better to locate it at a different address. It is relatively straightforward to relocate the program wherever you want by attending to the jump-to-subroutine



Microcomputers are coming — ride the wave! Learn to program with a new course written for the beginner. Learn BASIC the language of the small computer and the most easy-to-learn computer language in widespread use. A self-instruction course which takes you from complete ignorance step-by-step to real proficiency with a unique style of graded hints. 60 illustrated lessons teach the five essentials of good programming: problem definition; flow-charting; coding the program; debugging; clear documentation. And you don't even need a computer!

Price: \$22.95 including shipping.

Also available:

Design of Digital Systems — **\$19.95**

Digital Computer Logic and Electronics — **\$14.95**

Send check with order to:

Cambridge Learning Inc.,
1 Judith Drive
North Reading, MA 01864

or call (617) 664-3657 with Mastercard or VISA.

Mass. residents add 5% Sales Tax.
\$5 discount for orders over \$30.00 ✓ 271

CAMBRIDGE LEARNING INC.

Need a solution for Floppy Disk or R/W Head problems?

FDL

Floppy Disk Lube

Just THREE drops can:

- Prolong useful disk life.
- Increase head life.
- Allow initialization of "problem" disks.
- Save 'unbootable' disks.
- Reduce 'glitching' problems.
- Cut nuisance problems.

FLOPPY DISK LUBE - 1/2 oz.
WITH APPLICATOR. **\$4.00**

Add \$1.50 shipping and handling. Ohio residents add 5 1/2% sales tax.

DOSWARE, INC.
P.O. Box 10113
Cleveland, Ohio 44110

RS-232 Standard Pin Designation	
1.	Ground
2.	Data (Transmit)
3.	Data (Receive)
4.	Request to Send
5.	Clear to Send
6.	Data Set Ready
7.	Ground
8.	Carrier Detector
9.	Data Set Test
10.	Data Set Test
11.	Unassigned
12.	Secondary Carrier Detector
13.	Secondary Clear to Send
14.	Secondary Data (Transmit)
15.	Xmit. Clock (DCE)
16.	Secondary Data (Receive)
17.	Rcvr. clock (DCE)
18.	Unassigned
19.	Secondary Request to Send
20.	Data Terminal Ready
21.	Signal Quality Detector
22.	Ring Indicator
23.	Data Signal Rate Selector
24.	Xmit Clock (DTE)
25.	Unassigned

Table 3. DB-25 plug. Only pins 3, 5 and 7 are used here. Perhaps you can figure out a way to use the transmit signals so that the terminal can transmit as well as receive.

(JSR) instructions.

RS-232C Signals from Apple II

RS-232C signal standards were designed to supply large enough voltage swings that they would not be overcome by transmission noise on the wire between the sender and the receiver. For this reason, voltage levels were designed to be from +5 to +15 V for logic level 1 and -5 to -15 V for logic level 0. The only thing that the Selectric needs at its input port is an RS-232C serial data line and a ground reference. What this implies is that a simple single-pair speaker wire will carry all of the information needed. It may be run fairly long distances and there is no need for expensive ribbon cable.

The annunciator 0 port of the game paddle I/O connector can only provide a TTL level voltage swing of 0-5 V. Fortunately, it is a simple task to amplify these levels to RS-232C compatible voltages with a one-transistor circuit (see Fig. 1). The entire circuit consists of only five small parts, so with very little effort it can be built on top of a 16-pin dual-inline plug (DIP). A small cap can then be glued

over the circuit, leaving only the speaker wire running out of it. Any time there is a need to disconnect the printer, just pull the plug.

Additionally, it is not too difficult to connect another DIP socket onto the top of the transistor circuit cap. This can carry signals connected in parallel to the game paddle connector beneath it. That way the game paddles may remain plugged in while the

printer is being used, eliminating wear and tear on the plugs.

The parts for this circuit are cheap and easy to find. By using a few junk box components and a couple of Radio Shack parts, my total costs were (yes) exactly 83 cents! I highly recommend building a test circuit on an experimenter's protoboard to check the circuit performance before soldering it into its case. That will help prevent




Fig. 1. TTL-to-RS-232 driver circuit. This one-transistor circuit is the major cost factor in this project! Harness it properly and it can also be used to drive modems, high speed printers, synthesizers or any other serial input device.


DISCOUNT PRINTER RIBBONS

Brand New, Top Quality, Exact Replacement Ribbons & Cartridges. These Ribbons Produce **Super Jet** Black Impressions and Ultra Reliable Print Life. They Are Delivered to Your Door Promptly for Much Less Than Most Retail Stores

★SPECIAL! BUY 10 and GET ONE FREE!

YOUR PRINTER	PACK SIZE	RETAIL LIST**	YOUR WHOLESALE PRICE	SIZE	COMMENTS	CAT. ORDER#
RADIO SHACK LP111, LPV	one/pk	13.95/cart	8.95/Reload rib. only (8.95 ea)	.500" x 45'	Nylon Incl Instr	R-T3
RADIO SHACK LP111, LPV	3/pk	18.95/3 pk	11.95/3 pk (3.98 ea)	.563" x 45'	Nylon Jet Blk	C-700
CENTRONICS. MODS 700 to 703	3/pk	18.95/3 pk	11.95/3 pk (3.98 ea)	.563" x 45'	Nylon Jet Blk	C-700
CENTRONICS 100, 101A, 102, 103, 300, 301, 306, 308, 330, 358, 398, 500, 501, 503, 508, 588, 620, 820.	3/pk	26.33/3 pk	17.55/3 pk (5.85 ea)	1" x 108'	Nylon Jet Blk	C-100
CENTRONICS 704-705	1/pk	16.95 ea	13.95/Giant Cart (13.95 ea)	5/16" x 210'	Giant Cart	C-7045
IBM "SILVER DOLLAR" Sys. 34, Sys. 32 MDLA, Series IMDL4974, 5256, 3287, 3770, 3771-3774, 4974, 5100, 5103, 5110, 5228, 5256, 5320MDLA	5/pk	5.80 ea	14.90/5 pk (2.98 ea)	9/16" x 30'	Nylon Jet Blk	R-300
IBM - HARMONICA 1/2" SERIES I, MOD 4973/II, 3200, 3289, MOD 2.	3/pk	9.42 ea	20.85/3 pk (6.95 ea)	1/2" x 108'	Nylon Jet Blk	C-350
TELETYPE MOD 33, 28, 35, 37, 38, 88.	10/pk	2.40 ea	13.90/10 pk (1.39 ea)	1/2" x 36'	Nylon Jet Blk	R-450
DIABLO HYTYPE II (M/S BLK) HI YIELD. FITS 70 PRINTERS!	1/pk	9.31 ea	6.87 ea (6.87 ea)	5/16" x "High Yield"	300,000 plus imp.	C-511
QUME (FITS 80 PRINTER MODS)	3/pk	18.00/3 pk	13.95/3 pk (4.65 ea)	1/4" x 310'	Multistrike Film	C-525
WANG M/S. 5541W, WC, 5581, WD, 6581W, 2281W	1/pk	6.85 ea	5.95 ea (5.95 ea)	5/16" x 393'	Multistrike Film	C-550
DEC 1/2 x 40YD.	3/pk	17.77/3 pk	12.95/3 pk (4.32 ea)	1/2" x 120'	Double Spools	R-600
DEC 1/2 x 60YD.	3/pk	20.12/3 pk	14.25/3 pk (4.75 ea)	1/2" x 180'	Double Spools	R-644
NEC SPINWRITER	4/pk	23.40/3 cart	23.60/4 pk rb. reload (5.90 ea)	1/2" x 51'	Nylon/Ex Lng Life	R-400

40% OFF!! OR MORE!



TERMS:

MINIMUM PURCHASE - \$20
PAYMENT BY: C.O.D.(UPS), CHECK, MASTER CARD, OR VISA CHARGE CARD.

VOLUME DISCOUNTS:

20 - 50 PACKS 10%
51 - 100 PACKS 15%
*UNDER \$20, ADD \$5 HANDLING.
**APPROX. RETAIL. PRICE VARIES.

ANCIE LABORATORIES 187

9204 Baltimore Blvd. 301-345-6000 (Wash. D.C. Local)
College Park, MD 20740 301-792-2060 (Balto. MD Local)
800-638-0987 (National)

NAME _____
ADDRESS _____
CITY _____ STATE _____ ZIP _____

ANCIE Laboratories 301-345-6000 (Wash. D.C. Local)
9204 Baltimore Blvd. 301-792-2060 (Balto. MD Local)
College Park, MD 20740 800-638-0987 (National)

QTY CAT.# AMT.

TOTAL _____

☐ Check Enclosed
☐ C.O.D.
☐ VISA
☐ MASTER CHARGE

ACCT. # _____
EXP. DATE _____
MIN. ORDER \$20
PRICES SUBJECT TO CHANGE

wasted time if there is a need to debug the circuit.

The final part of creating an RS-232C port is the easiest to understand, but it goes against the grain of every Apple II owner I know. Don't worry! It's really quite minor, but it does mean modifying the Apple's main board. This is your chance to enhance the original design. It is nothing that is not already right there on the board; it's just not in enough places. This modification will improve your Apple II just by adding two small jumpers. The main consideration before taking this step should be the loss of the warranty. If the warranty loss is outweighed by your improvement, then plunge onward.

The final step is to run two wires to the two unused pins of the game paddle connector. These provide the +12 and -12 V supplies to the transistor circuit for the RS-232C voltage references. Check the Apple II Reference Manual (a great piece of work!) and observe that slot 7 has both of the needed voltages readily available and right next to the paddle connector.

The first wire should be run from

pin 33 of slot 7 to pin 9 of the paddle connector. The other wire is run from pin 50 of slot 7 to pin 16 of the game paddle connector. To attach the wires, you must get at the back of the main circuit board.

First, turn the Apple II off and remove all cables (line cord, video, cassette, etc.). Then lift off the lid from the Apple II by pulling up sharply at the rear of the lid to unsnap the Hedlok fasteners. Set the lid aside.

Disconnect all plug-in cards (disk drive, modem, etc.) and any remaining video or game connector cables.

Next, clear a large, clean work surface and protect it with a pad of some sort (e.g., a scrap of rug). Place the Apple II upside down upon it.

Unscrew the four black screws just under the front edge of the keyboard (see Fig. 2) and carefully set them aside. Next, unscrew the two screws on the outer edge of the left side, and the same on the right side. Unscrew the two last screws on each side of the back edge. Do not lose these screws!

Now, while tightly holding the top and bottom sections together, turn

the Apple II right-side up. Slowly lift up the front edge of the top section about two inches. Unplug the keyboard connector from the main board. Lay the top section aside.

Unplug the power supply by unclipping the metal fasteners. Unplug the speaker.

The main circuit board is attached to the bottom section by six nylon board supports and one 6/32 nut. First unscrew the nut from the center of the board. Then, starting at one end and working across, unclip the




Fig. 2. Remove only the screws indicated here. Be careful not to separate the top and bottom until the keyboard connector is unplugged.

OSI COMPATIBLE HARDWARE

IO-CA10X SERIAL PORT \$125
ACIA based RS-232 serial printer port. DIP SWITCH selectable baud rates of 300-9600. Handshaking (CTS) input line is provided to signal the computer when the printer buffer is full. Compatible with OS-65U V1.2 and OS-65D.

IO-CA9 PARALLEL PORT \$175
Centronics Standard Parallel printer interface for OSI computers. The card comes complete with 10 ft. of flat ribbon cable. Compatible with OS-65D and OS-65U software.

IO-CA9D DIABLO PARALLEL PORT \$175
DIABLO 12 BIT WORD Parallel port for use with word processor type printers. Complete with 10 ft. cable. Compatible with OS-65U software.

IO-LEVEL 3 MULTI-USER EXPANSION \$450
Provides 3 printer interfaces currently supported by OSI-Serial, Centronics Parallel, Diablo Parallel. 4K of memory at D000 for Multi-user executive. 4 Port serial cluster. The LEVEL 3 card allows expansion of an OSI C3 machine up to 4 users with appropriate additional memory partitions.

24MEM-CM9... \$380 **16MEM-CM9...** \$300 **8 MEM-CM9...** \$210
24K memory card is available at 3 different populated levels. All cards are fully socketed for 24K of memory. The card uses 2114-300ns chips. DIP SWITCH addressing is provided in the form of one 16K block and one 8K block. Also supports DIP SWITCH memory partition addressing for use in multi-user systems.

FL470 FLOPPY DISK CONTROLLER \$180
OSI-Type floppy disk controller and real time clock. Will Support 5 1/4" or 8", Single or double-sided drives. Requires drives with separated data and control outputs.

BIO-1600 BARE I/O CARD \$50
Super I/O Card. Supports 8K of 2114 memory in two DIP SWITCH addressable 4K blocks. 2 16 Bit Parallel Ports may be used as printer interfaces, 5 RS-232 Serial Ports with CTS & RTS handshaking. With manual and Molex connectors.

BMEM-CM9 BARE MEMORY CARD \$50
Bare 24K memory card, also supports OSI-type real time clock and floppy disk controller. With manual and Molex connectors.

#96 PROTOTYPE CARD \$35
Prototype board holds 96 14 or 16 pin IC's. Will also accommodate 18, 24, or 40 pin IC's. Row and column zone markings, easy layout. 1/8" epoxy glass P.C. board.

C1P-EXP EXPANSION INTERFACE \$65
Expansion for C1P 600 or 610 boards to the OSI 48 Pin Buss. Uses expansion socket and interface circuitry to expand to 48 Pin Backplane. Requires one slot in backplane.

BP-580 BACKPLANE \$47
Assembled 8-slot backplane with male Molex connectors and termination resistors.

DSK-SW DISK SWITCH \$29
A circuit when added to OSI Minifloppy systems extends the life of drives and media. Accomplish this by shutting off Minifloppy Spindle motor when system is not accessing the drive. Complete KIT and manual.

PW-5-6 POWER SUPPLY \$29
Power One brand supply 5V - 6 amps with overvoltage protection. Reg. \$49.95.

D&N MICRO PRODUCTS, INC. ✓293

3684 N. Wells Street Ft. Wayne, Indiana 46808
219/485-6414

TERMS: Check or money order Add \$2 Shipping, Outside U.S. add 10%.

COMPSTAT

THE MOST COMPREHENSIVE STATISTICS PACKAGE AVAILABLE FOR MICROCOMPUTERS. NORTH STAR BASIC AND 8" BAZIC* VERSIONS AVAILABLE.

OVER 420 PROGRAMS COVERING ANALYSIS OF VARIANCE, BASIC STATS, CONTINGENCY TABLE TECHNIQUES, ESTIMATION, EXPLORATORY DATA ANALYSIS, FOURIER ANALYSIS, NONPARAMETRIC STATISTICS, MULTIVARIATE STATISTICS, PROBABILITY PLOTTING, QUALITY CONTROL, RANDOM VARIATE GENERATION, REGRESSION, ROBUST TECHNIQUES, SAMPLING, STATISTICAL DISTRIBUTIONS, SURVIVAL TECHNIQUES AND TIME SERIES.

COMPLETE PACKAGE \$1500
MANUAL ONLY \$100


TOPICS SOLD SEPARATELY AT \$200 A TOPIC.

COMPSTAT ✓395
P.O. BOX 268
GLOUCESTER POINT, VA. 23062

*BAZIC IS A REGISTERED TRADEMARK OF MICRO MIKE'S.

Computerize your bookkeeping without terrifying your bookkeeper.

Introducing The Boss:™ the most advanced, yet most understandable, financial accounting system. Designed to automate your bookkeeping without confusion or mistakes.



Reference Number: 1000 Entry Date: 04-08-01
 Transaction: JOURNAL POST CASH RECEIPTS
 Date Received: 04-08-01
 Customer Check #: 1005
 Customer ID #: 1001 XYZ COMPANY 0.00
 Your Invoice #: 10222
 Customer P.O. #: 000-111
 Your Department: 100 SOFTWARE
 Your Category #: 100 PRODUCT 1
 Description: Received Payment

Account	Name	Amount	Debit/Credit
100	Checking Account	3000.45	Debit
500	Cash Sales-Parts	3000.45	Credit
Amount out of balance:		0.00	

Typical screen format - actual photograph.

If "fear of the unknown" is standing between you and computerization, you should find out about The Boss.

The Boss system is immediately comprehensible to bookkeepers because it utilizes virtually the same format they're used to.

So even someone with no previous computer experience can easily learn and operate The Boss system.

Features seldom found in packaged software.

The Boss system is fully interactive, fully departmentalized and exceptionally fast. It can generate an astounding number of complex reports at the touch of a button.

General Ledger and Accounts Receivable and Payable transactions can be entered in any order in a single program.

Up-to-the-minute financial reports can be obtained without batch processing.

The Boss system computes financial ratio analysis.

It protects data from unauthorized personnel as well as computer malfunction.

And it has the largest programming and storage capacity of any micro system.


The Boss runs on most small business computers with CP/M® or similar operating systems. Its cost is only \$2,495.

Get full support from Lifeboat.

The Boss is brought to you exclusively and supported completely by Lifeboat Associates, world's largest computer software publisher. For more information about how you can profit from this extraordinary financial accounting system, send us the coupon below. Or call (212) 860-0300.

For more information on The Boss, mail coupon to Lifeboat Associates, 1651 Third Avenue, New York, NY 10028.

Name _____
 Title _____
 Company _____
 Street _____
 City _____
 State _____
 Zip _____



2405

Boss is a trademark of Balcones Computer Corp.
 CPM is a trademark of Digital Research, Inc.

LIFEBOAT WORLDWIDE offers you the world's largest library of software. Contact your nearest dealer or Lifeboat:

Lifeboat Associates
 1651 Third Ave.
 New York, N.Y. 10028
 Tel: (212) 860-0300
 Telex: 640693 (LBSOFT NYK)
 TWX: 710-581-2524

Lifeboat Inc.
 OK Bldg., 5F
 1-2-8, Shiba-Daimon
 Minato-ku, Tokyo, 105 Japan
 Tel: 03-437-3901
 Telex: 2422723 (ASRTYOJ)

Lifeboat Associates, Ltd.
 PO Box 125
 London WC2H 9LU, England
 Tel: 01-836-9028
 Telex: 893709 (LBSOFTG)

Lifeboat Associates GmbH
 PO Box 168, Aegerstrasse 35
 CH 6340 Baar, Switzerland
 Tel: 042-31-2931
 Telex: 855265 (MICO CH)

Intersoft GmbH
 Schlossgartenweg 5
 D-8045 Ismaning, W. Germany
 Tel: 089-966-444
 Telex: 5213643 (ISOFTD)

Lifeboat Associates, SARL
 10, Grande Rue Charles de Gaulle
 92600 Asnieres, France
 Tel: 1-733-08-04
 Telex: 250303 (PUBLC X PARIS)

Lifeboat Associates ✓ 211
 Software with full support

nylon supports by lightly pinching them with a small pair of pliers. Be sure not to miss the one at location J9. The main circuit board should now be separated. Remove the main circuit board from the base and set the base aside.




Fig. 3. Add these two jumpers to the back of your Apple's main circuit board to boost its capabilities. The most common mistake is to miscount the pins.

Referring to Fig. 3, connect the new wire jumpers to their respective pins on the rear of the circuit board. Use small #22-#28 gauge solid wire. Do not use stranded wire; it tends to fray, possibly shorting to other nearby pins.

Measure the distance between the pins with a length of wire and cut it 1/4-inch longer than measured. Strip off 1/8-inch of insulation from each end. Make a small loop in the stripped end of the wire and hook it to the pin. Lightly touch a soldering pencil to the connection and feed in a minimal amount of solder. Avoid using too much solder; it could flow across to the next pin, causing a short.




The main problem to watch for at this stage is miscounting the pins on their respective sockets. Use insulated wire and clean soldering techniques, and you should not have a problem. Reassemble everything in reverse order. When the power is re-applied, check the modification with a voltmeter before plugging in the transistor circuit. Reversing the supplies on the transistor could damage your unit.

Once the modification is completed and checked, plug in the transistor circuit and measure the output voltage level. By slowly toggling the annunciator 0 port with the BASIC program in Listing 2, voltage swings in the 5-15 V range on either side of ground should be observed. If not, check the wiring and the values of the resistors. Also, the parameters of different transistors may vary, so try substituting a few to obtain the most balanced voltage swings.

The Printer Connection

Now that everything is done at the output end, it is time to prepare the Selectric for data input. On the back of the Selectric are two points of interest. The first is the DB-25 plug; the other is the line/local switch. Table 3 shows the pinout designations for the DB-25 plug. The idea is to trigger the terminal into the receive mode without having to supply another wire from the computer.

Because of this, only three pins on the DB-25 plug have significance in this application. Pin 3 receives the RS-232C serial data stream from the

Z-FORTH IN ROM by Tom Zimmer	
5 to 10 times faster than Basic. Once you use it, you'll never go back to basic!	\$ 75.00
source listing add	\$ 20.00
OSI FIG-FORTH True fig forth model for OS65D with fig editor named files, string package & much more	
	\$ 45.00
TINY PASCAL Operates in fig-forth, an exceptional value when purchased with forth.	
TINY PASCAL & documentation	\$ 45.00
FORTH & TINY PASCAL	\$ 65.00
SPACE INVADERS 100% machine code for all systems with 64 chr. video. Full color & sound on C2, 4P & 8P systems. The fastest arcade program available.	
	\$ 14.95
PROGRAMMABLE CHARACTER GENERATOR	
Use OSI's graphics or make a complete set of your own! Easy to use, comes assembled & tested.	\$ 99.95
2 Mhz. boards	\$109.95
PROGRAMMABLE SOUND BOARD	
Complete sound system featuring the AY-3-8910 sound chip. Bare boards available.	\$ 74.95
	\$ 29.95
32/64 CHARACTER VIDEO MODIFICATION	
Oldest and most popular video mod. True 32 chr. C1P, or 32/64 chr. C4P video display. Also adds many other options.	\$ 39.95
ROMS!!!	
Augment Video Mod with our Roms. Full screen editing, print at selectable scroll, and many more features.	
Basic 4 & Monitor	\$ 49.95
Basic 3	\$ 18.95
All 3 for	\$ 65.00
65D DISASSEMBLY MANUAL by Software Consultants	
First class throughout. A must for any 65D user.	\$ 24.95
NUMEROUS BASIC PROGRAMS, UTILITY PROGRAMS AND GAMES ALONG WITH HARDWARE PROJECTS. ALL PRICES ARE U.S. FUNDS.	
Send for our \$1.50 catalogue with free program (hardcopy) Memory Map and Auto Load Routine.	
 	
 OSI Software & Hardware ✓ 202 3336 Avondale Crescent Windsor, Ontario, Canada N9E 1X6 (519) 969-2500 3281 Countryside Circle Pontiac Township, Michigan 48057 (313) 373-0468	

progressive computing



Free. Fast. And a phone call away.

INMAC INTRODUCES THE SOLUTION TO YOUR MICRO SUPPLY AND ACCESSORY NEEDS.

- One-Stop Shopping. This new catalog offers over 1,000 products specifically for Micro Computers. Compatible with Apple, Atari, Northstar, TRS-80s and many others.
- Convenient Ordering. By mail or phone, ordering supplies and accessories from this catalog will be quick and easy.
- Fast Delivery. We'll ship your order within 24 hours from our distribution centers in New Jersey, California, Illinois and Texas. Overnight delivery available.
- Top Quality Products. Virtually all our products are guaranteed for at least one year. Risk-free trial of any product for 45 days.

Send for your FREE Inmac Catalog or call (408) 727-1970.

Inmac
 Dept. Micro, 2465 Augustine Drive,
 Santa Clara, CA 95051 ✓ 223

driver program. Pin 7 is the ground reference from the Apple II. And pin 5 needs to be supplied a logic 1 voltage level to set the terminal in the receive mode.

The logic 1 voltage for pin 5 is supplied from the 5 V supply within the printer. Unsnap the rear cover from the printer and locate the terminal block on the circuit board within. The terminal with the green wire is the 5 V supply. The one with the black wire is the ground. Measure their levels to confirm this. Connect a

short wire from the 5 V terminal to pin 5 of the DB-25 plug. That is the only work needed on the printer.

Initialization Protocol

Once the data line is connected to the printer and the jumper is installed, the interface is finished. It is now a working system and ready for use. To start it up, there is a short initialization protocol that has to be repeated each time the printer is turned on. These steps may be performed manually, but with some creativity a routine could be written to perform them automatically. There are five steps:

- Run the printer subroutine in the Apple II.
- Apply power to the printer.
- Flip the line/local switch to the line position. The ready and proceed lights on the front of the Selectric will come on.
- Press the initiate key on the right side of the Selectric keyboard. The proceed light will turn off.
- Send an EOA code (\$B4), which is the # character in the EBCD or BCD codes or the number 9 in the corre-

spondence code.

Once this character is sent, the terminal is in the receive mode and ready to print.

Added Benefits

The final result of this project is that an RS-232C output port has been created at the annunciator 0 pin of the game paddle I/O connector. This article has harnessed that port for only one purpose, but there are others. For example, Paul Lutus has included a little-talked-about subroutine in his excellent word processing program, Apple Writer. This subroutine can be accessed by entering the word SERIAL in response to the Print Menu. Its purpose is to feed a serial-bit stream to the annunciator 0 port at one of five user-defined baud rates (110, 150, 300, 600 and 1200 bits per second).

There is no reason that the transistor circuit described in this article cannot be harnessed to output this ASCII coded information just as easily as it outputs the data streams coded for Selectrics. The ramifications of this are that high-speed serial input

```

1  REM
   TOGGLE ANNUNCIATOR #0

10  POKE - 16296,0: REM - OFF
20  GET A$: REM - PAUSE
30  POKE - 16295,0: REM - ON
40  GET A$: REM - PAUSE
50  GOTO 10

```

Listing 2. The SWITCH program is for switching annunciator port 0 on and off when testing the transistor circuit of Fig. 1. Hit any key on the keyboard to toggle the port to the opposite state. When the transistor circuit is plugged in, its output should swing between +5 to +15 V and -5 to -15 V for proper RS-232 operation.



The "fast" sort for Oasis Systems

QISORT is a highly optimized easy to use sort utility designed for high speed sorting of ASCII sequential files into desired sequence. Benchmark tests were run on a Digital Microsystems DSC-3 using Oasis 5.4F single user operating system.

Benchmark tests show QISORT to be up to 7.9 times faster.

Record Length	File Size	Sort Key	QISORT		OASIS FILESORT	
			Hard Disk	Diskette	Hard Disk	Diskette
30	500	1-5	.23	.68	.90	2.40
		6-10,1-5D	.23	.68	.96	2.48
	1000	1-5	.41	1.28	2.36	5.48
		6-10,1-5D	.85	2.05	2.46	5.58
	2500	1-5	1.53	4.98	10.43	19.45
		6-10,1-5D	1.65	5.23	13.11	22.78
60	500	1-14	.40	1.25	1.35	4.13
		17-30,1-8D,9-16	.88	2.06	1.53	4.35
	1000	1-14	1.56	3.90	3.81	9.18
		17-30,1-8D,9-16	1.70	4.21	4.43	9.80
	2500	1-14	4.63	7.61	14.13	36.00
		17-30,1-8D,9-16	4.80		13.06	

Oasis is a registered trademark of Phase One Systems, Inc.

PLEASE FILL OUT AND RETURN TO:
QUANTUM INFORMATION SYSTEMS ✓246
860 N.W. 87th St., Seattle, WA 98117 (206) 784-2118

Please Send Me:

- ☐ QISORT \$100.00* ☐ Manual Only \$7.50
Washington State residents add 5.4% sales tax.

Company _____

Name _____ Title _____

Shipping Address _____

City _____ State _____ Zip _____

OASIS SERIAL NO. _____
(Required with order)

- ☐ check enclosed ☐ U.P.S.-COD

*add \$3.00 for shipping dealer inquiries invited

devices can also be connected for just 83 cents! In fact, this is the only way that Apple Writer can take full advantage of some printers.

Don't feel that the modification I have described here is limited to just printers—try plotters, modems, synthesizers or any other device that needs to receive RS-232C serial data from the Apple II.

The Reality of It All

The Selectric I purchased is a Carterfone S15B Data Terminal, which CFR Associates advertises for under \$500. It comes as is, which translates to: "it works, with quirks." Mine had a broken paddle on the line/local switch and I had to add a power cord. The folks at CFR (Box 144, Newton, NH 03858) have been helpful to me on the phone, and have been able to provide technical assistance in the form of a very lengthy manual about I/O electronics.

After several months of heavy use, the Selectric has earned its keep. So far it has not needed any repairs, but the good tend to die young, so it would probably be worth obtaining a

repair manual to keep everything running smoothly. It is also a good idea to acquaint oneself with the local Selectric service personnel. They can supply new ribbons (even fancy carbon ribbons), type elements and answers to technical questions about the machine. Most advertise in the phone book.

One of the advantages of Selectrics is that they have a friction-feed platen. Individual sheets of paper or inexpensive newsprint paper rolls may be used. A good source of roll paper is the local radio station. They are provided reams of it from their newswire services and can usually part with several cases at a time (for free!). A modified toilet paper dispenser is just fine for holding the roll and centering it so that it does not "walk" back and forth on the carriage. And, if it is really needed, pin-feed platens may be purchased from service centers, giving you the best of both methods.

Conclusion

When I set out to build this interface, the primary motive was money. Now that I have had time to look

back on it all, I realize that an even larger incentive was to expand the versatility of the Apple II via a grassroots effort. This microcomputer is tops in its class not just because of its design, but because owners and users have made imaginative use of its abilities.

If its users get too dependent on manufacturers to provide all of the expansion, the Apple II will quickly become outdated. On the other hand, as long as the users remain skilled in their craft, the Apple II will continue to dominate the market. Building this letter-quality printer interface makes investment in an Apple II the best choice you ever made. ■

References

1. "ASCII-to-Selectric Software Driver," Robert Munn, *Kilobaud Microcomputing*, Nov. 1979, p. 134.
2. "Programming the 6502," Rodney Zaks, SYBEX, Inc., 1979.
3. "6502 Applications Book," Rodney Zaks, SYBEX, Inc., 1979.
4. "Microcomputer Interfacing," Bruce A. Artwick, Prentice Hall, Inc., 1980.

GIMIX & MICROWARE present the 6809 PROFESSIONAL TOOLBOX

A GIMIX 56KB static RAM 2Mhz 6809 Dual Drive Mainframe System with MICROWARE's Multiuser OS9 Pro-Package --special combination price **\$3968.09**. This system includes the GIMIX Mainframe with 30 amp C.V. ferro-resonant power supply, SS50/50C Motherboard, 2Mhz 6809 CPU with time of day clock and battery back-up, 6840 programmable timer, 2 serial ports, 56K Bytes of Static RAM, and two 5 1/4" disk drives and double density controller installed in the GIMIX Mainframe with the same brownout protection and power supply reliability that GIMIX is famous for.

MICROWARE's OS9 Pro-Package includes OS9 Level 1, the BASIC09 interactive compiler, Macro Text Editor, Interactive Assembler, and Interactive Debugger which gives you the necessary tools for efficient structured software development.

All GIMIX Boards have gold plated bus connectors, and are burned in and 100% tested before shipping.

And this system is expandable. You can add memory, I/Os, video or graphics cards, Arithmetic processors, additional drive capacity, and other hardware now or in the future to this SS50 bus structured system from GIMIX or other SS50 bus compatible manufacturers. MICROWARE has other OS9 software such as the Stylograph Screen-Oriented Word Processor available now, and in the future will be announcing other languages and utilities that run under OS9. And coming soon from MICROWARE will be OS9 Level 2 that lets you address up to 1 megabyte of memory.

GIMIX & GHOST are trademarks of GIMIX Inc., Basic 09, OS9 and Microware are trademarks of Motorola and Microware Inc.

For further info on the best in 6809 Hardware, contact:



GIMIX Inc.
The Company that delivers
Quality Electronic products since 1975.

1337 WEST 37th PLACE, CHICAGO, IL 60609
(312) 927-5510 • TWX 910-221-4055

For further info on the best in 6809 Software, contact:



MICROWARE
Microware Systems Corp.
5835 Grand Avenue, Des Moines, Iowa 50304
(515) 279-8844 • TWIX 910-520-2535

See us at NCC booth 971-2

MOVING?

Let us know 8 weeks in advance so that you won't miss a single issue of *Kilobaud Microcomputing*. Attach old label where indicated and print new address in space provided. Also include your mailing label whenever you write concerning your subscription. It helps us serve you promptly.

- | | |
|---|---|
| <input type="checkbox"/> Address change only | <input type="checkbox"/> Payment enclosed |
| <input type="checkbox"/> Extend subscription | (1 extra BONUS issue) |
| <input type="checkbox"/> Enter new subscription | <input type="checkbox"/> Bill me later |
| <input type="checkbox"/> 1 year \$25.00 | |

If you have no label handy, print OLD address here.

AFFIX LABEL

Name _____ Call _____

Address _____

City _____ State _____ Zip _____

print NEW address here:

Name _____ Call _____

Address _____

City _____ State _____ Zip _____

Kilobaud Microcomputing P.O. Box 997 • Farmingdale NY 11737


INTRODUCING:

SPECTRONICS, INC.

(A Wholly Owned Subsidiary of Level IV Products)


- OFFERING -

The Full TRS-80* Line at Discount Prices, and Extended Warranty Coverage




COLOR COMPUTER

16K (R)	\$440
16K (E)	\$359
16K w/ext basic (R)	\$529
16K w/ext basic (E)	\$479



MOD III COMPUTER

16K (R)	\$859
32K 2-40 drives (R)	\$2010
48K 2-40 drives (E)	\$1859
48K 2-80 drives (E)	\$2119
RS232 interface add	\$89



MOD II COMPUTER

32K (R)	\$2950
64K (R)	\$3375
Expansion Dr#1 (R)	\$999
Expansion Dr#1-2-3 (E)	\$695

NOTE: THE MOD III CAN BE ASSEMBLED WITH UP TO 4 MEG UNFORMATTED FLOPPY DISK STORAGE CAPACITY (4-80 TRK DOUBLE SIDED DRIVES) - CALL FOR A QUOTE ON THE SYSTEM TAILORED TO YOUR EXACT NEEDS.

PRINTERS

Line Printer IV (R)	\$849
Line Printer VI (R)	\$986
Daisy Wheel II (R)	\$1679
C. ITOH Starwriters	Call
Centronics All	Call
Epson All	Call
Anadex All	Call

DRIVES

	COMPLETE	RAW
40 TRK MPI (E)	\$309	\$245
80 TRK MPI (E)	\$429	\$360
40/40 TRK MPI (E)	\$445	\$375
80/80 TRK MPI (E)	\$579	\$515

PERIPHERALS

E.I. OK (R)	\$249
E.I. 16K (R)	\$359
E.I. 32K (R)	\$469
E.I. 16K (E)	\$305
E.I. 32K (E)	\$362
16K RAM (200MS)	\$ 39

DEALER'S INQUIRIES INVITED, CALL FOR OUR WHOLESALE DEPARTMENT (313) 525-6201

WARRANTY POLICY

Items including non-Radio Shack components (E) are covered by an extended six-month parts/labor warranty in our tech service center.

Items constructed from Radio Shack approved components (R) are covered by a 90-day parts/labor warranty at any Radio Shack store, plus an additional 90 days in our tech service center.

TERMS OF SALE

2% Discount allowed on cash pre-paid orders. Personal checks require two weeks for bank clearance.

Visa, Master Charge and C.O.D. orders accepted. Add \$1.50 for C.O.D.'s.

Shipping/handling/insurance add 1.5% or \$2.50 minimum.

Prompt shipments from stock.

SPECTRONICS, INC.
32461 SCHOOLCRAFT ROAD
LIVONIA, MICHIGAN 48150
MICHIGAN - (313) 525-6200
TOLL FREE - 800-521-3305



*TRADEMARK OF TANDY CORP.

Apple BASIC Prettyprinter

By Michael Keith

Many high-level languages available under large operating systems (e.g., Pascal, C or LISP) have access to a prettyprinting program to automatically reformat other programs in a specified way to render

them more readable and understandable.

This simple prettyprinter, written in BASIC, is for the Apple II. It uses the powerful disk operating system file commands to manipulate the BASIC source program into a form suitable for prettyprinting. The system accepts programs written in either type of Apple BASIC (Integer or Applesoft). You can use this prettyprinter for final documentation of your own programs or as a study tool for reading programs written by others.

A Description

First, you read your program into memory. Next, a short program is appended to the end and run. This program transfers your program into a text file on disk. You then run the main program, which reads in the text file and processes it to produce the prettyprinted output.

The features of the prettyprinter output include highlighting of groups of one or more REM statements, automatic breakup of multiple-statement lines and FOR-NEXT and IF-THEN indentation.

A sample program and the output generated by the prettyprinter are shown in Sample 1.

The prettyprinter program consists of two files, which must reside on the same diskette: a text file called APPRINT and an Applesoft program called PRINT. The contents of APPRINT are shown in Listing 1. This text file can be created by writing a short program which opens a file called APPRINT, prints these lines and closes the file (for a detailed description of text files, see the Apple DOS manual). To operate the prettyprinter, do the following:

1. Load the BASIC program you wish to prettyprint into memory.
2. Insert the diskette containing the prettyprint files and type EXEC APPRINT.

After doing this, the following sequence of events takes place:

1. The program lines in APPRINT are appended to the user program.
2. The RUN 30000 command puts the user program in a text file called LISTING.
3. The main program, PRINT, is executed.

The main program, PRINT, is given in Listing 2, which was produced by the prettyprinter itself as a sample of its output.

The most time-consuming section of the PRINT program is the initial reading in and preprocessing of the program (lines 1-65). This can take from half a minute to five minutes depending on the size of the program. During this stage, the program is separated into single statements, which are stored in array elements A\$(1), A\$(2) . . . A\$(N). The user is then presented with a menu of functions: P for prettyprint, I for index or Q for quit.

```
10 REM PROGRAM TO FIND ALL
15 REM PERFECT NUMBERS<N
20 TEXT : CALL -936: VTAB 10: INPUT
  "WHAT VALUE OF N",N
30 DIM PN(10): NUMPERF=1: PN(1)=
  1
40 REM MAIN LOOP
50 FOR NUM=2 TO N: SUM=0
60 FOR DIV=1 TO NUM-1: IF NUM MOD
  DIV=0 THEN SUM=SUM+DIV: NEXT
  DIV
70 IF SUM#NUM THEN 90
80 NUMPERF=NUMPERF+1: PN(NUMPERF)
  =NUM
90 NEXT NUM
100 REM PRINT NUMBERS
110 FOR I=1 TO NUMPERF: PRINT PN(
  I): NEXT I
120 END
```

Sample 1a. Sample Integer BASIC program.

```
*****
10 REM PROGRAM TO FIND ALL
15 REM PERFECT NUMBERS<N
-----
20 TEXT :
  CALL -936:
  VTAB 10:
  INPUT "WHAT VALUE OF N",N
30 DIM PN(10):
  NUMPERF=1:
  PN(1)=1
*****
40 REM MAIN LOOP
-----
50 FOR NUM=2 TO N:
  SUM=0
60 FOR DIV=1 TO NUM-1:
  IF NUM MOD DIV=0
  THEN
    SUM=SUM+DIV:
  NEXT DIV
70 IF SUM#NUM
  THEN
    90
80 NUMPERF=NUMPERF+1:
  PN(NUMPERF)=NUM
90 NEXT NUM
*****
100 REM PRINT NUMBERS
-----
110 FOR I=1 TO NUMPERF:
  PRINT PN(I):
  NEXT I
120 END
```

Sample 1b. Program in Sample 1a after prettyprinting.

```
30000 D$=" ":REM CTRL-D
30005 PRINT D$:"OPEN LISTING":PRINT D$:
  "DELETE LISTING"
30010 PRINT D$:"OPEN LISTING":PRINT D$:
  "WRITE LISTING"
30020 POKE 33,30: LIST 1,30000
30030 PRINT D$:"CLOSE LISTING"
30040 END
RUN 30000
RUN PRINT
```

Listing 1. Contents of the text file APPRINT.

Address correspondence to Michael Keith, D46 Abington Drive, Hightstown, NJ 08520.

CompuServe is a lot more than fun and games and news.

Although we're probably best known for our consumer-oriented services, CompuServe maintains powerful services for the serious computer user. CompuServe has helped some of the nation's largest companies and financial institutions through a wide range of business and scientific-oriented computer programs. With our Information Service, we can extend this expertise to you. Here are some of the programs available to the personal computer user through the CompuServe Information Service:

PASCAL: DEC User Group version of this famous language.

XF4: Extended CompuServe Fortran compiler.

MACRO: Advanced Macro Assembly language for PDP-10. Talk about fast.

FILGE: Fast, easy file generator and editor. Line oriented, no line numbers required!

XBASIC: CompuServe extended BASIC.

JUMBLE: File encryption program.

TECO: High level text editor.

LINK: Linking loader program.

DDT: Dynamic debugging tool.

CREF: Symbolic cross-reference generator used with language compilers.

FILCOM: File comparison program.

SALARY: Calculates salary and increases in various time frames including per year, month, period and hour. This program is intended primarily for managers doing reviews.

SNOBOL: String manipulation language.

RUNFLO: Text formatting program (write resumes etc.).

RUNF10: Word processing and text formatting program (write resumes etc.).

CONCOR: Concordance generator. This program is very useful for documentation purposes. CONCOR reads an ASCII file and creates an output file which contains a line numbered listing of the original file, and a list of all the words contained in the file along with the numbers of the lines on which each word occurs (similar to an index).

BLIS10: High level implementation language for DEC PDP-10.

BINED: Binary file editor.

APL: A Programming Language.

FINTOL: Financial analysis tool. Contains several program modules which can perform financial analysis for business or personal needs.


- Loan Payment and Amortization
- Compound Interest Calculations
- Sum from a Periodic Investment
- Sinking Fund Deposit
- Present Value of Cash Flows
- Present Value and Internal Rate of Return (Capital Projects)
- Depreciation Analysis
- Compound Growth Rates

RANNO: Random number generator.

XEDIT: XF4 binary file editor.

We also offer high speed professional line printer service, error-free file transfer, CompuServe's Software Exchange, and computer manufacturers' newsletters. Computer Users Groups can exchange information and up-to-the-minute gossip in the computer world.

And . . . if Aunt Matilda comes over, you can still let her play Adventure. Demonstrations and software at all Radio Shack® Computer Centers and many Radio Shack® outlets.



CompuServe ✓ 147

Information Service Division
5000 Arlington Centre Boulevard
Columbus, Ohio 43220
(614) 457-8600

Radio Shack is a trademark of Tandy Corporation.

\$\$\$ DISCOUNT PRICES \$\$\$

SCOTCH DISKETTES

for Apple*, Pet and TRS-80 systems
soft sector - Single Density - 5 1/4 inch
32% less abrasive than the industry average.
Soft box of 10 \$27.95
Storage box of 10 \$28.95
3M Disk Drive Cleaning Kit (5 1/4 inch) \$22.95
Shipping & Insurance for each box/kit \$1.00
*Free 3M demonstration program - teaches
diskette design & handling - on request with
diskette order

APPLE II SOFTWARE

(Available only with purchase of diskettes)
Typing Teacher (teaches touch typing)* \$4.00
Math Sequences (gives hints - builds IQ)* \$2.00
Unicopy (copy diskette using 1 drive)** \$2.00
All three programs \$7.00
*Integer Basic **Applesoft

APPLE II SOFTWARE/HARDWARE

(With or without purchase of diskettes)
Back-It-Up

(use to backup most protected diskettes) \$54.00

Brain Surgeon (new version - more tests)

(diagnoses RAM, ROM, Disk drives, Micromodem II, & many more) \$44.00

Home Money Minder

(checks, charges, budget & graphics) \$31.00

VisiCalc (new 16 sector version)

(electronic worksheet analysis) \$149.00

Super Text II

(best word processor available) \$125.00

Lower Case Adaptor

(for Rev. 7 - works with most software) \$32.95

Shipping & Insurance for 1 or more items \$2.00

EPSON MX 80 PRINTER

90-day warranty supplied by Epson

(80 Chars/sec. 9x9 dot matrix-letter quality)

Apple II (with interface and cable) \$579.00

Pet (with IEEE interface and cable) \$565.00

TRS-80 or Atari (with cable) \$509.00

Shipping and Insurance for MX80 \$10.00

Add to above for new MX80FT model \$95.00

Visa and Mastercard accepted.

Michigan residents add sales tax.

THE COMPUTER ANSWER

P.O. Box 573 K

Birmingham, Michigan 48009

(313) 642-4338 (Order Phone - 24 hours/day)

As listed in Listing 2, the pretty-print option (P) will cause a hard-copy printout through an interface card in slot 2. To change to a different slot, merely change line 1001. To prettyprint to the video display only (the mode I usually use the program in), merely delete line 1001. In this mode, pressing any key on the keyboard can be used to pause and resume the listing at any point. The index option (I) produces a list of all REM statements in the program on the CRT. This is useful for locating a specific routine or for reading a program's documentation.

The formatting rules used by the prettyprinter follow:

1. A block of REM statements is highlighted as follows:

```
(blank line)
*****
(REM statements)
-----
```

Exception: In a multiple-statement line whose first statement is *not* a REM, the blank line and the asterisks are suppressed.

2. FOR-NEXT loops are indented as follows:

```
FOR (expression)
( statements )
NEXT
```

Loops within loops are indented further (once for each increase in nesting depth).

3. IF-THEN statements are reformatted as follows:

```
IF (expression)
THEN
( statements )
```

Finally, note that a prettyprinted program is not executable BASIC. However, it is simple to reconvert a prettyprinted listing to legal BASIC. You merely delete the REM highlighting, group the multiple statements together and then write IF-THENs on one line.

Summary

I have described a simple prettyprinter for Apple II BASIC programs, but there are many possible enhancements. One of the most useful (and also one of the most difficult) enhancements is to recode parts of the program in machine language for increased speed. Nevertheless, the program presented here has proven a useful tool for better understanding of programs and their operation. The basic technique of capturing and manipulating a BASIC program as a text


file can be used to produce more elaborate prettyprinters, conversion programs (e.g., to convert from one type of BASIC to another) or fancy program editors. These and other possibilities are left to you for further experimentation. ■

Listing 2. PRINT, the main prettyprinting program.

```
1 TEXT
2 DIM A$(500)
3 *****
4 REM READ IN PROGRAM FROM FILE 'L
  LISTING'
5 REM AND BREAK INTO SINGLE STATEM
  ENTS
6
7 N = 1:
8 D$ = CHR$(4):
9 PRINT D$;"OPEN LISTING":
10 PRINT D$;"READ LISTING"
11 A$(0) = "":
12 C = 0:
13 HOME:
14 VTAB 10:
15 PRINT "PROGRAM IS BEING READ IN A
  ND PROCESSED."
16 GET A$
17 IF A$ = CHR$(13) AND LEN(A$(N
  )) = 0
18 THEN
19
20 IF A$ = CHR$(13)
21 THEN
22 N = N + 1:
23 A$(N) = "":
24 C = 0:
25 GOTO 50
26 IF A$ = CHR$(34)
27 THEN
28 C = C + 1
29 IF A$ = ":" AND INT(C / 2) = C
  / 2
30 THEN
31 A$(N) = A$(N) + A$:
32 N = N + 1:
33 A$(N) = "":
34 C = 0:
35 GOTO 50
36 A$(N) = A$(N) + A$
37 IF A$(N) = "30000"
38 THEN
39
40 GOTO 20
41 PRINT D$;"NOMON":
42 VTAB PEEK(37):
43 CALL - 868
44 N = N - 1
45 PRINT D$;"CLOSE LISTING"
46
47 *****
48 REM INITIAL FORMATTING
49
50 GOSUB 2000
51
52 *****
53 REM NOW GO TO MAIN MENU
54
55 GOTO 500
56
57 *****
58 REM A COLLECTION OF SUBROUTINES
59 REM PLACED HERE FOR SPEED
60 REM REM-CHECK
61
62 BFLAG = 0:
63 EFLAG = 0
64 IF MID$(Z$,7,3) < > "REM"
65 THEN
66 RETURN
67 IF MID$(Z$,11,1) < > " "
68 THEN
69 Z$ = LEFT$(Z$,9) + " " + RIGHT
  $(Z$, LEN(Z$) - 9)
70 IF MID$(A$(I - 1),7,3) < > "RE
  M" AND LEFT$(Z$,6) < > "
71 "
72 THEN
73 BFLAG = 1
74 IF MID$(A$(I + 1),7,3) < > "RE
  M"
75 THEN
76 EFLAG = 1
77 IF BFLAG = 1
78 THEN
79 PRINT
80 IF BFLAG = 1
81 THEN
82 PRINT "*****"
83 *****
84 RETURN
85
86 *****
87 REM IF-THEN CHECK AND PRINT
```

More →

The Epson MX-80
Dot
Matrix
Printer.



~~\$490.00~~ CALL
MX-80FT CALL
MX-70 only \$375.

C. ITOH Starwriter Printer
Parallel 25CPS only \$1435.
Serial 25CPS only \$1520.

UNIVERSAL DATA PRODUCTS
103LP MODEM only \$175.
Lexicon LEX-11 Modem only \$125.

Scotch 3M Diskettes
8" SSSD 10/ \$2.90 50/ \$2.80
5 1/4" SSSD 10/ \$2.80 50/ \$2.70

Prices subject to change

J.C. Datatron
P.O. BOX 305
Massapequa NY 11758
(516) 798-7448

FOB Shipping Point NYS Res. Add Sales Tax
Terms: M.O. Cert. Chks. Allow 2 Weeks for
Personal Chks. HRS. 9am-2:30pm

Listing 2 continued

```

210 IF MID$(Z$,7,2) < > "IF"
    THEN
    RETURN
220 L$ = Z$
230 FOR J = 9 TO LEN(Z$):
    IF MID$(Z$,J,4) = "
        THEN 250
240 NEXT J
250 Z$ = LEFT$(L$,J-1):
    GOSUB 405
260 PRINT SPC(TB+6+3); "THEN"
270 Z$ = " " + RIGHT$(L$, LEN
    (L$) - 4 - J):
    GOSUB 405
275 IF MID$(L$,J+6,3) = "FOR" OR
    MID$(L$,J+5,3) = "FOR"
    THEN
    TB = TB + 3
280 POP:
    RETURN
399:
*****
400 REM FOLD AND PRINT Z$
-----
402 GOSUB 100:
    REM CHECK IF REM
-----
403 GOSUB 200:
    REM CHECK IF IF-THEN
-----
405 IF LEN(Z$) < 39 - TB
    THEN
    PRINT LEFT$(Z$,6); SPC(TB); R
    IGH$(Z$, LEN(Z$) - 6):
    GOTO 447
410 PRINT LEFT$(Z$,6); SPC(TB); M1
    D$(Z$,7,39 - TB - 6):
    X = 40 - TB
420 L = X + 32 - TB:
    IF L > LEN(Z$)
    THEN
    L = LEN(Z$)
425 PRINT SPC(TB+6):
430 PRINT MID$(Z$,X,L - X + 1)
440 IF L = LEN(Z$)
    THEN
    447
    X = X + 33 - TB:
    GOTO 420
447 IF EFLAG = 1
    THEN
    PRINT "-----"
448 RETURN
449:
*****
500 REM MAIN MENU
-----
510 HOME:
    VTAB 3:
    PRINT " *** APPLE BASIC PRETTYT
    RINTER ***"
520 VTAB 8:
    PRINT " I - INDEX TO ALL REM ST
    ATEMENTS"
550 PRINT:
    PRINT " P - PRINT PROGRAM"
565 PRINT:
    PRINT " Q - QUIT"
580 VTAB 22:
    PRINT:
    GET A$:
    IF A$ = "Q"
    THEN
    END
590 IF A$ = "P"
    THEN
    GOSUB 1000:
    GOTO 500
591 IF A$ = "I"
    THEN
    GOSUB 1800:
    GOTO 500
599 GOTO 580
999:
*****
1000 REM PAGE LIST
-----
1001 PR# 2
1002 TB = 0:
    REM INITIALIZE TAB
-----
1005 HOME
1010 FOR I = 1 TO N:
    Z$ = A$(I):
    GOSUB 400
1030 IF PEEK(-16384) > 127
    THEN
    POKE -16384,0:
    GET A$
*****
1040 REM CHECK FOR NEW TAB (FOR OR
    NEXT)
-----
1055 IF MID$(A$(I),7,3) = "FOR"
    THEN
    TB = TB + 3
1080 IF MID$(A$(I+1),7,4) < >
    "NEXT"
    THEN
    1089


```

```


1085 COUNT = 1:
    FOR Q = 5 TO LEN(A$(I+1))
1086 IF MID$(A$(I+1),Q,1) =
    " "
    THEN
    COUNT = COUNT + 1
1087 NEXT Q
1088 TB = TB - 3 * COUNT
1089 NEXT I:
    PRINT
1090 VTAB 24:
    PRINT "PRESS ANY KEY FOR MAIN MEN
    U...":
    GET A$:
    RETURN
1100 END
1799:
*****
1800 REM REM-INDEX
-----
1810 HOME:
    VTAB 2:
    PRINT " ***** REMARK INDEX #
    *****
1820 PRINT:
    FOR I = 1 TO N
1825 IF MID$(A$(I),7,3) < > "REM"
    THEN
    1900
    T = 10
1828 IF MID$(A$(I),T,1) = " "
1830 THEN
    T = T + 1:
    GOTO 1830
1835 Z$ = LEFT$(A$(I),6) + " " +
    RIGHT$(A$(I), LEN(A$(I)) -
    T + 1)
1838 GOSUB 400
1840 IF PEEK(37) < 21
    THEN
    1900
    VTAB 24:
    PRINT " PRESS RETURN FOR MORE
    , ESC TO QUIT "
1860 GET A$:
    IF ASC(A$) = 27
    THEN
    RETURN
1870 HOME
1900 NEXT I
1910 VTAB 23:
    PRINT "PRESS ANY KEY FOR MAIN MEN
    U...":
    GET A$:
    RETURN
*****
2000 REM INITIAL FORMATTING
2001 REM LEFT-JUSTIFIES LINE NUMBERS
    AND ALIGNS STATEMENT BEGINNINGS
-----
2002 IF LEFT$(A$(1),1) = " "
    THEN
    TYP = 1:
    REM TYP=1 MEANS INTEGER BASIC
-----
2005 FOR I = 1 TO N
2010 A = ASC(LEFT$(A$(I),1)) -
    ASC("0")
2012 IF TYP = 0
    THEN
    2020
    K = 1
2013 IF MID$(A$(I),K,1) = " "
2014 THEN
    K = K + 1:
    GOTO 2014
2015 A = ASC(MID$(A$(I),K,1)) -
    ASC("0")
2016 IF A < 0 OR A > 9
    THEN
    2100
    GOTO 2200
2017 IF A < 0 OR A > 9
    THEN
    2100
    J = 1
2030 A = ASC(MID$(A$(I),J,1)):
2040 A = A - 128 * INT(A / 128):
    IF (A > 47 AND A < 58) OR A =
    32
    THEN
    J = J + 1:
    GOTO 2040
    IF J > 6
    THEN
    2200
    FOR K = J TO 6:
    A$(I) = LEFT$(A$(I),J-1)
    + " " + RIGHT$(A$(I), L
    EN(A$(I)) - J + 1):
    NEXT
    GOTO 2200
2060 J = 1
2100 A = ASC(MID$(A$(I),J,1)):
2110 IF A = 32
    THEN
    J = J + 1:
    GOTO 2110
2120 A$(I) = " " + RIGHT$(A$
    (I), LEN(A$(I)) - J + 1)
2200 NEXT I:
    X = FRE(0):
    RETURN

```

meet a REAL PLUS




Color Computer 4K \$310
w/Ext. Basic 16K \$489



Model II 64K
\$3300



Atari 800 32K \$789



Model III 16K
\$859

These are just a few of our many fine offers — computers, peripherals, modems, printers, disc drives and an unusual selection of package values. Call TOLL FREE today and check us out for price and warranty.

Factory warranties on Apple and Atari equipment. Other equipment carries manufacturer's warranty or Computer Plus 180 day extended warranty. Combined warranties carry Computer Plus 180 day warranty or original manufacturer's warranty.

DEALER INQUIRIES ARE INVITED
Prices subject to change without notice.
TRS-80 is a registered trademark of Tandy Corp.

call TOLL FREE
1-800-343-8124

computer plus

Write for your
free catalog ...

Dept. K
245A Great Road
Littleton, MA 01460
(617) 486-3193

✓362

ENGINEERING AND PRODUCTION CONTROL SYSTEMS




Company founder and president, Walter L. Myers (right), pictured with production engineer Joe Zellers who developed the production control software for the MSI computer system.

system. Since 1975, the MSI system has been expanded to accommodate four users simultaneously, performing a variety of plant monitoring functions and management programs."

"The system is equipped with 10 megabytes of hard disk storage presently and we plan to add an additional 10 megabytes of storage soon. The maximum downtime has been only one or two days in the 5 years that the system has been in operation. MSI has provided excellent technical support and willingness to help us with our special requirements. We have nothing but praise for MSI, they have provided excellent system support."

SPRING ENGINEERING AND DESIGN

"All of the production at Myers Spring is performed to exact customer specifications rather than to the manufacture of standard spring products. This causes an ever increasing demand for quick and efficient design and engineering capabilities. Many parameters have to be taken into consideration in the design of any particular spring, including wire size, wire type, material modulus, spring diameter, number




One of four workstations where design engineering, checking of sales order status, and production control monitoring is performed.

THE COMPANY:

**MYERS SPRING COMPANY, INC.
LOGANSPOUT, INDIANA**

Myers Spring Company, Inc. was founded 35 years ago by Walter L. Myers for the manufacture of small mechanical springs which are used widely in mechanical appliances, electrical equipment, and by the automotive, construction, and many other industries. The Myers Spring company has grown to several million dollars in annual sales and employs approximately 50 people in its production facility.

Production engineer Joe Zellers comments, "we began looking at computer systems approximately ten years ago in order to keep up with the increasing demand of order processing, custom mechanical spring design engineering, and production control. In 1975, we selected the MSI system because they were the first company in the microcomputer industry to offer the necessary peripherals which would convert a microcomputer system into a usable business



The production facility at Myers Spring Co. is equipped with many automated machines for mechanical spring production.

of turns per inch, free length, spring loading, rate, solid height, working stress, working temperature, number of operating cycles, hysteresis, resonant frequency, expansion, and whether the spring has to be ground or not. It used to take over an hour for an engineer to design a spring taking into account all of these parameters. However, with the engineering software which we have developed for the MSI system, spring design can be completed in less than one minute by simply keying in the desired parameters. The MSI computer system not only designs the spring for us but prepares a complete quotation for the customer after consideration of the material to be used, the amount of waste, which equipment the production will use, the speed of the machines, the necessary labor rate, as well as the desired percentage of profit."

SALES QUOTATION SYSTEM

Following the computer spring design procedure, with automatic quotation feature, the actual production begins. Each quotation is reviewed and compared to actual job cost reports on the production run in order to make any necessary refinements in the quotation system software. This feature of our system has greatly improved our ability to prepare accurate quotations and to insure profitability of the company.

PRODUCTION CONTROL/JOB COST ACCOUNTING

Each production work order is tracked by the computer system at each stage of the production process. First, each order is checked against the customer quotation for accuracy. As each order is processed, exact shop labor time is recorded, for each production machine used, and each stage of the production process. Summary reports are produced showing the total amount of material used, time used on each production machine, amount of material used, and a total cost figure for each work order.

SALES SUMMARY REPORTS

The system is designed to produce monthly sales summaries which show the amount of products sold by each salesman, complete with dates, order numbers, type of product, quantity, type of material, material cost, sales commissions, etc. Totals for each desired category and for each salesman are reproduced.

ACCOUNTS RECEIVABLE SYSTEM


Each morning, invoices are generated for orders which will be shipped that day. The accounts receivable system maintains accounts for over 500 active customers. The system produces monthly statements complete with aging of open invoices.

MULTI USER CAPABILITY

The MSI system is equipped with four user terminals presently which are available for use simultaneously by the following departments: Order department, for entering new orders and checking order status. Inventory department, used for checking to see whether a particular product has been produced previously. Invoicing/Cost Accounting, used for preparation of invoices and for entry of labor and material cost accounting information. Design Engineering, used by company engineers to design new products.



Order entry, invoicing, monthly statements, and other management reports are carried out at this workstation at Myers Spring Co.



The MSI system at Myers Spring Company is equipped with 10 megabytes of hard disk memory, dual floppy disk drives, a high speed printer, and four user CRT terminal workstations.

GENERAL LEDGER TIE-INS

The MSI system automatically prepares journals for cost accounting information and sales data which can then be posted to the general ledger. Complete income statements and balance sheets are produced by the general ledger programs on the system.

MULTIPLE MANAGEMENT REPORTS

The MSI system is used in many different areas of the company in order to provide more efficient and effective management of our production facilities. Several of the reports which we obtain from the system are: **production schedules, due list for orders, new orders list, production summary by department, salesman's reports, individual customer reports and order histories, time studies, sales quotations, design engineering, sales summaries, customer statements, general ledger balance sheet and income statements.**


Consider MSI, evaluate us, talk to our users, and we think you'll buy your business system from us!

If you would like to know how an MSI business system can help you make your business more profitable, call or write, **MIDWEST SCIENTIFIC INSTRUMENTS, INC., 220 W. Cedar, Olathe, KS 66061, 800-255-6638, Telex 42525 or 437049**

MSI Helping to make your business run better.

✓ 144

Time for the Apple



By David Goss

Computerists often find it useful to keep track of time. To fill this need you can buy Apple's ready-to-plug-in Clock/Calendar Card for around \$280. Or, you might want to construct a versatile real-time clock/timer circuit card that will cost you only \$50 to \$60. It is designed for the Apple, but can be adapted to other systems by modifying the bus interface.

Our needs for timekeeping in computing generally fall into one of two categories. The first is interval timing; i.e., controlling or measuring the duration of an event, or the time between events. For example, computer-generated music and other sounds can be created by timing the interval between speaker pulses to determine pitch, and by timing the duration of each tone. You can do this with instruction loops, but using a hardware timer provides much greater accuracy and resolution, and does not require experimenting or cycle-counting to derive the number of instructions necessary for a desired time interval.

The second category involves the time-of-day and/or the date. Your computer might need a clock, for example, to determine when to turn lights or appliances in your computer-controlled home on or off, or to activate your modem to get the opening stock market reports while you catch an extra 40 winks. Functions of this sort are easily implemented with the help of a hardware clock.

You can make your timing device more useful by giving it the ability to generate interrupts to the processor. You can then set up a desired time function and put the processor to work doing other things until the interrupt occurs to indicate that the

function is complete, rather than having to continuously monitor time.

Thanks to large-scale integrated circuits, you can make a clock, calendar, timer and interrupt processor with just two large-scale integration (LSI) circuits, to provide the following features:

- Time in hours, minutes and seconds
- 12- or 24-hour format
- Date in month, day and year
- Day of the week
- Programmable interrupts once every second, minute or hour
- Two programmable interval timers
- Battery operation while the computer is turned off

The LSI circuits are the OKI MSM5832 real-time clock/calendar and the 6522 versatile interface adapter.

Clock/Calendar

The MSM5832 is an 18-pin CMOS IC which provides the full range of clock/calendar functions. It features an on-chip 32,768 Hz crystal-controlled time base, which is counted down to provide addressable four-bit binary-coded decimal (BCD) data describing hours, minutes, seconds, year, month, date and day of week. Data access is controlled by a four-bit address and by chip select, read and write inputs. Table 1 shows the address selection codes. A hold input is also provided to prevent the internal registers from being counted down during read or write operations. Timing accuracy will not be affected by the hold input if it is active for less than one second at a time.

The circuit also provides pulse outputs at rates of 1024 Hz, once/second, once/minute and once/hour on the data lines under the conditions speci-

fied in Table 2. I'll describe the use of these outputs to generate interrupts later.

The clock may be programmed to operate in either 12- or 24-hour format. In the 12-hour format it provides an AM/PM indicator. The calendar will roll over correctly for 30-day and 31-day months, and can adjust for leap years. The latter requires that the leap year bit in register 8 be set prior to midnight of Feb. 28 in the leap year. The clock will count a 29th day in February, and will automatically reset to give 28-day counts in succeeding Februarys. The leap year bit thus requires setting once every four years.

The MSM5832 is too slow to interface directly with the Apple bus. The hold input, for example, must be active for a minimum of 150 μ s prior to a read or write, and address inputs must be stable for at least six μ s prior to a read. An interface buffer is therefore necessary.

Versatile Interface Adapter

I selected the 6522 as the bus interface device primarily for its timer and interrupt ability. A block diagram of the device is shown in Fig. 1. Its full capability is too extensive to describe here, but I will cover the major points of interest.

The 6522 provides two bidirectional eight-bit I/O ports, each line of which can be independently programmed by the corresponding data direction register to act as either an input or an output. There are also two

David Goss (2021 Kornat Drive, Costa Mesa, CA 92626) is an electronics engineer employed in the aerospace industry. He has been an Apple user for a year and a half, and enjoys both hardware and software design.

control lines associated with each port, with each control line (CA1, CA2, CB1, CB2) programmable via the peripheral control register as either an interrupt input or an output. The port B control lines can also be used as a serial port to/from the shift register.

There are two on-chip 16-bit timers whose operating modes are controlled by the auxiliary control register. Both timers operate by counting down from a preset value and set interrupt flags when the count reaches zero. Timer T1 counts down on the 1-MHz-system clock, and so can time intervals of from one to 65,535 us. It can operate in either a one-shot or free-running (repeating) mode.

Countdown values are stored in two eight-bit latches. In the free-running mode, the contents of these latches are automatically transferred to the counter each time the count reaches zero. The latches can be loaded while the timer is counting, thus letting you modify the timing interval "on the fly."

Timer T2 can be used as a second one-to-65,535 us interval timer, or can be programmed to count down on pulses applied to line 6 of port B. That feature is used in this clock circuit to count on the 1024 Hz output from the clock chip, thus giving a timing range of (approximately) one to 65,535 ms.

The 6522 can handle seven separate interrupts, one each from CA1, CA2, CB1, CB2, T1, T2 and the shift register. Each interrupt has a corresponding bit in each of two registers, the interrupt enable register and the interrupt flag register. The interrupts may be selectively enabled or disabled by setting the appropriate bits in the IER to 1 or 0, respectively.

When an interrupt condition is met, a specified flag bit in the IFR is set. Bit 7 of the IFR is also set when any of the flag bits are set. If a flagged interrupt is enabled, the 6522 will lower the interrupt request (IRQ)

Address				Internal Counter	Data				Data Range	
A ₃	A ₂	A ₁	A ₀		D ₃	D ₂	D ₁	D ₀		
0	0	0	0	sec lo					0-9	Set to zero regardless of input when written to
0	0	0	1	sec hi	*				0-5	
0	0	1	0	min lo					0-9	
0	0	1	1	min hi	*				0-5	
0	1	0	0	hr lo					0-9	
0	1	0	1	hr hi	▲	▲			0-1 0-2	D ₂ = 1 for PM D ₃ = 1 for 24 hr D ₂ = 0 for AM D ₃ = 0 for 12 hr
0	1	1	0	day of wk	*				0-6	
0	1	1	1	day lo					0-9	
1	0	0	0	day hi	*	▲			0-3	D ₂ = 1 for 29 days in Feb
1	0	0	1	mo lo					0-9	
1	0	1	0	mo hi		*	*		0-1	
1	0	1	1	yr lo					0-9	
1	1	0	0	yr hi					0-9	

* Unused bits

▲ Bits used for AM/PM, 12/24 hr, and leap year

Table 1. Clock address codes. (From the March 1980 MSM5832 data sheets supplied by OKI Semiconductor, 1333 Lawrence Expressway, Santa Clara, CA.)

line, signalling the processor that the interrupt has occurred. Once set, the interrupt flags can be cleared directly by writing a 1 to that bit of the IFR, or indirectly as defined in Table 3.

Table 4 shows the address codes and functions of all 16 registers of the 6522.

Putting It All Together

The circuit schematic (Fig. 2) shows the interconnection of the MSM5832, 6522 and supporting circuitry, and the required connections to the Apple bus.

The lower four lines of port B and the upper four lines of port A on the 6522 are used as control outputs to the clock chip, while the lower four lines of port A are connected to the clock data lines. These lines are used as outputs when writing to the clock

and as inputs when reading the clock. The CA2, CB1 and CB2 lines are also connected to the data lines so that the timing pulses on these lines (once/second, once/minute, and once/hour) can be used as programmable interrupts. The 1024 Hz signal from D0 of the 5832 is connected to the 6522's PB6 input for use in conjunction with timer T2, as described earlier.

In addition to the two main ICs, it is necessary in this circuit to provide the address decode for the 6522 chip select. The objective here is to use the 16 peripheral I/O addresses, which Apple has reserved for each card slot, to address the 16 6522 registers. These addresses are between \$C0n0 and \$C0nF, where n is the slot number plus \$8 (\$ indicates a hexadecimal number).

The Apple peripheral bus provides a decoded access signal (device select) for this purpose, but unfortunately, it becomes active coincident with the rising edge of the phase 0 clock. That is too late for the 6522, which requires that the register select and chip select lines be stable 180 ns prior to the clock. We can meet that requirement if we decode the chip select directly from the address bus as shown, using 74LS127 and 74LS130 gates. The gate connections shown in


Conditions	Output	Frequency	Pulse Width
hold = low	D ₀ (1)	1024 Hz	50% duty
read = high	D ₁	1 Hz	122.1 us
c.s. = high	D ₂	1/60 Hz	122.1 us
A ₀ -A ₃ = high	D ₃	1/3600 Hz	122.1 us

(1) 1024 Hz output is independent of hold input.

Table 2. Pulse outputs. (From the MSM5832 data sheets.)

SURPLUS ELECTRONICS

ASCII



ASCII

TRS-80* COMPATIBLE,
IBM SELECTRIC®-BASED
I/O TERMINAL with
ASCII conversion installed: **\$645.00**

Many Other Items Available:
Tape Drives; Cable;

Cassette Drives; Wire; Power Supplies (5 volt 35
amp, others); Displays; Cabinets; Transformers;
Heat Sinks; Printers; Components.

Send for free catalog.

WORLDWIDE ELECT. INC.

130 Northeastern Blvd.

Nashua, NH 03062 ✓122


Phone orders accepted using
VISA or Master Charge

TOLL FREE 603-889-7661 • 1-800-258-1036

TRS-80 is a trademark of the Radio Shack Division of Tandy Corporation.

\$73.80*

Single Board Computer



* 100 piece price, model MCL11

6800 MPU, serial I/O, parallel I/O, RAM,
EPROM, 44-pin 4½" x 6½" PCB

EXPANSION MODULES

RAM, ROM, CMOS RAM/battery, analog
I/O, serial I/O, parallel I/O, counter/
timer, 488 GPIB, EPROM programmer,
power fail detect/power on reset



Wintek Corp.
1801 South Street
Lafayette, IN 47904
317-742-8428

Bit #

Set by

Cleared By

0	Active transition of the signal on the CA2 pin.	Reading or writing the A port Output Register (ORA) using address 0001.
1	Active transition of the signal on the CA1 pin.	Reading or writing the A Port Output Register (ORA) using address 0001.
2	Completion of eight shifts.	Reading or writing the Shift Register.
3	Active transition of the signal on the CB2 pin.	Reading or writing the B Port Output Register.
4	Active transition of the signal on the CB1 pin.	Reading or writing the B Port Output Register.
5	Time-out of Timer 2.	Reading T2 low order counter. Writing T2 high order counter.
6	Time-out of Timer 1.	Reading T1 low order counter. Writing T1 high order counter.

Table 3. Interrupt flag register. (From the Jan. 1978 SY6522 data sheets supplied by Synertex, PO Box 552, Santa Clara, CA.)

the schematic assume that you are installing the clock card in slot 4. Table 5 gives alternate connections for other slots.

The only other active circuit element required is the inverting circuit that drives the 5832 chip select line. This is necessary because a reset, which occurs when you turn the Apple on or press reset, causes the 6522 to go into a state in which all of the I/O lines are in the high-impedance input mode. Since these lines have internal pull-up resistors, they look at that point like logic 1 signals to the 5832 inputs, one of which is the hold line. A reset would therefore stop the clock.

By connecting the chip select as shown, you can deselect the 5832 when the reset occurs. In this condition the clock continues to count, since the hold and all other inputs are disabled. The next write or read to the clock card can then set the control

inputs back to the proper states.

The battery provides power to keep the clock running when the computer is off. The specifications say that a minimum of 2.2 V are required in the standby mode, so a battery supply of about 3 V is adequate. The specified battery current is 30 microamps (maximum) at 3 V, but measurements on a couple of samples showed only 5 to 7 microamps. At that rate a wide range of batteries would be suitable, including some of the button cells used in watches and calculators. Rechargeable cells could be used of course, but, considering the low current drain and consequent long life available from nonrechargeable cells, I did not feel that recharging was worth the extra circuitry required.

The final choice of battery in my case boiled down to one which was readily available and easy to connect. Ease of connection was important

Register Number	RS3	RS Coding RS2	RS1	RS0	Register Desig.	Write	Description	Read
0	0	0	0	0	ORB/IRB	Output Register "B"	Input Register "B"	
1	0	0	0	1	ORA/IRA	Output Register "A"	Input Register "A"	
2	0	0	1	0	DDRB	Data Direction Register "B"		
3	0	0	1	1	DDRA	Data Direction Register "A"		
4	0	1	0	0	T1C-L	T1 Low-Order Latches	T1 Low-Order Counter	
5	0	1	0	1	T1C-H	T1 High-Order Counter		
6	0	1	1	0	T1L-L	T1 Low-Order Latches		
7	0	1	1	1	T1L-H	T1 High-Order Latches		
8	1	0	0	0	T2C-L	T2 Low-Order Latches	T2 Low-Order Counter	
9	1	0	0	1	T2C-H	T2 High-Order Counter		
10	1	0	1	0	SR	Shift Register		
11	1	0	1	1	ACR	Auxiliary Control Register		
12	1	1	0	0	PCR	Peripheral Control Register		
13	1	1	0	1	IFR	Interrupt Flag Register		
14	1	1	1	0	IER	Interrupt Enable Register		
15	1	1	1	1	ORA/IRA	Same as Reg 1 Except No "Handshake"		

Table 4. 6522 address codes. (From the SY6522 data sheets.)


MODEL II



26-4002
64K 1 Drive
\$3440.00

26-4160 1 Drive Exp.....	\$1034.00
26-4161 2 Drive Exp.....	1574.00
26-4162 3 Drive Exp.....	2114.00
26-4530 Scripsit II.....	265.00
26-4512 Profile II.....	162.00
26-4511 Visicalc II.....	265.00
26-4501 Gen Ledger.....	180.00
26-4506 Mail List.....	72.00

PRINTERS



CENTRONICS BEST PRICES

Fast 100 CPS Centronics	
730-1A Printer.....	\$577.00
Text Quality Centronics	
737-1 Printer.....	\$737.00

\$ DISCOUNT \$ TRS-80® COMPUTER SPECIALISTS

DEALER A301

CALL US... SAVE MONEY


We carry the full line of TRS-80 Computers. All other R.S. software, furniture, and accessories at discount from catalog price. We stock most items to assure you fast delivery and save you money.

26-1140 Expansion Interface.....	\$249.00
26-1141 16K Exp. Interface.....	359.00
26-1142 32K Exp. IInterface.....	469.00
26-1145 RS232C Board.....	84.00
26-1160/1 Mini Disk Drive.....	419.00
26-1563 Scripsit-Disk.....	79.00
26-1566 Visicalc.....	83.00

*****PRINTERS*****

26-1155 Quick Printer.....	187.00
26-1167 9½ Dot Matrix Printer.....	360.00
26-1166 Line Printer VI.....	1080.00
26-1158 Daisy Wheel II.....	1799.00
26-1165 Line Printer V.....	1710.00

Pocket Computer




26-3501 1.9K P.C.....	\$221.00
26-3503 Cassette IF.....	45.00
14-812 Recorder.....	72.00

MODEL III



26-1061 4K I.....	\$629.00
26-1062 16K III.....	865.00
26-1063 32K III	
W/2 Drives, RS232.....	2225.00

COLOR



26-3001 4K.....	\$353.00
26-3002 16K Ext. Basic.....	533.00
26-3008 Joysticks.....	22.50
26-3010 Color Video.....	353.00
26-1206 Recorder.....	54.00



commodore
AUTHORIZED DEALER
CALL FOR PRICES

ALL POCKET AND COLOR
COMPUTER SOFTWARE
SOLD AT DISCOUNT

WRITE US FOR A
FREE CATALOG

1-800-841-0860 Toll Free Order Entry

MICRO MANAGEMENT SYSTEMS, INC. ✓100

No Taxes on Out Of
State Shipments

Immediate Shipment
From Stock on Most Items

DOWNTOWN PLAZA SHOPPING CENTER
115 C. SECOND AVE. S.W.
CAIRO, GEORGIA 31728

(912) 377-7120 Ga. Phone No. & Export


TRS-80 is a registered trademark of the Tandy Corp.

R.S. 90 Day Limited Warranty
F-48 Form Provided

Largest Inventory
In The S.E. U.S.A.

Buy by Mail and SAVE!

COMPUTERS



Intertec Superbrain SPECIALS

64K Ram, List \$3495 \$2595
64K Quad, List \$3995 \$2995

NorthStar

Horizon I 32K DD List \$2695 \$1989*
Horizon I QD List \$2995 \$2245*
Horizon 2 32DD List \$3095 \$2289*
IntersystemDPS-1 List \$1749 \$1495*

Call for latest NorthStar and
Intersystem Prices



Cromemco Z-2H, List \$9995 \$7945
System 2, 64K List \$4695 \$3749
System 3, 64K, List \$7995 \$6395

Disk Systems

Thinker Toys Discus 2D \$939
Dual Discus 2D \$1559
Discus 2 + 2, List \$1549 \$1259
M26 Hard Disk, List \$4995 \$3949

Printers & Terminals

Paper Tiger IDS-445 \$649
with graphic option \$719
Centronics 730-1, List \$795 \$549
737-1, List \$995 \$769
704-9 180 cps \$1495
703-9 180 cps \$1569
TI 810, List \$1895 \$1489
NEC SPINWRITER 5530 \$2395
NEC SPINWRITER 5515 \$2395
Diablo 630 List \$2711 \$2399
Intertube III List \$895 \$729
Zenith Z-19 \$719
Televideo 912C \$679
920C \$799
950 \$999
Hazeltime 1420 \$789
1500 \$845
Soroc 120 List \$995 \$689
IQ135 \$719
140 \$994

Computers Wholesale

P.O. Box 144 Camillus, NY 13031 ✓ 227

VISA (315) 472-2582

Most items in stock for immediate delivery. Factory sealed cartons, w/full factory warranty. NYS residents add appropriate sales tax. Prices do not include shipping. VISA and Master Charge add 3%. C.O.D. orders require 25% deposit. Prices subject to change without notice.

Slot	Address	74LS27			74LS30		
		9	10	11	4	5	12
1	CO9x	GND	A5	A6	A4	A7	PUB
2	COAx	GND	A4	A6	A5	A7	PUB
3	COBx	GND	GND	A6	A4	A5	A7
4	COCx	GND	A4	A5	A6	A7	PUB
5	CODx	GND	GND	A5	A4	A6	A7
6	COEx	GND	GND	A4	A5	A6	A7
7	COFx	GND	GND	A4*	A5	A6	A7

* requires inverting A4

Table 5. Chip select address decode.

because many candidate cells, such as the button types, require special clips or holders that are not generally available. My choice was a single 3 V alkaline cell (#532), which is available in camera shops. It features snap contacts, like those on 9 V transistor batteries, which provide a quick and positive connection. This battery should provide several years of service.

The diodes provide the required isolation between the battery and the computer's 5 V bus. Germanium diodes (1N270) were used because of their low (0.2 V) forward voltage drop. The series resistor is optional. I put it in just to provide some isolation to the battery in the event of a diode short.

Construction

The circuit was constructed on an Apple prototype card, using sockets for the ICs. You can take your choice of wiring method. I used solder connections with #30 solid conductor insulated wire-wrap wire. That type of

wire is easily formed around the socket pins, solders easily, and will lie flat against the card even when there is excess length.

The only awkward part of building up the card is the battery mounting. If you use the suggested battery you will find that it can be mounted directly on the card, but will cause a tight fit with respect to the next higher card. You could eliminate that problem by using slot 7. Otherwise, if you put the battery on the card, be sure to insulate the case so that it won't short anything. My solution was to mount the battery on the inside of the computer case using a stick-on wire tie pad. A pair of wires then connect the battery to the card. Not elegant, but practical. One advantage is that a battery leak won't be likely to seriously damage anything.

There is one option not shown in the schematic that you may be interested in. The 5832 has an ADJ input (pin 15), which is shown connected to ground. If you wish, you can connect that pin through a momentary con-





Fig. 1. SY6522 block diagram. (From the SY6522 data sheets.)

NOW THAT YOU'RE SEEING DOUBLE YOU NEED MORE ROOM...



DOUBLEVISION™ 80 x 24 Video Display from Computer Stop

DoubleVision is the time-tested upper-and-lower-case Video Display. And now it has a host of new features. Like the availability of a completely commented source listing of software and hardware schematics. Or the inclusion of a Sysgen program to select type of cursor, monitor band width and display of control characters.


Moreover, DoubleVision is compatible with CCA Data Management (and full screen map-

ping), Easywriter Professional System, Apple Pie 2.0, PASCAL, Z-80 Softcard, MAGIC-WAND and WORDSTAR.

It's the only 80-column card that has software on disk making it easy to provide updates. In fact, updates are automatically mailed to our customers and *billed* for cost of disk and shipping only. In short, DoubleVision is adaptable to meet your needs.

The price? It's just \$295.

...AND HERE'S MORE ROOM!



The CS16K RAM Card (compatible with PASCAL, CP/M®, DOS 3.3 and other Apple software)

When you add the CS16K RAM Card to your Apple II with 48K bytes of RAM already in place, you immediately increase your capacity to 64K.

The CS16K RAM Card is compatible with PASCAL, Digital Research's CP/M, DOS 3.3, COBOL, FORTRAN, Personal Software's VisiCalc, PILOT, Integer BASIC, Applesoft BASIC and other software cur-

rently used with APPLE II.

What's more, the CS16K RAM Card is backed by the Computer Stop reputation for excellent service. In fact, **we've doubled the warranty to 180 days**, instead of the usual 90.

And we've saved the best 'til last. The Price. It's only \$195.



computer stop

Your best stop for Apple products.

16919 Hawthorne Blvd.
Lawndale, CA 90260
(213) 371-8500

Available at select
Apple dealers.

283

Apple is a trademark of Apple Computer, Inc.
CP/M is a trademark of Digital Research

2545 W. 237th Street
Torrance, CA 90505
(213) 539-7670

Dealers: Ask about
special-priced demo unit.

Now with added words!*

ELECTRIC MOUTH



for S100, Elf II, Apple
TRS-80, Level II® From \$99.95 kit

Now — teach your computer to talk,
increasing interaction between you
and your machine.

That's right: the ELECTRIC MOUTH actually lets your computer talk! Installed and on-line in just minutes, it's ready for spoken-language use in office, business, industrial and commercial applications, and in games, special projects, R&D, education, security devices — there's no end to the ELECTRIC MOUTH's usefulness. Look at these features:

- Supplied with 143 letters/words/phonemes/numbers, capable of producing hundreds of words and phrases.
- Expandable on-board up to thousands of words and phrases with additional speech ROMs (see new speech ROM described below).
- Four models, that plug directly into S100, Apple, Elf II and TRS-80 Level II computers.
- Get ELECTRIC MOUTH to talk with either Basic or machine language (very easy to use, complete instructions with examples included).
- Uses National Semiconductor's "DigitalTalker."
- Includes on-board audio amplifier and speaker, with provisions for external speakers.
- Installs in just minutes.

Principle of Operation: The ELECTRIC MOUTH stores the digital equivalents of words in ROMs. When words, phrases and phonemes are desired, they simply are called for by your program and then synthesized into speech. The ELECTRIC MOUTH system requires none of your valuable memory space except for a few addresses if used in memory mapped mode. In most cases, output ports (user selectable) are used.

SPOKEN MATERIAL INCLUDED (VOX I)

one	eighteen	at	dollar	inches	number	ss	c	t
two	nineteen	cancel	down	is	of	second	d	u
three	twenty	case	equal	it	off	set	e	v
four	thirty	cent	error	kilo	on	space	f	w
five	forty	400hertz tone	feet	left	out	speed	g	x
six	fifty	80hertz tone	flow	less	over	star	h	y
seven	sixty	20ms silence	fuel	lesser	parenthesis	start	i	z
eight	seventy	40ms silence	gallon	limit	percent	stop	j	
nine	eighty	80ms silence	go	low	please	than	k	
ten	ninety	160ms silence	gum	lower	plus	the	l	
eleven	hundred	320ms silence	great	mark	point	time	m	
twelve	thousand	centi	greater	meter	pound	try	n	
thirteen	million	check	million	mile	pulses	up	o	
fourteen	zero	comma	high	rate	volt	p		
fifteen	again	control	higher	minus	re	weight	q	
sixteen	ampere	danger	hour	minute	ready	a	r	
seventeen	and	degree	in	near	right	b	s	

ADDITIONAL VOCABULARY NOW AVAILABLE (VOX II)

abort	complete	fifth	light	put	station
add	continue	fire	load	quarter	switch
adjust	copy	first	lock	range	system
alarm	correct	floor	longer	reached	temperature
alert	crease	fourth	more	receive	test
all	"de"	forward	move	record	"th"
ask	deposit	from	next	reverse	thank
assistance	dial	gas	no	red	third
attention	door	get	normal	repair	this
blue	east	going	north	repeat	turn
brake	"ed"	green	not	replace	under
button	emergency	hale	notice	room	use
buy	enter	heat	open	safe	waiting
call	entry	hello	operator	second	warning
called	"er"	help	secure	was	
caution	"eth"	hurts	pass	select	water
celsius	evacuate	hold	per	send	west
centigrade	exit	hot	power	service	wind
change	fail	press	side	slow	window
circuit	failure	incorrect	pressure	slow	yellow
cigar	fahrenheit	intruder	process	slower	yes
close	fast	key	pull	smoke	zone
cold	faster	level	push	south	

*Registered Trademarks

Continental U.S.A. Credit Card Buyers Outside Connecticut

TO ORDER

Call Toll Free: 800-243-7428

To Order From Connecticut, or For Technical Assistance, call (203) 354-9375

NETRONICS R&D LTD.
333 Litchfield Road, New Milford, CT 06776

Please send the items checked below:

- ☐ S100 "Electric Mouth" kit w/Vox I \$ 99.95
- ☐ Elf II "Electric Mouth" kit w/Vox I \$ 99.95
- ☐ Apple "Electric Mouth" kit w/Vox I \$119.95
- ☐ TRS-80 Level II "Electric Mouth" kit w/Vox I \$119.95
- ☐ VOX II (Second Word Set) \$ 39.95

Add \$20.00 for wired tested units instead of kits. VOX II postage & insurance \$1.00, all others \$3.00 postage and insurance. Conn. res. add sales tax.

Total Enclosed \$

☐ Personal Check ☐ Cashier's Check/Money Order

☐ Visa ☐ Master Charge (Bank No. _____)

Acct. No. _____ Exp. Date _____

Signature _____

Print Name _____

Address _____

City _____

State _____ Zip _____




Fig. 2. Apple clock/calendar.

Listing 1. Set Clock routine.

```

10 REM *****
12 REM * SET CLOCK ROUTINE *
14 REM * D.GOSS 22 AUG 80 *
16 REM *
18 REM *****
20 REM
30 : REM * SET LY=1 TO ENAB LEAP YEAR OPTION
40 :
50 :
60 LY = 0
70 SLOT = 4
80 BA = 49280 + SLOT * 16: REM BASE I/O ADDR
90 RC = 39000: REM ADDR OF RD CLK PROG
92 :
94 : REM * ROUTINE EXITS WITH CLK/TIMER INTERRUPTS DISABLED
99 :
100 B$ = CHR$(7):D$ = CHR$(4)
110 PRINT D$:"BLOAD READ CLOCK"
120 HOME:VTAB 3
130 PRINT "ENTER TIME: HH MM"
140 VTAB 3:HTAB 13
150 INPUT "":T$
160 H1 = VAL ( LEFT$ (T$,1))
180 IF H1 > 1 THEN 800
200 H2 = VAL ( MID$ (T$,2,1))
210 IF H1 = 1 AND H2 > 2 THEN 800
220 N1 = VAL ( MID$ (T$,4,1))
240 IF N1 > 5 THEN 800
260 N2 = VAL ( MID$ (T$,5,1))
350 VTAB 5
370 INPUT "AM OR PM? "M$
380 IF M$ <> "AM" AND M$ <> "PM" THEN PRINT B$:GOTO 350
400 VTAB 7
410 PRINT "ENTER DATE: MM DD YY"
420 VTAB 7:HTAB 13
430 INPUT "":D$
440 M1 = VAL ( LEFT$ (D$,1))
460 IF M1 > 1 THEN 850
480 M2 = VAL ( MID$ (D$,2,1))
490 IF M1 = 1 AND M2 > 2 THEN 850
510 D1 = VAL ( MID$ (D$,4,1))
520 IF D1 > 3 THEN 850
540 D2 = VAL ( MID$ (D$,5,1))
550 IF D1 = 3 AND D2 > 1 THEN 850
560 Y1 = VAL ( MID$ (D$,7,1))
580 Y2 = VAL ( MID$ (D$,8,1))
600 PRINT
610 IF NOT LY THEN 650
620 INPUT "LEAP YEAR? (Y/N) "L$
650 PRINT :PRINT
660 INPUT "PRESS RETURN TO SET CLOCK "A$
670 PRINT :PRINT
680 GOSUB 1000
690 PRINT "CLOCK NOW READS "I: CALL RC: PRINT
700 :
710 :PUKE BA,0: REM RELEASE HOLD

```

More

Listing 1 continued.

```

720 PRINT : PRINT
730 END
799 :
800 REM * TIME INPUT ERROR
810 PRINT B$
820 GOTO 120
849 :
850 REM * DATE INPUT ERROR
860 PRINT B$
870 GOTO 400
999 :
1000 REM * SET TIME
1010 RA = BA + 1: REM ORA ADDR
1020 POKE BA + 14,127: REM DISAB INTERRUPTS
1030 POKE BA + 3,255: REM DDRA
1040 POKE BA + 2,15: REM DDRB
1050 POKE BA,1: REM SET HOLD
1060 IF M$ = "AM" THEN POKE RA,80 + H1: REM HR HI,AM
1070 IF M$ = "PM" THEN POKE RA,84 + H1: REM HR HI,PM
1080 GOSUB 2000
1090 POKE RA,64 + H2: REM HR LO
1100 GOSUB 2000
1110 POKE RA,48 + N1: REM MI LO
1120 GOSUB 2000
1130 POKE RA,32 + N2: REM MI HI
1140 GOSUB 2000
1150 POKE RA,16: REM SEC HI = 0
1160 GOSUB 2000
1170 POKE RA,0: REM SEC LO = 0
1180 GOSUB 2000
1190 POKE RA,160 + M1: REM MO HI
1200 GOSUB 2000
1210 POKE RA,144 + M2: REM MO LO
1220 GOSUB 2000
1230 IF L$ < "Y" THEN POKE RA,128 + D1: REM DAY HI, NORM
1240 IF L$ = "Y" THEN POKE RA,132 + D1: REM DAY HI, LEAP YR
1250 GOSUB 2000
1260 POKE RA,112 + D2
1270 GOSUB 2000
1280 POKE RA,192 + Y1: REM YR HI
1290 GOSUB 2000
1300 POKE RA,176 + Y2: REM YR LO
1310 GOSUB 2000
1320 RETURN
1330 :
1999 :
2000 REM * WRITE DATA
2010 POKE BA,5: REM WRITE ON
2030 POKE BA,1: REM WRITE OFF
2040 RETURN

```

Listing 2. Read Clock routine.

```

0800 1 ;
0800 2 ;READ CLOCK ROUTINE
0800 3 ;REAL TIME CLOCK CARD
0800 4 ;SLOT 4
0800 5 ;
0800 6 ;VERSION 1.6
0800 7 ;07 SEPT 80
0800 8 ;
0800 9 PRLB2 EQU $F94A
0800 10 IOSAVE EQU $FF4A
0800 11 IOREST EQU $FF3F
0800 12 WAIT EQU $FCA8
0800 13 COUT EQU $FDED
0800 14 IORB EQU $C0C0
0800 15 IORA EQU $C0C1
0800 16 DDRB EQU $C0C2
0800 17 DDRA EQU $C0C3
0800 18 HIOSAV EQU $047C
0800 19 TDFLAG EQU $057C
0800 20 ORBSAV EQU $067C
0800 21 ;
0858 22 ORG $9858
0858 23 ORJ $0800
0858 24 ;
0858 25 ENTRY JSR IOSAVE ;TIME/DATE ENTRY
0858 26 LDA 0
0858 27 STA TDFLAG
0860 28 BEQ SETUP
0862 29 TONLY JSR IOSAVE ;TIME ONLY ENTRY
0865 30 LDA 1
0867 31 STA TDFLAG
0868 32 BNE SETUP
086A 33 DONLY JSR IOSAVE ;DATE ONLY ENTRY
086F 34 LDA 2
0871 35 STA TDFLAG
0874 36 SETUP SEI
0875 37 LDA IORB
0878 38 STA ORBSAV
087B 39 OFD
087D 40 STA DDRA
0880 41 LDA OF
0882 42 STA DDRB
0885 43 LDA 1
0887 44 STA IORB
088A 45 LDA 0
088C 46 JSR WAIT
088F 47 LDA 3
0891 48 STA IORB
0894 49 ;
0894 50 LDA TDFLAG
0897 51 CMP 2
0899 52 BEQ DATE
089B 53 LDA 50
089D 54 JSR READ
08A0 55 STA HIOSAV
08A3 56 AND 3
08A5 57 JSR PRINT
08A8 58 LDA 40
08AA 59 JSR RD.PT
08AD 60 LDA 0BA
08AF 61 JSR COUT
08B2 62 JSR 30
08B4 63 JSR RD.PT
08B7 64 LDA 20
08B9 65 JSR RD.PT
08BC 66 LDA 0BA
08BE 67 JSR COUT
08C1 68 LDA 10
08C3 69 JSR RD.PT
08C6 70 LDA 0
08C8 71 JSR RD.PT
08CB 72 LDA 0A0
08CD 73 JSR COUT

```

MMSFORTH VERSION 2.0: MORE FOR YOUR RADIO SHACK TRS-80 MODEL I OR MODEL III !

- ★ **MORE SPEED**
10-20 times faster than Level II BASIC.
- ★ **MORE ROOM**
Very compact compiled code plus VIRTUAL MEMORY makes your RAM act larger. Variable number of block buffers. 31-char-unique word-names use only 4 bytes in header!
- ★ **MORE INSTRUCTIONS**
Add YOUR commands to its 79-STANDARD-plus instruction set!
Far more complete than most Forths: single & double precision, arrays, string-handling, clock, more.
- ★ **MORE EASE**
Excellent full-screen Editor, structured & modular programming
Word search utility
NOTEPADS Letter writer
Optimized for your TRS-80 with keyboard repeats, upper/lower case display driver, full ASCII, single- & double-width graphics, etc.
- ★ **MORE POWER**
Forth operating system
Interpreter AND compiler
8080 Assembler
(Z80 Assembler also available)
Intermix 35- to 80-track disk drives
Model III System can read, write & run Model I diskettes!
VIRTUAL I/O for video and printer, disk and tape (10-Megabyte hard disk available)

mmsFORTH

THE PROFESSIONAL FORTH FOR TRS-80

(Over 1,500 systems in use)

Prices:
MMSFORTH Disk System V2.0 (requires 1 disk drive & 16K RAM, 32K for Model III) \$129.95*
MMSFORTH Cassette System V2.0 (requires Level II BASIC & 16K RAM) \$89.95*

AND MMS GIVES IT PROFESSIONAL SUPPORT

Source code provided
MMSFORTH Newsletter
Many demo programs aboard
MMSFORTH User Groups
Inexpensive upgrades to latest version
Programming staff can provide advice, modifications and custom programs, to fit YOUR needs.

MMSFORTH UTILITIES DISKETTE: includes FLOATING POINT MATH (L2 BASIC ROM routines plus Complex numbers, Rectangular-Polar coordinate conversions, Degrees mode, more), plus a full Forth-style Z80 ASSEMBLER; plus a powerful CROSS-REFERENCER to list Forth words by block and line. All on one diskette (requires MMSFORTH V2.0, 1 drive & 32K RAM) \$39.95*

FORTHCOM: communications package provides RS-232 driver, dumb terminal mode, transfer of FORTH blocks, and host mode to operate a remote TRS-80 (requires MMSFORTH V2.0, 1 drive & 32K RAM) \$39.95*

THE DATAHANDLER V1.2: a very sophisticated database management system operable by non-programmers (requires MMSFORTH V2.0, 1 drive & 32K RAM) \$59.95*

MMSFORTH GAMES DISKETTE: real-time graphics & board games w/source code. Includes BREAKFORTH, CRASHFORTH, FREEWAY, OHELLO & TICTACFORTH (requires MMSFORTH V2.0, 1 drive & 32K RAM) \$39.95*

Other MMSFORTH products under development

FORTH BOOKS AVAILABLE

MicroFORTH PRIMER - comes with MMSFORTH; separately \$15.00*
USING FORTH - more detailed and advanced than above \$25.00*
INVITATION TO FORTH - detailed beginner book on FORTH \$17.50*
THREADED INTERPRETIVE LANGUAGES - advanced, excellent analysis of MMSFORTH-like language \$18.95*
PROGRAM DESIGN & CONSTRUCTION - intro. to structured program, good for Forth \$8.95*
FORTH - 79 STANDARD MANUAL - official reference to 79-STANDARD word set, etc. \$10.00*
CALTECH FORTH MANUAL - good on Forth internal structure, etc \$10.00*
FORTH SPECIAL ISSUE, BYTE Magazine (Aug. 1980) - we stock this collector's item for Forth users and beginners \$4.00*

* - ORDERING INFORMATION: Software prices include manuals and require signing of a single system, single-user license. SPECIFY for Model I or Model III! Add \$2.00 SH plus \$1.00 per additional book. Mass. orders add 5% tax. Foreign orders add 20% UPS COD, VISA & M/C accepted; no unpaid purchase orders, please.

Send SASE for free MMSFORTH information.
Good dealers sought.

Get MMSFORTH products from your
computer dealer or

**MILLER MICROCOMPUTER
SERVICES (B8)**

61 Lake Shore Road, Natick, MA 01760 ✓ 255
(617) 653-6136

Listing 2 continued.

```

98D0 AD7C04 74 LDA H10SAV
98D3 6A 75 ROR
98D4 6A 76 ROR
98D5 6A 77 ROR
98D6 8008 78 BCS PRINTP ;IF AM/PM IS PM PRINT "P"
98D8 A9C1 79 LDA OC1 ;ELSE PRINT "A"
98DA 20EDFD 80 JSR COUT
98DD 4CE598 81 JMP PRINTM ;PRINT "P"
98E0 A9D0 82 LDA OBO ;PRINT "M"
98E5 A9CD 83 JSR COUT
98E7 20EDFD 85 JSR COUT
98EA 86 ;
98EA AD7C05 87 LDA TDFLAG
98ED C901 88 CMP 1 ;TIME ONLY?
98EF F032 89 BEQ EXIT ;IF SO EXIT
98F1 90 ;
98F3 A202 91 LDX 2
98F3 204AF9 92 JSR PRBL2 ;2 SPACES
98F6 A9A0 93 LDA OAO ;OUTPUT MO HI
98F8 204399 94 JSR RD.PT ;OUTPUT MO LO
98F8 A990 95 LDA OAF ;PRINT SLASH
98FD 204399 96 JSR RD.PT ;READ DAY HI
9900 A9AF 97 LDA OAF ;HASK LEAF YR BITS OFF
9902 20EDFD 98 JSR COUT
9905 A980 99 LDA 80
9909 203399 100 JSR READ
990A 2003 101 AND 03 ;
990C 204C99 102 JSR PRINT
990F A970 103 LDA 70
9911 204399 104 JSR RD.PT ;OUTPUT DAY LO
9914 A9AF 105 LDA OAF ;PRINT SLASH
9916 20EDFD 106 JSR COUT ;OUTPUT YR HI
9918 A9C0 107 LDA OCO
991E A980 109 LDA OBO ;OUTPUT YR LO
9920 204399 110 JSR RD.PT
9923 111 ;
9923 A9A0 112 EXIT LDA OAO
9925 20EDFD 113 JSR COUT ;SPACE
9928 A9F0 114 LDA OFO ;CLK ADDR = $F
992A BDC1C0 115 STA IORA ;SET UNUSED BITS TO ZERO
992D AD7C06 116 LDA ORRSAB ;RESTORE ORR
9930 290F 117 AND OF ;RESTORE 6502 REGISTERS
9932 BDC0C0 118 STA IORB
9935 203FFF 119 JSR IOREST
9938 60 120 RTS
9939 121 ;
9939 122 ;SUBROUTINES
9939 123 ;
9939 BDC1C0 124 READ STA IORA ;SET READ ADDR
993C EA 125 NOP
993D EA 126 NOP
993E EA 127 NOP
993F ADC1C0 128 LDA IORA ;DELAY 6 USEC
9942 60 129 RTS ;READ DATA
9943 BDC1C0 130 ;
9943 EA 131 RD.PT STA IORA ;SET READ ADDR
9946 EA 132 NOP
9947 EA 133 NOP
9948 EA 134 NOP
9949 ADC1C0 135 LDA IORA ;DELAY 6 USEC
994C 290F 136 AND OF ;READ DATA
994E A980 137 ORA OBO ;CLEAR BITS 4-7
9950 20EDFD 139 JSR COUT ;CONV TO ASCII
9953 60 140 RTS ;PRINT CHAR
9954 141 ;
142 END

```

tact switch to Vcc or to the pull-up resistor. Depressing the switch will then cause the clock's second-counter to reset to 0. The minute-counter will remain unchanged if the seconds count was less than 30, but will advance one minute if the seconds count was 30 or more.

I had some trouble locating all of the parts for the circuit, particularly the clock chip and crystal. I finally found that Advanced Computer Products (PO Box 17329, Irvine, CA 92713) had everything I needed.

Making It Play

The trimmer capacitor in the circuit provides a method of fine-tuning the oscillator for accuracy. Getting it set correctly will probably require some trial-and-error attempts over an extended period of time, but to start with, just set it at the midpoint and you should be close. When adjusting, you add capacitance to slow the clock down, and subtract to speed it up. The adjustment is sensitive, so use small increments. With a little patience you should be able to get it accurate to within one second/week or better.

To use the clock/calendar your programs must first set up the 6522 registers, and then write to or read from the 5832, one BCD digit at a time. Sample program listings are included to get you started. To understand how things work, it might be helpful to go through an explanation using the Set Clock program (Listing 1) as an example. This Applesoft program allows the clock and calendar to be set from the keyboard. It programs the clock in the 12-hour mode and includes a leap year option, but does not set day of week.

The actual clock setting routine begins at line 1000, using time and date variables input in lines 100 through 670. Line 1020 makes sure that all 6522 interrupts are disabled by writing a \$7F to the IER. (Interrupts are selectively enabled/disabled by writing to the IER with a 1 or 0, respectively, in bit 7, and a 1 in each bit 0-6 that you want to change.)

Line 1030 puts a \$FF in the DDRA, programming all eight lines of port A as outputs. Line 1040 writes \$0F to DDRB, making the lower four lines (PB0-PB3) outputs and the upper four (which are not used in this operation) inputs. Line 1050 then writes \$01 to output register B (ORB), causing line PB0 to apply the hold signal to the clock.

```


0800 1 ;
0800 2 ;CLOCK DEMO
0800 3 ;VERSION 1.1
0800 4 ;07 SEPT 80
0800 5 ;
0800 6 HOME EQU $FC58
0800 7 IOSAVE EQU $FF4A
0800 8 IOREST EQU $FF3F
0800 9 IORB EQU $C0C0
0800 10 IORA EQU $C0C1
0800 11 DDRB EQU $C0C2
0800 12 DDRA EQU $C0C3
0800 13 PCR EQU $C0C4
0800 14 IFR EQU $C0C5
0800 15 IER EQU $C0C6
0800 16 RDCLK EQU $8558
0800 17 ;
0800 18 ORG $9960
0800 19 OBJ $0800
0800 20 ;
0800 21 ENTRY SEI ;DISABLE 6502 INTERRUPTS
0800 22 JSR HOME
0800 23 LDA $00
0800 24 STA PCR ;PROG CA2 FOR INPUT, NEG ACTIVE EDGE
0800 25 ;
0800 26 LDA $F0
0800 27 STA DDRA ;ENABLE CLK ADDR OUTPUTS
0800 28 STA IORA ;SET CLK ADDR TO $F
0800 29 LDA $0F
0800 30 STA DDRB ;ENABLE CLK CONTROL OUTPUTS
0800 31 STA IORB ;TURN READ CMD ON
0800 32 LDA $81
0800 33 STA IER ;ENABLE CA2 INTERRUPT
0800 34 LDA $INTRPT
0800 35 STA $3FE ;SET INTERRUPT VECTOR LO
0800 36 STA $3FF ;CHECK FOR ANY KEY
0800 37 STA $3FF ;IF NOT, CHECK AGAIN
0800 38 CLI ;ELSE CLEAR KEY STROBE
0800 39 BIT $C000 ;DISABLE 6522 INTERRUPTS
0800 40 RPL KEYIN ;TURN OFF READ CMD
0800 41 RIT $C010 ;DISABLE 6502 INTERRUPTS
0800 42 LDA $7F ;RETURN TO MONITOR
0800 43 STA IER
0800 44 LDA $00
0800 45 STA IORB
0800 46 STA IFR
0800 47 JMP $FF69
0800 48 ;
0800 49 INTRPT LDA $09
0800 50 STA $24 ;CENTER PRINTOUT ON CRT
0800 51 JSR RDCLK ;OUTPUT TIME/DATE
0800 52 LDA $01
0800 53 STA IFR ;CLEAR CA2 INTERRUPT FLAG
0800 54 RTI ;RETURN
0800 55 ;
0800 56 END

```

Listing 3. Clock Demo.

WE WILL NOT BE UNDERSOLD

DISK DRIVES



FOR TRS-80* Model I
CCI-100 5 1/4", 40 Track (102K) \$314

ADD-ON DRIVES FOR ZENITH Z-89
CCI-189 5 1/4", 40 Track (102K) \$394
Z-87 Dual 5 1/4" system \$995

External card edge and power supply included. 90 day warranty/one year on power supply.

RAW DRIVES

5 1/4" TEAC or TANDON \$CALL POWER SUPPLIES \$CALL

DISKETTES

Box of 10

5 1/4" Maxell \$40 BASF/Verbatim \$26.95
8" Maxell \$45 BASF/Verbatim \$36.00

PLASTIC FILE BOX—Holds 50 5 1/4" diskettes \$19.00

PLASTIC LIBRARY CASE 5 1/4" \$3.00 8" \$ 4.00

HEAD CLEANING DISKETTE \$25.00

FLOPPY SAVER \$11.95 RINGS \$ 6.95

16K RAM KITS

200 ns for TRS-80*, Apple II, (specify): Jumpers \$2.50

SYSTEM SPECIAL

Apple II Plus 48K w/drive and controller. Epson MX-80 printer and interface. SUP-R Mod RF Modulator: List \$2965 You Pay \$2299

COMPUTERS/TERMINALS

ARCHIVES 64K, 2-Drives, 77 Track \$CALL

ALTOS ACS8000 Series \$CALL

TRS-80* II-64K \$3499 III-16K \$ 899

ZENITH 48K, all-in-one computer \$2200

ZENITH Z-19 \$ 725

TELEVIDEO 920C \$ 729 950 \$1039


IBM 3101 Display Terminal \$1189

ATARI 400 \$ 479 800 \$ 795

MATTEL INTELLIVISION \$ 229

APPLE PERIPHERALS \$CALL

PRINTERS



NEC SPINWRITER

Letter Quality High Speed Printer
R.O. \$2395
R.O. with tractor feed \$2555
KSR with tractor feed \$2795

NEC SPINWRITER 3500 Series, 5 new models \$CALL
EPSON MX-70 MX-80 MX-80FT MX100 \$CALL

PAPER TIGER

IDS 445 Graphics & 2K buffer \$ 695

IDS 460 Graphics & 2k buffer \$1050

IDS 560 Graphics \$1450

ANADIX DP-8000 \$ 849 DP-9500/01 \$1295

OKIDATA

Microline 80 Friction & pin feed \$ 415

Microline 80 Friction, and pin & tractor feed \$ 500

Microline 82 Friction & pin feed feed \$ 615

Microline 83 120 cps, uses up to 15" paper \$ 849

CENTRONICS 739, new model with graphics \$ 825

PRINTER SPECIAL

SEIKOSHA GP-80M List \$399 You Pay \$319

MONITORS

BELL & HOWELL 9" B & W BHD911 \$195

LEEDEX 12" B & W \$ 129 13" Color \$369

SANYO 9" B & W VM4509 \$149

SANYO 12" B & W DM5012 \$219

SANYO 12" Green Screen DM5112 \$238

SANYO 13" Color DMC6013 \$406

ZENITH 13" Color \$349

TELECOMMUNICATIONS

LIVERMORE STAR MODEM 2-year guarantee \$125

UNIVERSAL DATA SYSTEMS UDS-103 \$179



D-CAT HARD WIRED DIRECT MODEM \$189

AUTO-CAT Auto Answer, Direct Connect Modem \$249

D.C. HAYES MICRO-MODEM \$295

CCI Telnet Communications Package \$135

S-100 CALIFORNIA COMPUTER SYSTEMS



MAINFRAME Model 2200A \$349

Z80 CPU Model 2810 \$259

MOTHER BOARD Model 2501 \$106

16K STATIC RAM, 200ns Model 2116C \$309

32K STATIC RAM, 200ns Model 2032C \$619

64K DYNAMIC RAM Model 2065C \$580

FLOPPY DISC CONTROLLER Model 2422A \$345

EXTENDER BOARD Model 2520K \$ 52

2P + 2S I/O Model 2718A \$309

APPLE ACCESSORIES AND SOFTWARE

VISICALC \$155.00

DB MASTER \$159.00

Z-80 SOFTCARD \$259.00

VIDEX BOARD \$259.00

KEYBOARD ENHANCER \$110.00

16K CARD \$169.00

APPLE JOYSTICK \$ 49.00

SUP-R MOD \$ 25.00

CCS CARDS \$CALL

GALAXIAN \$ 22.95

SPACE ALBUM \$ 35.00

ASTEROIDS \$ 17.95

FLIGHT SIMULATOR \$ 29.00

WIZARD & PRINCESS \$ 28.00

SARGON 2 \$ 29.00

HI-RES FOOTBALL \$ 35.00

MYSTERY HOUSE \$ 24.00



For fast delivery, send certified checks, money orders or call to arrange direct bank wire transfers. Personal or company checks require two to three weeks to clear. All prices are mail order only and are subject to change without notice. Call for shipping charges.

DEALER (NATIONAL/INTERNATIONAL) INQUIRIES INVITED

Send for FREE Catalogue

The CPU SHOP

TO ORDER CALL TOLL FREE 1-800-343-6522

✓ 256 TWX: 710-348-1796

Massachusetts Residents call 617/242-3361

5 Dexter Row, Dept. K08M
Charlestown, Massachusetts 02129
Hours 10AM-6PM (EST) Mon.-Fri. (Sat. till 5)

Technical Information call 617/242-3361
Massachusetts Residents add 5% Sales Tax
Tandy Corporation Trademark® Digital Research




```

40 REM *****
50 REM *
60 REM * 6522 T2 TIMER DEMO *
70 REM * D.GOSS 11 OCT 80 *
80 REM *
90 REM *****
99 :
100 SLOT = 4
101 BA = 49280 + SLOT * 16: REM BASE I/O ADDR
102 IR = 768: REM BASE ADDR, INTERRUPT ROUTINE
103 IV = 1022: REM BASE ADDR, INTERRUPT VECTOR
104 EI = 800: REM BASE ADDR, ENAB IRQ
200 DATA 32,58,255,169,127,141,205,192,64
210 FOR I = 0 TO 8: READ D
220 POKE IR + I,D: NEXT I: REM LOAD INTERRUPT ROUTINE
240 POKE IV,0
250 POKE IV + 1,3: REM SET INTERRUPT VECTOR
280 HOME: VTAB 3
282 PRINT "THIS PROGRAM DEMONSTRATES OPERATION OF"
284 PRINT "THE T2 TIMER BY SETTING AN ALARM TIMER."
286 PRINT : PRINT
290 INPUT "ENTER TIME IN SEC (63 MAX): ";T
300 T = INT (T * 1024)
320 TH = INT (T / 256): TL = T - TH * 256
330 POKE BA + 3,240
340 POKE BA + 1,240: REM CLK ADDR = $F
350 POKE BA + 2,15
360 POKE BA + 2: REM SET READ CMD
370 POKE BA + 11,32: REM SET T2 PULSE COUNT MODE
380 POKE BA + 14,160: REM ENABLE T2 INTERRUPT
390 POKE BA + 8,TL: REM SET T2 LO
400 POKE BA + 9,TH: REM SET T2 HI
500 POKE EI + 1,96
520 CALL EI: REM ENABLE 6502 INTERRUPTS
530 PRINT : PRINT
540 PRINT "---- TONE WILL SOUND WHEN TIME EXPIRES"
550 PRINT
560 END

```

Listing 4. 6522 T2 Timer Demo.

Note that at this point we should allow a minimum delay of 150 us before writing data to the clock. The execution of BASIC is slow enough, however, that a separate delay statement is not required. Lines 1060 through 1320, in conjunction with the subroutine at line 2000, set the clock by writing one digit at a time.

The "POKE RA, —" statements set the appropriate clock address and data in output register A (ORA), following which the subroutine at 2000 loads the data into the clock by turning the write command on and then off. After all the data has been loaded, the program returns to line 690, which calls the machine-language Read Clock routine to read the clock and display the results for verification. Upon return the hold is released, allowing the clock to run normally.

Reading the Clock

The procedure for reading the clock is illustrated by the Read Clock routine (Listing 2), which prints the time and/or date on the screen or printer at the cursor location. Note that the routine starts at \$9858 (39000), which is in the DOS 3.2 buffer space for a 48K system. It will be safe there assuming that MAXFILES is three (the normal value) and that there are not more than two files open at one time. Also note that the routine is written for slot 4. If you put your card in a different slot you will need to change the card address references.


It may be easier to understand the card's operation from the assembly listing because it exposes more detail than the BASIC listing does. The procedure is very much like that used to set the clock, except that DDRA is programmed so that lines PA0-PA3 are inputs rather than outputs. The time and date are read out one digit at a time, converted to ASCII, and output using the monitor's COUT subroutine.

On exit the clock address is set to \$F, which is the address required to enable the timing pulse outputs. Note that the routine preserves the clock command status by saving the contents of output register B, and then restoring it prior to exit. The status of the read, write, hold and chip select lines will therefore be left unchanged.

A Clock Demonstration

The Clock Demo routine (Listing 3) is a short machine-language program which demonstrates the clock operation and the interrupt capability. The

Super-Text... In A Class By Itself.



Ease of use and a combination of powerful advanced features put Super-Text in a class by itself. The basics of text editing are easily learned within minutes. Yet the advanced features will meet your expanding word processing requirements far into the future.

Super-Text is unequalled by word processing systems costing many thousands of dollars more. Add the Form Letter Module and Address Book Mailing List for the ultimate in professional word processing.

Ask for a demonstration at your local computer store or write for specifications and the name of your nearest Muse retailer. Now that you're ready for word processing, think Super-Text.

available at your local computer store

MUSE SOFTWARE™ 381

Runs on the Apple II or II plus.
Apple II and II plus are trademarks
of the Apple Computer Corporation.

Dealer inquiries welcomed.

330 N. CHARLES STREET
BALTIMORE, MD 21201
(301) 659-7212

circuit is programmed to generate an interrupt once/second, and on each interrupt the time and date are displayed using the Read Clock routine. Pressing any key will terminate the program and return control to the monitor.

The demonstration routine starts by setting the 6522 to enable the once/second interrupt, then sets the interrupt vector in \$3FE and \$3FF.

The circuit is inexpensive and relatively simple to construct, but offers a good measure of capability.


The interrupt routine itself starts at \$99A1. It is a simplified routine in that only the once/second interrupt is expected. If multiple interrupts were enabled, it would be necessary to read the IFR and shift it right or left to determine which interrupt had occurred before taking further action. It would also be possible in that case for two or more interrupt flags to be set at the same time. Your program would then have to process them sequentially in accordance with whatever priority you set.

Using the Timers

The last program, Listing 4, is an Applesoft program that gives a simple demonstration of the 6522 timer capability. The program uses the T2 timer in the pulse counting mode, counting pulses from the 1024 Hz output of the 5832. The timer is set with a time value entered from the keyboard, and when the selected time interval expires, the timer generates an interrupt. The interrupt routine, which is poked into memory beginning at \$300, beeps the speaker and then clears the interrupt flag by writing directly to the interrupt flag register.

Summary

The circuit described here is inexpensive and relatively simple to construct, but offers a good measure of capability. The programming examples only begin to explore potential applications. To fully understand all of the available operating modes, particularly of the timers, you should have a copy of the specifications on the 6522. The one that I have been using is published by Synertek, PO Box 552, Santa Clara, CA 95052. ■



Deluxe Power Console
with Transient Absorber & RF filters
8 individually switched 120 Vac
Grounded outlets. Divided into 2
filtered circuits. Main on/off switch
Fuse and Indicator Light

\$79.95

K&G ELECTRONICS CO., INC.
DEPT. M C
COLONY DRIVE INDUSTRIAL PARK
6584 RUCH ROAD E ALLEN TWP ✓222
BETHLEHEM PA 18017

THE SPIKE-SPIKERS™ with Transient Absorber and R.F. Filters

Protects Computers & Sensitive Equipment
from most Transients & "Hash" Interference
Helps prevent Software "glitches" and unexplained memory losses



Mini-I Mini-II
Wall Mounted 2 Sockets
Transnt. Absorb. Transnt. Absorb.
Only + RF "Hash" Filt.
\$34.95 \$44.95

POWER LINE PROBLEMS??

PA Residents add 6%
dealers invited

ORDER FACTORY DIRECT
215-865-0006
OUT OF STATE ORDER TOLL FREE
800-523-9685

TRS-80 & OTHER NEEDS FILLED FOR LESS

- + + + COMPATIBLE DISK DRIVES WITH POWER SUPPLY AND CASE—90 DAY WARRANTY + + +
- * 40 TRACK (102,400 BYTE/DISK) DISK DRIVE WITH P.S. AND CASE, MODEL I & III \$295
- * 8 IN. DRIVE & P.S./CASE \$689 WITH P.S./CASE FOR 3 DRIVES \$829
- * 80 TRACK (204.8K BYTE) \$399
- * 4-DRIVE CABLE \$28 ** 10 DISKS-5 IN. @ \$24-8 IN. @ \$36 HARD CASE \$3 & 5
- BASE 2 PRINTER \$599 EPSON MX—80 PRINTER—CALL MICROLINE 80 PRINTER \$369
- * CENTRONICS 739 \$799 MICROLINE 82 \$549 CABLE @ \$25
- * MICROLINE 83 \$829
- * LEEDEX 12 IN B&W MONITOR \$114 LEEDEX 12 IN B&G MONITOR \$138
- * APF 10 IN B&W MONITOR \$99
- * 300 BAUD MODEM (ORIG/ANS) \$115. AND UP + + + + + 16K MEMORY SET (200 NANO) \$16
- * 16K MODEL II RADIO SHACK SYSTEM \$849 48K MODEL III \$949
- * APPLE, ATARI, RADIO SHACK HARDWARE/SOFTWARE DISCOUNTED, A/R, A/P, G/L, P/R FOR \$200 or \$59 ea. (MODEL 1) & \$329 or \$80 ea. (MODEL 2). APPLICATIONS INTERACT & ARE COMPLETE & PROFESSIONAL. WILL RUN ON OTHER COMPUTERS. THIS IS A SPECIAL INTRODUCTORY PRICE
- * ASK FOR FREE FLYER WITH OUR LOW PRICES—DEALER INQUIRIES INVITED MASS. RESIDENTS ADD 5% TAX—F.O.B. TEWKSBURY—FREIGHT EXTRA
- M/C, VISA OR CHECK ACCEPTED. TRS-80 IS A REG. TRADEMARK OF TANDY CORP

OMNITEK SYSTEMS 1899 MAIN ST., TEWKSBURY, MASS. 01876 CALL 617/851-4580 ✓140

16-K M E M O R Y 8/\$16.75

RAM

4116 2oons 8/\$16.75 \$2.75ea.
2114L3oons 8/\$19.75 \$2.55ea.
4164 2oons \$27.00ea.

CHIPS & DALE ✓170
P.O. Box 31607
Seattle, Washington
Zip 98103

Add \$2.50 Shipping & Handling
C.O.D. \$3.00, Wash. residents add 5.4% Sales Tax 1-206-524-9126

EPROMS

2732(5V)45ons 8/\$15.00 \$16.95ea.
2716(5V)45ons 8/\$5.75 \$6.35ea.

All chips are fully guaranteed
All chips factory new
Call for quantity pricing
We are Price Competitive



Subscription Problem?

Kilobaud Microcomputing does not keep subscription records on the premises, therefore calling us only adds time and doesn't solve the problem.

Please send a description of the problem and your most recent address label to:

Kilobaud Microcomputing
Subscription Dept.
PO Box 997
Farmingdale, NY 11737



Thank you and enjoy your subscription.

The Ten Cent Fix

By Don Lancaster

A ten-cent modification to a cassette recorder can dramatically improve its convenience and reliability as an I/O device for your computer.

Simply take the recorder apart and find the cassette's ear jack. Add a 470 ohm, $\frac{1}{4}$ watt resistor. Connect this resistor to the contacts on the ear jack, so that the speaker is driven through the resistor when something is plugged into the ear jack and is driven at normal volume when something is not (Fig. 1).

When you load a tape, the speaker will softly play back the tones as they go into your micro. This immediately tells you when your tone codes start and stop.

Better yet, with some practice, you'll be able to determine proper volume or tone settings and whether or not a tape is bad.

For some micros, including the Apple II, this "listen-quietly-to-the-tones-going-in" route lets you start the tone before you hit RETURN. This increases your chance of a good load, since it eliminates any glitches and pops before the tone starts.




Fig. 1. Adding a resistor to the ear jack lets you softly hear programs as they load.

This idea only works on micros that have a long "preamble" or "locking tone" ahead of the actual data that's to be loaded.

Some Other Hints

Some tape recorders are fussy about how you connect them. A few demand a low resistance output load, such as the speaker, a headphone or a 100 ohm resistor. Disconnect these, and the internal amplifier feedback may give you a distorted, unusable output. Unless you know your recorder very well, it pays to put a 100

switch that selects one or the other. Be sure to switch ground as well as the hot leads.

It's also a good idea to erase a tape *completely* before reuse. Should the old data start before you begin the new data, you'll get a glitch and an error message on the preamble almost every time.

Never record an "improved" program over the previous version. If anything goes wrong, you'll lose both old and new versions and have to reset to zero. Instead, use two tapes and alternate between them as you make

With some practice, you'll be able to determine proper volume or tone settings and whether or not a tape is bad.

ohm load on your the recorder's input line. Often, just the "quiet listen" resistor you added will do the trick.

Other recorders are intolerant of a ground loop between ear output and auxiliary input. This can put extra hum and noise into your programs. In a few cheap recorders, connecting both at once can even short out the amplifier electronics. So, again, unless you know your recorder, it is unwise to connect both the ear and auxiliary cables at the same time. You can get around this by plugging in only one at a time, or you can add a

improvements. Label your better improved versions. This way, if you have any problems, you only lose the most recent version, rather than everything you have done so far.

As a final hint, rewind your tapes before, rather than after, you use them. In this way, you can store your tapes with much less tension on them and prevent stretching. ■

Don Lancaster
Synergetics



INTERNATIONAL
APPLE CORE™ Presents

Apple Orchard

Including CONTACT

Apple Orchard magazine is an official publication of International Apple Core, and will keep you informed of new developments in all areas of Apple computing. The CONTACT section will help you better understand and make use of your Apple, and will inform you of new products and peripherals. The IAC section will provide you with names and addresses of each

member Apple user group, and will mention upcoming computer shows and fairs. PLUS... each issue contains great feature articles, such as "Applesoft Internals," "Hi-Res Graphics: Resolving the Resolution Myth," and "A BASIC to Machine Language Interface." Subscribe today... you can't afford to miss a single issue!

Please enter a one year subscription to Apple Orchard for:

NAME _____

ADDRESS _____

CITY _____

STATE _____

ZIP _____

Annual subscription rate: \$10.00 per year.
First class postage: \$5.00 per year additional (required): \$10.00 per year additional.
Overseas and other foreign air mail postage (required): \$10.00 per year additional.

☐ Check or money order enclosed
Make check or money order payable to "International Apple Core" and return with this form to:

☐ VISA ☐ MasterCard
Apple Orchard Subscriptions
P.O. Box 1493
Beaverton, OR 97075

✓387

K

Put Your Micro On Wall Street

By Dex Hart

TIMEGAIN is a short program which helps evaluate one or more stock portfolios over a specified period of time—a week, month, whatever. As written, it must be used with PORTVAL, described last month (but reprinted here), as all the data used is stored in PORTVAL and passed to TIMEGAIN with the Microsoft disk BASIC CHAIN command. (See "Put Your Micro on Wall Street," *Microcomputing*, July 1981, p. 126.) You could add READ-DATA lines to make the program stand alone, but the idea

is to make portfolio updating easy—because if it isn't easy you probably won't do it (I'm assuming the rest of the world is as lazy as I am). I use these programs to follow several portfolios, and, while short and simple, they work.

The intent is twofold: to offer programs genuinely useful in portfolio bookkeeping and management and to demonstrate some aspects of Microsoft BASIC that appear to me to have been somewhat neglected. In last month's article the emphasis was on

PRINT USING (and LPRINT USING) along with some elementary field arithmetic, especially how column totaling works. The second program, TIMEGAIN, chains to the original program and thus greatly simplifies data inputting. Note that CHAIN and COMMON are new to Microsoft BASIC as of version 5.0.

Target Group

I'm aiming this at those not-yet-expert BASIC programmers, a group in which I include myself. But I have learned some aspects of the language well, because I had to, and that limited area of acquired knowledge is what I'm sharing with you. You don't have to be a heavyweight investor to benefit from learning how these programs work, as the applications have wide general application.

I call TIMEGAIN a universal program, because it will work with any number of separate portfolio valuation programs and never has to be changed, updated or loaded with data.

PORTVAL Revisions

The revisions to last month's PORTVAL are slight. To distinguish the version with the CHAIN statement, I've called it PORTVAL.TWO. There are four revised lines and ten new ones. Lines 10, 310 and 550 are revised to reflect the program name change. Line 50 is revised to dimension for P1, the "old" share prices, since we now need stock prices for two different dates. New lines 182, 183 and 184 loop to read the old prices left in place as extra DATA. Note the remarks on the latter two of

PORTVAL.TWO.

```
10 REM ***** "PORTVAL.TWO" *****
20 CLEAR
30 N=5
40 IF N<=10 GOTO 60
50 DIM A$(N),D$(N),S(N),C(N),P(N),P1(N),V(N),D(N),G(N)
60 RESTORE
70 FOR I=1 TO N
80 READ A$(I),D$(I),S(I),C(I)
90 NEXT I
100 DATA Carlisle, 29Sep80,160,9991
110 DATA Crown Cork,18Mar71,100,2231
120 DATA Humana," 7Mar77",900,4900
130 DATA Kysor,18Dec69,200,2758
140 DATA Travelers," 2Dec68",100,3511
160 FOR I=1 TO N
170 READ P(I)
180 NEXT I
181 READ D1$ 'date of "new" prices—type w/o commas as item n+1
182 FOR I=1 TO N
183 READ P1(I) 'To update, input new prices ABOVE line 188;
184 NEXT I 'keep old prices on 188, delete 190, then RENUM
185 READ D2$ 'date of "old" prices
188 DATA 85,32,74.8,10.4,39.3,21 Jan 81
190 DATA 84.0,28.4,71.4,10.6,38.9,30 Dec 80
194 PRINT "Complete this run before chaining TIMEGAIN."
195 INPUT "Want to run TIMEGAIN? YES enter 1; NO hit return ",W
196 IF W=1 THEN 197 ELSE 200
197 COMMON N,A$(I),S(I),P(I),P1(I),D1$,D2$
198 CHAIN "TIMEGAIN"
200 T1=0:T2=0:T3=0:T4=0
210 FOR I=1 TO N
220 V(I)=S(I)*P(I)
230 D(I)=V(I)-C(I)
240 G(I)=100*D(I)/C(I)
250 T1=T1+C(I)
260 T2=T2+V(I)
270 T3=T3+D(I)
280 T4=100*T3/T1
290 NEXT I
300 PRINT CHR$(12) 'clear screen
310 PRINT"PORTVAL.TWO'.....Portfolio Valuation.....prices as of ";D1$
320 PRINT
330 PRINT" Stock Date Shares Cost Price Value Diff %Gain"
340 PRINT
350 FOR I=1 TO N
360 PRINT USING"## ";I;
```

More

Dex Hart (9414 SW 142 St., Miami, FL 33176) is a widely published boating writer.

these lines; I have not renumbered so as to avoid disturbing the original PORTVAL numbers, but when you do you will have to revise the line number references in these remarks.

There's an extra nonlooped READ line for the date of the "old" prices, D2\$, since we will need both dates in TIMEGAIN to fully identify the span of time involved. Each date is listed as the final (n+1) item following n prices. If a large number of stocks is involved, and more than one DATA line is needed for each set of prices, the date also serves as a nice visual break between the two series of prices. Just remember to add the newest date as the final entry whenever entering prices. (The newest prices are on line 188; the former prices on 190.) The CHAIN-related commands are new lines 194-198.

TIMEGAIN has only 51 lines, but part of its compactness is in the method of writing PRINT USING. Compare the PRINT USING sections of PORTVAL.TWO and TIMEGAIN. Recognize that they do the same thing—format a whole line of string and numerical data, controlling location, decimal places and rounding. It is an extremely useful command system. Table 1 of last month's article lists the variables. Add to that P1, which is used in TIMEGAIN for share prices predating the current prices.

What we are doing in TIMEGAIN is to multiply the older price by the number of shares to get the "old" total cost, C; we then multiply the new prices, P, by the number of shares to get the current value of each stock, V. The dollar difference, D, is again V minus C, and the gain, G, is again the percentage gain or loss.

Program Differences

The difference is that while PORTVAL does its arithmetic on each stock from the purchase date of that stock, TIMEGAIN uses start and end dates which are the same for each stock. A glance at the sample runs of the two programs illustrates the difference and also shows how useful TIMEGAIN is. Last month's PORTVAL was as of Dec. 31, 1980. This month's PORTVAL.TWO is three weeks later, as of Jan. 21, 1981. The specific numbers are not greatly different between the two runs, and it is not immediately obvious where the greatest changes took place across that three weeks (the Dec. 31 %Gain, for example, was in order: 34.5, 27.3, 1211.4,

Listing continued.

```

370 PRINT USING"\      \ ";A$(I);
380 PRINT USING"\      \ ";D$(I);
390 PRINT USING"### ";S(I);
400 PRINT USING"#### ";C(I);
410 PRINT USING"###.## ";P(I);
420 PRINT USING"#### ";V(I);
430 PRINT USING"#### ";D(I);
440 PRINT USING"####.##";G(I)
450 NEXT I
460 PRINT"*****"
470 PRINT "Totals";
480 PRINT TAB(29)USING" #####      ";T1;T2;
490 PRINT USING"#### ##.##";T3;T4
500 PRINT
510 INPUT "Hard copy?—YES enter 1 [printer on!]  
—NO hit RETURN ";J
520 IF J=1 THEN 550 ELSE 540
530 GOTO 550
540 END
550 LPRINT"PORTVAL.TWO'.....Portfolio Valuation....Prices as of ";D1$
560 LPRINT
570 LPRINT" Stock      Date  Shares Cost  Price  Value  Diff  %Gain"
580 LPRINT
590 FOR I=1 TO N
600 LPRINT USING"## ";I;
610 LPRINT USING"\      \ ";A$(I);
620 LPRINT USING"\      \ ";D$(I);
630 LPRINT USING"### ";S(I);
640 LPRINT USING"#### ";C(I);
650 LPRINT USING"###.## ";P(I);
660 LPRINT USING"#### ";V(I);
670 LPRINT USING"#### ";D(I);
680 LPRINT USING"####.##";G(I)
690 NEXT I
700 LPRINT"*****"
710 LPRINT"Totals";
720 LPRINT TAB(28)USING" #####      ";T1;T2;
730 LPRINT USING"#### ##.##";T3;T4
740 GOTO 540

```

'PORTVAL.TWO'.....Portfolio Valuation....Prices as of 21 Jan 81

Stock	Date	Shares	Cost	Price	Value	Diff	%Gain
1 Carlisle	29Sep80	160	9991	85.0	13600	3609	36.1
2 Crown Cork	18Mar71	100	2231	32.0	3200	969	43.4
3 Humana	7Mar77	900	4900	74.8	67320	62420	1273.9
4 Kysor	18Dec69	200	2758	10.4	2080	-678	-24.6
5 Travelers	2Dec68	100	3511	39.3	3930	419	11.9

Totals			23391		90130	66739	285.3

PORTVAL.TWO sample run.

—23.1, 10.8. Total gain, 270.0 percent).

But look at TIMEGAIN, which shows the gain only for that three-week period: Crown Cork had the largest move, three times that of Humana (although the Humana percentage gain has the most effect on the total gain, because it represents three-quarters of our arbitrary portfolio—a fact easily apparent since we have added a new column, percent of portfolio, to TIMEGAIN).

I keep a notebook titled, not surprisingly, "Portfolio." For any specific portfolio, I file each hard copy of PORTVAL, making notes on these copies of any transactions or items of special interest. I will occasionally run TIMEGAIN, normally as of the

last trading day of each month. I receive an overall portfolio valuation from either program, but one shows my overall progress (not always encouraging), the other my current progress (also not always encouraging). But good news or not, you need to know how you're doing. If there's a problem, you won't solve it with your head in the sand. The main point: the two programs give different information—and both are useful.

How TIMEGAIN and Chaining Work

You don't want to load two sets of prices at a time; it doubles the work. So what you do is just leave the former prices in PORTVAL, although you won't use them there. At the next

The whole idea is to never have to input more than a single set of prices at one time. It works just fine. There is a reminder in `PORTVAL.TWO` to finish its run first. That's because once you chain `TIMEGAIN`, you've lost `PORTVAL`. You could chain back, but why? Finish `PORTVAL`, print a hard copy if you choose, then

Again I remind you that "PRINT CHR\$(12)" is how I clear screen on my Superbrain. Your machine is probably different. "CLS" is a popular command. Or you might use a dif-

One final note: I never could figure out what WHILE-WEND meant. That is, I knew the WHILE meant "as long as," but WEND means to turn or proceed, right? You *wend* your way through? No clues from Microsoft (they don't answer letters either—at least not from me). Fortunately, I

TRS-80 TM 

COMPUTERS

64K MOD II \$3440.00
32K MOD III 2DR. \$2225.00

• **FREE SHIPPING** in 48
continental contiguous
states.

• **NO SALES TAX** collected on
out-of-state orders.

TOLL FREE ORDER NUMBER
800-531-7466
Texas & Principle Number
512-581-2766
Fort Worth No. 817-625-6333
Telex Number 767339

**Pan American
Electronics** ✓71

Sales and Main Office
Dept. 48 • 1117 Conway Ave
Mission, Texas 78572

NEW Fort Worth Branch
Dept. 48 • 2912 N. Main St.
Fort Worth, Texas 76106

Trademark of Tandy Corp.

```

10 REM ***** TIMEGAIN ***** Universal Chain/Common Program
20 DIM C(N),V(N),R(N),D(N),G(N)
30 T1=0:T2=0:T3=0:T4=0:T5=0
40 FOR I=1 TO N
50 C(I)=S(I)*P1(I)
60 V(I)=S(I)*P(I)
70 D(I)=V(I)-C(I)
80 G(I)=100*D(I)/C(I)
90 T1=T1+C(I)
100 T2=T2+V(I)
110 T4=T4+D(I)
120 T5=100*T4/T1
130 NEXT I
140 FOR I=1 TO N
150 R(I)=100*V(I)/T2
160 T3=T3+R(I)
170 NEXT I
180 PRINT CHR$(12)
190 PRINT "TIMEGAIN' Stock Value Change Over Time—New prices as of ";D1$
200 PRINT TAB(42)"Old prices as of ";D2$
210 PRINT
220 PRINT"
230 PRINT"      Stock      Old      Total      New      Current"
240 PRINT"      Shares Price      Cost      Price      Value      %Port      Diff      %Gain"
250 FOR I=1 TO N
260 PRINT USING"## \      \ ### ##.# ##### ";I;A$(I);S(I);P1(I);C(I);
270 PRINT USING"###.# ##### ##.# ##### ###.#";P(I);V(I);R(I);D(I);G(I)
280 NEXT I
290 PRINT"
300 PRINT "Totals";
310 PRINT TAB(27)USING"##### "T1;T2;
320 PRINT USING"###.# ##### ##.#";T3;T4;T5
330 PRINT

```

More

came across a FORTRAN book and found the answer. The FORTRAN commands are WHILE and END WHILE. So simple when you see it—WEND is WhileND. Why couldn't Microsoft have mentioned that?

Then there is the explanatory example Microsoft used. What kind of BASIC statements are WHILE FLIPS and FLIPS=0? Long variable names? Something to do with sorting, a particular weak point with me—but then, I have no need to sort.

I'll find out someday, from somewhere or someone. And after all, would this whole business be so fascinating if it was without challenge?

For the Future

As soon as I dig out a full historical listing of the Consumer Price Index (CPI), I plan to work up another program, also chained to PORTVAL, which will apply the index to stock values, comparing how a portfolio has done in current dollars to how it has done in deflated dollars. The results will once more probably be discouraging, but better to know than to ignore. Sure hope I don't need FLIPS to make it work. ■

Listing continued.

```
340 INPUT "Hard copy?—YES enter 1 (printer on!)—NO hit RETURN ",J
350 IF J=1 THEN 370 ELSE 360
360 END
370 LPRINT"TIMEGAIN' Stock Value Change Over Time—New prices as of ";D1$
380 LPRINT TAB(42)"Old prices as of ";D2$
390 LPRINT
400 LPRINT"
410 LPRINT" Stock      Shares Price      Cost      New      Current"
420 LPRINT"
430 FOR I=1 TO N
440 LPRINT USING"### \      \ ### ##.## ##.## " ;I;A$(I);S(I);P1(I);C(I);
450 LPRINT USING"###.## ##.## ##.## ##.##.## " ;P(I);V(I);R(I);D(I);G(I)
460 NEXT I
470 LPRINT"*****"
480 LPRINT"Totals";
490 LPRINT TAB(27)USING"##### ##.## " ;T1;T2;
500 LPRINT USING"###.## ##.## ##.##.## " ;T3;T4;T5
510 GOTO 360
```

'TIMEGAIN' Stock Value Change Over Time—New prices as of 21 Jan 81
Old prices as of 30 Dec 80

Stock	Shares	Price	Total Cost	New Price	Current Value	%Port	Diff	%Gain
1 Carlisle	160	84.0	13440	85.0	13600	15.1	160	1.2
2 Crown Cork	100	28.4	2840	32.0	3200	3.6	360	12.7
3 Humana	900	71.4	64260	74.8	67320	74.7	3060	4.8
4 Kysor	200	10.6	2120	10.4	2080	2.3	-40	-1.9
5 Travelers	100	38.9	3890	39.3	3930	4.4	40	1.0

Totals			86550		90130	100.0	3580	4.1

TIMEGAIN sample run.

IAS and CP/M™

Our Integrated Accounting System (IAS) has always been a good value, but wait until you see the latest version. And, it's now available for the CP/M™ operating system, too. Some of the features include:

Custom Chart of Accounts with a more flexible numbering system and 25 character account names. Improved financial reports, including an Income Statement with percent-of-sales figures. An expanded and more flexible check register. Expanded account names in AR and AP. AR incorporates a modified open-item, balance-forward account system with invoicing and statements. AP has a more flexible check writing program as does the PR subsystem. The GL, AP and PR check writing programs all are formatted for the same NEBS checks so you don't need three different types of checks. The AR invoicing and statement programs are also formatted for NEBS forms. All programs use our exclusive Skip-Sequential file structure for improved speed and disk efficiency. The user's manual has been expanded and includes sample printouts from most programs, and is written for the non-programmer.

The General Ledger is \$150.00 and may be used as a stand-alone system. The AR, AP and PR subsystems require the GL subsystem for proper operation. GL plus one subsystem is \$250.00; GL plus two subsystems is \$325.00 and the complete package is \$395.00. NOTE: the new IAS requires a 24 × 80 cursor-addressable terminal, 48K of memory and one 8" or two 5¼" disk drives. CP/M™ users must have the SoHo Group's Matchmaker, which we will provide free to the first 100 buyers of the complete IAS package (\$110.00 value). Matchmaker may otherwise be ordered with any IAS subsystem for \$75.00.

The IAS operator's manual may be purchased for \$25.00 (credited towards purchase). Please specify 8" SD (soft sector) or 5¼" North Star disk and CRT type when ordering.

CP/M is a registered trademark of Digital Research.



ECOSOFT ✓82
P.O. Box 68602
Indianapolis, IN 46268
(317) 283-8883

COMPUTER EQUIPMENT & SOFTWARE BARGAINS



EVERY MONTH

BUY, SELL OR TRADE ALL TYPES OF COMPUTER EQUIPMENT AND SOFTWARE (pre-owned and new) among 20,000 readers nationwide.

FEATURES:


- Low classified ad rates - 10¢ a word
- Hundreds of ads from individuals
- Categorized ads so you can find them instantly
- Large (11 by 14") easy to read pages

Subscribe now for \$10 and receive 13 issues/year (one FREE plus 12 regular issues). After receiving your first issue if you're not completely satisfied you may have a 100% refund and you still keep the first issue free. Bank cards accepted.

BONUS: If you have something to advertise (pre-owned or software) send in a classified ad with your subscription and we'll run it FREE.

The Nationwide Marketplace for Computer Equipment
COMPUTER SHOPPER ✓36
P.O. BOX F 21 • TITUSVILLE, FL 32780 • 305-269-3211
MasterCard & VISA subscriptions only, call TOLL FREE 1-800-327-9920

This program gives a lift to aerospace engineering and shows that micros can save time and money in high-technology endeavors.



TRS-80 Launchpad

By Terry L. Sunday

Most major aerospace missile system contractors have an advanced engineering concepts or preliminary design group whose purpose is to analyze the defense marketing environment and define new or modified weapon systems. They often must develop performance requirements of conceptual missile designs or characterize the abilities of existing missile systems used in new applications.

Until recently, the techniques to do this have been limited. Laborious hand calculations and pocket calculators cost time and accuracy, since many simplifying assumptions had to be made to reduce a problem to manageable size.

Existing missile simulation computer programs running on corporate mainframe systems, such as a CDC 7600 or IBM System 370, also presented problems. The data is used mainly to show the feasibility of a certain missile system concept, which requires that the system be simulated in enough detail for the results to be valid, but not in such detail that every nut and bolt is defined. Thus, full-blown mainframe simulations typically have far more capability than necessary. Also, the cost of generating data is very important, and cranking out a lot of numbers at a rate of \$30 per CPU-second can quickly deplete an annual computer budget.

Enter the Microcomputer

A missile preliminary design group can now own a dedicated computer

that will support its engineering analyses. Ready machine access and straightforward programming encourage use of such a computer in a wide variety of tasks. And best of all, after the initial system purchase, mountains of data can be generated at no cost to the user.

The program described here is for a TRS-80 Model I Level II, with 32K, two 5-1/4-inch disk drive units, a line printer and a power line filter assembly. The power line filter was necessary because of the system's sensitivity to line fluctuations, which was particularly apparent in the morning and afternoon hours when most employees arrived at or left the plant. The program is written in Level II BASIC and occupies about 10,500 bytes of memory.

The Program

The program is a two-degree-of-freedom (pitch-plane) missile trajectory simulation, and simulates the flight of a missile following launch either from the ground or from an aircraft. A completely arbitrary missile configuration may be used, so the same program is useful for many different analyses.

The missile may or may not have a rocket motor, and if it does, the motor is characterized by arbitrary thrust, ignition time, burn time and propellant weight. Of course, the motor parameters must be internally consistent. The missile configuration itself is defined by weight, size and aerodynamic characteristics. A flat, nonrotating earth is assumed, as well as an exponential atmosphere model. The flat earth assumption has proven

to be quite acceptable for the short ranges involved in all program utilization to date.

The program output consists of a tabular listing of missile range, altitude, flight path angle and velocity, all presented as a function of time. This output can be selected to appear either on the CRT display or in hard-copy form on the line printer.

Listing 1 is the current version of the program, which will be discussed in detail later. Table 1 shows the input parameters required by the program. Note that the input parameters are divided for convenience into missile configuration data, initial conditions, control parameters and aerodynamic characteristics. The aerodynamic data required is expressed as axial and normal force coefficients, as a function of Mach number and angle of attack, in missile body axes. Provisions are included to use both power on (rocket motor burning) and power off (rocket motor not burning) data sets. The differences between power-on and power-off aerodynamic data may be important in some applications. An option lets you use only power-off data, a simplification that may frequently be employed without introducing significant error. In that case, a data flag is set which bypasses the requirement to provide power-on data.

Details of the program structure may be seen by examining Listing 1. Lines 60 through 90 establish the array dimensions and assign values to

Terry L. Sunday (3005 Devils Tower, El Paso, TX 79904) is a staff engineer with Martin Marietta Aerospace.

various physical and atmospheric model constants. Lines 110 through 590 contain the data input routine.

In the present version, a separate disk file, using DATA statements and with its first line number greater than the highest simulation program line number (5000 is typically used), must be established. The simulation program is first loaded into the computer, and the MERGE command is then used to attach the data file to the end of the program. This technique lets you set up multiple data sets, each representing a different missile configuration. Note the extensive use of integer array subscripts, as identified by the % character, to help speed up program execution.

Lines 530 through 590 let you change any of the data items before running the program, or between the runs in a series. Lines 620 through 650 permit the output option—either CRT or line printer—to be chosen, and lines 660 through 690 let you input a descriptive alphanumeric title that will appear as a heading on the printout. Lines 700 through 890 set up the initial values for various parameters used in the integration loop.

The actual integration loop runs from line 940 to line 2170. It is within this loop that all of the missile trajectory computations are performed. A trapezoidal integration scheme is used, with the time interval for integration steps defined by the input variable DT. A value of .5 second for DT is usually adequate.

Lines 970 through 1040 establish the exponential atmosphere parameters as a function of missile altitude, and determine the instantaneous missile Mach number for entry into the aerodynamic data tables. Lines 1050 through 1290 contain a routine which modifies the computation interval to force an integration to be performed at the discontinuities represented by rocket motor ignition or burnout, which need not occur exactly coincident with a normal integration step. A forced line print also occurs at these times.

The heart of the integration loop lies between lines 1320 and 1780. Here the forces acting on the missile are computed on each pass through the loop. This portion of the program is divided into two segments—the region from line 1340 to line 1550 is used when the rocket motor is burning, and the region from line 1560 to line 1780 is used when the motor is

not burning. Each segment uses the appropriate table of power-on or power-off aerodynamic data, and if no power-on data is provided, the portion from line 1340 to line 1550 is bypassed. In either case, a double linear interpolation on both Mach number and angle of attack is used to produce as a final result the net drag and lift forces to which the missile responds. These forces are then used to determine missile longitudinal and lateral accelerations in lines 1790 and 1800, and then to update the missile velocity and position in lines 1810 through 1910. These are then used as starting conditions for the next pass through the loop.

The routine between lines 1920 and 2110 forces a line print at rocket motor ignition and burnout. If the line printer output option is selected, these lines are identified by the word "ignition" or "burnout" printed to the right side of the basic tabular output. On the CRT output, no such identifier is presented.

Lines 2120 and 2130 check to see whether the stopping conditions—either maximum time or cutoff altitude—are satisfied, in which case the program transfers to one of two termina-

tion routines. Lines 2210 through 2540 contain the output logic. This routine prints identifying headings on the columns of output data, conditions the missile trajectory data into the units employed for output and prints the data either on the CRT or printer.

A line of data output is triggered by any of the following three conditions: an incremental time period defined by the input value for print interval, PT, is reached; either ignition or burnout of the rocket motor occurs; or either of the program stopping conditions is satisfied. If a stopping condition is satisfied, the routine defined by lines 2550 through 2780 is executed, which causes the reason for program termination to be printed, along with the final trajectory conditions existing at that point.


Finally, lines 2790 through 2830 cause the program to prepare to execute again by returning the data pointer to the top of the data array, and asking the user if he desires to make another run. If the response is yes, program control transfers back to line 580, where any changes to the data set are made, and the cycle reinitiates.

TIME	RANGE	ALTITUDE	FLIGHT PATH	VELOCITY
(SEC)	(KM)	(AGL) (FT)	ANGLE (DEG)	(FT/SEC)
0	0	175	26.9926	1834
1	.48781	974.742	26.0916	1729.01
2	.945972	1695.84	25.1341	1606.87
3	1.37628	2343.1	24.0958	1500.48
4	1.78235	2923.77	22.9745	1407.01
5	2.16711	3443.73	21.7685	1324.04
6	2.53284	3907.65	20.4758	1249.35
7	2.88141	4319.39	19.0938	1182.14
8	3.21476	4682.63	17.6207	1123.21
9	3.53485	5000.78	16.0571	1072.02
10	3.84361	5276.87	14.4053	1028.29
11	4.14273	5513.4	12.6698	991.078
12	4.4337	5712.4	10.856	959.446
13	4.71764	5875.39	8.96993	932.071
14	4.99531	6003.49	7.0172	907.941
15	5.2673	6097.6	5.00297	886.679
16	5.53407	6158.44	2.93282	868.008
17	5.79602	6186.66	.812846	851.699
18	6.05345	6182.81	-1.35034	837.431
19	6.30657	6147.36	-3.54999	824.904
20	6.55558	6080.78	-5.77913	814.274
21	6.80061	5983.48	-8.03042	805.221
22	7.04179	5855.89	-10.2962	797.749
23	7.27924	5698.38	-12.5686	791.783
24	7.51304	5511.34	-14.8399	787.245
25	7.74327	5295.16	-17.1023	784.059
26	7.97	5050.21	-19.3484	782.145
27	8.19326	4776.9	-21.5711	781.423
28	8.4131	4475.63	-23.7638	781.808
29	8.62954	4146.81	-25.9208	783.216
30	8.8426	3790.89	-28.0367	785.557
31	9.0523	3408.32	-30.107	788.743
32	9.25862	2999.58	-32.128	792.685
33	9.46158	2565.19	-34.0965	797.293
34	9.66116	2105.66	-36.0103	802.476
35	9.85734	1621.58	-37.8677	808.146
36	10.0501	1113.51	-39.6677	814.215
37	10.2394	582.092	-41.4097	820.598
38	10.4253	27.9639	-43.0938	827.213
38.049	10.4343	0	-43.1742	827.543

FLIGHT TERMINATED AT CUTOFF ALTITUDE

Sample run.

SINGLE BOARD COMPUTER \$49.95



The MASTER CONTROLLER BOARD contains:

- Z-80 Microprocessor: will run 8080/8085 and Z-80 programs.
 - 72- Parallel I/O lines; three 8255s
 - Keyboard controller: 8279 (also can control a 16 digit seven segment display)
 - 12K- EPROM: three sockets for 2708, 2716, 2732,
 - 2K- RAM: 2114s
 - 8- Sixteen bit counter timer channels: one 8253 and one AMD 9513
 - 2- Serial I/O ports; one Z-80 SIO chip. One port has an RS-232 interface and connector.
 - 1- High speed arithmetic processor: AMD 9511 or AMD 9512
- All the I/O chips are memory mapped AND I/O mapped. A bus expansion connector is provided. Can be operated on 5 volts only.

All this on one board less than nine inches on a side

Only three LSI chips (Z-80, 8255, and EPROM) plus support gates and buffers are required for a working controller.

BARE BOARD \$49.95

With documentation.

MINIMUM KIT \$99.95 Includes bare board with documentation, one each Z-80, 8255, 2708, two 2114s, and support gates and buffers, all socketed.

MONITOR \$39.95 This program allows a TTY or CRT to control the MASTER CONTROLLER. This program requires the minimum kit and monitor parts kit. A programmed 2708 is supplied with the MONITOR.

MONITOR PARTS \$54.95

Includes 8253, Z-80 SIO, 1488, 1489, and connector.

POWER SUPPLY \$39.95 +5V 1A, -5V 1/4A, +12V 1/4A, -12V 1/4A

POWER SUPPLY \$44.95 +5V 2A, otherwise same as above.

Please include \$2 postage and handling.

OEM and dealer inquiries invited.
VISA and MASTER CARD accepted.

R.W. ELECTRONICS 390
3165 North Clybourn
Chicago, IL 60618
(312) 248-2480

D = MISSILE DIAMETER (INCHES)
W0 = MISSILE LAUNCH WEIGHT (POUNDS)
WF = MISSILE BURNOUT OR FINAL WEIGHT (POUNDS) NOTE: MAKE SAME AS LAUNCH WEIGHT FOR UNPOWERED MISSILE.
BT = MOTOR BURN TIME (SEC) NOTE: MAKE 0 IF NO MOTOR.
TT = MOTOR AVERAGE (CONSTANT) THRUST (POUNDS) NOTE: MAKE 0 IF NO MOTOR.
BD = MOTOR IGNITION DELAY AFTER T0 (SEC)

INITIAL CONDITIONS

H0 = INITIAL ALTITUDE ABOVE GROUND LEVEL (FT)
R0 = INITIAL RANGE (KM)
V0 = INITIAL VELOCITY (FT/SEC)
G0 = INITIAL FLIGHT PATH ANGLE (DEGREES) POSITIVE UPWARDS
T0 = INITIAL TIME (SEC)
AG = GROUND ALTITUDE (FT)

CONTROL PARAMETERS

TF = MAXIMUM FLIGHT TIME (SEC)
HF = CUTOFF ALTITUDE ABOVE GROUND LEVEL (FT) NOTE: CUTOFF WILL OCCUR ONLY IF MISSILE IS DESCENDING WHEN REACHING THIS ALTITUDE
DT = INTEGRATION STEP SIZE (SEC)
PT = PRINT INTERVAL FOR HARD COPY OR SCREEN DISPLAY (SEC)
TC(1) = TIME TO INITIATE CONSTANT ANGLE OF ATTACK FLIGHT MODE (SEC)
TC(2) = TIME TO TERMINATE CONSTANT ANGLE OF ATTACK FLIGHT MODE (SEC)
AC = CONSTANT ANGLE OF ATTACK (DEGREES) NOTE: TC(1) AND TC(2) MUST BE GREATER THAN ZERO
OIZ = POWER ON DATA FLAG: IF 0, NO POWER ON DATA
IF 1, READ POWER ON DATA

AERODYNAMIC CHARACTERISTICS

NM% = NUMBER OF MACH NUMBERS TO BE LOADED (POWER OFF) MAXIMUM 15
NA% = NUMBER OF ANGLES OF ATTACK TO BE LOADED (POWER OFF) MAXIMUM 10
M(1) TO M(NM%) = MACH NUMBER VALUES (POWER OFF)
A(1) TO A(NA%) = ANGLE OF ATTACK VALUES (DEGREES) (POWER OFF)
CA(M,A) = AXIAL FORCE COEFFICIENT AS A FUNCTION OF MACH NUMBER AND ANGLE OF ATTACK (POWER OFF)
CN(M,A) = NORMAL FORCE COEFFICIENT AS A FUNCTION OF MACH NUMBER AND ANGLE OF ATTACK (POWER OFF)
OM% = NUMBER OF MACH NUMBERS TO BE LOADED (POWER ON) MAXIMUM 15
OA% = NUMBER OF ANGLES OF ATTACK TO BE LOADED (POWER ON) MAXIMUM 10
M0(1) TO M0(OM%) = MACH NUMBER VALUES (POWER ON)
A0(1) TO A0(OA%) = ANGLE OF ATTACK VALUES (DEGREES) POWER ON
C0(M0,A0) = AXIAL FORCE COEFFICIENT AS A FUNCTION OF MACH NUMBER AND ANGLE OF ATTACK (POWER ON)
N0(M0,A0) = NORMAL FORCE COEFFICIENT AS A FUNCTION OF MACH NUMBER AND ANGLE OF ATTACK (POWER ON)

Table 1. Variable identification.

The missile used in the Sample run was fired at an angle of 30 degrees with an initial velocity of 1834 ft./sec., and did not use a rocket motor. The configuration actually represents a guided artillery projectile which has been under development for some time, and which was chosen as a test case because a large body of performance data exists which was used to verify the programming of the major equations of motion.

In this example, the projectile fired with the specified initial conditions hit the ground at a range of 10.43 km from the launch point following a ballistic flight of 38.049 seconds duration. These values are extremely close to those obtained by running a complete (and costly) six-degree-of-freedom projectile simulation on a System 370. The value of this TRS-80 simulation becomes immediately apparent.

The program has also to date been used to study performance abilities for a cannon-launched rocket-propelled guided projectile, and for a guided missile launched from an air-

craft under a variety of flight conditions.

Modifications

Several changes may be made in the future. An option to simulate constant angle-of-attack glide is currently included in the program, but has not been sufficiently checked out to assure that it is completely debugged. A proportional navigation guidance scheme to simulate target engagements would add immeasurably to the program, and a simplified mechanization could be incorporated fairly easily.

Another useful modification would be to add the third degree of translational freedom, cross-range, so the effect of crosswinds and other lateral disturbances could be assessed.

Finally, a major effort is anticipated to reduce program execution time by streamlining the logic wherever possible. In its present form, one second of simulated flight requires about five seconds of real time with an integration interval of 0.5 second, and

OSI

AARDVARK NOW MEANS BUSINESS!

OSI

WORD PROCESSING THE EASY WAY— WITH MAXI-PROS

This is a line-oriented word processor designed for the office that doesn't want to send every new girl out for training in how to type a letter.

It has automatic right and left margin justification and lets you vary the width and margins during printing. It has automatic pagination and automatic page numbering. It will print any text single, double or triple spaced and has text centering commands. It will make any number of multiple copies or chain files together to print an entire disk of data at one time.

MAXI-PROS has both global and line edit capability and the polled keyboard versions contain a corrected keyboard routine that make the OSI keyboard decode as a standard typewriter keyboard.

MAXI-PROS also has sophisticated file capabilities. It can access a file for names and addresses, stop for inputs, and print form letters. It has file merging capabilities so that it can store and combine paragraphs and pages in any order.

Best of all, it is in BASIC (OS65D 51/4" or 8" disk) so that it can be easily adapted to any printer or printing job and so that it can be sold for a measly price.

MAXI-PROS — \$39.95

THE EDSON PACK ALL MACHINE CODE GAMES FOR THE 8K CIP

INTERCEPTOR — You man a fast interceptor protecting your cities from Hordes of Yucky Invaders. A pair of automatic cannon help out, but the action speeds up with each incoming wave. It's action, action everywhere. Lots of excitement! \$14.95

MONSTER MAZE — An Arcade style action game where you run a maze devouring monsters as you go. If one sees you first, you become lunch meat. Easy enough for the kids to learn, and challenging enough to keep daddy happy. \$12.95

COLLIDE — Fast-paced lane-switching excitement as you pick up points avoiding the jam car. If you succeed, we'll add more cars. The assembler code provides fast graphics and smooth action. \$9.95

**SPECIAL DEAL—THE ENTIRE EDSON PACK—
ALL THREE GAMES FOR \$29.95**

THE AARDVARK JOURNAL

FOR OSI USERS — This is a bi-monthly tutorial journal running only articles about OSI systems. Every issue contains programs customized for OSI, tutorials on how to use and modify the system, and reviews of OSI related products. In the last two years we have run articles like these!

- 1) A tutorial on Machine Code for BASIC programmers.
- 2) Complete listings of two word processors for BASIC IN ROM machines.
- 3) Moving the Directory off track 12.
- 4) Listings for 20 game programs for the OSI.
- 5) How to write high speed BASIC — and lots more —

Vol. 1 (1980) 6 back issues - \$9.00

Vol. 2 (1981) 2 back issues and subscription for 4 additional issues - \$9.00.

ACCOUNTS RECEIVABLE — This program will handle up to 420 open accounts. It will age accounts, print invoices (including payment reminders) and give account totals. It can add automatic interest charges and warnings on late accounts, and can automatically provide and calculate volume discounts.

24K and OS65D required, dual disks recommended. Specify system.
Accounts Receivable. \$99.95

*** SPECIAL DEAL — NO LESS! ***

A complete business package for OSI small systems — (C1, C2, C4 or C8). Includes MAXI-PROS, GENERAL LEDGER, INVENTORY, PAYROLL AND ACCOUNTS RECEIVABLE — ALL THE PROGRAMS THE SMALL BUSINESS MAN NEEDS. \$299.95

P.S. We're so confident of the quality of these programs that the documentation contains the programmer's home phone number!

SUPERDISK II

This disk contains a new BEXEC* that boots up with a numbered directory and which allows creation, deletion and renaming of files without calling other programs. It also contains a slight modification to BASIC to allow 14 character file names.

The disk contains a disk manager that contains a disk packer, a hex/dec calculator and several other utilities.

It also has a full screen editor (in machine code on C2P/C4) that makes corrections a snap. We'll also toss in renumbering and program search programs — and sell the whole thing for — SUPERDISK II \$29.95 (5 1/4") \$34.95 (8").

BOOKKEEPING THE EASY WAY — WITH BUSINESS I

Our business package 1 is a set of programs designed for the small businessman who does not have and does not need a full time accountant on his payroll.

This package is built around a **GENERAL LEDGER** program which records all transactions and which provides monthly, quarterly, annual, and year-to-date PROFIT AND LOSS statements. GENERAL LEDGER also provides for cash account balancing, provides a **BALANCE SHEET** and has modules for **DEPRECIATION** and **LOAN ACCOUNT** computation.
GENERAL LEDGER (and MODULES) \$129.95.

PAYROLL is designed to interface with the GENERAL LEDGER. It will handle annual records on 30 employees with as many as 6 deductions per employee.
PAYROLL - \$49.95.

INVENTORY is also designed to interface with the general ledger. This one will provide instant information on suppliers, initial cost and current value of your inventory. It also keeps track of the order points and date of last shipment.
INVENTORY - \$59.95.

GAMES FOR ALL SYSTEMS

GALAXIAN - 4K - One of the fastest and finest arcade games ever written for the OSI, this one features rows of hard-hitting evasive dogfighting aliens thirsty for your blood. For those who loved (and tired of) Alien Invaders. Specify system — A bargain at \$9.95

MINOS - 8K - Features amazing 3D graphics. You see a maze from the top, the screen blanks, and when it clears, you are in the maze at ground level finding your way through on foot. Realistic enough to cause claustrophobia. — \$12.95

NEW — NEW — NEW


LABYRINTH - 8K - This has a display background similar to MINOS as the action takes place in a realistic maze seen from ground level. This is, however, a real time monster hunt as you track down and shoot mobile monsters on foot. Checking out and testing this one was the most fun I've had in years! — \$13.95.

TIME TREK - 8K - Real Time and Real graphics Trek. See your torpedoes hit and watch your instruments work in real time. No more unrealistic scrolling displays! — \$9.95

SUPPORT ROMS FOR BASIC IN ROM MACHINES — C1S/C2S. This ROM adds line edit functions, software selectable scroll windows, bell support, choice of OSI or standard keyboard routines, two callable screen clears, and software support for 32-64 characters per line video. Has one character command to switch model 2 C1P from 24 to 48 character line. When installed in C2 or C4 (C2S) requires installation of additional chip. C1P requires only a jumper change. — \$39.95

C1E/C2E similar to above but with extended machine code monitor. — \$59.95

AND FUN, TOO!



Please specify system on all orders

This is only a partial listing of what we have to offer. We now offer over 100 programs, data sheets, ROMS, and boards for OSI systems. Our \$1.00 catalog lists it all and contains free program listings and programming hints to boot.

AARDVARK TECHNICAL SERVICES, LTD.
2352 S. Commerce, Walled Lake, MI 48088
(313) 669-3110



OSI



OSI

this publication is available in microform



University Microfilms International

300 North Zeeb Road
Dept. P.R.
Ann Arbor, MI 48106
U.S.A.

18 Bedford Row
Dept. P.R.
London, WC1R 4EJ
England

UNIDEP T.M.

Asset Management Program

Designed for you. Adapts to your accounting system & hardware. You choose:

- depreciation type
- length of term
- reporting period
- when to print reports
- when to update values

Change any value any time.
Includes investment credit, bonus depr. \$99 for Apple II (32K) or TRS 80 Mod II (64 K), 1 Disk.

Another UNIFACE® product from
Natural Language Systems, Inc.
411 Barber Ave.
Ann Arbor, Mich 48103
(313) 668-1806

✓378

Apple is a registered trademark of Apple Computer, Inc.
TRS 80 is a registered trademark of Radio Shack.

'68' MICRO JOURNAL™

6800-6809-68000

★ The only ALL 68XX Computer Magazine

Foreign Orders—Add:

Air Mail \$35.00/Year—Surface \$12.00/Year

Canada & Mexico Add \$5.50 to USA Rate

1-Year \$18.50 2 Years \$32.50

3 Years \$48.50

OK, PLEASE ENTER MY
SUBSCRIPTION

Bill my: M/C ☐ — VISA ☐

Card # _____

Expiration Date _____

For ☐ 1-Yr. ☐ 2 Yrs. ☐ 3 Yrs.

Enclosed: \$ _____

Name _____

Street _____

City _____

State _____ Zip _____

'68' MICRO JOURNAL™

3018 Hamill Road
HIXSON, TN 37343

✓132

this is approaching the point wherein interactive sessions become too time-consuming, due to the wait required for execution to be completed.

During program development, we found that the CRT output option was used very infrequently, so consideration is being given to removing this option entirely, with a consequent reduction in computation time and much simplification of the complex output logic. Use of a BASIC compiler rather than the existing BASIC interpreter would greatly improve execution time.

Conclusion

This article has presented a snapshot of a TRS-80 program that has proven to be very useful in aerospace engineering analyses. Program development is not complete, and probably never will be, because there is always another option to add. Nevertheless, even in its present state, it has served to demonstrate important new capabilities of the current crop of microcomputers, and to illustrate once again that these machines are far more than sophisticated video games. ■

Listing 1. Missile Flight Simulation program for the TRS-80 Model I, Level II.

```

10 "PROGRAM FILESPEC IS TESTSIM VERSION 6/27/80
20 "A TRAJECTORY SIMULATION FOR AIR OR GROUND-LAUNCHED MISSILES
30 "
40 "INITIALIZATION
50 "
60 DIM M(15), A(10), CA(15,10), CN(15,10), TA(2), TC(2), X(5), D(4), E(4)
70 DIM M0(15), A0(10), C0(15,10), N0(15,10)
80 F1=0: G=32.174: PI=3.1415926: RD=0.01745329: R1=20855531: C=0.01874342
90 FI=0.00694444: AZ=518.67: AV=0.00356616: AX=2116.2162: AH=0.00058256: AV=49.02219586
100 "
110 "DATA INPUT
120 READ D,W0,Wf,BT,TT,BD "PHYSICAL PARAMETERS"
130 READ H0,R0,V0,G0,T0,AG "INITIAL CONDITIONS"
140 READ TF,HF,DT,PT,TC(1),TC(2),AC "CONTROL PARAMETERS"
150 "AERODYNAMIC COEFFICIENTS"
160 READ NM%,NA%
170 FOR K%=1 TO NM%
180 READ M(K%): "MACH NUMBER"
190 NEXT K%
200 FOR K%=1 TO NA%
210 READ A(K%): "ANGLE OF ATTACK"
220 NEXT K%
230 FOR I%=1 TO NM%
240 FOR J%=1 TO NA%
250 READ CA(I%,J%): "AXIAL FORCE COEFFICIENT - POWER OFF"
260 NEXT J%
270 NEXT I%
280 FOR I%=1 TO NM%
290 FOR J%=1 TO NA%
300 READ CN(I%,J%): "NORMAL FORCE COEFFICIENT - POWER OFF"
310 NEXT J%
320 NEXT I%
330 READ OI%
340 IF OI%=0 THEN 520
350 READ O0%,AO%
360 FOR K%=1 TO O0%
370 READ M0(K%)
380 NEXT K%
390 FOR K%=1 TO AO%
400 READ A0(K%)
410 NEXT K%
420 FOR I%=1 TO O0%
430 FOR J%=1 TO AO%
440 READ C0(I%,J%): "AXIAL FORCE COEFFICIENT - POWER ON"
450 NEXT J%
460 NEXT I%
470 FOR I%=1 TO O0%
480 FOR J%=1 TO AO%
490 READ N0(I%,J%): "NORMAL FORCE COEFFICIENT - POWER ON"
500 NEXT J%
510 NEXT I%
520 CLS
530 IF F1=1 THEN 580
540 INPUT "DO YOU WANT TO EDIT THE DATA FOR THE FIRST RUN Y/N":E#
550 IF E#="Y" THEN 580
560 GOTO 600
570 IF F1=0 THEN 600
580 PRINT "INPUT NEW DATA AND TYPE CONT TO RUN"
590 STOP
600 D1=DT: FFZ=0: PFZ=0: SFZ=0: TP=PT: TR=TT
610 CLS
620 INPUT "DO YOU WANT A HARD COPY Y/N":A#
630 IF A#="N" THEN 660
640 PRINT "TURN ON LINE PRINTER AND TYPE CONT TO CONTINUE"
650 STOP
660 ON ERROR GOTO 680
670 GOTO 690
680 PRINT "TOO MANY CHARACTERS IN TITLE - TRY AGAIN"
690 INPUT "TYPE IN RUN TITLE":T#
700 SR=PI*((DC2)/4)*FI
710 W=W0
720 A5=0
730 IF TR=0 THEN 760
740 BR=(W0-WF)/BT
750 "MATRIX INITIALIZATION"
760 X(1)=R0

```

More →

Listing 1 continued.

```


770 RG=R0
780 X(2)=H0+AG
790 RL=X(2)
800 X(3)=G0+RD
810 GA=X(3)*57.28
820 X(4)=V0
830 X(5)=T0
840 T=T0
850 V=X(4)
860 D(1)=V*COS(X(3))      /"XDOT"
870 D(2)=V*SIN(X(3))      /"ZDOT"
880 D(3)=-G+COS(X(3))/V    /"GAMMADOT"
890 D(4)=-G*SIN(X(3))      /"VDOT"
900 GOTO 2270
910 /"
920 /"INTEGRATION LOOP STARTS HERE"
930 /"
940 FOR I%=1 TO 4
950 E(I%)=D(I%)
960 NEXT I%
970 Z=X(2)
980 H=R1+Z/(R1+Z)
990 T3=AZ-AY*H
1000 P=RX/((AZ/T3)/(C/AY))
1010 R=AW*P/T3
1020 A1=AY+SQR(T3)
1030 M1=X(4)/A1
1040 Q1=0.5*R*(X(4)/I2)
1050 IF TT=0 THEN 1250
1060 IF X(5)<(T0+BD) THEN TR=0 ELSE TR=TT
1070 IF X(5)>=(T0+BD+BT) THEN TR=0
1080 IF X(5)<(T0+BD) THEN 1250
1090 IF X(5)>=(T0+BD) AND FF%=0 THEN 1110
1100 IF X(5)>=(T0+BD+BT) THEN 1160
1110 IF FF%=1 THEN 1230
1120 XD=X(5)
1130 X(5)=(T0+BD)
1140 FF%=1
1150 GOTO 1220
1160 IF FF%=2 THEN 1280
1170 XD=X(5)
1180 X(5)=(T0+BT+BD)
1190 FF%=2
1200 DT=X(5)-XD+D1
1210 GOTO 1280
1220 DT=X(5)-XD+D1
1230 W=W0-(BR*(X(5)-BD))
1240 GOTO 1290
1250 W=W0
1260 GOTO 1290
1270 TR=0
1280 W=WF
1290 M=W/G
1300 IF T0(1)<X(5)<T0(2) THEN A5=AC ELSE A5=0
1310 IF X(5)<T0(1) OR X(5)>T0(2) THEN A5=0
1320 IF AC=0 THEN A5=0
1330 IF O1%=0 OR TR=0 THEN 1560
1340 Q%=1
1350 GOTO 1370
1360 Q%=Q%+1
1370 IF A5=A0(Q%) THEN 1360
1380 P%=Q%-1
1390 K%=1
1400 GOTO 1420
1410 K%=K%+1
1420 IF M1>M0(K%) THEN 1410
1430 J%=K%-1
1440 S1=(M1-M0(J%))/(M0(K%)-M0(J%))
1450 C6=N0(J%,P%)+S1*(N0(K%,P%)-N0(J%,P%))
1460 C7=N0(J%,Q%)+S1*(N0(K%,Q%)-N0(J%,Q%))
1470 C8=C6+(C7-C6)*(A5-A0(P%))/(A0(Q%)-A0(P%))
1480 L=Q1*SR+C8
1490 C1=C0(J%,P%)+S1*(C0(K%,P%)-C0(J%,P%))
1500 C2=C0(J%,Q%)+S1*(C0(K%,Q%)-C0(J%,Q%))
1510 C3=C1+(C2-C1)*(A5-A0(P%))/(A0(Q%)-A0(P%))
1520 DR=Q1*SR+C3
1530 ND=(TR-DR)*COS(A5*RD)-L*SIN(A5*RD)
1540 NL=(TR-DR)*SIN(A5*RD)+L*COS(A5*RD)
1550 GOTO 1790
1560 Q%=1
1570 GOTO 1590
1580 Q%=Q%+1
1590 IF A5=A(Q%) THEN 1590
1600 P%=Q%-1
1610 K%=1
1620 GOTO 1640
1630 K%=K%+1
1640 IF M1>M(K%) THEN 1630
1650 J%=K%-1
1660 S1=(M1-M(J%))/(M(K%)-M(J%))
1670 C6=CN(J%,P%)+S1*(CN(K%,P%)-CN(J%,P%))
1680 C7=CN(J%,Q%)+S1*(CN(K%,Q%)-CN(J%,Q%))
1690 C8=C6+(C7-C6)*(A5-A(P%))/(A(Q%)-A(P%))
1700 L=Q1*SR+C8
1710 C1=CA(J%,P%)+S1*(CA(K%,P%)-CA(J%,P%))
1720 C2=CA(J%,Q%)+S1*(CA(K%,Q%)-CA(J%,Q%))
1730 C3=C1+(C2-C1)*(A5-A(P%))/(A(Q%)-A(P%))
1740 DR=Q1*SR+C3
1750 IF TT=0 THEN ND=-DR*COS(A5*RD)-L*SIN(A5*RD)
1760 IF TT=0 THEN 1780
1770 ND=(TR-DR)*COS(A5*RD)-L*SIN(A5*RD)
1780 NL=(TR-DR)*SIN(A5*RD)+L*COS(A5*RD)
1790 D(4)=-G*SIN(X(3))+ND/M
1800 D(3)=-G*COS(X(3))+NL/(M*V)
1810 LG=X(3)

```

More


Measure, Control, Document...

Computer Systems and Peripherals designed to coordinate with the Apple Computers that let you measure, monitor, regulate, control and document with laboratory precision, at affordable cost.



AI13 Analog Input System (A/D, 12bits)

Measure voltages with 0.024% precision
Monitor 16 separate inputs under program control
Choose from 8 voltage ranges under program control; 100mV to 10V
Make a reading in 20 microseconds



AI02 Analog Input System (A/D, 8bits)

Measure voltages with 0.4% precision
Monitor 16 separate inputs under program control
Match most sensors with a standard 5 volt range
Signal Conditioning System SC14 available




A003 Analog Output System (D/A, 8 bits)

Control voltage levels from a simple program
Conversion in less than 3 μ sec.
Standard 0 to 10 V Range
Jumpers select 0 to 5V or 5 to 5V
2, 4, or 8 channel models
Each channel has its own memory
Each channel has range, offset adjustments




DI09 Digital Interface

Monitor or control 32 circuits in any combination
Measure time intervals or count pulses
Plug into BCD, parallel, or switch closure instrument outputs




UI06 Isolated Power Interface

Control 110VAC circuits from a program
Operate DC relays or solenoids
Receive logic pulses in noisy environments
Avoid interference and grounding problems in large systems
Start with one circuit — expand to dozens



PR12 Intelligent Printer System

Clear, readable printing on standard paper
Intermix graphics and text of three sizes
A true **printing system** including intelligent interface, and a complete manual.



PL12 Intelligent Plotter System

Produce detailed pen drawings from a program
8 x 10 Plotting surface with .005" resolution
Automatically plot from Basic arrays and strings
A true **plotting system** including intelligent interface and complete manual.

Interactive Structures has been producing laboratory systems and interfaces for Apple Computer since 1977. Our technology is in use in thousands of applications — from our own Spacelab instrumentation system to automobile engine research and woodstove analysis.

Contact us for the details on affordable laboratory computing.



Interactive Structures, Inc. 73
P.O. Box 404
Bala Cynwyd, PA 19004
215-667-1713

FAST FASTER FASTEST

IT'S YOUR CHOICE

You can sort fast using your present facilities, or you can do it faster with Racet's superb facilities, or you can use the fastest: SUPERSNAPP X. The heart of SUPERSNAPP X is a SUPER FAST in-memory sort routine that has been benchmarked against everything on the market and beats them all ... hands down.

SUPERSNAPP X is the most important component of SNAPP X EXTENDED BUILT-IN FUNCTIONS which is a much needed set of additions to the Model II BASIC interpreter that will put time saving power at your fingertips. Let's compare (using random data) SUPERSNAPP X and Racet's GSF SORT for speed:

SORT	SUPERSNAPP X	RACET GSF
10,000 integers	39 seconds	59 seconds
5,000 Singles	22 seconds	34 seconds
2,000 Strings	10 seconds	15 seconds

SUPERSNAPP X is guaranteed to be the FASTEST in memory SORT on the market at your money back. With it you also get these EXTENDED BUILT-IN FUNCTIONS: PEEK, PEEKW, POKE, POKEW, XDAT\$, XTIM\$, ETIM\$, FILES AND THE SPECIAL SCMD (SNAPP-COMMAND). PLUS: open "E". Set SCROLL PROTECTION. ERASE all ARRAYS in one command. Specify size and Blink rate of CURSOR. Long ERROR messages. Read from Video. Screen Read. Diskette ID's and more! If you want the FASTEST SORT on the market, you want SUPERSNAPP X. Don't waste time. Call or write today for SUPERSNAPP X. \$100.00

SNAPPWARE
SNAPPWARE
SNAPPWARE
SNAPPWARE
SNAPPWARE
SNAPPWARE

3719 Mantell
Cincinnati, Ohio 45236



Call Toll Free

1-800-543-4628

Ohio residents

call collect (513) 891-4496


TRS-80 is a trademark of the Radio Shack division of Tandy Corporation.

Listing 1 continued.

```

1820 LV=X(4)
1830 LR=X(1)
1840 LA=X(2)
1850 LT=X(5)
1860 X(3)=X(3)+0.5*DT*(D(3)+E(3))
1870 X(4)=X(4)+0.5*DT*(D(4)+E(4))
1880 D(1)=X(4)*COS(X(3))
1890 D(2)=X(4)*SIN(X(3))
1900 X(1)=X(1)+0.5*DT*(D(1)+E(1))
1910 X(2)=X(2)+0.5*DT*(D(2)+E(2))
1920 IF X(5)=(T0+BD) THEN 1950
1930 IF X(5)=(T0+BD+BT) THEN 2030
1940 GOTO 2110
1950 IF TT=0 THEN 2110
1960 IF A$="N" THEN 1990
1970 LPRINT X(5);TAB(15)X(1)/3280.;TAB(31)X(2);TAB(47)X(3)*57.28;TAB(63)X(4);"  IGNITION"
1980 GOTO 2000
1990 PRINT USING F$; X(5);X(1)/3280.;X(2);X(3)*57.28;X(4)
2000 DT=D1-DT
2010 IF DT=0 THEN DT=D1
2020 GOTO 2120
2030 IF TT=0 THEN 2110
2040 IF A$="N" THEN 2070
2050 LPRINT X(5);TAB(15)X(1)/3280.;TAB(31)X(2);TAB(47)X(3)*57.28;TAB(63)X(4);"  BURNOUT"
2060 GOTO 2080
2070 PRINT USING F$; X(5);X(1)/3280.;X(2);X(3)*57.28;X(4)
2080 DT=D1-DT
2090 IF DT=0 THEN DT=D1
2100 GOTO 2120
2110 DT=D1
2120 IF X(5)=TF THEN 2220
2130 IF X(2)<(HF+AG) AND X(3)<0 THEN 2550
2140 IF X(5)=TP THEN 2210
2150 X(5)=X(5)+DT
2160 V=X(4)
2170 GOTO 940
2180 "INTEGRATION LOOP ENDS HERE"
2190 "OUTPUT LOGIC FOLLOWS"
2200 "
2210 TP=TP+PT
2220 T=X(5)
2230 RG=X(1)/3280.
2240 AL=X(2)
2250 GA=X(3)*57.28
2260 V=X(4)
2270 IF A$="Y" THEN 2410
2280 IF SFZ=1 THEN 2350
2290 CLS
2300 PRINT T$
2310 PRINT
2320 PRINT TAB(5)"TIME";TAB(13)"RANGE";TAB(20)"ALTITUDE";TAB(31)"GAMMA";TAB(38)"VELOCITY"
2330 PRINT TAB(4)"(SEC)";TAB(14)"(KM)";TAB(22)"(FT)";TAB(31)"(DEG)";TAB(38)"(FT/SEC)"
2340 SFZ=1
2350 IF T=TF THEN 2710
2360 IF AL<(HF+AG) AND GA<0 THEN 2550
2370 F$="#####.##"
2380 AP=AL-AG
2390 PRINT USING F$; T, RG, AP, GA, V
2400 GOTO 2150
2410 IF T=TF THEN 2710
2420 IF AL<(HF+AG) AND GA<0 THEN 2550
2430 IF PFZ=1 THEN 2520
2440 PFZ=1
2450 LPRINT TAB(5)T$
2460 LPRINT " "CHR$(10)
2470 LPRINT " "CHR$(10)
2480 LPRINT TAB(2)"TIME";TAB(16)"RANGE";TAB(31)"ALTITUDE";TAB(47)"FLIGHT PATH";TAB(63)"VELOCITY"
2490 LPRINT TAB(32)"(AGL)";TAB(50)"ANGLE"
2500 LPRINT TAB(2)"(SEC)";TAB(16)"(KM)";TAB(33)"(FT)";TAB(50)"(DEG)";TAB(63)"(FT/SEC)"
2510 LPRINT " "CHR$(10)
2520 AP=AL-AG
2530 LPRINT T;TAB(15)RG;TAB(31)AP;TAB(47)GA;TAB(63)V
2540 GOTO 2150
2550 AL=HF+AG
2560 X(2)=ABS(X(2))
2570 DI=(LA-(HF+AG))/(LA-X(2))
2575 T=X(5)-DT+(DT*DI)
2580 RG=(LR+((X(1)-LR)*DI))/3280.
2590 GA=(LG+((X(3)-LG)*DI))*57.28
2600 V=LV+((X(4)-LV)*DI)
2610 AP=AL-AG
2620 IF A$="Y" THEN 2670
2630 PRINT USING F$; T, RG, AP, GA, V
2640 PRINT
2650 PRINT "FLIGHT TERMINATED AT CUTOFF ALTITUDE"
2660 GOTO 2790
2670 LPRINT T;TAB(15)RG;TAB(31)AP;TAB(47)GA;TAB(63)V
2680 LPRINT " "CHR$(10)
2690 LPRINT TAB(15)"FLIGHT TERMINATED AT CUTOFF ALTITUDE"
2700 GOTO 2290
2710 IF A$="Y" THEN 2760
2720 PRINT USING F$; T, RG, AP, GA, V
2730 PRINT
2740 PRINT "FLIGHT TERMINATED ON MAXIMUM TIME"
2750 GOTO 2790
2760 LPRINT T;TAB(15)RG;TAB(31)AP;TAB(47)GA;TAB(63)V
2770 LPRINT " "CHR$(10)
2780 LPRINT TAB(15)"FLIGHT TERMINATED ON MAXIMUM TIME"
2790 F1=1
2800 RESTORE
2810 T$=" "
2820 INPUT "DO YOU WANT TO MAKE ANOTHER RUN?";R$
2830 IF R$="Y" THEN 500
2840 END

```

(Model I or III)

MPI Disk Drives

Model B/51 250K, 1 Side, 40 Tracks.....\$321.00

B/52 500K, 2 Sides, 40 Tracks per side \$439.00

B/91 500K, 1 side, 80 Tracks. \$439.00

B/92 1 Meq, 2 Sides, 80 Tracks per side.....\$590.00

Includes: Case and Power Supply — Fully Tested

10 Day Money Back Guarantee

90 Days Parts and Labor Warranty (Excl. Shpg.)

Here's just a few of the features of MPI Disk Drives

Other Money Savings Opportunities Order by Phone or Mail

CABLES

2 Drive Cable.....	\$29.00
4 Drive Cable.....	\$39.00

Diskettes

Verbatim 10 for **\$31.00**
Syncom 10 for **\$35.00**
Plastic File Box **\$3.95**

Operating Systems

TRSDOS 2.3.....	\$14.95
40 Track Patch.....	\$9.95
NEWDOS + 40 Track.....	\$99.00
Newdos 80.....	\$139.00
TRSDOS Manual.....	\$5.95
Super Utility.....	\$49.00
Make 80.....	\$14.00

TRS-80

16K Model III	\$899.00
48K Model III	
w/2 Disks	\$1900.00
Expansion Interface	
OK	\$274.00

Printers

Centronics 737-1.....	\$815.00
IDS 460.....	\$1219.00
Epson MX80.....	\$550.00
Okidata M80.....	\$499.00
Microline 82.....	\$650.00
Microline 83.....	\$950.00
Okidata prices include tractors	
NEC Spinwriter 5530	
(freight collect).....	\$2579.00
16K Memory Kits	

Prime NEC 200ns dynamic RAM. Comes with complete instructions. **\$39.00**

MPI Service	
Manual	\$3.00
MPI Engineering	
Manual	\$30.00

- 40/80 Tracks
- 5 ms track-to-track
- Auto-eject
- Hi-Temp stability
- Speed constant $<1\frac{1}{2}\%$
- Single/double density
- Optical sensors—no switches
- 102K per disk

ADDS MORE POWER TO YOUR SYSTEM

Save time . . . Order by phone

Orders only: 1-800-621-3229

Information: 312-987-1024

Tech. assistance: 312-987-1032



MIDWEST

COMPUTER

PERIPHERALS® ✓ 150

1467 S. MICHIGAN
CHICAGO, ILLINOIS 60605

TRS 80 TANDY CORP

FREE! UPS GROUND SHIPPING ON ALL ORDERS OVER \$100.00

Quantity	Description	\$ each	Total
(Minimum order \$50.00)		6% IL Tax	
		TOTAL	

(Minimum order \$50.00)

6% IL Tax
TOTAL

- ☐ Check enclosed
Bill my ☐ Visa ☐ Am Ex
☐ Master Charge
Acct. No. _____



Name _____
Address _____
City _____ State _____ Zip _____

Not Responsible for Typographical Errors. Prices Subject to Change w/o notice.

An Atari Disassembler

By William L. Colsher

When a new computer is introduced, we hobbyists are naturally curious about how it operates. How does it use RAM? Are undocumented features buried in the ROMs? What tape recording format does it use? To answer these questions requires patience and experience; digging through the ROMs and the reserved work areas requires a tool. That tool is the disassembler.

A disassembler is the opposite of an assembler. Instead of generating machine code as output, it accepts ma-

chine code and produces assembly-language listings as output. Naturally, the original labels aren't reproduced, but the result is a lot easier to use than a hex dump.

Because a disassembler is the opposite of an assembler, you would naturally expect that the two programs would be similar in structure. You would hope to see tables of machine operation codes (op codes), mnemonics, addressing modes and instruction lengths. The tables are used in much the same way as an assembler would

use them but in the opposite direction. For example, a disassembler takes the op code and generates a mnemonic, while an assembler accepts a mnemonic and generates an op code.

If you now look at the program listing, you'll see that all these tables are, in fact, defined in line 100. A\$(168) is a string containing the mnemonics. OC(151) is an array that holds the op codes. CD(151) combines with LN(13) to provide the information on addressing modes and instruction lengths. CD(151) also holds a pointer for each op code into the A\$ string to enable the computer to find the correct mnemonic. The DATA statements in lines 30000 through 30310 are read to fill these tables.

To save space this program combines the pointer to the mnemonic table with the addressing mode. Table CD contains four-digit numbers: the first two digits are the mnemonic number and the second two are the addressing mode. The addressing mode points into the array LN, which contains the lengths of the instructions using the various addressing modes.

How It Works

Now let's take a look at how the disassembler works. In the listing,

Program listing.

```
100 DIM A$(168),B$(3),OC(151),CD(151),F$(4),H$(4),D$(1),T$(4),LN(13)
110 FOR I=1 TO 56
120 READ B$
130 A$((I-1)*3+1)=B$
140 NEXT I
150 FOR I=1 TO 151
160 READ A,B
170 OC(I)=A:CD(I)=B
180 NEXT I
190 FOR I=1 TO 13:READ A:LN(I)=A:NEXT I
200 GRAPHICS 0
210 PRINT "Enter all input in hexadecimal"
220 PRINT "Dis-assemble from:";
230 INPUT F$
240 PRINT "          to:";
250 INPUT T$
260 H$=F$:GOSUB 10000:F=INT(H)+1:IF H=0 THEN F=0
270 H$=T$:GOSUB 10000:T=INT(H)+1:IF H=0 THEN T=0
280 GRAPHICS 0
290 POSITION 2,23
1000 REM ***START DIS-ASSEMBLY LOOP
1010 B=PEEK(F)
1020 GOSUB 10100
1030 IF ISOP THEN GOSUB 2000
1040 IF NOT (ISOP) THEN GOSUB 3000
1050 IF F<=T THEN GOTO 1010
1060 PRINT "DIS-ASSEMBLY COMPLETE"
1070 PRINT "PRESS RETURN TO CONTINUE"
1080 INPUT H$
1090 GOTO 200
2000 REM ***DISPLAY AN INSTRUCTION
```

More

Address correspondence to William L. Colsher,
1711 Robin Lane, Lisle, IL 60532.

lines 100 through 290 perform all the necessary setup functions: filling the tables from the DATA statements and getting the start and end addresses from the user.

Lines 1000 through 1090 form the main loop of the program. After getting a byte to be disassembled, the subroutine at line 10100 is called. If the byte is an operation code, the subroutine beginning at line 2000 is called to display it. If the byte is *not* an op code, the subroutine at line 3000 is called. Both of these routines increment the pointer into memory F as appropriate. The loop continues until F is greater than or equal to T (the highest location to be disassembled).

Line 2000 begins the section of code that actually performs the disassembly. First, the routine beginning at line 10200 is called to output the address (the value in F). Then, several routines starting at line 9000 take over to display the hexadecimal machine code, the mnemonic and operands, and the ASCII version of the op code.

The ASCII version of the op code is

Listing continued.

```

2010 GOSUB 10200
2020 GOSUB 9000
2025 PRINT
2030 RETURN
3000 REM ***PRINT A DATA BYTE
3010 GOSUB 10200
3020 B=PEEK(F):GOSUB 10400
3030 POSITION 16,23:PRINT "DATA";
3040 POSITION 30,23:PRINT " ";CHR$(PEEK(F));" "
3050 F=F+1:RETURN
9000 REM ***PRINT HEX OPERATION
9010 MN=INT(CD(OP1)/100)
9020 AM=INT(CD(OP1)-100*MN)+1
9030 FOR I=0 TO LN(AM)-1
9040 B=PEEK(F+I)
9050 GOSUB 10400
9060 NEXT I
9070 FOR I=LN(AM) TO 3:PRINT " ";NEXT I:PRINT " "
9085 REM ***PRINT MNEMONIC
9090 BS=AS((MN-1)*3+1)
9100 PRINT BS;" ";
9110 ON AM-1 GOSUB 9200,9650,9250,9300,9350,9400,9450,9500,9200,9200,9550,9600
9120 POSITION 30,23:PRINT " ";
9130 FOR I=0 TO LN(AM)-1
9140 PRINT CHR$(PEEK(F+I));
9150 NEXT I:PRINT " ";
9160 F=F+LN(AM):RETURN
9200 REM ***IMMEDIATE, ACCUMULATOR & RELATIVE
9210 B=PEEK(F+1):GOSUB 10400:RETURN
9250 REM ***ZEROPAGE X
9260 GOSUB 9650:PRINT ".X*":RETURN
9300 REM ***ABSOLUTE
9310 B=PEEK(F+2):GOSUB 10400
9320 B=PEEK(F+1):GOSUB 10400
9330 RETURN
9350 REM ***ABSOLUTE X
9360 GOSUB 9300:PRINT ".X*":RETURN
9400 REM ***ABSOLUTE Y
9410 GOSUB 9300:PRINT ".Y*":RETURN
9450 REM ***INDIRECT X
9460 PRINT "( ";GOSUB 9200:PRINT " ),X*":RETURN
9500 REM ***INDIRECT Y
9510 PRINT "( ";GOSUB 9200:PRINT " ),Y*":RETURN
9550 REM ***INDIR

```

More →

6502	7.45	10/6.95	50/6.55	100/6.15
6502A	8.40	10/7.95	50/7.35	100/6.90
6520 PIA	5.15	10/4.90	50/4.45	100/4.15
6522 VIA	6.45	10/6.10	50/5.75	100/5.45
6532	7.90	10/7.40	50/7.00	100/6.60
2114-L200 ns RAM	3.75	20/3.50	100/3.25	
2716 EPROM (5 volt)	9.90	5/9.45	10/8.90	
TMS 2532 EPROM			23.50	
4116-200 ns RAM			8 for 29.00	
S-100 Wire Wrap			2.65	

DISKS

(write for quantity prices)

SCOTCH (3M) 5 1/4"	10/2.90	50/2.80	100/2.70
SCOTCH (3M) 8"	10/2.95	50/2.85	100/2.75
Verbatim 5 1/4"	10/2.45	50/2.40	100/2.35
(add 1.00 for 5 1/4" Verbatim plastic storage box)			
Verbatim 8" Dbl. Dens.	10/3.45	50/3.35	100/3.25
BASF 5 1/4"	10/2.60	20/2.50	100/2.40
BASF 8"	10/2.65	20/2.55	100/2.45

Maxell Disks in stock - write for prices

Diskette Storage Pages	10 for 3.95
Disk Library Cases	8" - 2.85 5" - 2.15

A P Products
15% OFF



A P HOBBY-BLOX 15% OFF

All books 15% off

STAR RS232 Modem	\$135
SYM-1	209
KTM 2/80	349
EPSON MX-80	Call
EPSON MX-70	Call
Itoh STARWRITER	1500
Leedex Monitor	129
Watanabe Plotter	1145
Centronics 737	790
C-10 Cassettes	10/5.65
ZENITH DATA SYSTEMS	
Zenith Z19	735
Zenith Z89 - 48K	2150
fullFORTH + for PET	65
PASCAL for PET	\$75
PET Disk Assembler	65
Apple II+	Call
NEC Spinwriter	2500



APPLE II+

BELL & HOWELL

COMMODORE PET-CBM

Write or call for quotes

NEW 8016/32 80 column screen

NEW 8050 950K Dual Drive

EDUCATIONAL DISCOUNTS AVAILABLE



ATARI 800 \$777

ATARI Software 20% OFF

EDUCATIONAL DISCOUNTS available

WRITE FOR CATALOG

Add \$1.25 per prepaid order for UPS shipping

A B Computers

✓ 121

115 E. Stump Road
Montgomeryville, PA 18936
(215) 699-5826

Computers, Peripherals, Unlimited! DON'T MISS THIS MONTH'S SPECIALS!!!

19" COLOR MONITORS

Manufactured by CONRAC, studio quality, full color monitors with built-in de-Gauss, independent R.G.B. & Sync inputs & much, much more. Originally over \$1K.

- 19" Diagonal Screen
- by CONRAC; Pro-Quality
- 120VAC, 50/60 Hz
- R, G, B & Sync Inputs
- Perfect for Graphics, Etc.
- Locked Access Door
- Ideal Color Monitor for All Purposes
- Like New, Unused (as-is)

Model #5111/19

Only
\$479⁰⁰


each
w/ DATA



*Selectric-II I/O PRINTER

Stepper
Modified

A REAL
BARGAIN!!!



DC stepper motors position the carrier and platen, and the standard "Selectric" selection and function solenoids offer parallel control capabilities. Driver circuitry not included. Fantastic bidirectional capabilities for plotting, proportional spacing and more!! Used, removed from sophisticated word processors, whole, AS-IS. Includes data and info. No type element included. Only...

*Selectric-II is a trademark of IBM Corp.
Packaging & Handling - \$20. Pay Shipping On Delivery

\$349⁰⁰

each

12" P-31 VIDEO MONITORS OEM-QUALITY!!

Motorola #XM 351, featuring adjustable horizontal osc. for all display configurations, 117/230 VAC operation, xfr input for isolation, BNC composite video input, contrast & brightness controls. Used, tested, and operational; good cond. 16x64 or 80x24 formats. Originally cost over \$200.00!

TOP QUALITY DISPLAY!! DATA INCLUDED.



Only...
\$79⁰⁰
each
Plus Shipping

Packaging & Handling - \$5.00

DAISY WHEEL TERMINAL Tested & FunctionalNOW ONLY **\$999⁰⁰**

COMPUTERS, ✓ 110
PERIPHERALS,
UNLIMITED!

(Formerly
CFR Associates, Inc.)

— NEW NUMBER —

617/372-8637

18 GRANITE STREET
HAVERHILL, MASS. 01830



MasterCharge & VISA Accepted



Listing continued.

```

9560 PRINT "(::GOSUB 9300:PRINT "):RETURN
9600 REM ***ZERO PAGE Y
9610 GOSUB 9650:PRINT ",Y":RETURN
9650 REM ***ZERO PAGE
9660 PRINT "(::GOSUB 9200:PRINT "):RETURN
10000 REM ***HEX TO DECIMAL
10010 H=0:D=0:T=0
10020 FOR I=LEN(H$) TO 1 STEP -1
10030 D$=H$(I)
10040 T=ASC(D$)-48
10050 IF T>9 THEN T=T-7
10060 H=H+T*(16^D)
10070 D=D+1
10080 NEXT I
10090 RETURN
10100 REM ***SEE IF B IS VALID OP CODE
10110 ISOP=0
10120 FOR OP1=1 TO 151
10130 IF B=OC(OP1) THEN GOTO 10160
10140 NEXT OP1
10150 RETURN
10160 POP :ISOP=1:RETURN
10200 REM ***HEX ADDR. FROM F
10205 P=1:T1=F
10210 FOR D=3 TO 0 STEP -1
10220 FOR E=1 TO 16
10230 IF F-(E*(INT((16^D)+1)))<0 THEN GOTO 10250
10240 NEXT E
10250 POP :E=E-1:F=F-(E*(INT((16^D)+1)))
10260 E=E+48:IF E>57 THEN E=E+7
10270 H$(P)=CHR$(E)
10280 P=P+1
10290 NEXT D
10300 F=T1
10310 PRINT H$;" ";:RETURN
10400 REM ***CONVERT & PRINT 1 BYTE
10405 B$="":P=1
10410 FOR D=1 TO 0 STEP -1
10420 FOR E=1 TO 16
10430 IF B-(E*(INT((16^D)+1)))<0 THEN GOTO 10450
10440 NEXT E
10450 POP :E=E-1:B=B-(E*(INT((16^D)+1)))
10460 E=E+48:IF E>57 THEN E=E+7
10470 B$(P)=CHR$(E)

```

More

displayed because it is quite possible that a piece of data could be interpreted as a legal instruction. For example, the ASCII code for the character X is the same as the op code for the instruction CLD (a hex D8). In some cases, of course, there will be data that is not printable ASCII, but at least with this technique we can catch some of it.

Line 3000 begins the routine to handle data that the program is able to recognize as data (since it has discovered that the byte is *not* a legal op code). Once again the address is displayed, as well as the byte at that location. Then, the word DATA is printed and the ASCII version of that byte is displayed in the appropriate column.

Occasionally, the ASCII version of a byte turns out to be a control code. The result of printing such codes on the screen can sometimes be interesting. I have left out any code to detect such codes but, if the occasional skipped line or tab is offensive, it would be a simple matter to detect and override (perhaps with blanks) their printing.



S-100 CARD NOW AVAILABLE IN KIT OR AS BARE BOARDS. YOU CAN'T BEAT THESE PRICES FOR OEM QUALITY. ALL ARE CPM® AND IEEE/S100 COMPATIBLE.

S-100 CARD NOW AVAILABLE IN KIT OR AS BARE BOARDS. YOU CAN'T BEAT THESE PRICES FOR OEM QUALITY. ALL ARE CPM® AND IEEE/S100 COMPATIBLE.

THE MCP/SOC Z80 CPU CARD FEATURES:

TWO SERIAL PORTS WITH RS232 DRIVE AND HANDSHAKING. BAUD RATES FROM 50 TO 19.2K. AN 8255 PROGRAMMABLE PARALLEL INTERFACE. 1K ONBOARD STATIC RAM AND 1K EPROM. WITH MONITOR PROGRAM FOR SERIAL TERMINAL INCLUDED. 2K 2716 EPROM OPTIONAL. ONBOARD RAM/EPROM OPERATE IN SHADOW MODE TO ALLOW 64K ADDRESSING. OPERATES AT 2 OR 4 MHZ.

ASSEMBLED AND TESTED \$299.95

BARE BOARD \$65.00; KIT INCLUDING EPROM \$249.95

HIGH PERFORMANCE MCP/SCC-6 NOW AVAILABLE:

INCLUDES FEATURES OF THE MCP/SCC Z80 CPU CARD. PLUS THE 2716 EPROM AND MONITOR ARE STANDARD. THIS CARD FEATURES THE Z80B CPU AND WILL OPERATE AT 2, 4 OR 6 MHZ.

ASSEMBLED AND TESTED \$369.95

BARE BOARD \$65.00; KIT INCLUDING EPROM \$299.95

THE MCP/FDC DOUBLE DENSITY DISK CONTROLLER:

UTILIZES THE WD1793 DOUBLE DENSITY F/D CONTROLLER CHIP AND THE WD1691 FLOPPY SUPPORT LOGIC CHIP. THIS CHIP SET OFFERS SUPERB PERFORMANCE AND RELIABILITY DUE TO ENHANCED DATA RECOVERY AND WRITE PRECOMP SUPPORT. THE MCP/FDC WILL SUPPORT UP TO FOUR 8" SINGLE OR DOUBLE SIDED SHUGART OR SHUGART COMPATIBLE DRIVES. THE MCP/FDC OPERATES IN SINGLE OR DOUBLE DENSITY MODE WITH 4 AND 6 MHZ SYSTEMS.

ASSEMBLED AND TESTED \$299.95

BARE BOARD \$65.00

THE MCP/VDB 80x24 VIDEO BOARD FEATURES:

A 7x9 CHARACTER MATRIX WITH LOWERCASE DESCENDERS. MEMORY MAPPED WITH 2K ONBOARD RAM. KEYBOARD INPUT PORT. PROGRAMMABLE FORMAT. HARDWARE SCROLL. NON DESTRUCTIVE CURSOR WITH 2 BLINK RATES. AND REVERSE VIDEO.

ASSEMBLED AND TESTED \$259.95

BARE BOARD \$65.00; KIT \$209.95

COMPLETE MCP 80/100 MAINFRAMES, DUAL 8" SINGLE OR DOUBLE SIDED SHUGART DISK. (CALL FOR LOW PRICE) CPM IS A REGISTERED TRADEMARK OF DIGITAL RESEARCH.



SUITE 444D
6992 EL CAMINO REAL
CARLSBAD, CA. 92008
PHONE (714) 438-3270

MASTERCHARGE & VISA ACCEPTED

AT LAST!

Mass production prices for high quality software. Buy direct and save 50%. Also available for CPM and HDOS.

DATA BASE MANAGER

Mod I & III \$69, \$149 (48K). Mod-II \$199
Maintain a data base and produce reports, all without user programming. Define file parameters and report formats on-line. Key random access, fast multi-key sort, field arithmetics, audit log, label. No time-consuming overlays. 500 happy users in one year. Mod-II and 48K versions have over 50 enhancements, including 40 fields maximum. "IDM-M2 is great!" - 80-US.

A/R

Mod-I \$69 Mod-II \$149 Mod-III \$69
Handles invoices, statements, aging, sales analysis, credit checking, forms input, and order entry. Unlike other accounts receivable programs, ours can be used by doctors, store managers, etc.

WORD PROCESSOR

\$49
Centers, justifies, indents, and numbers pages. Mod-I version features upper/lower case without hardware modification! File merge option available.

MAILING LIST

Mod I & III \$59, \$79 (48K). Mod-II \$99
The best! Compare and be selective. Includes forms input, 5-digit selection code, zip code extension, sort on any field, and multiple labels. Who else offers a report writer and merges with word processor?

INVENTORY

Mod I & III \$89, \$109 (48K) Mod-II \$149
Fast key random access. Reports include order info, performance summary, EQO and user-specified reports. Many people have converted to our system! "Next to impossible to damage the file."

GL. A/R. A/P. PAYROLL

Mod-II \$129 each
Integrated accounting package. 100+ page manual. As opposed to Osborne's slow binary search and 64 column screen, we use fast ISAM and 80 columns. Dual disk and TRSDOS required.

L216

\$59
A cassette package of 10 business programs for Level II 16 K systems. Includes word processor and data base manager. Poker game \$19.

Most programs are on-line, interactive, random-access, bug-free, documented, and delivered on disks. Mod-I programs require 32K TRSDOS. We're #1 in business software—don't let our low price fool you! Ask for our free 20-page catalog if you're still not convinced. Compiled versions are available.



MICRO ARCHITECT, INC.
96 Dothan St., Arlington, MA 02174

108

Now you're ready to go snooping through your Atari's ROMs. If you're not familiar with the 6502, here are a couple of addresses that may interest you (or provide a place to start snooping). Locations FFFC-FFFF (in hex, of course) contain the address to which a 6502 branches when a reset occurs. Locations FFFA-FFFF contain the address that is branched to as a result of a non-maskable interrupt. Locations FFFE-FFFF contain the address that is branched to as a result of a maskable interrupt. With these as a starting point, you should be able to discover quite a lot about how your Atari computer works.

For the sake of standardization, I have used the mnemonics and notation in *6502 Software Gourmet Guide and Cookbook*, except that to make zero page addressing more distinct from immediate mode, I have placed parentheses around zero page operands. Since I'm new to the 6502 and don't yet have the Atari Assembler cartridge, it is possible that the conventions I have chosen are not standard. If anyone is offended by my choice, please accept my apologies. ■

Listing continued.

```

10480 P=P+1
10490 NEXT D:PRINT B$;:RETURN
30000 REM ***MNEMONICS
30005 DATA ADC,AND,ASL,BCC,BCS,BEQ,BIT,BMI,BNE,BPL
30010 DATA BRK,BVC,BUS,CLC,CLD,CLI,CLV,CMF,CPX,CPY
30020 DATA DEC,DEX,DEY,EOR,INC,INX,INY,JMP,JSR,LDA
30030 DATA LDX,LDY,LSR,NOP,ORA,PHA,PHP,PLA,PLP,ROL
30040 DATA ROR,RTI,RTS,SBC,SEC,SED,SEI,STA,STX,STY
30050 DATA TAX,TAY,TSX,TXA,TXS,TYA
30100 REM ***OP CODES, ADDRESSING MODES
30110 DATA 105,101,101,102,117,103,109,104,125,105,121,106,97,107,113,108,41,201,
,37,202
30120 DATA 53,202,45,204,61,205,57,206,33,207,49,208,10,309,6,302,22,303,14,304,
40,305
30130 DATA 144,410,176,510,240,610,36,702,44,704,48,810,208,910,16,1010,0,1100,8
0,1210
30140 DATA 112,1310,24,1400,216,1500,88,1600,134,1700,201,1801,197,1802,213,1803
,205,1804,221,1805
30150 DATA 217,1806,193,1907,209,1808,224,1901,228,1902,236,1904,192,2001,196,20
02,204,2004
30160 DATA 198,2102,214,2103,206,2104,222,2105,202,2200,136,2300,73,2401,69,2402
,85,2403
30170 DATA 77,2404,93,2405,89,2406,66,2407,81,2408,230,2502,246,2503,238,2504,25
4,2505
30180 DATA 232,2600,200,2700,76,2804,108,2811,32,2904,169,3001,165,3002,181,3003
,173,3004,189,3005
30190 DATA 185,3006,161,3007,177,3008,162,3101,166,3102,172,3112,174,3104,190,31
06
30200 DATA 160,3201,164,3202,180,3203,172,3204,188,3205,74,3309,70,3302,86,3303,
78,3304
30210 DATA 94,3305,234,3400,9,3501,5,3502,21,3503,13,3504,29,3505,25,3506,1,3507
,17,3508
30220 DATA 72,3600,8,3700,104,3800,40,3900,42,4009,38,4002,54,4003,46,4004,62,40
05,106,4109
30230 DATA 102,4102,118,4103,110,4104,126,4105,64,4200,96,4300,233,4401,229,4402
,245,4403,237,4404
30240 DATA 253,4405,249,4406,225,4407,241,4408,56,4500,248,4600,120,4700,133,480
2,149,4803,141,4804
30250 DATA 157,4805,153,4806,129,4807,145,4808,134,4902,150,4912,142,4904,132,50
02,148,5003,140,5004
30260 DATA 170,5100,168,5200,186,5300,138,5400,154,5500,152,5600
30300 REM ***ADDRESSING MODE LENGTHS
30310 DATA 1,2,2,2,3,3,3,2,2,1,2,3,2

```

APPLE II+
48K RAM
\$1199.00

ATARI 400
16K RAM
\$399.00*
(Basic cartridge not included)

APPLE PRODUCTS	LIST	OUR PRICE
Apple II + 48K	\$1530	\$1199.
Apple Disk w/cont	\$645	\$549.
Apple Disk w/o cont	\$525	\$469.
Apple Pascal System	\$495	\$399.
Apple Integer Card	\$200	\$159.
Apple Centronics Card	\$225	\$189.
Apple H.S. Serial Card	\$195	\$159.
Apple Silentype Printer	\$595	\$529.
Apple Fortran	\$200	\$169.
Apple Pilot	\$150	\$125.
Apple Writer	\$75	\$60.
DOS Tool Kit	\$75	\$60.
Apple Plot	\$70	\$58.

Microsoft 280 Softcard	\$349	\$299.
Microsoft 16K Ram Board	\$195	\$179.
Microsoft Fortran	\$195	\$179.
Buy All 3 Microsoft Prods.	\$739	\$629.

APPLE III 128K RAM-SANYO
12 in. MONITOR
And Information Analyst Package **\$3995**

C. ITOH FP1500-25 Letter Quality Printer	\$1595.00
IDS Paper Tiger 480 G Printer	\$1128.00
Okidata Microline 80 Printer	\$495.00
Epson MX-70 Printer	\$399.00

EPSON MX-80 Printer	\$489.00
Hi-RES Software for EPSON MX-80	\$39.95
TYMAC PPC-100 Parallel Printer Card w/Cable	\$99.00

Sanyo 9 in B & W Monitor	\$179.00
Sanyo 12" B & W Monitor	\$249.00
Sanyo 13" Color Monitor	\$429.00
NEC 12" Green Phospor Monitor	\$259.00
CCS 7710A Serial Interface	\$149.00

ATARI PRODUCTS	LIST	OUR PRICE
Atari 400 16K	\$499.95	\$399.
Atari Basic Cartridge	\$59.95	\$47.95
Atari 800 16K	\$1080.00	\$799.
Atari 410 Recorder	\$89.95	\$69.
Atari 810 Disk Drive	\$599.95	\$499.
Atari 850 Interface	\$219.95	\$189.
Ram Cram 32K Board	\$399.00	\$199.
Atari 16 K Ram	\$199.95	\$159.

APPLE HAM PROGRAMS
CW, RTTY, ASCII, TRANSCEIVE PROGRAM
On Cassette \$19.95 On Diskette \$29.95
Show scan receive program \$19.95

SPECIALS

Andromeda 16K Ram Card	\$159.00
Visicalc	\$119.00
Desktop Plan	\$75.00
DB Master	\$159.00

SOFTWARE FOR APPLE

BPI General Ledger	\$350.00
BPI Accounts Receivable	\$350.00
BPI Inventory	\$350.00
Stockpile Inventory Sys.	\$395.00
Easywriter Professional	\$195.00
LJK Wordprocessor 80 Col.	\$149.00

ATARI 400 DISC SYSTEM

Atari 16K Computer	\$898.
810 Disc Drive & Basic Cartridge	

Hayes Micromodem II	\$319.00
MNT Comp AID & DIA Board	\$299.00
MNT Comp Romplus Board	\$179.00
MNT Comp Introl X/10 Sys	\$269.00


OLENSKY BROS., INC.
COMPUTER SALES DIVISION

3763 AIRPORT BLVD. • MOBILE, ALA. 36608
(205) 344-7448 • CST 9-6



MEMOREX FLEXIBLE DISCS

BUY THE BEST FOR LESS.
Lowest prices. **WE WILL NOT
BE UNDERSOLD!!** Buy any
quantity. Call free (800) 235-
4137 for prices and information.
Dealer inquiries invited. C.O.D.'s
accepted.



**PACIFIC
EXCHANGES** ✓172
100 Foothill Blvd.
San Luis Obispo, CA
93401. In Cal. call
(800)592-5935 or
(805)543-1037



The Sorcerer Speaks

By Peter Vernon

The Cognivox VIO-132 from Voicetek, Inc. (PO Box 388, Goleta, CA 93116), is a speech recognition and voice-response peripheral for the Exidy Sorcerer. [Editor's Note: Voicetek also manufactures models for AIM-65, Apple II, Commodore PET and CBM, and the TRS-80 computers.] Up to 32 words or short phrases can be entered into the computer's memory and recalled as desired. Any of the stored words can be recognized by the computer and used to control the flow of a program. Music and sound effects can also be reproduced.

The length of Cognivox's voice-response vocabulary depends on the length of the words used and the memory size of your Sorcerer. At least 32K of RAM is required for maximum capability, but the Cognivox can be used with 16K; in this case the response vocabulary will be limited to 12-16 short words, but the word recognition vocabulary will still be 32 words.

From the outside the Cognivox is deceptively simple. It is enclosed in a plastic box measuring 159 mm x 96 mm x 50 mm, with a 7 cm speaker covered by a mesh grille, a volume control and a socket for a microphone at one end of the box. A dynamic microphone is supplied with the peripheral, along with a cassette of operating and demonstration programs. An 18-page user's manual is also provided, containing a brief description of the operation of the device and fur-

ther sample programs.

The unit comes fully assembled, ready to plug into the parallel I/O port of the Sorcerer and run immediately.

Before discussing the operation of the Cognivox in more detail, however, let's take a look at the various methods of speech synthesis available for use with small computers.

Speech Synthesis

Three methods can be used to produce speech from a computer. Speaking devices such as those from Texas Instruments use a phoneme synthesis method. Their speech synthesizer chip, used in the Speak & Spell and as a peripheral for the TI 99/4 home computer, is an array of programmable filters, and noise and tone sources. Any desired sound can be reproduced by manipulating the parameters of the filters. This method is also used by the Computalker and the Votrax Type 'n Talk speech synthesizers, although they use discrete components to carry out the same operations as the TI chip.

The main difference between the operation of the TI synthesizer and, for example, the Votrax is that the TI devices contain code for complete words stored in ROM, while the Votrax synthesizer stores codes for the individual phonemes of the English language, allowing words to be built up from combinations of sounds. The Votrax synthesizers are thus more

flexible, although much programming effort is needed to use them effectively.

The Computalker is similar to the Votrax devices, although it also provides direct control of nine of the speech parameters in addition to phoneme-based synthesis.

The second method of reproducing speech is digital storage of speech information, using a compression algorithm which eliminates the redundancy of speech information to conserve memory. Data is read out and then expanded to drive a digital-to-analog converter and an amplifier. This is the method used in Digitalker DT1050, the National Semiconductor speech synthesis set. (See "Build a Low Cost Speech-Synthesizer Interface" by Steve Ciarcia in the June, 1981 *Byte* for a board based on this set that can be used with a number of computers.)

The SD200 Supertalker from Mountain Computer also uses a data compression technique. This is the only device besides the Cognivox which offers both speech input and output in one peripheral.

The third possible technique is digital recording, the method used by the Cognivox. Speech signals from a microphone are filtered, and the out-

Peter Vernon, 31 Georgina St., Newtown, NSW 2042, Australia, is a free-lance technical writer and computer systems consultant.

put of the filters is sampled periodically and stored in the computer's memory. Playback is a matter of reading out the digital information and converting it to analog form to drive an amplifier and speaker. Word recognition is performed by comparing the patterns of the input word with the patterns in memory and reporting the closest match.

The advantage of phoneme-driven synthesizers is that, in theory, any word can be reproduced. In practice, however, the intelligibility and quality of the speech suffers unless the synthesizer is carefully programmed by an experienced user. Fixed vocabulary synthesizers store the data for each word in ROM, eliminating the need to program each sound segment of the word individually, but, of course, the vocabulary is limited to the words already coded in the ROM. In some applications this is not a disadvantage, as only a fixed vocabulary is necessary. Telesensory Systems, Inc., has marketed a talking calculator using this approach, and has had considerable success. Both Telesensory Systems and Texas Instruments offer fixed vocabulary synthesizer modules for OEM applications.

Digital recording is the easiest system to use, and has the advantage that the vocabulary can be easily changed. The disadvantage is that the technique uses large amounts of memory to store the speech data. The Cognivox uses a digital sampling technique that sacrifices speech quality for memory storage and ease of use. The sampling rate of about 6 kHz limits the bandwidth of speech to about 3 kHz, creating a degree of distortion similar to speech heard over a telephone. Intelligibility can be quite good if care is taken in entering the words into memory when the vocabulary is first created.

A second advantage of digital recording is that the stored data can be used to identify a word which has previously been entered into memory. The success rate of the recognizer is said to be 98 percent, but in practice seems to be closer to 85 percent. This success rate is dependent on the speaker. You must pronounce each word in the same way each time it is used, and the device will only recognize the voice of the person who trained it.

Using the Cognivox

The Cognivox plugs into the paral-

el port of the Sorcerer, and takes its power from the computer. The Monitor stack and the BASIC stack must be relocated downwards to create a protected area of memory in which the Cognivox machine-language driver and speech data can be stored. A BASIC program called BOOT is provided on the accompanying cassette to perform this relocation.

The software supplied on the demonstration cassette is recorded at 300 baud for improved reliability. This naturally increases the time taken to load the program, but is not a serious disadvantage. The manual accompanying the Cognivox suggests that you might like to record the programs at 1200 baud to speed loading. (The Sorcerer provides for both baud rates.)

After BOOT has been loaded and run, approximately 4K of RAM remains for application programs. The machine-language driver, VOX2, is not position-independent, and must be loaded into RAM at addresses 1200H to 15FFH. Data tables for this program occupy addresses 1600H to 1CFFH, and speech data is stored from 1D00H to the end of RAM (3FFFH for a 16K Sorcerer, 7FFFH for a 32K machine). [Editor's Note: Voicetek has informed us that a relocated version of VOX2 is available starting at 7200H for users with 48K Sorcerers. This version allows more space for user programs and does not conflict with DOS systems.]


All the application programs supplied with the Cognivox will run on a 16K Sorcerer, although a 32K Sorcerer

er provides more room for the storage of speech data, so that the voice-response vocabulary can be slightly longer and use longer words.

After running BOOT and loading the machine-language driver, your applications programs can be loaded. A demonstration program called PROG2 is provided, and is a good example of the abilities of the system. The program provides six options, covering entry of a vocabulary, playback and recognition. Training the Cognivox requires three passes through the vocabulary. On the first pass the device samples the characteristics of your voice in preparation for the second pass, which enters the spoken words into memory. The third pass plays back the stored words and asks you to repeat each one into the microphone to fine-tune the system.

The words entered can be played back using option 2 of the demonstration program. I had fun getting my computer to say "Hello, I am a computer. How can I help you?" Each word of a sentence is entered separately, so it requires some practice to achieve a natural-sounding intonation.

Options 4 and 5 exercise the voice recognition abilities of the unit. Option 4 provides recognition with voice response; you say the word, and the computer searches the stored data for a matching pattern and speaks the word it has found. Option 5 is similar, except that rather than speaking the word the computer dis-



Voicetek's speech synthesis unit for the Sorcerer.

plays the number of the word it has found. (Words are numbered in the data area in the order in which they were entered into memory.) Using this program as a guide, it is easy to write BASIC programs which recognize a word and then perform some action on the basis of the word recognized. This is the operating principle of the two demonstration game programs supplied on the cassette.

Since the Cognivox uses a digital recording technique, most of the characteristics of the speaker's voice are retained and reproduced; the unit faithfully reproduces tones of voice, inflections and accents.

Cognivox is useful for more than just games, as another program on the supplied cassette demonstrates. VDUMP is a verbal memory dump. After entering the numbers from zero to nine and the letters from A to F, via the microphone, you can specify an area of memory which will be examined. The program displays addresses and data on the screen for the selected area of RAM, and at the same time the Cognivox speaks the hex value of the byte stored in each memory location. It is also possible to

use the routines from PROG2 to reverse the process and have the Cognivox enter data into RAM in response to a spoken message. Entering a machine-language program is then a matter of speaking into the microphone.

Not Just Words

The Cognivox is not restricted to producing words. A demonstration program is supplied which illustrates its music and sound-effects capabilities, first with random computer music and then with classical and popular tunes. Several examples of similar programs are given in the operating manual, together with a list of values to produce specific notes of the musical scale. You can control both the frequency and the duration of the sounds.

It is at this point that a limitation of the Cognivox, and of the manual, becomes apparent. To produce middle C the manual suggests that you poke a value of 268 to a location in memory. It is simply not possible to store any number higher than 255 in a single eight-bit byte, and, if an attempt is made to do so on the Sorcerer, a

Function Call (FC) error message will be displayed. This means that the lowest note possible for the Cognivox is C sharp above middle C. There may be some way around this problem, but the manual makes no mention of it, and it seems that the author of the manual was unaware that any problem existed.

This is the one fault I found in the system, and is an exception to the generally fine presentation and clarity of the manual.

Other programs supplied on the demonstration cassette are VOTH, a voice-operated version of the game Othello, and VTRAP, a game in which you and the computer maneuver a trace on the display screen to corner the opponent and block any further movement. VOTH uses the word recognition ability of the Cognivox to let the player enter his or her moves verbally, while to play VTRAP you first enter the words "left," "right," "down," "go up" and "faster" and train the Cognivox to recognize them—the player's moving trace on the display then responds to these commands.

The final program supplied is

RACET SORTS — RACET UTILITIES — RACET computes — RACET SORTS — RACET UTILITIES

HARD DISK MULTIPLEXOR WITH 10 MEG HARD DISK FOR THE TRS-80* Mod II

NOW YOU CAN HAVE THAT LARGE COMMON DATA BASE!!

- Allows up to 4 Mod II's to connect to a single controller — up to 4 hard disk drives per controller. Users may access the same file simultaneously (first-come first-served).
- Uses Cameo controller and standard 10-megabyte cartridge (hard) disk drives along with RACET Hard/Soft Disk System (HSD) software.
- Access times 3 to 8 times faster than floppy. Mixed floppy/hard disk operation supported.
- Compatible with your existing TRSDOS programs! All BASIC statements are identical.
- A single file may be as large as one disk. Alternate mode allows 24-million byte record range. Directory expandable to handle thousands of files.
- Includes special utilities — backup and copies, HPURGE for multiple deletions, HDOS directory catalog system, and Hard Disk Superzap. FORMAT utility includes options for specifying sectors/track, platters/disk, logical disk size, etc.

HARD DISK DRIVE & CONTROLLER \$5995 RACET HSD Software \$400
Call for multiuser pricing. Dealers call for OEM pricing.

BASIC LINK FACILITY 'BLINK' \$25 Mod I, \$50 Mod II
Link from one BASIC program to another saving all variables! The new program can be smaller or larger than the original program in memory. The chained program may either replace the original program, or can be merged by statement number. The statement number where the chained program execution is to begin may be specified! (Mod I Min 32K 1-disk)

INFINITE BASIC (Mod I Tape or Disk) \$49.95
Extends Level II BASIC with complete MATRIX functions and 50 more string functions. Includes RACET machine language sorts! Sort 1000 elements in 9 seconds!! Select only functions you want to optimize memory usage.

INFINITE BUSINESS (Requires Infinite BASIC) \$29.95
Complete printer pagination controls — auto headers, footers, page numbers. Packed decimal arithmetic — 127 digit accuracy +, -, *, /. Binary search of sorted and unsorted arrays. Hash codes.

*TRS-80 IS A REGISTERED TRADEMARK OF TANDY CORPORATION

RACET COMPUTES


702 Palmdale, Orange, CA 92665

TELEPHONE ORDERS ACCEPTED (714) 637-5016

RACET SORTS — RACET UTILITIES — RACET computes — RACET SORTS — RACET UTILITIES

Radio Shack Dealer #R491

MODEL III LEVEL III BASIC 26-1062




\$825.00

WE ACCEPT CHECK, MONEY ORDER, OR PHONE ORDERS WITH VISA OR MASTER CHARGE. SHIPPING COSTS WILL BE ADDED TO CHARGE ORDERS. DISK DRIVES, PRINTERS, PERIPHERALS, AND SOFTWARE—YOU NAME IT, WE'VE GOT IT. WRITE OR CALL FOR OUR COMPLETE PRICE LIST.

C & S ELECTRONICS, LTD. 32 EAST MAIN ST. MILAN, MICH. 48160
(313) 439-1508 (313) 439-1400

C & S ELECTRONICS MART IS AN AUTHORIZED RADIO SHACK DEALER #491



The guy on the left doesn't stand a chance.

The guy on the left has two file folders, a news magazine, and a sandwich.

The guy on the right has the OSBORNE 1®, a fully functional computer system in a portable package the size of a briefcase. Also in the case are the equivalent of over 1600 typed pages, stored on floppy diskettes.

The owner of the OSBORNE 1 is going to get more work done—and *better* work done—in less time, and with less effort.

Unfold it, plug it in, and go to work like you've never worked before. . . .

Go to work with WORDSTAR® word processing, so your correspondence, reports, and memos take less time to produce, and say more of what you wanted to say. And with MAILMERGE®—the mailing system that turns out personalized mass mailings in the time you'd spend on a rough draft.

Go to work with SUPERCALC®, the electronic spreadsheet package that handles complex projections, financial planning, statistics, and "what if" questions instantly. For the more technically minded, SUPERCALC will process scientific data and calculate results.

Go to work with powerful BASIC language tools—the CBASIC-2® business BASIC, or the Microsoft BASIC® interpreter.

That's standard equipment.

Options include about a thousand different software packages from a host of vendors designed to run on the CP/M® computer system.

Go to work at the office, at home, or in the field.

Or anywhere. Optional battery packs and telephone

transmission couplers mean you need never work without the capabilities of the OSBORNE 1. That's good, because you won't want to work again without it.

All for \$1795. It's inevitable.

The OSBORNE 1 is the productivity machine that's changing the way people work. Put simply, the machine delivers a significant productivity edge—day in and day out—to virtually anyone who deals with words or numbers. Or both.

Since the entire system is only \$1795, it won't be too long before the guy on the left has an OSBORNE 1 of his own. The same probably goes for the person reading this ad. In fact, we think it's inevitable.

The OSBORNE 1 includes a Z80A® CPU, 64K bytes of RAM memory, two 100 kilobyte floppy disk drives, a business keyboard, built-in monitor, IEEE 488 and RS232 interfaces for printers and other things that get connected to computers, plus CP/M, CBASIC-2, Microsoft BASIC, WORDSTAR, and SUPERCALC. The system is available from computer retailers nationally.

\$1795. It's inevitable.



OSBORNE
COMPUTER CORPORATION

26500 Corporate Avenue Hayward, California 94545
Phone (415) 887-8080 TWX (910) 383-2021

✓ 368

called CALC, and turns the Sorcerer into a talking calculator. Numbers are announced as they are entered from the keyboard, and are displayed on the screen, together with the arithmetic operation requested. The answer to the problem is also displayed and announced.

Although this demonstration program is limited to four functions and exponentiation, it can be expanded infinitely, to turn your Sorcerer into a talking, programmable scientific calculator with RAM.

The user's manual gives further examples of routines for storing and playing back speech, and for creating music and sound effects. It also provides a circuit diagram for connecting the Cognivox to an external amplifier. The quality of the voice output can be considerably improved with the addition of an amplifier and a larger speaker with a properly constructed baffle.

Opening up the Cognivox voids the 90-day warranty, and reveals the lengths to which Voicetek has gone to protect the secrets of the device. All you will see is a small circuit board, approximately 70 mm x 40 mm, en-

The Cognivox represents an excellent value for the money.

tirely covered with a thick blob of epoxy resin. The only information available from Voicetek on the operation of the device is as follows:

"We have reduced the analog preprocessor to a single IC plus a few resistors and capacitors. In addition, our software uses unique learning algorithms that provide superior pattern-matching capabilities. In fact, Cognivox is so novel we are applying for a patent."

The Cognivox works very well—it combines voice response, speech recognition and music and sound-effects generation in one compact unit. You can get good results with a small amount of practice. The combination of all these abilities makes the Cognivox very cost-effective. Instead of separate units for voice output and

speech recognition, and another unit for music and sound effects, owners of the Sorcerer can purchase one device, for \$149 plus \$4 shipping, which fulfills all these functions.

The Cognivox is easier to use than the Computalker or Votrax speech synthesizers, and eliminates the need for a separate speech recognition device. The limitation of the vocabulary size is easily overcome by creating several vocabulary databases and storing them on tape or disk, to be loaded into memory for a particular application, or loaded in response to a spoken keyword. Using this approach, you can make the vocabulary as large as required, divided into blocks of 16 or 32 words.

All in all, the Cognivox is an interesting and useful device, and represents an excellent value for the money. If you would like to add a voice and an ear to your Sorcerer, the Cognivox is for you. [Editor's Note: Voicetek has recently made hardware improvements to the VIO-132 increasing voice-recognition accuracy. The company has updated and extended the manual (by 25 pages) and increased it to 120 pages.]■

CENTRONICS® 737


RS LP IV
ATARI 825

the missing link:

...your COMPUTER



OR for the Apple® II



available Aug. 15

ETI's own microprocessor intelligence can put all the power of your 737 Printer at your fingertips...

ETI's pioneering design (patents pending) allows you to control all the options of this powerful printer with simple commands right from Basic or the body of your wordprocessing text.

Provides maximum printing speed with mainframe-like dedicated peripheral control and programmability.

Compatible with most popular wordprocessing packages and microcomputer hardware.

Features:

- access to all six fonts of the 737 printer
- true proportional spacing with justification
- superscript, subscript, underlining
- user definable spacing, line centering, form feed
- UPPER/lowercase support also for UPPER-only systems
- optional use of BASIC as a simple but flexible wordprocessor
- no additional cables—Centronics-like edge-card connector

ETI-module: \$173. ETI-CARD with cable \$185.

order now directly from us (check, MO, Visa, MC) or your local printer dealer (N.J. residents please add 5% tax)



microDome
CORPORATION

Denville, New Jersey 07834
P.O. Box 392 (201) 627-8554

✓ 248



GO PIGGYBACK!



CENTRONICS ADD lowercase with our PLUG-IN piggyback board!

9WX7H Dot Matrix \$135

5WX7H Dot Matrix \$ 95

TWO complete character sets on board:

96 character ASCII PLUS choice of
128 character APL, TRS-80/H-19 Graphics or
Scientific. (Customer defined: add \$50/set).

Most printers convertible: specify logic board #



SYDNEY SEZ:
Shop Comparatively!

DSE

✓ 212

Digital Systems Engineering

12503 King's Lake Drive, Reston VA 22091 (703) 620-2994

ALSO AVAILABLE: New Centronics and Integral Data Systems printers at 15-20% below list; also, used printers of several makes. Call for information!

MasterCard, VISA, Check, MO, PO


All products warranted 90 days

Student-Proof Your Computer

By Ken Reid

A hobbyist's computer is in a protected environment. The user has money invested in his system, and takes precautions to avoid such expensive mistakes as spilling Pepsi on his keyboard.

But schools are different. If a fragile input device is left unsupervised, it won't be functioning for long. Software, too, is vulnerable; it takes only one clever or malicious student who knows how your system works to produce startling changes in your carefully constructed educational program.



The input keybox.

easy construction, and the cover is attached to the box by four nylon machine screws. These are sealed after assembly with plastic cement. The seven keys are Hall-effect switches (Microswitch PK 8913-3), which we obtained as a surplus lot from NCE Compumart. We used blank keycaps and inserted our special labels.

The keybox circuit is shown in Fig. 1. Each box provides a one-bit "I'm here" signal as long as it is connected and another three bits indicating which key has been pressed. Once a key has been pressed the output locks; further keypresses have no effect until the computer reads the signal and returns a reset pulse. Two four-bit keyboxes share one eight-bit parallel port, 12 ports for our 24 stations. At present we are using three Imsai 4PIO boards to provide these.

Our 24-keyboard installation has been in service for over a year. During this period we have had two boxes quit due to off-voltage regulators. We have had no key failures.

Numerous keycaps—at least 40 so far—have been cracked, due to excessive force. We find that "key-beating" occurs (a) when the system is heavily loaded and response is slow or (b) when the system has malfunctioned. This "kick the machine" attitude must be acknowledged by any system designer whose machinery is open to unsupervised use by the general public. Be prepared! ■




Fig. 1. Keybox circuit.

Experiences of this type were uppermost in our minds when we developed a classroom-sized (24 work stations) input system for a microprocessor-controlled CAI system for our Health Sciences Library at the University of Louisville. Our student access terminals had to be foolproof. So we developed an input keybox.

Why use special input keyboards? First, the signals enter your program and cannot be used for anything else. This restriction is an absolute necessity for any system which is intended for, or exposed to, unrestricted public access. The operator's console is separate and can be kept safely behind locked doors.

Second, the user is less likely to be confused if his options are restricted. Few CAI programs require more than four or five options at each choice point.

Third, simple keyboards cost less than complex ones, both in dollars and maintenance.

The box is made of heavy black plastic. The key assembly and circuitry is mounted on the cover for

Ken Reid, 1935 Trevilian Way, Louisville, KY 40205

What's the Difference?

By R. B. Nottingham

While rereading the November 1980 issue of *Microcomputing*, my attention was drawn to the wind chill temperature program in Robert Baker's PET-pourri column (p. 14). Suddenly, the antennae of my memory began to quiver. I looked closely at the data, and it was familiar. I had seen it before. Here it was again and still wrong!

How was I able to recognize the data, tell that it was wrong by inspection, correct it and then amplify it? Mathematicians refer to the method as difference calculus or the method of finite differences. Don't let the reference to calculus throw you. You can use difference methods if you can add and subtract, or tell your microcomputer to.

I have never seen the topic mentioned in the recent *Microcomputing* literature, and I think it is too good a tool not to have in your bag of tricks. So I'll briefly discuss difference methods and then apply them to the problem mentioned above.

Back to Babbage

About 120 years ago, Charles Babbage conceived the stored program computer with hard-copy output. He called his device a difference, or analytical, engine. He was concerned with the problem of producing errorless tables of functions for use in navigation at sea. He had realized that the only way to produce error-free tables was to produce them automatically, without human intervention.

Babbage realized that you could

generate any continuous function over an interval by simply adding differences. If you look at the squares of the integers 1, 4, 9, 16, 25, and at their first differences, 3, 5, 7, 9, you'll see that their second differences are a

constant 2. So you can generate a table of squares by successively adding 2 and then successively adding these numbers.

Now try it with cubes. Yes, there is a theorem that in a series of this type,

```
1 REM DIFFERENCE CALCULUS APPLIED TO WIND-CHILL DATA
2 REM R. B. NOTTINGHAM, 10-31-80
60 DIM C(8,11)
70 FOR W = 0 TO 8: FOR T = 0 TO 11
80 READ C(W,T):NEXT T: NEXT W
90 DATA -60,-50,-40,-30,-20,-10,0,10,20,30,40,50
100 DATA -68,-57,-47,-36,-26,-15,-5,6,16,27,37,48
110 DATA -95,-83,-70,-58,-46,-33,-21,-9,4,16,28,40
120 DATA -112,-99,-85,-72,-58,-45,-36,-18,-5,11,22,36
130 DATA -124,-110,-96,-82,-67,-53,-39,-25,-10,3,18,32
140 DATA -133,-118,-104,-88,-74,-59,-44,-29,-15,0,13,30
150 DATA -140,-125,-109,-94,-79,-63,-48,-33,-18,-2,13,28
160 DATA -145,-129,-113,-98,-82,-67,-49,-35,-20,-4,11,27
170 DATA -148,-132,-116,-100,-85,-69,-53,-37,-21,-6,10,26
185 GOTO 1000
1900 FOR W=1 TO 8
1910 FOR T= 1 TO 11
1920 PRINT"C(";W;",";T;")= ";
1930 PRINTC(W,T);
1940 IF T=11 THEN GOTO 1110
1950 D1(T)=C(W,T)-C(W,(T+1))
1960 IF T=0 OR T>9 THEN GOTO 1070
1970 PRINTD1(T)
1980 IF T<2 OR T>9 THEN GOTO 1110
1990 D2=D1(T)-D1(T-1)
1100 PRINT TAB(20)D2
1110 NEXT T
1120 PRINT
1130 INPUT"PRESS ENTER TO CONTINUE";QQ
1140 NEXT W
1150 FOR T=0 TO 11
1160 FOR W=1 TO 8
1170 PRINT"C(";W;",";T;")= ";
1180 PRINTC(W,T);
1190 IF W=8 THEN GOTO 1250
1200 D1(W)=C(W,T)-C(W+1,T)
1210 PRINTD1(W)
1220 IF W<2 OR W>6 THEN GOTO 1250
1230 D2=D1(W)-D1(W-1)
1240 PRINTTAB(20)D2
1250 NEXT W
1260 PRINT
1270 INPUT"PRESS ENTER TO CONTINUE",
1280 NEXT T
1290 END
```

Program listing.

Address correspondence to R. B. Nottingham,
1619 SE 3rd Court, Deerfield Beach, FL 33441.

the difference which becomes constant is the power of the series. Squares, second difference; cubes, third difference, and so on.

This is a useful tool. If you have a function—the flight of a model rocket, the landing path of an airplane or whatever—that you want to show on your computer, it may make much better sense to store the equation of the curve and calculate it as you need it, rather than store all the data of the curve itself. If you examine the successive differences in the data, and you find that some difference tends to become a constant, that gives the order of the polynomial that will be needed to fit the data.

Wind Chill

Now regarding wind chill. I had found an article on the subject several years ago in a bicycling magazine, giving the same data which Baker used. If you do not have his program handy, lines 60–170 in Listing 1 are copied directly from it. The data in line 90 represents Fahrenheit temperatures from –60 to +50.

The lower temperatures are a little exotic unless you plan to wing-walk at high altitudes or visit the poles. Plus 50 was not quite high enough to suit me. It is rarely that cold in south Florida, and believe it or not, when one is acclimated here, riding a bike with the temperature in the 60s can feel chilly, particularly if the sun isn't shining. So I decided to extend the table up to 70 or 80 degrees, perhaps discarding the very low temperatures.

Line 100 gives the wind chill for a five mph wind, and successive lines increase the speed in increments of five mph. Comparing line 90 and line 100, from right to left, you see that the wind chill increases as the air temperature gets lower. Reasonable enough. If you read down any column, you'll see that the increase in wind chill gets less as the wind speed increases. The increases from 35 mph to 40 mph (lines 160, 170) are very small. Apparently, once the wind speed is high enough to carry away all our body heat, more wind doesn't make much difference.

Now, if you look at the differences along any line, the wind chill seems to increase about 10 or 15 degrees for every ten-degree change in temperature. But look at the right end of line 120. The differences are 14, 11, 16, 13, etc. There is no way that the differences can jump around like this.

As our German friends don't say, "Etwas ist gestunken."

Apparently, the wrong table has been copied and copied with no reference to the original. Errors have crept in and have propagated. So what do we do about it?

Since you have a microcomputer, you might as well put it to work. If you have the Baker Wind-Chill program loaded, just add line 185 from Listing 1, and lines 1000–1160. Do not add line 2120. It is simply my approximately corrected version of line 120. You may well be able to do better.

Now run the program; you will see the original data and the first and second differences, first along the rows, and then down the columns. Obviously there is trouble. What you want to do is make the differences uniform. When you find a difference you don't like, press the break key.

Then, in the direct mode, enter $C(W,T)=X$, replacing W,T and X with the appropriate values. Type GOTO 1000. Do not type RUN or the variables will be set to zero. Repeat this until the differences please you

and then correct the DATA statements. If you have a printer, you may, of course, LLIST the array for your new data.

If you wish to extrapolate the table to higher temperatures, this is easy to do, if you watch the differences. For example, at five mph, it looks like the difference at 60 degrees will be either one or two degrees, and at 70, one degree.

At 40 mph, the difference is running about 16 degrees, so you might make the wind-chill temperature for 60, 42 degrees, and for 70, about 67 degrees. If you keep the differences smooth you won't be far off, even though extrapolation (going out beyond the original data) is always dangerous. A function may be discontinuous, but I would be very surprised if wind chill were. If you add temperatures to each data line, be sure to either delete temperatures at the left of the line, or revise the dimensions of the arrays.

Have fun. I think that the method of differences is a useful tool, and just thinking in terms of differences can often let you spot bad data. ■

Happy Hands

Offers Discounts on All

TRS-80TM COMPUTERS

We Have What You Are Looking For

- ☐ PROMPT SHIPPING
- ☐ AVAILABLE SERVICE CONTRACTS
- ☐ DISCOUNTED PRICES COMPARABLE TO ANY OTHERS
- ☐ NO TAX ON OUT OF STATE SHIPMENTS

Call Collect For Prices
And Shipping Schedules

505-257-7865

or write

HAPPY HANDS ✓243
P.O. DRAWER I
RUIDOSO, NEW MEXICO
88345

AMERICAN SOFTWARE & SYSTEMS, INC.

SOFTWARE FOR TRS80*
MODEL I LEVEL II / MODEL III and
APPLE II PLUS (Disk Format)**

- 1. WORDTYPE** — word processing offering latest text editing, page length/numbering and additional features available in more expensive software. **\$89.95**
- 2. BUSINESS APPLICATIONS** — Accts Rec/Pay, Inventory, Invoice Mailing List and others. **\$69.95**
- 3. HOME APPLICATIONS & GAMES** — Checkbook, inventory, payable, recipe and others. **\$29.95**
- 4. SCIENTIFIC & GAMES** — Conversions, Mathematics, hydraulic calculations, bar graph presentation of data games and others. **\$39.95**
- 5. AMATEUR RADIO & ELECTRONICS** — Antenna design (quad/beam/dipole), db loss, ccode and others. **\$34.95**
- 6. GAMES** — Wheel of Fortune, Slots, Keno and more. **\$9.95**

TERMS: M.O., Visa, or Master Charge.
Add \$1.50 for shipping and handling.

FOR CATALOG SEND \$1.50
FOR SHIPPING AND HANDLING

**AMERICAN SOFTWARE
& SYSTEMS, INC.** ✓249

2110 North Carson Street
Carson City, Nevada 89701
(702) 883-3274

*A trademark of Tandy Corp.

**A trademark of Apple Computer Inc.

TSC Extended BASIC

By Phil Hughes

TSC Extended BASIC (Technical Systems Consultants, PO Box 2570, W. Lafayette, IN 47906) is an excellent product for the 6800 and 6809 microprocessors. It has the abilities of a comprehensive BASIC, is well-documented and relatively bug-free. If you are running Flex and need a BASIC with these capabilities, it is well worth its price. It costs \$100, configured for either five- or eight-inch disks.

In spite of the comprehensive additions, TSC Extended BASIC is fast. Table 1 shows comparison times for the fastest BASIC (OSI), Altair extended BASIC and the other two 6800 BASICs. These times are for running Tom Rugg's and Phil Feldman's benchmark programs that appeared in the June 1977 issue of *Kilobaud* ("BASIC Timing Comparisons," p. 66).

Note that OSI BASIC was run on a system that could not support disk drives because the clock speed was doubled. The first TSC Extended BASIC test ran with the benchmarks exactly as written. The second line shows timing information when the control variables in the FOR-NEXT loops were changed to integer data type.

Extensions

Now that you know that this BASIC is competitive in speed, let's look at the extensions in detail. First consider the extensions to variables and operators. Variable names have been

extended to allow two alphabetic characters, as well as the standard alphabetic and alphabetic followed by a numeric. For example, AB is a valid variable name, as are A and A1. This is important because it is easier to imagine that ST stands for subtotal than S or S7.

Note that there are seven two-letter combinations that are keywords and therefore cannot be used as variable names. They are AS, FN, IF, ON, OR, PI and TO.

The other big addition to variables is the integer data type. These variables may be mixed with floating point (real) variables, and will save both execution time and storage space. They are particularly useful for loop control variables and array subscripts.

Their range is from -32768 to 32767 and they take only two bytes of storage. Compare this with eight bytes for a floating point variable. An integer variable is identified by the suffix %. For example,

```
FOR I% = 1 TO 100:NEXT I%
```

is a loop with the integer control variable I%.

New operators consist of the logical operators AND, OR and NOT and the string concatenation operator, +. The logical operators operate on integers in a bit-by-bit fashion. If the arguments of a logical operator are real variables, they are automatically converted to integers before the operation is performed. Also, if the real

variables have too large a value for conversion, an error message is printed.

The next group of new features, statement extensions, is added to existing BASIC statements. The first of these is an addition to the RESTORE statement which lets you specify the statement number to which the data pointer should be reset. This would have saved me some time when I converted WUMPUS 2 to run on the SWTP system in 1977.

Next, and definitely more important, is the addition of the ELSE clause to the IF statement. In a sentence, this allows you to write a statement with the form

```
IF condition THEN do this ELSE do something else
```

INPUT LINE lets you read an entire line of input, including spaces, punctuation and quotes, into a single string variable. This is very useful when you are trying to make programs easy for the naive user. PRINT USING is a very important feature for business programming. This statement lets you format your output as you wish, overriding the automatic zoning of BASIC.

Although it's hard to think of PEEK

Phil Hughes (PO Box 2847, Olympia, WA 98507) owns Specialized Systems Consultants, a computer hardware/software consulting company.

Hardware/Software	CPU	1	2	3	4	5	6	7
1. OSI 8K BASIC @ 2MHz	6502	.9	4.6	8.2	9.3	10.0	14.8	21.6
10. Altair Disk Extended BASIC	8080	1.9	7.5	20.6	20.9	22.1	36.9	58.5
28. Southwest Tech 8K BASIC 1.0	6800	14.9	24.7	96.1	105.3	109.8	174.1	204.5
*** TSC Extended BASIC	6800	1.2	4.4	19	21.5	22	29	38.5
*** TSC Extended BASIC w/integer control variables	6800	.4	2.9	7.5	7.5	8	12	20.5

Table 1. Comparison times for standard and extended BASICs.

and POKE as extensions anymore, they are included. With the capability of the HEX function (see functions) they are somewhat more usable.

Two new statements that seem to fit into this same group are DIGITS and SWAP. The DIGITS statement specifies the maximum number of digits that are to be printed in an answer. This is independent of PRINT USING. DIGITS is useful for those of us with a background in mathematics who know how absurd it is to tell someone that the average of 13, 55, 97, 87, 66, 90, 94, 64 and 45 is about 67.888888888888891.

SWAP is useful for speeding up sorts. It switches the values of two variables in one step. It is particularly useful with string variables, where it changes the contents of two four-byte string descriptors rather than moving the actual data strings.

The next category of extensions is functions. The standard mathematical functions exist with 16-digit accuracy for LOG, EXP and SQR, and 13-1/2-digit accuracy for ATN, COS, SIN and TAN. There is also a full set of string-to-integer, integer-to-string and substring handling functions.

The substring function least likely to exist in other BASICs is INSTR, the equivalent of the PL/1 function, IN-DEX. This function will search a specified string, starting at a given position, and return the location of a specified substring. This function, along with INPUT LINE, makes an excellent tool for fancy input handling routines.

Another important function is HEX, which converts a string of up to four characters into an integer with an equivalent value. For example, you can write HEX ("8000") instead of 32768.

System Interface Extensions

The system interface extensions exist at the command level of BASIC, and let you communicate with the operating system. Note that some of

these capabilities may also be used within statements. The standard ones are RUN, LIST, CONT, LOAD, SAVE and NEW. TSC Extended BASIC offers a whole lot more.

The first one is COMPILE. This lets you save a BASIC program on disk in a compiled form. In this form the program uses less disk space, and therefore will load faster than its source. At execution time a source or compiled program will run at essentially the same speed. Also, a compiled program cannot be listed or edited. This gives you a method of releasing executable programs to others without making the source available.

TRON and TROFF allow you to turn on and off the line number trace. This is not very useful, since you cannot embed TRON and TROFF statements in your program and therefore must trace everything. SCALE allows you to force the roundoff of floating point numbers. In early BASICs, it was quite common to get .999999 as the result of dividing 10 by 10. This BASIC takes care of its own roundoff problems, but SCALE is there if you have a special case. One special case is, of course, rounding off dollars and cents to even pennies.

RENUMBER is actually a program that is loaded into the utility command space of Flex. It comes with BASIC, works very fast and rennumbers lines in the currently loaded BASIC program. It's about time BASIC came with this important feature.

KILL and RENAME allow you to delete and rename disk files. Both of these commands can also appear in statements. This lets you handle file maintenance within the BASIC program. CHAIN, another system interface command that can appear in a program statement, allows you to load and start execution of a new program. CHAIN also lets you specify the line number where execution is to begin.

In addition to these specific BASIC commands, any Flex command that

INTERCOMtm

FOR BUSINESS CP/M* USERS -

\$75.00

- versatile communications utility
- system commands-within program
- batch mode for unattended quantity file transfer
- four auto "sign-on" routines
- three standard communications protocols
- block protocol allows verified data transfer of all file types
- *CP/M is a trademark of Digital Research

END OF FILE, INC.

3140 E. Shadowlawn Ave. ✓339
Atlanta, GA 30305
404-233-9825

Flat Rate

DISK DRIVE OVERHAUL

One Week Turnaround Typical

Complete Service on Floppy Disk Drives.

FLAT RATES

8" Double Sided Drive	\$170.00*
8" Single Sided Drive	\$150.00*
5 1/4" M.P.I. Drive	\$100.00*

*Broken, Bent, or Damaged Parts Extra.
You'll Be Notified of

- The date we received your drive.
- Any delays and approximate time of completion.
- Date Drive was shipped from our plant.
- Repairs performed on your Drive.
- Parts used (" and description).
- Any helpful hints for more reliable performance.


90 Day Warranty.
Ship Your Drive Today.

Write or call for further details.

PHONE (417) 485-2501

FESSENDEN COMPUTER SERVICE

116 N. 3RD STREET ✓131 OZARK, MO 65721

MAXELL® OR  DYSAN CORPORATION

Some computerists pay less - but may not receive Shuggart® or IBM® approved disks.

8" SINGLE SIDE DOUBLE DENSITY.....Box of 10 for \$80

8" DOUBLE SIDE DOUBLE DENSITY.....Box of 10 for \$70

5 1/4" MINI.....Box of 10 for \$50

DYSAN® DISKS

5 1/4" MINI.....Box of 5 for \$25
(Specify - 8" Soft or Hard Sector/5" Soft or Hard Sector)



C.O.D. - \$1.00 Additional

Custom Electronics Inc.


238 EXCHANGE STREET
CHICOPEE, MA. 01013

413-592-4761 ✓141


established 1960 - closed Mondays

ATARI TI/99-4 PET


**We have THE
LOWEST PRICES
ON TRS-80™**



Model II 64K \$ 3298



Model III 16K \$839



Line Printer VII. \$329

OKIDATA	Microline 80	\$394
	Microline 82	\$499
EPSON MX-70		\$369
EPSON MX-80		\$479

\$ SAVE

**MOST ORDERS
SHIPPED WITHIN
ONE BUSINESS DAY**

VERBATIM DATALIFETM DISKETTES	
5 1/4-inch (box of 10)	\$25.95
8-inch Double-Density.	\$43.95

* Payment: Money Order, Cashier's Check, Certified Check. Personal Checks require 3 weeks to clear. VISA, MASTERCHARGE — Add 3%.

WRITE OR CALL FOR OUR COMPLETE PRICE LIST.

CALL (602) 458-2477

— All prices are mail order only —

RAND'S

2185 E. FRY BLVD.

SIERRA VISTA, AZ 85635
TRS-80 is a trademark of Tandy Corporation.

loads into the utility command space can be executed by preceding its name with a plus sign (+). Through this method CAT (catalog list), TTY-SET (configure terminal characteristics) and many other commands can be accessed. The BASIC statement EXEC permits access from within a program. Don't try +NEWDISK; although it loads into the UCS, it appears to use low memory for an I/O buffer, and you never hear from BASIC (or anything else until you push RESET) once you start it.

Advanced Disk Capabilities

TSC devotes 14 pages of the user's manual to advanced disk capabilities, but even with this much information you may spend a lot of time rereading and testing to get the hang of it. I can only let you know the capabilities are there—plan to spend some time getting to know how to use them.

All of these capabilities have to do with random access disk files. The first one, virtual arrays, consists of an array (dimensioned variable) stored in a disk file instead of RAM. It can be used just like any other array, with a few exceptions. A reference to an element of the array causes an automatic read from, or write to, disk. The reference is considerably slower than if the element had been in RAM, but much larger arrays can be handled.

Now the exceptions. All elements of a string virtual array must be the same length. The maximum length of a string element in a virtual array is 252 bytes (vs 32767 for ordinary string arrays). The third exception is that values in a virtual array cannot be displayed using PRINT if a program has terminated in error. Although, initially, this third exception seems like a severe handicap in debugging, it can be sidestepped by using the ON ERROR and STOP statements.

The second type of random I/O is Record I/O, which allows you to read or write any sector within a disk file. These sectors correspond to physical disk sectors, which consist of 252 data bytes and four Flex header bytes. A read is performed by the GET statement, and a write is performed by the PUT statement. This is the basis for Record I/O; everything else is just a set of tools to make it easier to use.

The first tool is the FIELD statement. FIELD allows you to assign string variable names to parts of the 252-byte buffer which is used by GET and PUT. Two other tools, LSET

and RSET, allow you to store data in the portions of the buffer described by the FIELD statements. The four tools completing the available set are conversion routines which convert integers and floating point numbers to and from strings. These are necessary because Record I/O files contain only characters.

Using these tools, you can describe records consisting of specified fields of data, and read and write these records. If these records are 252 bytes in length, then a record is a sector and everything goes smoothly.

To handle records less than 252 bytes, you must either waste disk space or pack multiple records into a single sector. Packing can be done with the FIELD statement, but it takes a lot of the pleasure out of having this type of I/O. In a sentence, it isn't elegant but it does the job.

Now that you know what Record I/O is, you can see that it makes doing inventory systems and the like feasible. Using Record I/O for data files and virtual arrays for indexes, you will find that inverted key (look up by more than one thing) file access systems become practical. For example, you can look up an entry in an address list by either last name or ZIP code.

Some Problems

Bug-wise, the version that I have (version 8) is a very stable product. This is the third version that I have had, but TSC was very cooperative in sending updated versions in response to my documented problems. The only remaining problem that I find irritating is that certain errors in a program cause the LOAD command to terminate without loading the entire file. Actually, the irritating part is that no error message is issued. This only occurs on files which have been created by the editor or another BASIC. TSC Extended BASIC will not allow you to enter lines that cause this error.

I have two other complaints. First, extended BASIC is very big—a little over 18K. For the features available, the size is not excessive, but you may have to justify the cost of that new 16K memory board along with the cost of BASIC. And the documentation on extended BASIC, like most other TSC documentation, is hard to use. I don't know why this is, but my customers have the same problem. All of the information is in the manual—it's just hard to find. ■

THE ORIGINAL MAGAZINE FOR OWNERS OF THE TRS-80™* MICROCOMPUTER

* TRS-80™ IS A TRADEMARK OF TANDY CORP.

SOFTWARE
FOR TRS-80™
OWNERS

H & E COMPUTRONICS INC.

MONTHLY
NEWSMAGAZINE
FOR TRS-80™
OWNERS

MONTHLY NEWSMAGAZINE Practical Support For Model I, II & III

- PRACTICAL APPLICATIONS
- BUSINESS
- GAMBLING • GAMES
- EDUCATION
- PERSONAL FINANCE
- BEGINNER'S CORNER
- NEW PRODUCTS
- SOFTWARE EXCHANGE
- MARKET PLACE
- QUESTIONS AND ANSWERS
- PROGRAM PRINTOUTS
- AND MORE

NOW IN OUR 4th YEAR

PROGRAMS AND ARTICLES PUBLISHED IN RECENT ISSUES
INCLUDE THE FOLLOWING:

- FINCALC - A COMPLETE FINANCIAL APPLICATIONS PACKAGE
- INFORMATION SYSTEM REVIEW
- STATISTICAL COMBINATIONS
- PASCAL'S TRIANGLE
- ASSEMBLY LANGUAGE FOR BEGINNERS
- DISK FILES
- MOD-III REVIEW
- KEYBOARD THUNDER AND LIGHTING EXPLAINED
- DOS COMMANDS IN LEVEL II
- PROBABILITY CURVE GENERATOR
- CALCULATOR SIMULATIONS
- THE MEGABYTE GAP
- STOCKS AND BONDS
- BUDGET ANALYSIS (FOR BUSINESS AND HOME)
- NEWDOS/80 REVIEW
- DUTCHING - THE HORSE SYSTEM THAT CAN'T LOSE
- A SIMULATED GOLF GAME
- CONTINUOUS FORM SOURCES
- TAX/SAVER REVIEW
- AND MORE

FREE* WITH
YOUR
SUBSCRIPTION
OR
RENEWAL

FINCALC

A Complete Financial Analysis Package Used To Calculate Markup, Margin, Annuities, Compound Interest, Nominal And Effective Rates, Sinking Funds, Mortgage Calculations, Future Value, Savings and Insurance, Percentage Difference Between Two Numbers, Amortization Schedule and More

SEND FOR OUR NEW 64 PAGE SOFTWARE CATALOG (INCLUDING LISTINGS OF HUNDREDS OF TRS-80™ PROGRAMS AVAILABLE ON CASSETTE AND DISKETTE). \$2.00 OR FREE WITH EACH SUBSCRIPTIONS OR SAMPLE ISSUE

* All programs are supplied on cassette (add \$3 for Diskette Version - add \$5 for modified Mod-II Version).

H & E COMPUTRONICS ✓6
MATHEMATICAL APPLICATIONS SERVICE™

50 N. PASCACK ROAD
SPRING VALLEY, NEW YORK 10977

ONE YEAR SUBSCRIPTION \$24

TWO YEAR SUBSCRIPTION \$48

SAMPLE OF LATEST ISSUE \$ 4

START MY SUBSCRIPTION WITH ISSUE.....

(#1 - July 1978 • #12 - June 1979 • #24 - July 1980 • #30 - January 1981)

NEW SUBSCRIPTION..... RENEWAL.....

NEW TOLL-FREE
ORDER LINE
(OUTSIDE OF N.Y. STATE)
(800) 431-2818

NEW!!!
MOD-II NEWSLETTER
\$18/year (or 12 issues)



24 HOUR
ORDER
LINE



(914) 425-1535

CREDIT CARD NUMBER _____ EXP. DATE _____

SIGNATURE _____ NAME _____

ADDRESS _____ CITY _____ STATE _____ ZIP _____

*** ADD \$12/YEAR (CANADA, MEXICO) - ADD \$24/YEAR AIR MAIL - OUTSIDE OF U.S.A., CANADA & MEXICO ***

How to Maximize Profits

By James R. Burns

A dentist is faced with deciding how best to split his practice between the two services he offers—general dentistry and pedodontics (children's dental care). Given his resources, how much of each service should he provide to maximize his profits?

He can find the answer with the help of a process known as mathematical programming (MP). This is not programming in the computer sense of the word, but instead refers to a specific set of mathematical procedures used to solve a problem.

Every mathematical programming problem consists of a goal and a set of constraints. For the business manager, the goal is to find a product mix that will realize the greatest net return. The constraint is that the resources he can allocate to his products or services are limited. These resources might include money, man-hours, machine capacities or warehouse space.

Since the computer can do the computational work, a manager need not be a mathematician to use MP successfully. What he must be able to do, however, is 1) recognize when MP is an appropriate method to use, 2) formulate the problem so that it can be solved (by the computer) and 3) interpret the results and use them correctly.

A Resource Allocation Problem

The dentist mentioned above employs three assistants and uses two operatories (work stations). Each pedodontic service requires .75 hours

of operator time, 1.5 hours of an assistant's time and .25 hours of the dentist's time. A general dentistry service requires .75 hours of an operator, 1 hour of an assistant's time and .5 hours of the dentist's time. Net profit

for each service is \$10 for each pedodontic service and \$7.50 for each general dental service. Since the dentist's office is open eight hours a day, there are eight hours of dentist's time each day, 16 hours of operator time, and

Listing 1. Mathematical programming in TRS-80 Level II BASIC.

```
10 CLS:CLS:PRINTSTRING$(63,191):PRINT@83,"MAXIMIZE YOUR PROFITS":PRINTSTRING$(63,149)
20 PRINTTAB(23)"JAMES R. BURNS"
30 PRINTTAB(15)"SOFTWARE ENGINEERING SYSTEMS, INC."
40 PRINTTAB(22)"3204 80TH STREET"
50 PRINTTAB(21)"LUBBOCK, TEXAS 79423"
60 FORI%=1TO20:PRINT@448,STRING$(63,191):PRINT@448,STRING$(63,149):NEXTI%
70 '
80 ' ENTER NUMBER OF VARIABLES AND NUMBER OF CONSTRAINTS
90 '
100 INPUT"WHAT IS THE NUMBER OF PRIMAL VARIABLES":N%
110 INPUT"WHAT IS THE NUMBER OF CONSTRAINTS":M%
120 EX=1:L%=M%+EX:K%=N%+L%
130 DINTA(L%,K%),RA(M%)
140 '
150 ' DEFINE CONSTRAINT COEFFICIENTS
160 '
170 FORI%=EX%TO M%
180 FORJ%=EX%TO N%
190 PRINT"COEFFICIENT OF VARIABLE":J%:"IN CONSTRAINT":I%:
200 INPUT"IS":TA(I%,J%):NEXTJ%
210 PRINT"AMOUNT OF RESOURCES IN CONSTRAINT":I%:
220 INPUT"IS":TA(I%,K%):TA(I%,N%+I%)=EX:NEXTI%
230 '
240 ' DEFINE OBJECTIVE FUNCTION COEFFICIENTS
250 '
260 FORJ%=EX%TO N%
270 PRINT"WHAT IS THE COEFFICIENT ASSOCIATED WITH VARIABLE":J%:"IN THE"
280 INPUT"OBJECTIVE FUNCTION":TA(L%,J%)
290 TA(L%,J%)=-TA(L%,J%):NEXTJ%
300 INPUT"DO YOU WISH THE TABLEAU PRINTED AFTER EVERY ITERATION--Y/N":T%
310 '
320 ' BEGIN SIMPLEX ITERATIONS HERE
330 '
340 ' PICK THAT COLUMN WITH THE MOST NEGATIVE "INDICATOR" AS THE NEXT
350 ' VARIABLE TO ENTER THE BASIS. START WITH ONLY SLACK
360 ' VARIABLES IN THE INITIAL BASIS.
370 '
380 GOSUBS90
390 MI=1E30
400 FORQ%=EX%TO N%+M%
410 IFMI<TA(L%,Q%)THEN440
420 MI=TA(L%,Q%)
430 J%=Q%
440 NEXTQ%
450 IFMI>0THEN820
460 '
470 ' A COLUMN (J%) WITH THE MOST NEGATIVE INDICATOR HAS BEEN FOUND
480 '
490 FORI%=EX%TO M%
500 '
510 ' FIND THE ROW WHOSE RATIO IS SMALLEST POSITIVE. ASSOCIATED
520 ' VARIABLE IS EXITING BASIS VARIABLE.
530 '
```

James R. Burns (3204 80th St., Lubbock, TX 79423) is an associate professor at Texas Tech University and president of Software Engineering Systems, Inc.

24 hours of assistants' time each day.

The objective is to divide each eight-hour day between general practice and pedodontics in such a way as to maximize profit. Let x_1 represent the number of pedodontic patients seen per day and x_2 the general dentistry patients seen per day. Then the objective function for this problem is expressed by $10x_1 + 7.5x_2$.

The constraints are the total hours available for each of the three resource categories—dentist's time, operator time and assistants' time. Eight hours are available to the dentist. Each pedodontic service requires (as stated) .25 hours of the dentist's time, and each general practice, .5 hours. The total time devoted to these two categories is $.25x_1 + .5x_2$. Since this must be less than or equal to eight, the constraint is written

$$.25x_1 + .5x_2 \leq 8 \text{ (dentist's time)}$$

The remaining two constraints are written

Formulating an MP problem begins with an identification of the resources and the products or services.

$$1.5x_1 + x_2 \leq 24 \text{ (assistants' time)}$$

$$.75x_1 + .75x_2 \leq 16 \text{ (operator time)}$$

In total the problem as formulated is

$$\text{maximize } 10x_1 + 7.5x_2$$

subject to

$$.25x_1 + .5x_2 \leq 8 \text{ dentist}$$

$$1.5x_1 + x_2 \leq 24 \text{ assistants}$$

$$.75x_1 + .75x_2 \leq 16 \text{ operatories.}$$

How to Formulate an MP Problem

As the example above shows, the task of formulating an MP problem begins with an identification of the resources and the products or services. For each product or service, a variable x_i is defined. Then the objective is written in the language of mathematics as a statement of the

profit potential for a given time period. Each x_i variable is multiplied by the net profit accruing from the sale of just one unit of the product or service.

In the problem above, \$10 of profit is realized from each pedodontic (patient) service. If five such services were provided in any given day, then \$50 of profit would accrue from pedodontic services alone. Similar statements could be made about general dentistry services. Hence, total profit is the sum of the individual profits arising from the provision of these two services.

Once the objective is formulated, the constraints are written. Each constraint expresses the resource requirements for a particular product mix. The total resource requirement must be less than or equal to the total amount of resource available for a particular resource. Mathematically, this is written as an inequality. In the problem posed above, there are three resources, and therefore three inequalities. In addition to these inequalities, the x_i variables must be non-negative. (A negative value for x_1 , the number of hours devoted to pedodontic services, has no meaning; similarly for x_2 .)

How to Use the Computer Program

The computer program shown in Listing 1 can be used to solve this problem. As listed, the program is ready to run on a TRS-80 Level II machine. Some modification may be required for other machines. The program uses the simplex method of solution and is able to detect when the problem is unbounded. Appropriate responses to the queries posed by the program for the problem described above are shown in Sample 1a.

User responses appear to the right of each query (which ends with a question mark). The queries request the number of variables and constraints, followed by all coefficients in the constraints and in the objective function. Array dimensions and slack variables are taken care of automatically by the program and do not require user attention. To properly enter responses to the queries you must define (for yourself) the variables, ob-

```

540 IFTA(I%,J%)<1E-10THENRA(I%)=1E35:GOTO560
550 RA(I%)=TA(I%,K%)/TA(I%,J%)
560 NEXTI%
570 MI=1E35:IN%=100
580 FORI%=E%TOM%
590 IFR(A(I%))=MIORRA(I%)<=0THEN510
600 MI=RA(I%):IN%=I%
610 NEXTI%
620 IFIN%=100THENPRINT"SOLUTION UNBOUNDED":END
630 DI=TA(IN%,J%)
640 FORI%=E%TOK%
650 TA(IN%,I%)=TA(IN%,I%)/DI
660 NEXTI%
670 FORA%=E%TOL%
680 IFA%=IN%THEN760
690 '
700 ' BEGIN PIVOT HERE
710 '
720 MU=TA(A%,J%)
730 FORI%=E%TOK%
740 TA(A%,I%)=TA(A%,I%)-MU*TA(IN%,I%)
750 NEXTI%
760 NEXTA%:GOSUB990
770 GOTO390
780 '
790 ' SOLUTION HAS BEEN FOUND AS THERE ARE NO COLUMNS WITH NEGATIVE
800 ' INDICATORS. RESULTS ARE PRINTED IN THE STATEMENTS THAT FOLLOW.
810 '
820 CLS:PRINT"MAXIMUM OBJECTIVE FUNCTION VALUE IS":TA(L%,K%)
830 FORJ%=E%TON%
840 IFTA(L%,J%)>0.THEN880
850 FORI%=E%TOM%
860 IF.999<TA(I%,J%)ANDTA(I%,J%)<1.001THENPRINT"MAXIMUM VALUE FOR VARIABLE":J%:"
IS":TA(I%,K%):GOTO880
870 NEXTI%
880 NEXTJ%
890 INPUT"HIT ENTER TO SEE SHADOW PRICES--OK":XX
900 CLS:PRINT"SENSITIVITY COEFFICIENTS (DUAL VARIABLES) ARE"
910 FORI%=E%TOM%
920 PRINTTAB(20)TA(L%,N%+I%)
930 NEXTI%
940 INPUT"HIT ENTER TO END":XX
950 END
960 '
970 ' ROUTINE TO PRINT SIMPLEX TABLEAU
980 '
990 IFT%<>"Y"THENRETURN
1000 FORU%=E%TOL%
1010 PRINT"ROW":U%:STRING$(1,170);
1020 FORU%=E%TOK%
1030 PRINTTA(U%,U%);
1040 NEXTU%
1050 PRINT
1060 NEXTU%
1070 INPUT"HIT ENTER TO RETURN--OK":XX
1080 RETURN

```



```

WHAT IS THE NUMBER OF PRIMAL VARIABLES? 2
WHAT IS THE NUMBER OF CONSTRAINTS? 3
COEFFICIENT OF VARIABLE 1 IN CONSTRAINT 1? .25
COEFFICIENT OF VARIABLE 2 IN CONSTRAINT 1? .5
AMOUNT OF RESOURCES IN CONSTRAINT 1? 8
COEFFICIENT OF VARIABLE 1 IN CONSTRAINT 2? 1.5
COEFFICIENT OF VARIABLE 2 IN CONSTRAINT 2? 1
AMOUNT OF RESOURCES IN CONSTRAINT 2? 24
COEFFICIENT OF VARIABLE 1 IN CONSTRAINT 3? .75
COEFFICIENT OF VARIABLE 2 IN CONSTRAINT 3? .75
AMOUNT OF RESOURCES IN CONSTRAINT 3? 16
WHAT IS THE COEFFICIENT ASSOCIATED WITH VARIABLE 1 IN THE OBJECTIVE
FUNCTION? 10
WHAT IS THE COEFFICIENT ASSOCIATED WITH VARIABLE 2 IN THE OBJECTIVE
FUNCTION? 7.5
DO YOU WISH THE TABLEAU PRINTED AFTER EVERY ITERATION—Y/N? N

```

Sample 1a.

```

OPTIMUM ANSWER IS 170
MAXIMUM VALUE FOR VARIABLE 1 IS 8
MAXIMUM VALUE FOR VARIABLE 2 IS 12
HIT ENTER TO SEE SHADOW PRICES—OK?
SENSITIVITY COEFFICIENTS (DUAL VARIABLES) ARE
    2.5
    6.25
    0
HIT ENTER TO END?

```

Sample 1b.

jective function, constraints and coefficients that are needed in the MP model. From the responses entered in Sample 1a it should be clear that the following conventions were used:

- variable 1— x_1 , pedodontic patients seen per day
- variable 2— x_2 , general dentistry patients seen per day
- constraint 1—dentist's time per day
- constraint 2—assistants' time per day
- constraint 3—operatory time per day.

Once computations required by the simplex algorithm are complete, the reports in Sample 1b are printed.

Clearly the optimum (maximum) objective function value is \$170 daily. The dentist should see eight pedodontic patients per day and 12 general dentistry patients per day. In addition to the above reports the program will also print the simplex tableau after each iteration if you respond with "Y" to the last query in the sequence. It is easy to verify that when (8, 12) replaces (x_1 , x_2) in the objective function, a value of 170 is realized—i.e., $10 \times 8 + 7.5 \times 12 = 170$. Also, it is easy to verify that all of the dentist's time

per day and all of the assistants' time per day are used up by the combination (8, 12).

Sensitivity Studies

The sensitivity coefficients indicated in Sample 1b tell how sensitive the optimum answer (objective function value) is to changes in the resource value associated with each constraint. Thus, the resource associated with constraint 1 (dentist's time) has a sensitivity value of 2.5, the resource associated with constraint 2 (assistants' time) has a sensitivity value of 6.25, and so on. Since there are three constraints in the problem, three sensitivity coefficients are printed.

Obviously, the answer is most sensitive to changes in the assistants' time resource. In fact, one unit of increase in this resource will produce

6.25 additional units of profit in the objective function. Our hypothetical dentist would be well-advised to add extra hours of dental assistants' time per day; it is the resource that should be increased first.

A Portfolio Selection Problem

Resource allocation problems are not the only MP problems solvable by the program in Listing 1. The program can also be used to solve portfolio-selection problems, as typified by the following.

A stockbroker has been asked by a client to invest a sizeable sum of money in a portfolio of common stocks. The overall objective is to maximize the growth of capital. However, the portfolio is not to exceed a prescribed degree of risk. Also, the portfolio must provide at least enough income to pay for taxes and other expenses.

The stockbroker has available to him information on a large number of companies, broken down into various industry groups. Each company is rated on a scale of 0 to 9 for its growth and risk potential, where 0 indicates no growth or no risk and 9 indicates highest growth or highest risk. No more than 35 percent of the portfolio is to be invested in any one industry group. The risk factor cannot exceed 10. The information about the companies is given in Table 1.

Let x_i represent the fraction of the portfolio to be invested in company i . Then the MP problem can be formulated in accordance with the remarks made above as follows:


maximize $7x_1 + 2x_2 + 8x_3 + 9x_4 + 3x_5 + 6x_6 + 7x_7 + 8x_8 + 6x_9 + 4x_{10} + 3x_{11} + 4x_{12} + 8x_{13} + 8x_{14} + 8x_{15} + 9x_{16}$
subject to
 $3x_1 + 6x_2 + 5x_3 + 8x_4 + x_5 + 5x_6 + 7x_7 + 2x_8 + x_9 + 4x_{10} + 5x_{11} + 6x_{12} + 9x_{13} + 7x_{14} + 8x_{15} + 7x_{16} \leq 10$
 $x_1 + x_2 + x_3 + x_4 + x_5 + x_6 + x_7 + x_8 + x_9 + x_{10} + x_{11} + x_{12} + x_{13} + x_{14} + x_{15} + x_{16} \leq 1$
 $x_1 + x_2 + x_3 + x_4 \leq .35$
 $x_5 + x_6 + x_7 + x_8 \leq .35$
 $x_9 + x_{10} + x_{11} + x_{12} \leq .35$
 $x_{13} + x_{14} + x_{15} + x_{16} \leq .35$

In all, this problem has 16 variables and six constraints. The first constraint relates to risk. The second

Industry	A				B				C				D			
Company	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Growth	7	2	8	9	3	6	7	8	6	4	3	4	8	8	8	9
Risk	3	6	5	8	1	3	7	2	1	4	5	6	9	7	8	7

Table 1.

**Special
of the Month!**



commodore

4032 COMPUTER	\$1061
(8032 Add \$160)	
4040 DISK	\$1061
4022 PRINTER	\$ 651
CBM-IEEE CABLE	\$ 33
IEEE-IEEE CABLE	\$ 41

COMPLETE SYSTEM = \$2841

No Surcharge for Credit Cards Orders • We Accept C.O.D.'s

All Equipment Factory Fresh With MFT. Warranty • Stock Shipments Same Day or Next

**NEC
OKIDATA
APPLE**

**TELEVIDEO
COMMODORE**

**RADIO SHAC
AMDEK**

ATARI



EPSON MX-80

DIABLO 630	\$2099
INTERTEC SUPERBRAIN 64K RAM	\$2799
QD SUPERBRAIN	\$3195
NEC 5510 SPINWRITER	\$2495
NEC 5530 SPINWRITER	\$2495
OKIDATA MICROLINE-80	\$ 399
OKIDATA MICROLINE-82	\$ 529
OKIDATA MICROLINE-83	\$ 799
APPLE II PLUS 48K	\$1189
APPLE DISK w/3.3 DOS Controller	\$ 545
APPLE DISK w/o Controller	\$ 435
BASE II PRINTER	\$ 599
HAZELTINE 1420	\$ 799
NORTHSTAR HORIZON II 32K QD	\$2975
ANADEX DP-9500	\$1295
TELEVIDEO 912C	\$ 669
TELEVIDEO 920C	\$ 729
TELEVIDEO 950	\$ 959
CBM 8032 COMPUTER	\$1225
CBM 8050 DISK DRIVE	\$1449
CBM 4032 COMPUTER	\$1090
CBM 4040 DISK DRIVE	\$1090
CBM 4022	\$ 679
CBM VIC-20	\$ 289
CBM C2N	\$ 85
RADIO SHACK II 64K	\$3245
RADIO SHACK III 16K	\$ 839
LEEDEX/AMDEK 100	\$ 139
LEEDEX/AMDEK 100G	\$ 169
LEEDEX/AMDEK COLOR-1 13" Color Monitor	\$ 349
MICROTEK 16K RAMBOARD for Atari	\$99.95
MICROTEK 32K	\$ 165
ATARI 400 16K	\$ 349
ATARI 825 PRINTER	\$ 619
ATARI 850 INTERFACE	\$ 139
or both together	\$ 749
ATARI 810 DISK DRIVE	\$ 449
ATARI 800 32K	\$ 769
Call for price list of ATARI software	
NEC 12" MONITOR	\$ 229

PRICES ARE SUBJECT TO CHANGE WITHOUT NOTICE.

**WEST COAST
1-800-235-3581**

OMEGA SALES CO.
3533 Old Conejo Rd. #102
Newbury Park, CA 91320
1-805-499-3678

CA. TOLL FREE 1-800-322-1873

Ω
**OMEGA
SALES
CO.**

**EAST COAST
1-800-556-7586**

OMEGA SALES CO.
12 Meeting St.
Cumberland, RI 02864
1-401-722-1027

Ω OMEGA SALES COMPANY


```

WHAT IS THE NUMBER OF PRIMAL VARIABLES? 16
WHAT IS THE NUMBER OF CONSTRAINTS? 6
COEFFICIENT OF VARIABLE 1 IN CONSTRAINT 1 IS? 3
COEFFICIENT OF VARIABLE 2 IN CONSTRAINT 1 IS? 6
COEFFICIENT OF VARIABLE 3 IN CONSTRAINT 1 IS? 5
COEFFICIENT OF VARIABLE 4 IN CONSTRAINT 1 IS? 8
COEFFICIENT OF VARIABLE 5 IN CONSTRAINT 1 IS? 1
COEFFICIENT OF VARIABLE 6 IN CONSTRAINT 1 IS? 5
COEFFICIENT OF VARIABLE 7 IN CONSTRAINT 1 IS? 7
COEFFICIENT OF VARIABLE 8 IN CONSTRAINT 1 IS? 2
COEFFICIENT OF VARIABLE 9 IN CONSTRAINT 1 IS? 1
COEFFICIENT OF VARIABLE 10 IN CONSTRAINT 1 IS? 4
COEFFICIENT OF VARIABLE 11 IN CONSTRAINT 1 IS? 5
COEFFICIENT OF VARIABLE 12 IN CONSTRAINT 1 IS? 6
COEFFICIENT OF VARIABLE 13 IN CONSTRAINT 1 IS? 9
COEFFICIENT OF VARIABLE 14 IN CONSTRAINT 1 IS? 7
COEFFICIENT OF VARIABLE 15 IN CONSTRAINT 1 IS? 8
COEFFICIENT OF VARIABLE 16 IN CONSTRAINT 1 IS? 7
AMOUNT OF RESOURCES IN CONSTRAINT 1 IS? 10
COEFFICIENT OF VARIABLE 1 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 2 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 3 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 4 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 5 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 6 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 7 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 8 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 9 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 10 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 11 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 12 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 13 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 14 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 15 IN CONSTRAINT 2 IS? 1
COEFFICIENT OF VARIABLE 16 IN CONSTRAINT 2 IS? 1
AMOUNT OF RESOURCES IN CONSTRAINT 2 IS? 1

```

Sample 2a.

constraint merely states the fact that all fractions must sum to 1. The third, fourth, fifth and sixth constraints stipulate that no one industry can represent more than 35 percent of the portfolio.

To enter this problem the user must respond to roughly 100 queries, a portion of which is provided in Sample 2a.

The outputs produced by the program in Listing 1 are shown in Sample 2b.

These outputs suggest that 35 percent of the portfolio should be invested in company 4, 30 percent in company 8 and 35 percent in company 16. Maximum return from this portfolio is 8.7. The sensitivity coefficients suggest that the second constraint is the one to which the maximum objective function value is most sensitive. However, the right-hand-side value of this constraint cannot be increased. The third and sixth constraints also influence the objective function value, as indicated by the

third and sixth sensitivity coefficient values above.

Epilogue

The program shown in Listing 1 is able to solve maximization problems with \leq inequalities. Two such problems were solved in this article. However, MP problems can also be mini-

mization problems and can involve \geq inequalities and equalities. One of the three programs in the Mathematical Programming System offered by Software Engineering Systems is able to solve this more general class of problems. The program uses the simplex algorithm in condensed tableau form. All slack, surplus and artificial variables required to solve a problem are inserted into the formulation automatically. As in the algorithm in Listing 1, all arrays are dynamically dimensioned to accommodate the number of variables and the number of constraints and do not require user attention.

The package sells for \$29 on cassette (\$33 on diskette) and includes a transportation algorithm (modified distribution method), and a network flow optimization algorithm (out-of-kilter method) in addition to the simplex algorithm.

Conclusion

Personal computers are devices with vast problem-solving capabilities. However, the literature on personal computing suggests that these capabilities have been overlooked, while other capabilities such as accounting, word processing, education and games are touted.

One such problem—the problem of maximizing profits—has been treated here. Once formulated, the problem is easily solved by the computer program in Listing 1. The solution to the problem informs the problem solver which product mix is best—that is, how much of each product (or service) to produce (or provide). In addition, the solution tells the user to which resource the profit is most sensitive. This is the resource which, if increased, will cause the greatest increase in profit. ■

```

MAXIMUM OBJECTIVE FUNCTION VALUE IS 8.7
MAXIMUM VALUE FOR VARIABLE 4 IS .35
MAXIMUM VALUE FOR VARIABLE 8 IS .3
MAXIMUM VALUE FOR VARIABLE 16 IS .35
HIT ENTER TO SEE SHADOW PRICES—OK?
SENSITIVITY COEFFICIENTS (DUAL VARIABLES) ARE
0
8
1
0
0
1
HIT ENTER TO END?

```

Sample 2b.

Listing continued from page 80.

```

0000      380 ;VIDEO IS THE BEGINNING ADDRESS ASSIGNED TO THE
0000      390 ;MEMORY MAPPED VIDEO RAM. ITS VALUE IS STORED
0000      400 ;IN THE BUFFER AREA FOR EASY MODIFICATION.
C000      410 ORIG 0C000H
C000      420 :VIDEO ;
C000      430 ;
C000      440 ;LOC IS THE BEGINNING ADDRESS OF THIS VIDEO
C000      450 ;DRIVER ROUTINE SOFTWARE
1030      460 ORIG 1030H
1030      470 :LOC ;
1030      480 ;
1030      490 ;RWMAX REPRESENTS THE MAXIMUM ROW COUNT FOR
1030      500 ;THE VIDEO SCREEN. IT IS THE TOTAL CHARACTERS
1030      510 ;COUNT UP TO THE FIRST SPOT ON THE LAST
1030      520 ;ROW. FOR 24 LINES, THE COUNT IS 0730H
0030      530 ORIG 30H
0030      540 :RWMAXL ;
0007      550 ORIG 7
0007      560 :RWMAXH ;
0007      570 ;
0007      580 ;15 BYTES OF RAM ARE NEEDED FOR HOUSEKEEPING.
0007      590 ;THESE BYTES MUST BE IN AN AREA UNUSED BY
0007      600 ;OTHER PROGRAMS. THE BASE ADDRESS IS STORED
0007      610 ;IN REGISTER IX EACH TIME THE ROUTINE IS USED.
0007      620 ;MERELY TWO ADDR CHANGES IN THIS PROGRAM WILL
0007      630 ;RELOCATE THIS BUFFER AREA. THEY ARE LOCATED
0007      635 ;IN STATEMENTS 1110 AND 5310.
BFF0      640 ORIG 0BFF0
BFF0      650 :BUFFER ;
BFF0      660 ;
BFF0      670 ;ASSIGN VALUES TO BUFFER POINTERS
0000      672 ORIG 0
0000      674 :SPARE ;
0001      680 ORIG 1
0001      690 :VIDLO ;
0002      700 ORIG 2
0002      710 :VIDHI ;
0003      720 ORIG 3
0003      730 :BUFLO ;
0004      740 ORIG 4
0004      750 :BUFHI ;
0005      760 ORIG 5
0005      770 :HOMLO ;
0006      780 ORIG 6
0006      790 :HOMHI ;
0007      800 ORIG 7
0007      810 :CHARTR
0008      820 ORIG 8
0008      830 :CURLO ;
0009      840 ORIG 9
0009      850 :CURHI ;
000A      860 ORIG 0AH
000A      870 :ROWLO ;
000B      880 ORIG 0BH
000B      890 :ROWHI ;
000C      900 ORIG 0CH
000C      910 :COLUMN ;
000D      920 ORIG 0DH
000D      930 :PLOTTR ;NON-ZERO WHEN PLOTTING
000D      960 ;
000D      970 ;
000D      999 ;*****
000D      1000 ;***** SECTION 1 *****
000D      1005 ;*****
000D      1010 ;
000D      1020 ; NORMAL ENTRY POINT
000D      1030 ; EXPECTS CHARACTER OR COMMAND IN B
000D      1040 ; RETURNS CHARACTER IN A
000D      1050 ; PRINTS ALL BYTES LARGER THAN 0EH
000D      1060 ;
1030      1070 ORIG LOC
1030 0000      1072 FCDB 0
1032 0000      1074 FCDB 0
1034 0000      1076 FCDB 0
1036 E5        1080 PUSH HL ;SAVE HL ON STACK
1037 D5        1090 PUSH DE ;DE TOO
1038 C5        1100 PUSH BC ;BC TOO
1039 DDE5      1105 PUSH IX ;ALSO IX
103B          1106 ; (MUST BE USER PERSONALIZED)
103B DD21F0BF 1110 LD IX,BUFFER ;INITIALIZE BUFFER AREA
103F          1120 ; TAKES 16 BYTES OF RAM.
103F DD7E0D    1122 LD A,(IX+PLOTTR)
1042 FE00      1124 CP 0
1044 C27B10    1126 JP .NZ,EXIT ;DO NOT PRINT IF GRAPHICS MODE
1047 78        1130 LD A,B ;CHARACTER TO A
1048 DD7007    1140 LD (IX+CHARTR),B ;STORE CHAR IN BUFFER
104B D606      1150 SUB 6 ;EXIT IF CNTL-A TO CNTL-F
104D 382C      1160 JR .C,EXIT
104F FE08      1170 CP 8 ;TEST IF CHAR IS A VIDEO CMD
1051 3805      1180 JR .C,CMDVCT ;IF SO, VECTOR TO CMD
1053 CD1611    1190 CALL CHAROT
1056 1823      1200 JR EXIT
1058          1210 ;
1058          1220 ; TRANSFER TO VIDEO COMMAND ROUTINE
1058          1230 ;

```

More

FACTORY PRIME STATIC RAM CHIPS

2114 Super Low Power
 200ns. 1Kx4 \$ 2.90
 6514 CMOS 300ns. 1Kx4 \$ 6.90
 6116 CMOS 200ns. 2Kx8 \$22.50
 Add \$5.00 Handling on Orders Under \$200.00

FACTORY PRIME From the same shipments used in
 GIMIX Professional quality boards

32KB STATIC RAM CARDS

for the SS50 and SS50C BUS
 (16KB - \$298.12), (24KB - 348.14)
 (32KB - \$398.15)

NEW! 64KB BATTERY BACK UP CMOS RAM CARDS

Two independently addressable 32KB
 blocks, each with extended addressing.

(56KB - \$994.56), (64KB - \$1088.64)

2MHZ 6809 56KB SS50 SYSTEMS \$2498.29

DISK SYSTEMS AVAILABLE

GIMIX inc. 301

1337 W. 37th Place • Chicago, IL 60609
 (312) 927-5510 • TWX 910-221-4055

The Company that delivers.

Quality Electronic products since 1975.

GIMIX® and GHOST® are Registered Trademarks of GIMIX INC.

IF
 YOU'VE GOT

OSI

We've
 got great
 products for you!

OS-65D V3.2 DISASSEMBLY MANUAL 60 page manual,
 complete with cross reference listings. Fully com-
 mented. \$24.95.

REF COMMAND UNDER BASIC Lists line numbers, var-
 iables, constants for 65D or 65U. \$29.95.

SPOOLER-DESPOOLER UTILITY Super fast. Frees up
 screen, feeds data to serial or parallel printers. \$59.95.

FIG FORTH UNDER OS-65U Runs under multi-user,
 hard disk systems with all the extras. \$79.95.

VIDEO ROUTINE Convenient control of variable screen
 parameters. May be connected to graphics resolution
 booster. \$24.95 or \$29.95.

GRAPHICS RESOLUTION BOOSTER Hardware to boost
 screen resolution by 8 times to 128 x 128. \$49.95. With
 video routine and software extensions \$79.95.

Write or call for free product catalog and
 get all the details.

SOFTWARE
 CONSULTANTS

7053 Rose Trail ✓213
 Memphis, Tn. 38134
 901/377-3503

**No.1
 UNBELIEVABLE
 OPPORTUNITY!**

If You've Written a
 Topnotch Program--

We'd Like to Publish It!

Programs needed for **BUSINESS/
 OFFICE Applications:**

**WORD PROCESSING
 PAYROLL/TAX CALCULATION
 GENERAL LEDGER/AR-AP
 ORDER ENTRY/INVENTORY**

Start collecting your royalty
 checks soon! Write for our free
 Programmer's Kit today.

INSTANT SOFTWARE, INC.

Submissions Dept.

Peterborough, NH 03458 ✓75

Designed for your . . .
TRS-80™
 the **PHOTOPOINT™** Light Pen*
 a whole NEW concept in
 computer application

- Just plugs into your TRS-80 with disk or without! (Does not void warranties.)
- Programs with 3 lines in Basic!
- Comes with two Programs
- Complete instructions!!
- Just point to play!
- Often eliminates confusing keyboard from games, education, or multiple choice.

All you need to get up and running the same day you receive your PhotoPoint is included.
 For only . . .

\$19.95 Order NOW from
MICRO MATRIX
 Complete P.O. Box 938
 Pacifica, CA 94044

*Dealer inquiries welcomed!

✓ 134

H-8/H-89

DIGITAL TALKER

QUALITY VOICE with INFLECTION
 FUN TO USE --- EASY TO PROGRAM
 INTERFACE TO H8 BUSS OR PARALLEL BOARD
 APPLICATIONS: TELECOMMUNICATION,
 TEACHING AIDS, TALKING CLOCK, LANGUAGE
 TRANSLATION, GAMES, AND MORE.
 INCLUDES DEMONSTRATION "Basic" PROGRAM

\$149.95

add \$2.50 shipping and insurance

MI-8 ✓ 190

822 E. County Rd. 30
 Ft. Collins, Colo. 80525



Comes assembled and tested, includes
 connecting cable & plug. Or Kit only
 \$119.95. FREE CATALOG. The V-8 VOICE
 SYNTHESIZER, BSR HOME CONTROL inter-
 face, MODEM kit, PC-12 CLOCK board.
 TO ORDER BY PHONE (303) 669-4116

No. 2 UNBELIEVABLE OPPORTUNITY!

If You've Written an
 Outstanding Program--
 We'd Like to Publish It!

We're looking for EDUCATION
 Programs:

SPECIAL EDUCATION/AID
 TO THE HANDICAPPED
 MULTI-MEDIA COMPUTER INSTRUCTION
 TEACHER-AUTHORING LANGUAGES
 MANAGEMENT TRAINING
 SIMULATIONS

Earn money while helping others.
 Write for our free Programmer's
 Kit today!

INSTANT SOFTWARE, INC.
 Submissions Dept.
 Peterborough, NH 03458

✓ 75

Listing 2 continued.

```

1058 3D
1059 E607
105B CB07
105D 216D10
1060 1600
1062 5F
1063 19
1064 5E
1065 23
1066 56
1067 EB
1068 117B10
106B D5
106C E9
106D
106D
106D
106D OB11
106F 8210
1071
1071 B410
1073 C510
1075
1075 9B10
1077 D910
1079 EA10
107B
107B
107B
107B DDE1
107D C1
107E 78
107F D1
1080 E1
1081 C9
1082
1082
1082
1082 DD7E0C
1085 FE00
1087 2804
1089 CD8011
108C C9
108D DD360C4F
1091 CD6112
1094 CDA111
1097 CD1A12
109A C9
109B
109B
109B
109B DD7E0C
109E FE4F
10A0 3004
10A2 CD5D11
10A5 C9
10A6 DD360C00
10AA CD6112
10AD CDA111
10B0 CD1A12
10B3 C9
10B4
10B4
10B4
10B4 CD6112
10B7 AF
10B8 BD
10B9 2006
10BB BC
10BC 2003
10BE CDDA11
10C1 CD8E11
10C4 C9
10C5
10C5
10C5
10C5
10C5 CD6112
10C8 3E30
10CA BD
10CB 2008
10CD 3E07
10CF BC
10D0 2003
10D2 CDB011
10D5 CD6F11
10D8 C9
10D9
10D9
10D9
10D9
10D9 DD360C00
10DD 210000
10E0 CD6812
10E3 CDA111
10E6 CD1A12

1240 :CMDVCT DEC A
1250 AND 07H ;MASK OFF UPPER 5 BITS
1260 RLC A
1270 LD HL,VECTOR ;BASE OF CMD VECTOR TABLE
1280 LD D,0 ;ZERO D
1290 LD E,A ;MOVE OFFSET TO E
1300 ADD HL,DE ;HL HOLDS VECTOR TABLE ADDR
1310 LD E,(HL) ;LOWER BYTE OF VECTOR TO E
1320 INC HL
1330 LD D,(HL) ;UPPER BYTE OF VECTOR TO D
1340 EX DE,HL ;VECTOR TO HL
1350 LD DE,EXIT ;ADDR OF EXIT ROUTINE TO DE
1360 PUSH DE ;STORE ON STACK FOR 'RET'
1370 JP (HL) ;TRANSFER PROG CNTL TO HL
1380 ;
1390 ;ADDR TABLE FOR VIDEOGRAPHIC COMMANDS
1400 ;
1405 :VECTOR ;
1410 FCDB BELLS ;CNTL-G RING A BELL
1420 FCDB BACKSP ;CNTL-H BACKSPACE
1430 ; (CURSOR BACK)
1440 FCDB LASTRW ;CNTL-I CURSOR UP
1450 FCDB NEXTRW ;CNTL-J LINEFEED
1460 ; (CURSOR DOWN)
1470 FCDB FWDSP ;CNTL-K CURSOR FORWARD
1480 FCDB HOME ;CNTL-L CURSOR HOME
1490 FCDB CRRTN ;CNTL-M CARRIAGE RETURN
1500 ;
1510 ; EXIT ROUTINE RESTORES REGISTERS
1520 ;
1530 :EXIT POP IX ;RESTORE IX
1532 POP BC ;BC TOO
1535 LD A,B ;CHARACTER TO A
1540 POP DE
1550 POP HL
1560 RET ;RETURN TO USER'S PROGRAM
1600 ;
1610 ; CURSOR BACK ROUTINE
1620 ;
1630 :BACKSP LD A,(IX+COLUMN) ;COLUMN CNT TO A
1640 CP 0 ;IS IT ZERO?
1650 JR .Z,BACK1 ;IF SO, JUMP
1660 CALL REGI ;SHIFT CURSOR 1 COLUMN LEFT
1670 RET
1680 :BACK1 LD (IX+COLUMN),4FH ;LAST LINE COLMN
1690 CALL HL)ROW ;SAVE 79D IN ROW CNT
1700 CALL CALCUR ;CALCULATE NEW CURSOR
1710 CALL CURSLD
1720 RET
1740 ;
1750 ; CURSOR FORM RD ROUTINE
1760 ;
1770 :FWDSP LD A,(IX+COLUMN)
1780 CP 4FH ;IS A LESS THAN 79D?
1790 JR .NC,FWD1 ;JP IF END OF LINE
1800 CALL ADVI ;ADVANCE CURSOR
1805 RET
1810 :FWD1 LD (IX+COLUMN),0 ;ZERO COLUMN CNT
1820 CALL HL)ROW ;ROW CNT TO HL
1830 CALL CALCUR
1840 CALL CURSLD
1850 RET
1860 ;
1870 ; CURSOR UP ROUTINE
1880 ;
1890 :LASTRW CALL HL)ROW ;ROW CNT TO HL
1900 XOR A ;ZERO A
1910 CP L ;IS L=0?
1920 JR .NZ,LAST4
1930 CP H ;IS H=0?
1940 JR .NZ,LAST4
1950 CALL ROLLDN ;SINCE FIRST ROW, ROLL-DOWN
1960 :LAST4 CALL REGIII ;MOVE CURSOR UP 1 ROW
1970 RET
1980 ;
1990 ; CURSOR DOWN ROUTINE
2000 ; DOES NOT CLEAR NEXT LINE IF ROLLED-UP
2010 ;
2020 :NEXTRW CALL HL)ROW ;ROW CNT TO HL
2030 LD A,RWMAXL ;0730H IS ROW CNT FOR
2040 CP L ;THE LAST LINE
2050 JR .NZ,NEXT4 ;JP IF L#80H
2060 LD A,RWMAXH ;NOW CHECK H
2070 CP H ;IS H=7?
2080 JR .NZ,NEXT4
2090 CALL ROLLUP ;IT IS THE LAST LINE, SO ROLL
2100 :NEXT4 CALL ADVIII ;ADVANCE CURSOR 1 LINE
2110 RET
2120 ;
2130 ; CURSOR HOME ROUTINE
2140 ;
2150 :HOME LD (IX+COLUMN),0 ;ZERO COLUMN CNT
2160 LD HL,0 ;ZERO HL
2170 CALL ROW)HL ;ZERO ROW CNT
2180 CALL CALCUR ;CALCULATE CURSOR'S ADDR
2190 CALL CURSLD ;LOAD CURSOR AT 'HOME'

```

More

Listing 2 continued.

```

10E9 C9      2200 RET
10EA        2210 ;
10EA        2220 ; CARRIAGE RETURN ROUTINE
10EA        2230 ; CLEARS THE NEXT LINE IF A ROLL-UP OCCURS
10EA        2240 ; DEPOSITS '0D' IN MEMORY AS CR
10EA        2250 ;
10EA CD1611  2260 :CRRTN CALL CHAROT ;DEP CR IN MEMORY
10ED CD6112  2270 CALL HL)ROW ;ROW COUNT TO HL
10F0 3E30    2280 LD A,RWMAXL ;CHECK IF LAST LINE L=80H?
10F2 BD      2290 CP L
10F3 200B    2300 JR .NZ,CRR2
10F5 3E07    2310 LD A,RWMAXH ;H=7?
10F7 BC      2320 CP H
10F8 2006    2330 JR .NZ,CRR2
10FA CDB011  2340 CALL ROLLUP ;LAST LINE, SO ROLL-UP SCREEN
10FD CD0612  2350 CALL CLRLIN ;FILL NEXT LINE W/ SPACES
1100 DD360C00 2360 :CRR2 LD (IX+COLUMN),0 ;PUT CURSOR BOL
1104 CDA111  2370 CALL CALCUR
1107 CD1A12  2374 CALL CURSLD
110A C9      2378 RET
110B        2380 ;
110B        2390 ; RING A BELL ROUTINE
110B        2400 ;
110B DB00    2410 :BELLS IN A,(00H) ;CHECK STATUS
110D E680    2420 AND 80H ;MASK OFF BYTE
110F 28FA    2430 JR .Z,BELLS ;JP BACK IF NOT READY
1111 3E07    2440 LD A,07H ;A HOLDS ASCII BELL
1113 D301    2450 OUT (01H),A ;SET I/O ADDR FOR YOUR MACHINE
1115 C9      2460 RET
1116        2600 ;
1116        2610 ; CHARACTER POSITIONING ROUTINE
1116        2620 ;
1116 DD7E0C  2630 :CHAROT LD A,(IX+COLUMN) ;COLUMN CNT TO A
1119 FE4F    2640 CP 4FH ;IS IT 79D?
111B 2807    2650 JR .Z,CHAR2 ;JP IF LAST CHAR IN ROW
111D CD4611  2660 CALL CHARLD ;LOAD CHARACTER TO MEM
1120 CD5D11  2670 CALL ADVI ;ADVANCE CURSOR
1123 C9      2680 RET
1124 DD7E0B  2690 :CHAR2 LD A,(IX+ROWHI) ;GET ROW CNT
1127 FE07    2700 CP RWMAXH ;CHECK IF LAST ROW
1129 2007    2710 JR .NZ,CHAR4 ;JP IF NOT YET
112B DD7E0A  2720 LD A,(IX+ROWLO)
112E FE30    2730 CP RWMAXL ;LOW BYTE MATCH?
1130 2807    2740 JR .Z,CHAR6 ;JP IF SO, LAST LINE
1132 CD4611  2750 :CHAR4 CALL CHARLD
1135 CD6B11  2760 CALL ADVII
1138 C9      2770 RET
1139 CD4611  2780 :CHAR6 CALL CHARLD ;LOAD CHAR IN LAST POSIT
113C CDB011  2790 CALL ROLLUP ;SCROLL IN A NEW LINE
113F CD0612  2800 CALL CLRLIN ;CLEAR NEW LINE
1142 CD6B11  2810 CALL ADVII ;MOVE CURSOR TO NEW LINE
1145 C9      2820 RET
1146        2830 ;
1146        2840 ; LOAD CHARACTER ROUTINE
1146        2850 ;
1146 CD6112  2860 :CHARLD CALL HL)ROW ;ROW CNT TO HL
1149 CDA111  2870 CALL CALCUR ;CALCULATE CURSOR ADDR
114C E5      2880 PUSH HL ;SAVE THAT ADDR
114D CDF611  2890 CALL CLRROW ;CLEAR ROW CHAR TEST ROUTINE
1150 E1      2900 POP HL
1151 CD7D12  2905 CALL MASK8K ;MASK END AROUND
1154 CD3E12  2910 CALL DE)VID ;MEMORY MAPPED VIDEO ADDR TO DE
1157 19      2930 ADD HL,DE ;HL NOW HOLDS ABSOLUTE ADDR
1158 DD7E07  2940 LD A,(IX+CHARTR) ;CHAR BYTE TO A
115B 77      2950 LD (HL),A ;LOAD BYTE TO MEMORY
115C C9      2960 RET
115D        3000 ;
115D        3005 ;*****
115D        3010 ;**** SECTION 2 ****
115D        3015 ;*****
115D        3020 ; ELEMENTAL SUBROUTINES FOR VIDEO
115D        3030 ;
115D        3040 ;
115D        3050 ; MIDDLE OF SCREEN CURSOR ADVANCE
115D        3060 ; CURSOR AND COLUMN INCREMENT
115D        3070 ;
115D DD340C  3080 :ADVI INC (IX+COLUMN) ;INCREMENT COLUMN CNT
1160 CD6F12  3090 CALL HL)CUR ;CURSOR ADDR TO HL
1163 23      3100 INC HL ;POINT TO NEXT CHAR
1164 CD7612  3120 CALL CUR)HL ;STORE HL TO CURSOR
1167 CD1A12  3125 CALL CURSLD
116A C9      3130 RET
116B        3140 ;
116B        3150 ; END OF LINE CURSOR ADVANCE
116B        3160 ; CURSOR AND COLUMN TO NEXT LINE
116B        3170 ; ROW COUNT INCREMENTS BY 1
116B        3180 ; CONTINUES TO ADVIII
116B        3190 ;
116B DD360C00 3200 :ADVII LD (IX+COLUMN),0 ;ZERO COLUMN CNT
116F        3210 ;
116F        3220 ; MIDDLE OF LINE CURSOR DOWN
116F        3230 ; CURSOR STAYS IN SAME COLUMN BUT
116F        3240 ; ON THE NEXT LINE
116F        3250 ; EXPECTS THAT NEXT LINE IS ON SCREEN
116F        3260 ;
116F CD6112  3270 :ADVIII CALL HL)ROW ;ROW CNT TO HL

```

More →

INTRODUCTORY OFFER!

Turn your Micro-Computer into a Mini-Computer.
Try the world's #1 programming language-COBOL!
Finally at a price you can afford and with no risk!

Introducing...

NPS-MICRO-COBOL

This is the Naval Post Graduate School Cobol that you've heard so much about. Designed to pass the stringent government Hypo-COBOL tests used by GSA in their Compiler Certification Program. This is the first public release of version 2.1. This is an elaborate ANSI-COBOL subset. Comes complete with users manual in DeLuxe three-ring binder.

- Perfect for learning COBOL.
- Perfect for teaching COBOL
- FREE sample programs included
- Runs in 24K
- Requires 8080, Z-80®, or 8085 and standard CP/M® system
- Provided on standard 8" disk or Northstar Double Density CP/M 5"

Only \$69.95!

FREE ALGOL INCLUDED!

FREE BONUS. All purchasers receive a **FREE** copy of NPS-ALGOL at no extra cost. A favorite language in Europe, ALGOL is the original structured language. Comes with **FREE** sample programs.

MONEY-BACK GUARANTEE. If you're not completely satisfied with this software. You may return it within fifteen days for any reason and get a full refund.

Send Check, Money Order or Credit Card Information and order a copy today! Please add \$2.50 shipping and handling on all orders.

Credit Card buyers: For Extra Fast service call (415) 527-7730

Order from: The Software Review ✓ 294
704 Solano Avenue, Albany, CA 94706

Yes, I want to run COBOL on my system! Enclosed find \$69.95 plus \$2.50 shipping/handling (California residents please add appropriate sales tax). I will receive the NPS-COBOL system plus a **FREE** copy of NPS-ALGOL. I understand that I may return the software within 15 days if not completely satisfied for a full refund.

NAME _____

COMPANY _____

STREET _____

CITY _____

STATE _____ ZIP _____

AMOUNT ENCLOSED \$ _____

Disk size desired: 5" 8"

☐ Check Enclosed ☐ VISA

☐ UPS C.O.D. ☐ Mastercharge

Card number _____

Expiration Date _____

Signature _____

☐ Check here for more information
CP/M is a trademark of Digital Research and Z-80 is a trademark of Zilog.



NEW! for
the '89 from

MAGNOLIA
MICROSYSTEMS

✓234

DOUBLE DENSITY DISK CONTROLLER

for both 5 1/4" & 8" drives


only **\$595** complete

including CP/M™ 2.2

MAGNOLIA MICROSYSTEMS, INC.
2812 Thornhyke W., Seattle 98199
(206) 285-7266 (800) 426-2841

CP/M is a trademark of Digital Research.

Model 6800CL4N CalClock/TIMER



IT'S A HARDWARE CALENDAR/CLOCK

- Keeps date and time without servicing by the computer
- Day-of-week, month/day/year, hour/minute (12/24hr. + auto Leap Year)
- Hands off setting/control/access of ALL functions via software
- On-card battery and charging circuit keeps time for months, power off

WITH AN INTERVAL TIMER INCLUDED

- For (TSC/Flex2) compatible printer spooling, multi-tasking, etc.

Full assembly & tested* \$99.95 5" Disk (Flex2) Flex9 □ \$10.00
Complete kit* \$69.95 Goldplated buss connectors \$ 6.00
Bare board* \$35.00 Shipping & handling \$ 3.00

* FULLY DOCUMENTED: instructions; diagrams; theory; more than 20 pages of sample software (automatically puts date in Flex2/9 date buffer, adds time-of-day to assembly listings, maintains constant, current time+date display on top line of CRT). Batteries not included. All IC's socketed.

© FLEX is the registered trademark of Technical Systems Consultants, Inc.

COMPUWARE Corporation
P.O. Box 2710
Cherry Hill, NJ 08003
609-428-2309

Dealer & Volume Discounts
New Jersey buyers: ADD 5%
Terms: CASH; MC; or Visa
Flex9 □ Flex2 □ (default) □

✓197

No. 3 UNBELIEVABLE OPPORTUNITY!

*If You've Written an
Extraordinary Program--
We'd Like to Publish It!*

**Programs needed for MANAGE-
MENT applications:**

**PERT & CPM SCHEDULING
PREDICTIVE MODELING
DECISION-MAKING SIMULATIONS
PRODUCTION SCHEDULING
EXPENSE ANALYSES**

**Royalty checks may be in YOUR
future. Write for our free Pro-
grammer's Kit today.**

**INSTANT SOFTWARE, INC. ✓75
Submissions Dept.
Peterborough, NH 03458**

Listing 2 continued.

```

1172 115000
1175 19
1176 CD6812
1179 CDA111
117C CD1A12
117F C9
1180
1180
1180
1180 DD350C
1183 CD6F12
1186 2B
1187 CD7612
118A CD1A12
118D C9
118E
118E
118E
118E
118E
118E CD6112
1191 115000
1194 B7
1195 ED52
1197 CD6812
119A CDA111
119D CD1A12
11A0 C9
11A1
11A1
11A1
11A1
11A1 1600
11A3 DD5E0C
11A6 19
11A7 EB
11A8 CD5312
11AB 19
11AC CD7612
11AF C9
11B0
11B0
11B0
11B0
11B0
11B0
11B0
11B0
11B0 115000
11B3 D5
11B4 CD5312
11B7 19
11B8 CD7D12
11BB CD5A12
11BE 1607
11C0 1E30
11C2 19
11C3 CD7D12
11C6 CD4C12
11C9 B7
11CA D1
11CB CD6112
11CE ED52
11D0 CD7D12
11D3 CD6812
11D6 CD2C12
11D9 C9
11DA
11DA
11DA
11DA
11DA
11DA
11DA 115000
11DD D5
11DE CD5312
11E1 B7
11E2 ED52
11E4 CD7D12
11E7 CD5A12
11EA CD6112
11ED D1
11EE 19
11EF CD6812
11F2 CD2C12
11F5 C9
11F6
11F6
11F6
11F6
11F6
11F6 CD4512
3280 LD DE,50H ;80D TO DE
3290 ADD HL,DE ;HL=ROW CNT + 80D
3300 CALL ROW)HL ;STORE NEW ROW CNT
3310 CALL CALCUR ;CALCULATE NEW CURSOR
3320 CALL CURSLD
3330 RET
3340 ;
3350 ; MIDDLE OF SCREEN CURSOR REGRESS
3360 ; CURSOR MOVES BACK 1 LOCATION
3370 ; CURSOR AND COLUMN CNT DECREMENTED
3380 ;
3390 :REGI DEC (IX+COLUMN) ;DECREMENT COLUMN CNT
3400 CALL HL)CUR ;CURSOR LOC TO HL
3410 DEC HL
3430 CALL CUR)HL ;SAVE NEW CURSOR
3440 CALL CURSLD
3450 RET
3460 ;
3470 ; MIDDLE OF LINE CURSOR UP
3480 ; CURSOR REMAINS IN SAME COLUMN BUT
3490 ; ONE LINE HIGHER
3500 ; EXPECTS HIGHER LINE TO BE ON SCREEN
3510 ;
3520 :REGIII CALL HL)ROW
3530 LD DE,50H ;80D TO DE
3540 OR A ;CLEAR CARRY FLAG
3550 SBC HL,DE ;HL=ROW COUNT - 80D
3560 CALL ROW)HL ;SAVE NEW ROW CNT
3570 CALL CALCUR ;CALCULATE NEW CURSOR ADDR
3580 CALL CURSLD
3590 RET
3600 ;
3610 ; CALCULATE CURSOR ADDR ROUTINE
3620 ; USES HOME ADDR + COLUMN CNT
3630 ; + ROW CNT. EXPECTS ROW CNT IN HL
3640 ;
3650 :CALCUR LD D,0 ;ZERO D
3660 LD E,(IX+COLUMN) ;COLUMN CNT TO E
3670 ADD HL,DE ;HL=ROW+COLUMN
3680 EX DE,HL ;SAVE IN DE
3690 CALL HL)HOM ;HOME ADDR IN HL
3700 ADD HL,DE ;HL=ROW+COLUMN+HOME
3720 CALL CUR)HL ;STORE IN HL
3730 RET
3740 ;
3750 ; ROLL-UP ROUTINE
3760 ; ROLLS SCREEN UP 1 LINE BASED ON HOME
3770 ; CURSOR AND COLUMN CNT STAY ON SAME CHAR
3780 ; DECREMENTS ROW CNT BY ONE
3790 ; DOES NOT CLEAR NEW LINE, 1ST CHAR ADDR
3800 ; ON THE NEW LINE IS IN IX+BUFF
3810 ;
3820 :ROLLUP LD DE,50H ;80D TO DE
3830 PUSH DE ;SAVE IT
3840 CALL HL)HOM ;HOME ADDR TO HL
3850 ADD HL,DE ;NEW HOME ADDR
3860 CALL MASK8K ;ADJUST FOR END-AROUND
3870 CALL HOM)HL ;SAVE HOME
3880 LD D,RWMAXH ;LAST ROW HIBYTE TO D
3890 LD E,RWMAXL ;LAST ROW LOBYTE TO E
3900 ADD HL,DE ;HL=1ST CHAR IN NEXT LINE
3910 CALL MASK8K ;MASK END AROUND
3920 CALL BUF)HL
3930 OR A ;CLEAR CARRY
3940 POP DE ;80D TO DE
3950 CALL HL)ROW ;ROW CNT TO HL
3960 SBC HL,DE ;HL=ROW CNT - 80D
3970 CALL MASK8K
3980 CALL ROW)HL ;SAVE NEW ROW CNT
3990 CALL HOMLD ;READJUST VIDEO HOME ADDR
4000 RET
4010 ;
4020 ; ROLL-DOWN ROUTINE
4030 ; ROLLS SCREEN DOWN 1 LINE
4040 ; INCREMENTS ROW COUNT BY ONE LINE
4050 ; CURSOR AND COLUMN STAY AT SAME CHAR
4060 ;
4070 :ROLLDN LD DE,50H ;80D TO DE
4080 PUSH DE
4090 CALL HL)HOM ;HOME ADDR TO HL
4100 OR A ;CLEAR CARRY FLAG
4110 SBC HL,DE ;HL=NEW HOME ADDR
4120 CALL MASK8K
4130 CALL HOM)HL ;SAVE HOME
4140 CALL HL)ROW ;ROW CNT TO HL
4150 POP DE ;80D IN DE
4160 ADD HL,DE
4170 CALL ROW)HL ;SAVE NEW ROW CNT
4180 CALL HOMLD ;READJUST VIDEO HOME ADDR
4190 RET
4200 ;
4210 ; CLEAR ROW TEST ROUTINE
4220 ; FILLS LINE W/ SP'S IF FIRST CHAR
4230 ; OF PRESENT LINE IS FOF
4240 ;
4250 :CLRROW CALL HL)BUFF ;LOC OF 1ST CHAR

```

More

Listing 2 continued.

```

11F9 CD3E12      4270 CALL DE)VID ;MEMORY MAP ADDR TO DE
11FC 3EFO        4280 LD A,0F0H ;CLEAR ROW DELIMITER
11FE 19          4290 ADD HL,DE
11FF BE          4300 CP (HL) ;IS CHAR A 0F0H?
1200 C0          4310 RET .NZ ;RETURN IF NOT
1201 CD0612      4320 CALL CLRLIN ;FILL ROW W/ SPACES
1204 C9          4330 RET
1205             4340 ;
1205             4350 ; CLEAR LINE ROUTINE
1205             4360 ; EXPECTS IX+BUFF TO HOLD 1ST CHAR OF LINE
1205             4370 ;
1205 20          4380 :SPACE FCB 20H ;SPACE BYTE
1206 CD4512      4390 :CLRLIN CALL HL)BUFF ;LOC OF FIRST CHAR
1209 CD3E12      4400 CALL DE)VID ;ABSOLUTE MEM-MAPPED ADDR TO DE
120C 19          4410 ADD HL,DE ;ABSOLUTE CHARACTER ADDR TO HL
120D 015000      4420 LD BC,50H ;COUNTER BC HOLDS 80D
1210 110512      4430 LD DE,SPACE ;DE POINTS TO 20H
1213 EB          4440 EX DE,HL ;SWITCH DE + HL
1214 EDA0        4450 :CLRL LDI ;MOVE A SP TO MEMORY
1216 E0          4460 RET .PO ;EXIT WHEN BC=0
1217 2B          4470 DEC HL ;KEEP HL POINTING AT 20H
1218 18FA        4480 JR CLRL ;REPEAT TILL DONE
121A             4490 ;
121A             4500 ; LOADS CURSOR ADDR TO 6845 CHIP
121A             4510 ;
121A 3E0F        4520 :CURSLD LD A,0FH ;CURSOR LOW REGISTER
121C D370        4530 OUT (70H),A ;OUTPUT REG # TO 6845
121E CD6F12      4540 CALL HL)CUR ;CURSOR ADDR TO HL
1221 7D          4550 LD A,L
1222 D371        4560 OUT (71H),A ;OUTPUT LO BYTE
1224 3E0E        4570 LD A,0EH
1226 D370        4580 OUT (70H),A ;REG # TO 6845
1228 7C          4590 LD A,H
1229 D371        4600 OUT (71H),A ;OUTPUT HI BYTE
122B C9          4610 RET
122C             4620 ;
122C             4630 ; LOADS HOME ADDR TO 6845 CHIP
122C             4640 ;
122C 3E0D        4650 :HOMLD LD A,0DH
122E D370        4660 OUT (70H),A ;REG # TO 6845
1230 CD5312      4670 CALL HL)HOM ;HOME ADDR TO HL
1233 7D          4680 LD A,L
1234 D371        4690 OUT (71H),A ;OUTPUT LO BYTE
1236 3E0C        4700 LD A,0CH
1238 D370        4710 OUT (70H),A
123A 7C          4720 LD A,H
123B D371        4730 OUT (71H),A ;OUTPUT HI BYTE
123D C9          4740 RET
123E             4750 ;
123E             4760 ; ASSORTED LOADING ROUTINES
123E             4770 ;
123E DD5E01      4780 :DE)VID LD E,(IX+VIDLO)
1241 DD5602      4790 LD D,(IX+VIDHI)
1244 C9          4800 RET
1245 DD6E03      4810 :HL)BUF LD L,(IX+BUFLO)
1248 DD6604      4820 LD H,(IX+BUFHI)
124B C9          4830 RET
124C DD7503      4840 :BUF)HL LD (IX+BUFLO),L
124F DD7404      4850 LD (IX+BUFHI),H
1252 C9          4860 RET
1253 DD6E05      4870 :HL)HOM LD L,(IX+HOMLO)
1256 DD6606      4880 LD H,(IX+HOMHI)
1259 C9          4890 RET
125A DD7505      4900 :HOM)HL LD (IX+HOMLO),L
125D DD7406      4910 LD (IX+HOMHI),H
1260 C9          4920 RET
1261 DD6E0A      4930 :HL)ROW LD L,(IX+ROWLO)
1264 DD660B      4940 LD H,(IX+ROWHI)
1267 C9          4950 RET
1268 DD750A      4960 :ROW)HL LD (IX+ROWLO),L
126B DD740B      4970 LD (IX+ROWHI),H
126E C9          4980 RET
126F DD6E08      4990 :HL)CUR LD L,(IX+CURLO)
1272 DD6609      5000 LD H,(IX+CURHI)
1275 C9          5010 RET
1276 DD7508      5020 :CUR)HL LD (IX+CURLO),L
1279 DD7409      5030 LD (IX+CURHI),H
127C C9          5040 RET
127D             5050 ;
127D             5055 ;MASK8K
127D             5060 ; MASK OFF 3 MOST SIGNIFICANT BITS
127D             5070 ; OF ADDR TO SET END-AROUND ON VIDEO MAP.
127D             5080 ; THE MEMORY MAPPED SIZE ---- 8K.
127D             5085 ; NOTE: THE CURSOR IS NOT MASKED SINCE
127D             5088 ; IT IS AN INTERNAL COUNTER.
127D             5090 ;
127D F5          5100 :MASK8K PUSH AF
127E 7C          5110 LD A,H
127F E61F        5120 AND 1FH
1281 67          5130 LD H,A
1282 F1          5140 POP AF
1283 C9          5150 RET
1284             5160 ;
1284             5165 ;*****
1284             5170 ;**** SECTION 3 ****
1284             5175 ;*****

```

9 TRACK TAPE DRIVES

800 BPI
45 IPS
FULL MANUAL
\$4850 VALUE



\$2400
NEW IN
ORIGINAL
BOXES

PERTEC Model 8840A-9-45
INDUSTRY STANDARD INTERFACE
CAPABLE OF IND. STD. ANSI-IBM DATA FORMAT

- READ/WRITE DATA IN STANDARD ANSI-IBM COMPATIBLE FORMAT
- DUMP WINCHESTERS AND HARD DISKS; 10 inch reels hold up to 3600' of tape = 34.56 Megabytes unlocked.
- EXCHANGE DATA & PROGRAMS WITH LARGE MAIN FRAMES AT SCHOOL, WORK, SERVICE BUREAUS ETC.
- BARGAIN PRICED MINI-COMPUTER UPGRADE. OEM List \$4850

A large OEM overstock makes these industry standard drives available at a fraction of their current list price. Full size drives handle up to 10.5 inch reels of standard inexpensive 1/2 inch mag tape. 19 inch rack mount or use right out of the box on steel shipping frame.

SPECIFICATION SUMMARY: 9-track, 800 BPI, dual head (read after write), 45 IPS read/write, 200 IPS rewind, BOT/EOT sensing, 110 VAC/60-Hz, solid state, recent manufacture, all I/O signals TTL/DTL compatible, tension arm tape buffering, full control panel. Call or write for full set of technical specifications.

INTERFACES: Electrovalue encourages the development of interfaces to popular systems. Interfaces exist for popular minis and are being developed for several hobby computers. If you'd like to develop and document an interface to a popular small system call to discuss discounts.

ELECTROVALUE INDUSTRIAL INC.
P.O. BOX 157-K
MORRIS PLAINS, NJ 07950
Formerly Electrovalue Industrial

Phone reservations and questions are welcome.
201/267-1117

BUY! SELL! TRADE! COMPUTER & HAM EQUIPMENT COMPUTER

TRADER ✓176

"GREEN SHEETS"

Mailed 1st class, 1st and 15th of every month
SEND ADS FIVE DAYS BEFORE MAILING DATE

— RATES —

Subscriptions	Ads
One Year..... \$10.00	Hobby ... 20¢ Word/Number
Six Months..... \$6.00	Business ... 55¢ Word/Number
Per Copy..... \$1.00	(Non-Subscriber ... Add 15¢ Word/Number)

SAVE 50% on your 1st ad accompanying your subscription
Send Ads and Subscriptions with remittance to:

COMPUTER TRADER®

Chet Lambert, W4WDR
1704 Sam Drive • Birmingham, AL 35235
(205) 854-0271

For ads count name and address, words and numbers
(zip/area code free)

Please include your name, address, call sign or phone number

No. 4
UNBELIEVABLE
OPPORTUNITY!

You've Written
a Fantastic Game?

Then We'd Like to Publish It!

We're looking for hot GAME programs:

ARCADE (HI-SPEED GRAPHICS)
ADVENTURE FORMAT
FANTASY WARGAMING
BOARD GAMES
LOGIC & PUZZLE GAMES

There's Gold in them there Games! Write for our free Programmer's Kit today.

INSTANT SOFTWARE, INC. ✓75
Submissions Dept.
Peterborough, NH 03458

★ SOFTWARE FOR OSI

★ VIDEO GAMES 3 ... **NEW!** \$14.95

Three games. Meteor Mission is an asteroids game. Space Wars is a battle between two starships. Meteor Wars is a combination of the two above games. All three are in machine language with fast, real time action, and super graphics.

★ ADVENTURE: IMMORTALITY **NEW!** \$11.95

You are an intrepid explorer searching for the fabled "Dust of Immortality". This is the largest adventure yet available for 8K OS! hidden room load so you can't cheat

★ SUPER BUG! \$6.95

Here's a super-fast, BASIC/Machine language hybrid race game. Ten levels of difficulty and an infinitely changing track will keep you challenged.

★ STARGATE MERCHANT \$9.95

You are a trader in the distant future, traveling through 'stargates' to get to various star systems. Part video game, part board game, always challenging.

★ DISASSEMBLER \$11.95

Use this to look at the ROMs in your machine to see what makes BASIC tick. Reconstruct the assembler source code of machine language programs to understand how they work. Our disassembler outputs unique suffixes which identify the addressing mode being used, no other program has this!

★ MAROONED IN SPACE ... \$11.95

An adventure that runs in 8K! Save your ship and yourself from destruction

★ SUPER! BIORHYTHMS ... \$14.95

A unique sophisticated biorhythm program

★ DUNGEON CHASE \$9.95

real-time video game where you explore a dungeon.

Write for **FREE** catalog

ORION SOFTWARE ✓ 329

147 Main St. Ossining, NY 10562



IS YOUR North Star OUT OF SORTS?

**INCREASE YOUR BASIC'S
SORTING POWER OVER 1800%!**

N*SORT is easy to use and will perform sorts on one and two dimensional or string arrays using optional sort keys. For example, to alphabetize A\$:

10 A\$ = "ZYXWVUTS" \ REM Define String
20 SRT A\$.LEN(A\$) \ REM Sort A\$

N*SORT interfaces to any release 4 or later North Star Basic and can be yours for **ONLY \$89** plus \$1.50 shipping

Calif. Res. add 6% tax.
Send check VISA or M/C
Complete Brochure Available

✓ 111 **SZ Software Systems**

1269 Rubio Vista Road, Altadena, Calif. 91001
(213) 791-3202

No. 5 UNBELIEVABLE OPPORTUNITY!

*If You've Written
State-of-the-Art Software--
We'd Like to Publish It!*

We're looking for SYSTEM software:

**DISK OPERATING SYSTEMS
MONITORS
PROGRAMMER AIDS/UTILITIES
LANGUAGES**

DATA BASE SYSTEMS
Then, sit back and collect your
royalty checks. Write for our free
Programmer's Kit today!

INSTANT SOFTWARE, INC. ✓ 75
Submissions Dept.
Peterborough, NH 03458

Listing 2 continued.

```

1284 ;INITIALIZATION SECTION
1284 ;
1284 ;
1284 ;***CALL GRAPH AND INITIALIZE FOR GRAPHIC MODE
1284 :GRAPH LD HL,CLRMEM-1 ;POINT TO OFFH
1287 CALL CLRMEM
1288 CALL INITBF
1288 CALL DOTS
1290 INC (IX+PLOTTR) ;MAKE GRAPHICS FLAG NON-ZERO
1293 RET
1294 ;***CALL LITRS AND INITIALIZE FOR CHARACTER MODE
1294 :LITRS LD HL,SPACE
1297 CALL CLRMEM
1298 CALL INITBF
1298 CALL CHARS
1298 RET
1299 ;
1299 ; FILL VIDEO MEMORY WITH SPACE OR FF'S
1299 ; HL MUST POINT TO CHARACTER TO BLANK SCREEN
1299 ;
1299 FCB OFFH
1299 :CLRMEM LD DE,0C000H ;FIRST ADDR OF 8K BOARD
1299 LD BC,2000H ;LENGTH OF MEMORY
1299 :CLRMEM LDI ;MOVE A SPACE TO VIDEO
1299 RET .PO ;RET WHEN BC=0
1299 DEC HL ;CONTINUE TO POINT TO FILL CHAR
1299 JR CLRMEM1 ;REPEAT
1299 FCDB 0
1299 ;
1299 ; INITIALIZE VIDEOGRAPHIC BUFFER VALUES
1299 ;
1299 :INITBF LD IX,BUFFER ;SET UP IX POINTER
1299 ; NOTE: CHANGE VALUE OF BUFFER FOR
1299 ; A DIFFERENT BUFFER LOCATION
1299 LD HL,0 ;ZERO HL
1299 CALL ROW)HL
1299 CALL BUF)HL
1299 CALL CUR)HL
1299 CALL HOM)HL
1299 LD (IX+COLUMN),0 ;ZERO COLUMN CNT
1299 LD (IX+PLOTTR),0 ;RESET GRAPHICS FLAG
1299 LD HL,VIDEO
1299 LD (IX+VIDLO),L
1299 LD (IX+VIDHI),H
1299 LD (IX+PLOTTR),0 ;RESET GRAPHICS FLAG FOR CHAR MODE
1299 RET
1299 ;
1299 ; INITIALIZE THE 6845 CHIP FOR 24X80 DISPLAY
1299 ;
1299 :CHARS LD C,0
1299 LD B,66H ;R0 H-TOTAL
1299 CALL CHIP
1299 LD B,50H ;R1 H-DISPLAYED
1299 CALL CHIP
1299 LD B,56H ;R2 H-SYNC
1299 CALL CHIP
1299 LD B,0CH ;R3 H-PULSE WIDTH
1299 CALL CHIP
1299 LD B,18H ;R4 V-TOTAL
1299 CALL CHIP
1299 LD B,13H ;R5 V-ADJUST
1299 CALL CHIP
1299 LD B,18H ;R6 V-DISPLAYED
1299 CALL CHIP
1299 LD B,18H ;R7 V-SYNC
1299 CALL CHIP
1299 LD B,0 ;R8 VIDEO MODE
1299 CALL CHIP
1299 LD B,0BH ;R9 SCANS/ROW
1299 CALL CHIP
1299 LD B,49H ;R10 CURSOR LIMIT HI
1299 CALL CHIP
1299 LD B,0BH ;R11 CURSOR LIMIT LO
1299 CALL CHIP
1299 CALL HOMLD ;R12 + R13 HOME ADDR
1299 CALL CURSLD ;R14 + R15 CURSOR ADDR
1299 OUT (61H),A ;PUT VIDEO BOARD IN CHAR MODE
1299 RET
1299 ;
1299 :CHIP LD A,C ;LOAD REGISTER CNT TO A
1299 OUT (70H),A ;SEND REGISTER ADDR TO 6845
1299 INC C
1299 LD A,B
1299 OUT (71H),A ;SEND PROGRAMMING INFO TO 6845
1299 RET
1299 ;
1299 ; INITIALIZE THE 6845 FOR 256X248 DISPLAY
1299 ;
1299 :DOTS OUT (60H),A ;PUT VIDEO IN GRAPHIC MODE
1299 LD HL,DOTS2
1299 LD C,0
1299 :DOTS1 LD A,(HL)
1299 CP 0EEH
1299 RET .Z
1299 LD B,A
1299 CALL CHIP
1299 INC HL
1299 JR DOTS1

```

More →

4MHZ, DOUBLE DENSITY, COLOR & B/W GRAPHICS. .THE LNW80 COMPUTER



When you've compared the features of an LNW80 Computer, you'll quickly understand why the LNW80 is the ultimate TRS80 software compatible system. LNW RESEARCH offers the most complete microcomputer system at an outstanding low price. We back up our product with an unconventional 6 month warranty and a 10 days full refund policy, less shipping charges.

LNW80 Computer \$1,450.00
LNW80 Computer w/B&W Monitor & one 5" Drive \$1,914.00
All orders must be prepaid, CA residents please include 6% sales tax.
Contact us for shipping charges

* TRS80 Product of Tandy Corporation.
** PMC Product of Personal Microcomputer, Inc.

COMPARE THE FEATURES AND PERFORMANCE			
FEATURES	LNW80	PMC-80**	TRS-80* MODEL 111
PROCESSOR	4.0 MHZ	1.8 MHZ	2.0 MHZ
LEVEL II BASIC INTERP.	YES	YES	LEVEL III BASIC
TRS80 MODEL 1 LEVEL II COMPATIBLE	YES	YES	NO
48K BYTES RAM	YES	YES	YES
CASSETTE BAUD RATE	500/1000	500	500/1500
FLOPPY DISK CONTROLLER	SINGLE/DOUBLE	SINGLE	SINGLE/DOUBLE
SERIAL RS232 PORT	YES	YES	YES
PRINTER PORT	YES	YES	YES
REAL TIME CLOCK	YES	YES	YES
24 X 80 CHARACTERS	YES	NO	NO
VIDEO MONITOR	YES	YES	YES
UPPER AND LOWER CASE	YES	OPTIONAL	YES
REVERSE VIDEO	YES	NO	NO
KEYBOARD	63 KEY	53 KEY	53 KEY
NUMERIC KEY PAD	YES	NO	YES
B/W GRAPHICS, 128 X 48	YES	YES	YES
HI-RESOLUTION B/W GRAPHICS, 480 X 192	YES	NO	NO
HI-RESOLUTION COLOR GRAPHICS (NTSC), 128 X 192 IN 8 COLORS	YES	NO	NO
HI-RESOLUTION COLOR GRAPHICS (RGB), 384 X 192 IN 8 COLORS	OPTIONAL	NO	NO
WARRANTY	6 MONTHS	90 DAYS	90 DAYS
TOTAL SYSTEM PRICE	\$1,914.00	\$1,840.00	\$2,187.00
LESS MONITOR AND DISK DRIVE	\$1,450.00	\$1,375.00	---

LNW80

- BARE PRINTED CIRCUIT BOARD & MANUAL \$89.95

The LNW80 - A high-speed color computer totally compatible with the TRS-80*. The LNW80 gives you the edge in satisfying your computation needs in business, scientific and personal computation. With performance of 4 MHz, 280A CPU, you'll achieve performance of over twice the processing speed of a TRS-80*. This means you'll get the performance that is comparable to the most expensive microcomputer with the compatibility to the world's most popular computer (TRS-80*) resulting in the widest software base.

FEATURES:

- TRS-80 Model 1 Level II Software Compatible
- High Resolution Graphics
 - RGB Output - 384 x 192 in 8 Colors
 - NTSC Video or RF MOD - 128 x 192 in 8 Colors
 - Black and White - 480 x 192
- 4 MHz CPU
- 500/1000 Baud Cassette
- Upper and Lower Case
- 16K Bytes RAM, 12K Bytes ROM
- Solder Masked and Silkscreened

LNW SYSTEM EXPANSION

- BARE PRINTED CIRCUIT BOARD AND MANUAL \$69.95
WITH GOLD CONNECTORS \$84.95

The System Expansion will allow you to expand your LNW80, TRS-80*, or PMC-80** to a complete computer system that is still totally software compatible with the TRS-80* Model 1 Level II.

FEATURES:

- 32K Bytes Memory
- 5" Floppy Controller
- Serial RS232 20ma I/O
- Parallel Printer
- Real Time Clock
- Screen Printer Bus
- On Board Power Supply
- Solder Masked and Silkscreened

LNW RESEARCH
CORPORATION

2620 WALNUT
TUSTIN CA. 92680

ORDERS & INFO. NO. 714-544-5744
SERVICE NO. 714-641-8850

LNDbabler & DOS PLUS 3.3D

- Assembled and Tested W/DOS PLUS 3.3D. \$175.00

Double-density disk storage for the LNW Research's "System Expansion" or the Tandy's "Expansion Interface". The LNDbabler™ is totally software compatible with any double density software generated for the Percom's Doubler***. The LNDbabler™ provides the following outstanding features.

- Store up to 350K bytes on a single 5" disk
- Single and double density data separation
- Precision write precompensation circuit
- Software switch between single and double density
- Easy plug in installation requiring no etch cuts, jumpers or soldering
- 35, 40, 77, 80 track 5" disk operation
- 120 day parts and labor Warranty

*** Doubler is a product of Percom Data Company, Inc.

DOS PLUS 3.3D

Micro Systems software's double density disk operating system. This operating system contains all the outstanding features of a well developed DOS, with ease in useability.

KEYBOARD

LNW80 KEYBOARD KIT \$84.95

The Keyboard Kit contains a 63 key plus a 10 key, P.C. board, and remaining components.

CASE

LNW80 CASE \$84.95

The streamline design of this metal case will house the LNW80, LNW System Expansion, LNW80 Keyboard, power supply and fan, LNDbabler™, or LNW Data Separator. This kit includes all the hardware to mount all of the above. Add \$12.00 for shipping

PARTS AVAILABLE FROM LNW RESEARCH

- 4116 - 200ns RAM
 - 6 chip set \$26.00
 - 8 chip set \$33.50
 - 16 chip set \$64.00
 - 24 chip set \$94.00
 - 32 chip set \$124.00
- LNW80 "Start up parts set" LNW80-1 \$82.00
- LNW80 "Video parts set" LNW80-2 \$31.00
- LNW80 Transformer LNW80-3 \$18.00
- LNW80 Keyboard cable LNW80-4 \$16.00
- 40 Pin computer to expansion cable \$15.00
- System Expansion Transformer \$19.00
- Floppy Controller (FD1771) and UART (TR1602) \$30.00

VISA MASTER CHARGE UNLESS NOTED
ACCEPTED ADD \$3 FOR SHIPPING

SOFTWARE GAIN CONTROL

For additional details about the AD-100-4 and other fine California Data Corporation 100% individually tested, high reliability products, circle the reader service card number below or for faster response write or call us.

(805) 498-3651

299

QCB-9 YOUR LOGICAL CHOICE



- 6809 or 6802 Microprocessor
- 24K bytes of EPROM/RAM space
- Serial RS-232 port with 14 baud rates
- 16 Decoded Address Lines
- Jumper configurable Address Map
- Floppy Disc Controller for three 5" Drives
- Printer port, Centronic type compatible
- Keyboard/Parallel interface
- Runs Flex DOS
- QBUG Resident Debug Monitor
- 1K bytes of RAM and 2K bytes of EPROM
- DEALER/OEM INQUIRIES INVITED
- Check or Money Order

• Price:	OCB-9/5802 with STD features	\$ 195.00
	OCB-9/6809 with STD features	225.00
	Floppy Controller Option	75.00
	Printer/Keyboard Option	30.00

CALL (305) 974-0967

LOGICAL DEVICES, INC. ✓ 373
781 W. Oakland Park Blvd.
Ft. Lauderdale, Fla. 33311
Tel: (305) 565-8103



Thank you and enjoy your subscription.

More

Listing 2 continued.

```

1382 7E      7960 LD A, (HL)
1383 47      7970 LD B,A
1384 CB42    7980 BIT 0,D
1386 2809    7990 JR .Z,DOT3
1388 CB4A    8000 BIT 1,D
138A 280E    8010 JR .Z,DOT4
138C CBDF    8020 SET 3,A
138E CBF8    8030 SET 7,B
1390 C9      8040 RET
1391 CB4A    8050 :DOT3 BIT 1,D
1393 280A    8060 JR .Z,DOT5
1395 CBD7    8070 SET 2,A
1397 CBF0    8080 SET 6,B
1399 C9      8090 RET
139A CBCF    8100 :DOT4 SET 1,A
139C CBE8    8110 SET 5,B
139E C9      8120 RET
139F CBC7    8130 :DOT5 SET 0,A
13A1 CBE0    8140 SET 4,B
13A3 C9      8150 RET
13A4         8160 ;
13A4         8170 :SETDOT ;SAME AS UNDOT, BUT CREATES THE
13A4         8180 ; DOT RATHER THAN REMOVING IT
13A4         8190 ;
13A4 7E      8200 LD A, (HL)
13A5 47      8210 LD B,A
13A6 CB42    8215 BIT 0,D
13A8 2809    8220 JR .Z,UNDOT3
13AA CB4A    8230 BIT 1,D
13AC 280E    8240 JR .Z,UNDOT4
13AE CB9F    8250 RES 3,A
13B0 CBB8    8260 RES 7,B
13B2 C9      8270 RET
13B3 CB4A    8280 :UNDOT3 BIT 1,D
13B5 280A    8290 JR .Z,UNDOT5
13B7 CB97    8300 RES 2,A
13B9 CBB0    8310 RES 6,B
13BB C9      8320 RET
13BC CB8F    8330 :UNDOT4 RES 1,A
13BE CBA8    8340 RES 5,B
13C0 C9      8350 RET
13C1 CB87    8360 :UNDOT5 RES 0,A
13C3 CBA0    8370 RES 4,B
13C5 C9      8380 RET
13C6         8600 ;
13C6         8610 ;LINE ROUTINE THIS ROUTINE CALCULATES A POINT
13C6         8620 ; TO POINT LINE BETWEEN ANY TWO INPUTTED-POINTS.
13C6         8630 ; IT IS DESIGNED FOR A 256X248 MATRIX USING A
13C6         8640 ; STACK-ORIENTED ALGORITHM. THIS ROUTINE IS A
13C6         8650 ; MODIFICATION OF A ROUTINE FROM A 'BYTE' ARTICLE
13C6         8660 ; BY JOHN BEETEM IN THE OCTOBER 1980 ISSUE.
13C6         8670 ;
13C6         8680 ; THE BASIS OF THIS ALGORITHM IS THAT IT SUBDIVIDES
13C6         8690 ; A LINE BY TWO, RECURSIVELY, UNTIL THEY CAN PLOT
13C6         8700 ; AS A SINGLE POINT. IT THEN REPEATS ITSELF ON
13C6         8710 ; OTHER LINE SEGMENTS UNTIL THE LINE IS FINISHED.
13C6         8715 ; 40 BYTES OF STACK USAGE IS NEEDED FOR THIS ROUTINE.
13C6         8720 ;
13C6         8730 ;TWO ENTRY MODES ARE PROVIDED:
13C6         8740 ; MODE 1 --- 'VEC1' --- THE TWO ENDPOINTS ARE ENTERED
13C6         8750 ; ON THE STACK. PUSH THE POINTS ON THE STACK
13C6         8760 ; FOLLOWED BY THE RETURN ADDRESS.
13C6         8770 ; MODE 2 --- 'VEC2' --- ENTER THE TWO ENDPOINTS
13C6         8775 ; AS FOLLOWS:
13C6         8780 ; POINT 1 IN DE (X COMPONENT IS D)
13C6         8790 ; POINT 2 IN HL (Y COMPONENT IS L)
13C6         8800 ;
13C6         8900 :VEC1 ;HIGHER LEVEL PROGRAM ENTRY POINT
13C6 M 8910 POP DE ;GET 1ST POINT
13C7 E1      8920 POP HL ;GET 2ND POINT
13C8 CDCC13  8930 CALL VEC2
13CB C9      8940 RET ;RETURN TO HIGHER LEVEL CALLING PROGRAM
13CC         8950 ;
13CC         8960 :VEC2 ;BASE LINE DRAWING ROUTINE
13CC 010000  8970 LD BC,0 ;STACK FINISHED FLAG
13CF C5      8980 PUSH BC
13D0 7A      8990 LD A,D
13D1 BC      9000 CP H ;MAKE DE THE SMALLER #
13D2 3807    9010 JR .C,NOXG
13D4 2004    9020 JR .NZ,XNG
13D6 7B      9030 LD A,E
13D7 BD      9040 CP L
13D8 3801    9050 JR .C,NOXG
13DA EB      9060 :XNG EX DE,HL ;TRADE DE WITH HL
13DB         9070 :NOXG ;CHOOSE LOOP1 OR LOOP2 BASED
13DB         9080 ; RELATIVE Y-COORDINATE VALUES
13DB E5      9090 PUSH HL
13DC C1      9100 POP BC ;BC=HL
13DD 7B      9110 LD A,E
13DE B9      9120 CP C
13DF 3828    9130 JR .C,LOOP2
13E1         9140 ;
13E1         9150 :LOOP1
13E1 7A      9160 LD A,D ;COMPARE X-VALUES
13E2 B8      9170 CP B
13E3 2812    9180 JR .Z,EQX1

```

More →

TYPRINTER 450 **\$2100**
 45 CHAR/SEC DAISYWHEEL PRINTER/
 TERMINAL. RS232; IDEAL FOR WORD
 PROCESSING; WILL SUPPORT DIABLO,
 QUME, AND NEC PROTOCOLS

TYPRINTER 550 **\$2300**
 SAME AS ABOVE BUT
 55 CHAR/SEC PRINT SPEED

QUME **\$1000**
 55 CHAR/SEC OEM PRINTER MECHANISM

**SHUGART 8" FLOPPY
 DISK DRIVES** **\$360**
 SA800 SOFT-SECTORED
 SINGLE/DOUBLE DENSITY

MICROSWITCH KEYBOARDS **\$85**
 HALL EFFECT. ASCII MOD. 74SW12

INTERFACE **\$325**
 OEM DAISYWHEEL PRINTER INTER-
 FACE. INTERFACES DIABLO OR
 QUME OEM PRINTER TO RS232 OR
 CENTRONICS PARALLEL

RIBBONS **\$2.50**
 DIABLO HYTYPE 1 OR QUME. CLOTH
 OR MULTI/STRIKE. 1 DOZ. MINIMUM

COMPUTER DYNAMICS, INC.
 211 WHITE WATER
 GREER, S.C. 29651 • (803) 244-7872 ✓370

System Software Design, Inc.
 presents
 Ultimate Data System
 for

- The Apple II* computer with
 - Applesoft* in ROM or Language System*
 - 48K of RAM
 - 2 Disk Drives
 - Optional Printer
 - This easy-to-use data manager will make
 - General ledger
 - Mailing lists
 - Inventory
 - Any other data related tasks
 quick and efficient to manage
 - Seek times under 1/2 second for data lists
 up to 7500 records
 - Many more fast and powerful features
 - Single copy \$100.00
 - Dealer terms available
- Write to:
 System Software Design, Inc.
 124 Eleventh St.
 Providence, R.I. 02906

*T.M. of Apple Computer Inc.

✓367

No. 6
UNBELIEVABLE
OPPORTUNITY!

*If You've Written
 a Useful Program--
 We'd Like to Publish It!*

**We want programs for
 INDUSTRIAL applications:**

**JOB COST ESTIMATES
 INDUSTRIAL (PROCESS) CONTROL
 JOB TRACKING
 MACHINE SCHEDULING**

**Get published and earn royalties!
 Write for our free Programmer's
 Kit today.**

INSTANT SOFTWARE, INC. ✓75
Submissions Dept.
Peterborough, NH 03458

Call For Manuscripts

Kilobaud Microcomputing is looking for business articles!

Businessmen in all fields are beginning to take notice of the micro-computer. They are eager to know which computers, peripheral equipment and applications software will let them take full advantage of this new tool. What knowledge do you have to share?

Here are the kinds of articles that we want you to write for us:

- Are you a businessman with a system up and running? We want to know how it works. What were your expectations? Have they been fulfilled? Did you find the software that you wanted? What problems have you had? How did you overcome them? What recommendations do you have for other businessmen?

- We want reviews from a businessman's perspective of specific hardware and software. If you've recently bought a new product and want to tell others how great—or poor—it is, *Microcomputing* will provide you with a forum.

- What programs have you written to meet your specific needs? Perhaps another businessman can use them, too. Even if he can't, your program may serve as a springboard for other ideas.

- Perhaps you aren't using your micro for business, but know a company that is. Trot on down with your pencil and notebook, and find out what they're up to. While they might not have the time to write up their experiences, they might be more than willing to tell somebody else about them. And an outside observer will often be able to see things with a unique and valuable perspective.

Don't worry if you're not a professional writer. That's what we editors are here for. And we'll be more than happy to send you a copy of our writer's guidelines.

Send your manuscripts and correspondence to:

Kilobaud Microcomputing
Pine St.
Peterborough, NH 03458

Listing 2 continued.

```

13E5 C5
13E6 80
13E7 1F
13E8 47
13E9 3C
13EA 67
13EB 7B
13EC B9
13ED 2804
13EF 81
13F0 1F
13F1 4F
13F2 0C
13F3 6F
13F4 E5
13F5 18EA
13F7 7B
13F8 B9
13F9 2804
13FB C5
13FC 62
13FD 18F0
13FF CD4B13
1402 D1
1403 7A
1404 B3
1405 C8
1406 C1
1407 18D8
1409
1409
1409
1409 7A
140A B8
140B 2812
140D C5
140E 80
140F 1F
1410 47
1411 3C
1412 67
1413 7B
1414 B9
1415 2804
1417 81
1418 1F
1419 4F
141A 3C
141B 6F
141C E5
141D 18EA
141F 7B
1420 B9
1421 2804
1423 C5
1424 62
1425 18F0
1427 CD4B13
142A D1
142B 7A
142C B3
142D C8
142E C1
142F 18D8
1431 D1
1432 CD4B13
1435 C9

9190 PUSH BC ;SINCE X1#X2, SAVE OLD 2ND POINT
9200 ADD A,B ; AS FUTURE 1ST POINT
9210 RRA ;COMPUTE X HALFWAY POINT
9220 LD B,A ;INSTALL AS NEW 2ND X
9230 INC A ;INCR TO FORM X-MIDPOINT
9240 LD H,A ;INSTALL NEW X-MIDPOINT
9250 LD A,E ;NOW X1#X2, SO COMPARE Y VALUES
9260 CP C
9270 JR .Z,EQY1 ;JMP IF NEW Y-MID NOT NEEDED
9280 :NEQY1 ADD A,C ;SINCE Y1#Y2,
9290 RRA ;COMPUTE NEW Y-MIDPOINT
9300 LD C,A ;PUT INTO C AND
9310 INC C ;INCR TO FORM NEW Y2
9320 :EQY1 LD L,A ;SINCE NEITHER X'S OR Y'S EQUAL
9330 PUSH HL ;SAVE MIDPOINT AS FUTURE 2ND POINT
9340 JR LOOP1 ;CONTINUE ON DIFFERENT SEGMENT
9350 :EQX1 LD A,E ;SINCE X1=X2, THEN COMPARE
9360 CP C ; Y VALUES.
9370 JR .Z,EQXY1 ;IF Y1=Y2, JMP AND PLOT
9380 PUSH BC ;OTHERWISE, SAVE 2ND POINT AS FUTURE
9390 LD H,D ; 1ST POINT. MAKE MIDPOINT X=X1
9400 JR NEQY1
9410 :EQXY1 CALL DRAW ;PLOT COORDINATES IN DE
9420 POP DE ;RETRIEVE ANOTHER SEGMENT'S 1ST POINT
9430 LD A,D ;CHECK IF STACK EMPTY
9435 OR E
9440 RET .Z ;DONE IF ZERO
9450 POP BC ;RETRIEVE ANOTHER SEGMENT'S 2ND POINT
9460 JR LOOP1 ;JP BACK TO KEEP MAKING LINE
9500
9510 :LOOP2 ;SAME INSTS AS LOOP1 EXCEPT LINE 9680,
9520 ; SO THE REMARKS WILL BE OMMITTED.
9530 LD A,D
9540 CP B
9550 JR .Z,EQX2
9560 PUSH BC
9570 ADD A,B
9580 RRA
9590 LD B,A
9600 INC A
9610 LD H,A
9620 LD A,E
9630 CP C
9640 JR .Z,EQY2
9650 :NEQY2 ADD A,C
9660 RRA
9670 LD C,A
9680 INC A ;THIS STATEMENT IS DIFFERENT THAN LOOP1
9690 :EQY2 LD L,A
9700 PUSH HL
9710 JR LOOP2
9720 :EQX2 LD A,E
9730 CP C
9740 JR .Z,EQXY2
9750 PUSH BC
9760 LD H,D
9770 JR NEQY2
9780 :EQXY2 CALL DRAW
9790 POP DE
9800 LD A,D
9810 OR E
9820 RET .Z
9830 POP BC
9840 JR LOOP2
10000 POP DE
10010 CALL DRAW
10020 RET

BACK1 0406 ADVI 115D ADVII 116B ADVIII 116F
BUFHI 108D BACKSP 1082 BELLS 110B BUFFER BFF0
CHAR2 0004 BUFLO 0003 BUF)HL 124C CALCUR 11A1
CHAR2 1124 CHAR4 1132 CHAR6 1139 CHARLD 1146
CHAROT 1116 CHARS 12D9 CHARTR 0007 CHIP 1320
CLR1 1214 CLRLIN 1206 CLRMEM 12A2 CLRMM1 12A8
CLRRW 11F6 CMDVCT 1058 COLUMN 000C CRR2 1100
CRRTN 10EA CURHI 0009 CURLO 0008 CURSLD 121A
CUR)HL 1276 DE)VID 123E DOT3 1391 DOT4 139A
DOT5 139F DOTA 1363 DOTB 137B DOTB1 1380
DOTS 1328 DOTS1 132F EQX1 13FF EQXY1 13FF EQXY2 1427
EQX1 13F7 EQY2 141B EXIT 107B FWD1 10A6
EQY1 13F3 GRAPH 1284 HL)BUF 1245 HL)CUR 126F
FWDSP 109B HL)ROW 1261 HOME 10D9 HOMHI 0006
HL)HOM 1253 HOMLO 0005 HOM)HL 125A INITBF 12B0
HOMLD 122C LAST4 10C1 LASTRW 10B4 LOC 1030 LOOP1 13E1
LAST4 10C1 LITRS 1294 MASK8K 127D NEQY1 13EF
LOOP2 1409 NEXT4 10D5 NEXTRW 10C5 NOXG 13DB
NEQY2 1417 REGI 1180 REGIII 118E ROLLDN 11DA
PLOTTR 000D ROWHI 000B ROWLO 000A ROW)HL 1268
ROLLUP 11B0 RWMAXL 0030 SETDOT 13A4 SPACE 1205
RWMAXH 0007 UNDOT 1382 UNDOT3 13B3 UNDOT4 13BC
SPARE 0000 UNDRAW 1357 VEC1 13C6 VEC2 13CC
UNDOT5 13C1 VIDEO C000 VIDHI 0002 VIDLO 0001
VECTOR 106D
XNG 13DA

```


kb microcomputing book nook



new —Z-80—

• **TRS-80 ASSEMBLY LANGUAGE**—BK1217—by Hubert S. Howe, Jr. This book incorporates into a single volume all the pertinent facts and information you need to know to program and enjoy the TRS-80. Included are clear presentations of all introductory concepts, completely tested practical programs and subroutines, details of ROM and RAM and disk operating systems, plus comprehensive tables, charts and appendices. Suitable for the first time user or more experienced users. \$9.95.*

• **INSIDE LEVEL II**—BK1183—For machine language programmers! This is a comprehensive reference guide to the Level II ROMs, allowing easy utilization of the sophisticated routines they contain. It concisely explains set-ups, calling sequences, variable passage and I/O routines. Part II presents an entirely new composite program structure which unloads under the SYSTEM command and executes in both BASIC and machine code with the speed and efficiency of a compiler. Special consideration is given to disk systems. \$15.95.*

• **PROGRAMMING THE Z-80**—BK1122—by Rodnay Zaks. Here is assembly language programming for the Z-80 presented as a progressive, step-by-step course. This book is both an educational text and a self-contained reference book, useful to both the beginning and the experienced programmer who wish to learn about the Z-80. Exercises to test the reader are included. \$14.95.*

• **Z-80 SOFTWARE GOURMET GUIDE AND COOKBOOK**—BK1045—by Nat Wadsworth. Scelbi's newest cookbook! This book contains a complete description of the powerful Z-80 instruction set and a wide variety of programming information. Use the author's ingredients including routines, subroutines and short programs, choose a time-tested recipe and start cooking! \$16.99.*

• **Z-80 ASSEMBLY LANGUAGE PROGRAMMING**—BK1177—by Lance A. Leventhal. This book thoroughly covers the Z-80 instruction set, abounding in simple programming examples which illustrate software development concepts and actual assembly language usage. Features include Z-80 I/O devices and interfacing methods, assembler conventions, and comparisons with 8080A/8085 instruction sets and interrupt structure. \$16.99.*

• **VOL. I COMPONENT TESTERS**—LB7359—... how to build transistor testers (8), diode testers (3), IC testers (3), voltmeters and VTVMs (9), ohmmeters (8 different kinds), inductance (3), capacity (9), Q measurement, crystal checking (6), temperature (2), aural meters for the blind (3) and all sorts of miscellaneous data on meters... using them, making them more versatile, making standards. Invaluable book. \$4.95.*

• **VOL. II AUDIO FREQUENCY TESTERS**—LB7360—... jam packed with all kinds of audio frequency test equipment. If you're into SSB, RTTY, SSTV, etc., this book is a must for you... a good book for hi-fi addicts and experimenters, too! \$4.95.*

• **VOL. III RADIO FREQUENCY TESTERS**—LB7361—Radio frequency waves, the common denominator of Amateur Radio. Such items as SWR, antenna impedance, line impedance, rf output and field strength; detailed instructions on testing these items includes sections on signal generators, crystal calibrators, grid dip oscillators, noise generators, dummy loads and much more. \$4.95.*

• **VOL. IV IC TEST EQUIPMENT**—LB7362—Become a troubleshooting wizard! In this fourth volume of the 73 TEST EQUIPMENT LIBRARY are 42 home construction projects for building test equipment to work with your ham station and in servicing digital equipment. Plus a cumulative index for all four volumes for the 73 TEST EQUIPMENT LIBRARY. \$4.95.*

PROGRAMMING

The Microprocessor Software Engineering Series by John Zarrella provides common sense descriptions of advanced computer system topics for engineers, programmers and development managers. Each volume is a self-contained review of a software engineering topic, explaining fundamental concepts in easy-to-understand language and describing sophisticated software tools and techniques. Detailed glossary of technical jargon is included in each volume. This series will help you find the solutions to your software problems.

• **OPERATING SYSTEMS: CONCEPTS AND PRINCIPLES**—BK1193—Presents an overview of the basic operating system types, their components and capabilities. \$7.95.*

• **WORD PROCESSING AND TEXT EDITING**—BK1194—Provides a firm basis for understanding word processing terminology and for comparing systems. \$7.95.*

• **SYSTEM ARCHITECTURE**—BK1195—Presents a detailed overview of advanced computer system design including object architecture and capability-based addressing. \$9.95.*

—6502—

* • **THE APPLE II USER'S GUIDE**—BK1220—by Lon Poole, Martin McNiff, and Steven Cook. This guide is the key to unlocking the full power of your Apple II or Apple II Plus. Topics include: "Applesoft and Integer BASIC Programming"—especially how to make the best use of Apple's sound, color and graphics capabilities. "Machine Level Programming." "Hardware Features"—which covers the disk drive and printer, and "Advanced Programming"—describing high resolution graphics techniques and other advanced applications. Well organized and easy to use. \$15.00.*

• **PROGRAMMING THE 6502 (Third Edition)**—BK1005—Rodnay Zaks has designed a self-contained text to learn programming, using the 6502. It can be used by a person who has never programmed before, and should be of value to anyone using the 6502. The many exercises will allow you to test yourself and practice the concepts presented. \$12.95.*

• **6502 APPLICATIONS BOOK**—BK1006—Rodnay Zaks presents practical-application techniques for the 6502 microprocessor, assuming an elementary knowledge of microprocessor programming. You will build and design your own domestic-use systems and peripherals. Self-test exercises included. \$12.95.*

• **6502 ASSEMBLY LANGUAGE PROGRAMMING**—BK1176—by Lance A. Leventhal. This book provides comprehensive coverage of the 6502 microprocessor assembly language. Leventhal covers over 80 programming examples from simple memory load loops to complete design projects. Features include 6502 assembler conventions, input/output devices and interfacing methods, and programming the 6502 interrupt system. \$16.99.*

• **6502 SOFTWARE GOURMET GUIDE AND COOKBOOK**—BK1055—by Robert Findley. This book introduces the BASIC language programmer into the realm of machine-language programming. The description of the 6502 structure and instruction set, various routines, subroutines and programs are the ingredients in this cookbook. "Recipes" are included to help you put together exactly the programs to suit your taste. \$12.95.*

• **MICROCOMPUTING CODING SHEETS** Microcomputing's dozen or so programmers wouldn't try to work without these handy scratch pads, which help prevent the little errors that can cost hours and hours of programming time. Available for programming is Assembly/Machine Language (PD1001), which has columns for address, instruction (3 bytes), source code (label, op code, operand) and comments; and for BASIC (PD1002) which is 72 columns wide. 50 sheets to a pad. \$2.39.*

—8080/8080A—6800—

* • **6809 MICROCOMPUTER PROGRAMMING AND INTERFACING**—BK1215—by Andrew C. Staugaard, Jr. Getting involved with Tandy's new Color Computer? If so, this new book from the Blacksburg Group will allow you to exploit the awesome power of the machine's 6809 microprocessor. Detailed information on processor architecture, addressing modes, register operation, data movement, arithmetic logic operations, I/O and interfacing is provided, as well as a review section at the end of each chapter. Four appendices are included covering the 6809 instruction set, specification sheets of the 6809 family of processors, other 6800 series equipment and the 6809/6821 Peripheral Interface Adapter. This book is a must for the serious Color Computer owner. \$13.95.*

* • **68000 MICROPROCESSOR HANDBOOK**—BK1216—by Gerry Kane. Whether you're currently using the 68000, planning to use it, or simply curious about one of the newest and most powerful microprocessors, this handbook has all the answers. A clear presentation of signal conversions, timing diagram conventions, functional logic, three different instruction set tables, exception processing, and family support devices provides more information about the 68000 than the manufacturer's data sheets. A stand alone reference book which can also be used as a supplement to *An Introduction to Microcomputers: Vol. 2—Some Real Microprocessors*. \$6.99.*

• **8080A/8085 ASSEMBLY LANGUAGE PROGRAMMING**—by Lance Leventhal—BK1004—Assembly language programming for the 8080A/8085 is explained with a description of the functions of assemblers and assembly instructions, and a discussion of basic software development concepts. Many fully debugged, practical programs are included as is a special section on structured programming. \$15.99.*

• **8080 SOFTWARE GOURMET GUIDE AND COOKBOOK**—BK1102—If you have been spending too much time developing simple routines for your 8080, try this new book by Scelbi Computing and Robert Findley. Describes sorting, searching, and many other routines for the 8080 user. \$12.95.*

—COOKBOOKS—

• **CMOS COOKBOOK**—BK1011—by Don Lancaster. Details the application of CMOS, the low power logic family suitable for most applications presently dominated by TTL. Required reading for every serious digital experimenter! \$10.50.*

• **TVT COOKBOOK**—BK1064—by Don Lancaster. Describes the use of a standard television receiver as a microprocessor CRT terminal. Explains and describes character generation, cursor control and interface information in typical, easy-to-understand Lancaster style. \$9.95.*

• **TTL COOKBOOK**—BK1063—by Don Lancaster. Explains what TTL is, how it works, and how to use it. Discusses practical applications, such as a digital counter and display system, events counter, electronic stopwatch, digital voltmeter and a digital tachometer. \$9.50.*

* Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to Kilobaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.

No C.O.D. orders accepted. All orders add \$1.50 handling. Please allow 4-6 weeks for delivery. Questions regarding your order? Please write to Customer Service at the above address.

PRICES SUBJECT TO CHANGE WITHOUT NOTICE



*** new**

FOR TOLL FREE ORDERING CALL 1-800-258-5473

kb microcomputing book nook

—BASIC & PASCAL—

—BUSINESS—



new

● **INTRODUCTION TO TRS-80 LEVEL II BASIC AND COMPUTER PROGRAMMING**—BK1219—by Michael P. Zabinski. Written by an experienced educator, this is the book for those beginners who want to learn about computers without having to become an expert. It has practical programs, useful line-by-line comments, excellent flowcharts accompanied by line numbers and over 200 exercises which help the reader assess progress, reinforce comprehension, and provide valuable practical experience. \$10.95.*

● **50 BASIC EXERCISES**—BK1192—by J. P. Lamoitier. This book is structured around the idea that the best way to learn a language is through actual practice. It contains 50 completely explained exercises: statement and analysis of the problem, flowcharts, programs and actual runs. Program subjects include mathematics, business, games, and operations research, and are presented in varying levels of difficulty. This format enables anyone to learn BASIC rapidly, checking their progress at each step. \$12.95.*

● **THE BASIC HANDBOOK**—BK1174—by David Lien. This book is unique. It is a virtual ENCYCLOPEDIA of BASIC. While not favoring one computer over another, it explains over 250 BASIC words, how to use them and alternate strategies. If a computer does not possess the capabilities of a needed or specified word, there are often ways to accomplish the same function by using another word or combination of words. That's where the HANDBOOK comes in. It helps you get the most from your computer, be it a "bottom-of-the-line" micro or an oversized monster. \$14.95.*

● **LEARNING LEVEL II**—BK1175—by David Lien. Written especially for the TRS-80, this book concentrates on Level II BASIC, exploring every important BASIC language capability. Updates are included for those who have studied the Level I User's Manual. Sections include: how to use the Editor, dual cassette operation, printers and peripheral devices, and the conversion of Level I programs to Level II. \$15.95.*

● **BASIC BASIC (2ND EDITION)**—BK1026—by James S. Coan. This is a textbook which incorporates the learning of computer programming using the BASIC language with the teaching of mathematics. Over 100 sample programs illustrate the techniques of the BASIC language and every section is followed by practical problems. This second edition covers character string handling and the use of data files. \$10.50.*

● **ADVANCED BASIC**—BK1000—Applications, including strings and files, coordinate geometry, area, sequences and series, simulation, graphing and games. \$10.75.*

● **SIXTY CHALLENGING PROBLEMS WITH BASIC SOLUTIONS (2nd Edition)**—BK1073—by Donald Spencer, provides the serious student of BASIC programming with interesting problems and solutions. No knowledge of math above algebra required. Includes a number of game programs, as well as programs for financial interest, conversions and numeric manipulations. \$6.95.*

new

● **PASCAL**—BK1188—by Paul M. Chirlian. Professor Chirlian's textbook combines a simple approach to the PASCAL language with comprehensive coverage on how a computer works, how to use a flowchart, working from a terminal as well as batch operation and debugging. Special attention is paid to idiosyncrasies of the language and syntax flowcharts abound for the convenience of the experienced programmer. Well indexed. \$12.95.*

● **INTRODUCTION TO PASCAL**—BK1189—by Rodnay Zaks. A step-by-step introduction for anyone wanting to learn the language quickly and completely. Each concept is explained simply and in a logical order. All features of the language are presented in a clear, easy-to-understand format with exercises to test the reader at the end of each chapter. It describes both standard PASCAL and UCSD PASCAL, the most widely used dialect for small computers. No computer or programming experience is necessary. \$14.95.*

● **PROGRAMMING IN PASCAL**—BK1140—by Peter Grogono. The computer programming language PASCAL was the first language to embody in a coherent way the concepts of structured programming, which has been defined by Edsger Dijkstra and C.A.R. Hoare. As such, it is a landmark in the development of programming languages. PASCAL was developed by Niklaus Wirth in Zurich; it is derived from the language ALGOL 60 but is more powerful and easier to use. PASCAL is now widely accepted as a useful language that can be efficiently implemented, and as an excellent teaching tool. It does not assume knowledge of any other programming language; it is therefore suitable for an introductory course. \$12.95.*

—GAMES—

● **40 COMPUTER GAMES**—BK7381—Forty games in all in nine different categories. Games for large and small systems, and even a section on calculator games. Many versions of BASIC used and a wide variety of systems represented. A must for the serious computer gamesman. \$7.95.*

● **BASIC COMPUTER GAMES**—BK1074—Okay, so once you get your computer and are running in BASIC, then what? Then you need some programs in BASIC, that's what. This book has 101 games for you from very simple to real buggers. You get the games, a description of the games, the listing to put in your computer and a sample run to show you how they work. Fun. Any one game will be worth more than the price of the book for the fun you and your family will have with it. \$7.50.*

● **MORE BASIC COMPUTER GAMES**—BK1182—edited by David H. Ahl. More fun in BASIC! 84 new games from the people who brought you BASIC Computer Games. Includes such favorites as Minotaur (battle the mythical beast) and Eliza (unload your troubles on the doctor at bargain rates). Complete with game description, listing and sample run. \$7.50.*


● **WHAT TO DO AFTER YOU HIT RETURN**—BK1071—PCC's first book of computer games... 48 different computer games you can play in BASIC... programs, descriptions, many illustrations. Lunar Landing, Hamurabi, King, Civel 2, Qubic 5, Taxman, Star Trek, Crash, Market, etc. \$10.95.*

● **PAYROLL WITH COST ACCOUNTING—IN BASIC**—BK1001—by L. Poole & M. Borchers, includes program listings with remarks, descriptions, discussions of the principle behind each program, file layouts, and a complete user's manual with step-by-step instructions, flowcharts, and simple reports and CRT displays. Payroll and cost accounting features include separate payrolls for up to 10 companies, time-tested interactive data entry, easy correction of data entry errors, job costing (labor of distribution), check printing with full deduction and pay detail, and 16 different printed reports, including W-2 and 941 (in CBASIC). \$20.00.*

● **SOME COMMON BASIC PROGRAMS**—BK1053—published by Adam Osborne & Associates, Inc. Perfect for non-technical computerists requiring ready-to-use programs. Business programs, plus miscellaneous programs. Invaluable for the user who is not an experienced programmer. All will operate in the stand-alone mode. \$14.99 paperback.

● **PIMS: PERSONAL INFORMATION MANAGEMENT SYSTEM**—BK1009—Learn how to unleash the power of a personal computer for your own benefit in this ready-to-use data-base management program. \$11.95.*

—MONEYMAKING—



● **HOW TO MAKE MONEY WITH COMPUTERS**—BK1003—In 10 information-packed chapters, Jerry Felsen describes more than 30 computer-related, money-making, high profit, low capital investment opportunities. \$15.00.*

● **HOW TO SELL ANYTHING TO ANYBODY**—BK7306—According to *The Guinness Book of World Records*, the author, Joe Girard, is "the world's greatest salesman." This book reveals how he made a fortune—and how you can, too. \$2.25.*

● **THE INCREDIBLE SECRET MONEY MACHINE**—BK1178—by Don Lancaster. A different kind of "cookbook" from Don Lancaster. Want to slash taxes? Get free vacations? Win at investments? Make money from something that you like to do? You'll find this book essential to give you the key insider details of what is really involved in starting up your own money machine. \$5.95.*

*Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to Kilobaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.


No C.O.D. orders accepted. All orders add \$1.50 handling. Please allow 4-6 weeks for delivery. Questions regarding your order? Please write to Customer Service at the above address.

PRICES SUBJECT TO CHANGE WITHOUT NOTICE

FOR TOLL FREE ORDERING CALL 1-800-258-5473

kb microcomputing book nook

—INTRODUCTION—



● **HOBBY COMPUTERS ARE HERE!**—BK7322—If you want to come up to speed on how computers work... hardware and software... this is an excellent book. It starts with fundamentals and explains the circuits, and the basics of programming, along with a couple of TVT construction projects, ASCII-Baudot, etc. This book has the highest recommendations as a teaching aid. \$4.95.*

● **THE NEW HOBBY COMPUTERS**—BK7340—This book takes it from where "HOBBY COMPUTERS ARE HERE!" leaves off, with chapters on Large Scale Integration, how to choose a microprocessor chip, an introduction to programming, low cost I/O for a computer, computer arithmetic, checking memory boards... and much, much more! Don't miss this tremendous value! Only \$4.95.*

● **AN INTRODUCTION TO MICROCOMPUTERS, VOL. 0**—BK1130—The Beginner's Book—Written for readers who know nothing about computers—for those who have an interest in how to use computers—and for everyone else who must live with computers and should know a little about them. The first in a series of 4 volumes, this book will explain how computers work and what they can do. Computers have become an integral part of life and society. During any given day you are affected by computers, so start learning more about them with Volume 0. \$7.95.*

● **VOL. I—BK1030—2nd Edition completely revised.** Dedicated to the basic concepts of microcomputers and hardware theory. The purpose of Volume I is to give you a thorough understanding of what microcomputers are. From basic concepts (which are covered in detail), Volume I builds the necessary components of a microcomputer system. This book highlights the difference between minicomputers and microcomputers. \$12.99.*

● **VOL. II—BK1040 (with binder)**—Contains descriptions of individual microprocessors and support devices used only with the parent microprocessor. Volume II describes all available chips. \$31.99*

● **VOL. III—BK1133 (with binder)**—Contains descriptions of all support devices that can be used with any microprocessor. \$21.99*

● **UNDERSTANDING AND PROGRAMMING MICROCOMPUTERS**—BK7382—A valuable addition to your computing library. This two-part text includes the best articles that have appeared in 73 and KiloBaud Microcomputing magazines on the hardware and software aspects of microcomputing. Well-known authors and well-structured text helps the reader get involved. \$10.95*


● **SOME OF THE BEST FROM KILOBAUD MICROCOMPUTING**—BK7311—A collection of the best articles that have appeared in KiloBaud MicroCOMPUTING. Included is material on the TRS-80 and PET systems, CP/M, the 8080/8085/Z-80 chips, the ASR-33 terminal. Data base management, word processing, text editors and file structures are covered too. Programming techniques and hard-core hardware construction projects for modems, high speed cassette interfaces and TVTs are also included in this large format, 200 plus page edition. \$10.95.*

new

● **YOUR FIRST COMPUTER**—BK1191—by Rodney Zaks. Whether you are using a computer, thinking about using one or considering purchasing one, this book is indispensable. It explains what a computer system is, what it can do, how it works and how to select various components and peripheral units. It is written in everyday language and contains invaluable information for the novice and the experienced programmer. (The first edition of this book was published under the title "An Introduction to Personal and Business Computing".) \$7.95*

● **MICROPROCESSOR INTERFACING TECHNIQUES**—BK1037—by Austin Lesea & Rodney Zaks—will teach you how to interconnect a complete system and interface it to all the usual peripherals. It covers hardware and software skills and techniques, including the use and design of model buses such as the IEEE 488 or S-100. \$15.95.*

—SPECIAL INTERESTS—



● **TRS-80 DISK AND OTHER MYSTERIES**—BK1181—by Harvard C. Pennington. This is the definitive work on the TRS-80 disk system. It is full of detailed "How to" information with examples, samples and in-depth explanations suitable for beginners and professionals alike. The recovery of one lost file is worth the price alone. \$22.50.*

● **MICROSOFT BASIC DECODED AND OTHER MYSTERIES**—BK1186—by James Favour. From the company that brought you TRS-80 DISK AND OTHER MYSTERIES! Contains more than 6500 lines of comments for the disassembled Level II ROMs, six additional chapters describing every BASIC subroutine, with assembly language routines showing how to use them. Flowcharts for all major routines give the reader a real insight into how the interpreter works. \$29.50.


new

● **THE CUSTOM TRS-80 AND OTHER MYSTERIES**—BK1218—by Dennis Kitz. More than 300 pages of TRS-80 customizing information. With this book you'll be able to explore your computer like never before. Want to turn an 8 track into a mass storage unit? Individual reverse characters? Replace the BASIC ROMs? Make Music? High speed, reverse video, Level I and Level II? Fix it if it breaks down? All this and much, much more. Even if you have never used a soldering iron or read a circuit diagram, this book will teach you how! This is the definitive guide to customizing your 80! \$29.95.*

● **BASIC FASTER AND BETTER AND OTHER MYSTERIES**—BK1221—by Lewis Rosenfelder. You don't have to learn assembly language to make your programs run fast. With the dozens of programming tricks and techniques in this book you can sort at high speed, swap screens in the twinkling of an eye, write INKEY routines that people think are in assembly language and add your own commands to BASIC. Find out how to write elegant code that makes your BASIC really hum, and explore the power of USR calls. \$22.50.* Available end of August.

● **THE CP/M HANDBOOK (with MP/M)**—BK1187—by Rodney Zaks. A complete guide and reference handbook for CP/M—the industry standard in operating systems. Step-by-step instruction for everything from turning on the system and inserting the diskette to correct user discipline and remedial action for problem situations. This also includes a complete discussion of all versions of CP/M up to and including 2.2, MP/M and CDOS. \$14.95.*

● **INTRODUCTION TO TRS-80 GRAPHICS**—BK1180—by Don Inman. Dissatisfied with your Level I or Level II manual's coverage of graphics capabilities? This well-structured book (suitable for classroom use) is ideal for those who want to use all the graphics capabilities built into the TRS-80. A tutorial method is used with many demonstrations. It is based on the Level I, but all material is suitable for Level II use. \$8.95.*



● **TOOLS & TECHNIQUES FOR ELECTRONICS**—BK7348—by A. A. Wicks is an easy-to-understand book written for the beginning kit builder as well as the experienced hobbyist. It has numerous pictures and descriptions of the safe and correct ways to use basic and specialized tools for electronic projects as well as specialized metal working tools and the chemical aids which are used in repair shops. \$4.95.*

● **HOW TO BUILD A MICROCOMPUTER—AND REALLY UNDERSTAND IT**—BK7325—by Sam Creason. The electronics hobbyist who wants to build his own microcomputer system now has a practical "How-To" guidebook. This book is a combination technical manual and programming guide that takes the hobbyist step-by-step through the design, construction, testing and debugging of a complete microcomputer system. Must reading for anyone desiring a true understanding of small computer systems. \$9.95.*

*Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to KiloBaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.

No C.O.D. orders accepted. All orders add \$1.50 handling. Please allow 4-6 weeks for delivery. Questions regarding your order? Please write to Customer Service at the above address.

PRICES SUBJECT TO CHANGE WITHOUT NOTICE

FOR TOLL FREE ORDERING CALL 1-800-258-5473

TWO SIZZLING SPECIALS

FOR THE IEEE 696/S-100 BUS: CPU Z for \$199!

older systems, **CPU Z** is backward compatible with most S-100 mainframes, down to a switch selectable choice of 2 or 4 MHz operation—there's even a plug that accepts the connector from an IMSAI front panel.

Here's one deal you can't afford to pass up. . . visit your local **CompuPro** representative, or order direct from the factory, but hurry—quantities are limited.

CPU Z hardly needs any introduction—since the day we introduced this Z80* workhorse, professional systems integrators have made it the CPU board of choice for high performance 8 bit systems.

What is new is the price: Until September 30th, **CPU Z** (assembled) is yours for an amazingly low **\$199!**

For new systems, **CPU Z's** superior flexibility (24 bit addressing, sockets for adding up to 8 Kbytes of on-board RAM or ROM, 4 MHz operation, on-board fully maskable interrupts, and much more) puts it miles ahead of the competition. For upgrading

FOR MEMORY EXPANSION: EIGHT 16K DYNAMIC RAMS for \$19.95!

You can't beat the quality or the price: eight low power, high speed dynamic RAMs, suitable for expanding memory in TRS-80* -I, -II, and -III (color computer too); H89; Apple; newer PETs; etc. Backed by 1 year limited warranty. Add \$3 for two DIP shunts plus TRS-80 conversion instructions.

IEEE 696/S-100 COMPONENT LEVEL PRODUCTS

DISK EQUIPMENT/SYSTEMS

Disk 1 Controller Board Ultra-fast operation, thanks to properly implemented DMA (with arbitration) and data transfer that's independent of CPU speed. Handles up to four 8" or 5.25" floppy disk drives, single or double-sided, single or double density (soft sector). Includes BIOS for CP/M-80 (provided on 8" soft sector diskette). Manual only: \$25. A/T \$495, CSC \$595.

Available only with Disk 1 purchase: CP/M-80 diskette with documentation, \$175; CP/M-86 diskette with documentation, \$300.

Complete Dual Disk Drive System With Disk 1 board, desktop dual drive enclosure with Shugart SA-800 series drives, disk cables, and power supply cable. Also includes CP/M-80. Introductory special: \$2195.

COMPUTER ENCLOSURES

Computer Enclosure 2. With fused, constant voltage power supply (+8V at 25A, +16V at 3A, and -16V at 3A); line filter; 20 slot shielded/active terminated motherboard; and rugged, all-metal enclosure that minimizes interference problems. \$825 desk top version, \$895 rack mount version.

Computer Enclosure 1. Same as CE2, but enclosure only. \$289 desktop, \$329 rack mount (slides included).

INTERFACERS

Interfacer 1. Two RS-232 serial ports, with full handshaking and independently selectable Baud rates. \$199 Unkit, \$249 A/T, \$324 CSC.

Interfacer 2. Three full duplex parallel ports, plus one serial port. \$199 Unkit, \$249 A/T, \$324 CSC.

Interfacer 3-5. Five RS-232 serial ports (2 synchronous/asynchronous, 3 asynchronous) with full handshaking. \$599 A/T, \$699 CSC.

Interfacer 3-8. Eight full RS-232 serial ports (2 synchronous/asynchronous, 6 asynchronous). Ideal for multi-user/multi-terminal systems. \$699 A/T, \$849 CSC.

MEMORY BOARDS

48K/64K RAM 17 Static Memory Board. Exceptionally low power (4W max, 2W typ for 64K), high speed static memory; runs faster, cooler, and handles DMA better in ultra-high speed systems than competing dynamic memory boards. **RAM 17-48K:** \$1048 A/T, \$1198.50 CSC. **RAM 17-64K:** \$1095 Unkit, \$1395 A/T, \$1595 CSC.

96K/128K RAM 21 Static Memory Board. Exceptionally low power, high speed static memory. **RAM 21-96K** and **RAM 21-128 K:** Price upon request.

2708 EPROM Board. This board is the way to store often used routines or pieces of software. \$85 Unkit, \$135 A/T, \$195 CSC (2708s not included).

DOCUMENTATION

User manuals are available for all products for \$5, with the following exceptions: **Interfacer 3**, \$10; **Disk Controller**, \$25; **System Support 1**, \$20. Also available: "CompuPro Product User Manuals: 1975-1980", 250+ pages on all Godbout/CompuPro products up through 1980. Excellent for evaluating the innovative engineering behind CompuPro products, or studying the nuts and bolts of high speed computer operation. \$20 plus shipping.

FLASH! Phase 1's single- and multi-user Oasis operating system is now available configured for Disk 1. See next month for full details and prices.

Most CompuPro products are available in Unkit form, Assembled/Tested, or qualified under the high-reliability Certified System Component (CSC) program (200 hour, burn-in, more). Note: Unkits are not intended for novices, as de-bugging may be required due to problems such as IC infant mortality. Factory service is available for Unkits at a flat service charge.

TERMS: Prices shown do not include dealer installation and support services. Cal res add tax. Allow at least 5% shipping; excess refunded. Orders under \$15 add \$2 handling. VISA® and Mastercard® orders (\$25 min) call our 24 hour order desk at (415) 562-0636. Include street address for UPS delivery. Prices and specifications subject to change without notice.

*LEGAL CORNER: Z-80 is a registered trademark of Zilog; CP/M is a registered trademark of Digital Research; TRS-80 is a trademark of the Tandy Corporation.

If your computer store doesn't stock CompuPro products yet,
call (415) 562-0636 and we'll tell you who does.

CompuPro™
BOX 2355, OAKLAND AIRPORT, CA 94614


✓ 42
division of

GODBOUNT
ELECTRONICS

(415) 562-0636

TRS-80 SERIAL I/O

- Can input into basic
- Can use LLIST and LPRINT to output, or output continuously
- RS-232 compatible
- Can be used with or without the expansion bus
- On board switch selectable baud rates of 110, 150, 300, 600, 1200, 2400, parity or no parity odd or even, 5 to 8 data bits, and 1 or 2 stop bits. D.T.R. line
- Requires +5, -12 VDC
- Board only \$19.95 Part No. 8010, with parts \$76.69 Part No. 8010A, assembled \$98.25 Part No. 8010 C. No connectors provided, see below.



EIA/RS-232 connector Part No. DB25P \$5.00, with 9' 5 conductor cable \$19.65 Part No. DB25P9.




3' Ribbon cable with attached connectors to fit TRS-80 and our serial board \$37.10 Part No. 3CAB40.

VIDEO TERMINAL




16 lines, 64 columns • Upper and lower case • 5x7 dot matrix • Serial RS-232 in and out with TTL parallel keyboard input • On board baud rate generator 75, 110, 150, 300, 600, & 1200 jumper selectable • Memory 1024 characters (7-21L02) • Video processor chip SFF96364 by Neculonic • Control characters (CR, LF, →, ←, ↑, ↓, non destructive cursor, CS, home, CL) • White characters on black background or vice-versa • With the addition of a keyboard, video monitor or TV set with TV interface (part no. 107A) and power supply this is a complete stand alone terminal • also S-100 compatible • requires +16, & -16 VDC at 100mA, and 8VDC at 1A. Part No. 1000A \$296.45 kit.

GAME PADDLES & SOUND FOR TRS-80



Includes: 2 game paddles, interface, software, speaker, power supply, full documentation including: schematics, theory of operation, and user guide; plus 2 games on cassette, Pong and Starship War \$157.29 Complete Part No. 7922C

SERIAL/ PARALLEL INTERFACE




- Converts serial to parallel and parallel to serial
- Low cost on board baud rate generator
- 110 to 19.2K
- Low power drain +5 volts and -12 volts required
- TTL compatible
- All characters contain a start bit, 5 to 8 data bits, 1 or 2 stop bits, and either odd or even parity.
- All connections go to a 44 pin gold plated edge connector
- Board only \$11.95 Part No. 101, with parts \$42.89 Part No. 101A, 44 pin edge connector \$4.00 Part No. 44P

MODEM



- Type 103
- Full or half duplex
- Works up to 300 baud
- Originate or Answer
- Serial TTL input and output
- connect 8 Ω speaker and crystal mic. directly to board
- Requires +5 volts
- Board only \$7.60 Part No. 109, with parts \$29.95 Part No. 109A.

OPTO-ISOLATED PARALLEL INPUT BOARD FOR APPLE II



Part No. 120, with parts \$69.95. Part No. 120A.


There are 8 inputs that can be driven from TTL logic or any 5 volt source. The circuit board can be plugged into any of the 8 sockets of your Apple II. It has a 16 pin socket for standard dip ribbon cable connection. Board only \$15.65

SUPER MODEM




Originate, RS-232 and 20 mA compatible. Full duplex, and half duplex, direct connect or acoustic coupled, on board power supply, carrier detect light, DB25 plug, 300 BAUD, Type 103 compatible frequencies. Bare board Part No. 2000 \$21.89, Kit Part No. 2000A \$133.80

8K EPROM SAVER




- Programs 2708's address relocation of each 4K of memory to any 4K boundary
- Power on jump and reset jump option for "turnkey" systems and computers without a front panel
- Program saver software in 1 2708 EPROM \$25. Bare board \$45.59 including custom coil, board with parts but no EPROMS \$164.69.

APPLE II SERIAL I/O INTERFACE



Baud rate is continuously adjustable from 0 to 30,000 • Plugs into any peripheral connector • Low current drain. RS-232 input and output • On board switch selectable 5 to 8 data bits, 1 or 2 stop bits, and parity or no parity either odd or even • Jumper selectable address • SOFTWARE • Input and Output routine from monitor or BASIC to teletype or other serial printer • Program for using an Apple II for a video or an intelligent terminal. Also can output in correspondence code to interface with some electrics. • Also watches DTR • Board only \$14.95 Part No. 2, with parts \$51.25 Part No. 2A, assembled \$62.95 Part No. 2C

PARALLEL TRIAC OUTPUT BOARD FOR APPLE II



This board has 8 triacs capable of switching 110 volt 6 amp loads (660 watts per channel) or a total of 5280 watts. Board only \$15.65 Part No. 210, with parts \$119.95 Part No. 210A


APPLE II PROTOTYPING HOBBY/CARD

Part No. 7907 \$21.95

RS-232/20mA INTERFACE


This board has two passive, opto-isolated circuits. One converts RS-232 to 20mA, the other converts 20mA to RS-232. All connections go to a 10 pin edge connector. Requires +12 and -12 volts. Board only \$9.95, part no. 7901, with parts \$14.95 Part No. 7901A.

T.V. INTERFACE




- Converts video to AM modulated RF, Channels 2 or 3. So powerful almost no tuning is required. On board regulated power supply makes this extremely stable. Rated very highly in Doctor Dobbs' Journal. Recommended by Apple
- Power required is 12 volts AC C.T., or +5 volts DC
- Board only \$8.19 part No. 107, with parts \$18.85 Part No. 107A

TAPE INTERFACE



- Converts a low cost tape recorder to a digital recorder
- Works up to 1200 baud
- Digital in and out are TTL serial
- Output of board connects to mic. in of recorder
- Earphone of recorder connects to input on board
- No coils
- Requires +5 volts, low power drain
- Board only \$7.60 Part No. 111, with parts \$29.95 Part No. 111A

RS-232/TTL INTERFACE



- Converts TTL to RS-232, and converts RS-232 to TTL
- Two separate circuits
- Requires -12 and +12 volts
- All connections go to a 10 pin edge connector; kit \$9.95 Part No. 232A 10Pin edge connector \$3.00 part No. 10P.

S-100 BUS ACTIVE TERMINATOR




Board only \$18.15 Part No. 900, with parts \$29.89 Part No. 900A.

SERIAL I/O



Four Serial I/O RS-232 ports. S-100 Bus, Software or jumper selectable baud rate (110, 300, 600, 1200, 2400, 4800, 9600, 19.2K), on board Xtal baud rate generator, Addressing, switch selectable, Parity or no parity (odd or even) switch selectable, 1 or 2 stop bits, 5 to 8 bits/character. Board only \$35.19 Part No. 7908, With parts (kit) \$199.95, Part No. 7908A.

RS-232/TTY INTERFACE



This board has two active circuits, one converts RS-232 to 20 mA, the other converts 20 mA to RS-232. Requires +12 and -12 volts. \$9.95 Part No. 600A Kit.

Send for FREE catalog ... a big self-addressed envelope with 86¢ postage gets it fastest!

To Order:

Mention part no., description, and price. In USA shipping paid by us for orders accompanied by check or money order. We accept C.O.D. orders (U.S. only) or a VISA or Master Charge no., expiration date, signature and phone no., shipping charges will be added. CA residents add 6.5% for tax. Outside USA add 15% for air mail postage and handling. Payment must be in U.S. dollars. Dealer inquiries invited. Prices subject to change without notice.



ORDER LINE: (408) 226-4064

ELECTRONIC SYSTEMS

Dept. KB, P.O. Box 18220, San Jose, CA USA 95158

7400

SN7400N	.25	SN7472N	.29	SN74156N	.79
SN7401N	.20	SN7473N	.35	SN74157N	.69
SN7402N	.25	SN7474N	.35	SN74158N	.89
SN7403N	.25	SN7475N	.49	SN74159N	.89
SN7404N	.25	SN7476N	.35	SN74160N	.89
SN7405N	.29	SN7477N	5.00	SN74161N	.89
SN7406N	.35	SN7478N	.50	SN74162N	.89
SN7407N	.35	SN7479N	.50	SN74163N	.89
SN7408N	.29	SN7480N	.50	SN74164N	.89
SN7409N	.29	SN7481N	.50	SN74165N	.89
SN7410N	.25	SN7482N	.50	SN74166N	1.25
SN7411N	.25	SN7483N	.69	SN74167N	1.29
SN7412N	.35	SN7484N	.35	SN74168N	.89
SN7413N	.40	SN7485N	1.75	SN74169N	1.35
SN7414N	.69	SN7486N	.50	SN74170N	4.99
SN7415N	.29	SN7487N	.50	SN74171N	.99
SN7416N	.29	SN7488N	.50	SN74172N	.99
SN7417N	.29	SN7489N	.50	SN74173N	.99
SN7420N	.25	SN7490N	.50	SN74174N	.99
SN7421N	.29	SN7491N	.50	SN74175N	.99
SN7422N	.45	SN7492N	.50	SN74176N	.99
SN7423N	.29	SN7493N	1.49	SN74177N	.99
SN7424N	.29	SN7494N	.69	SN74178N	1.49
SN7425N	.29	SN7495N	.69	SN74179N	1.49
SN7426N	.29	SN7496N	.69	SN74180N	.79
SN7427N	.25	SN7497N	3.00	SN74181N	2.25
SN7428N	.49	SN7498N	1.49	SN74182N	.79
SN7429N	.25	SN7499N	.50	SN74183N	.89
SN7430N	.25	SN7500N	.50	SN74184N	2.49
SN7431N	.25	SN7501N	.50	SN74185N	2.49
SN7432N	.25	SN7502N	.50	SN74186N	1.25
SN7433N	.25	SN7503N	.50	SN74187N	1.25
SN7434N	.25	SN7504N	.50	SN74188N	.89
SN7435N	.25	SN7505N	.50	SN74189N	.89
SN7436N	.25	SN7506N	.50	SN74190N	.89
SN7437N	.25	SN7507N	.50	SN74191N	.89
SN7438N	.40	SN7508N	.50	SN74192N	.89
SN7439N	.25	SN7509N	.50	SN74193N	.89
SN7440N	.25	SN7510N	.50	SN74194N	.89
SN7441N	.89	SN7511N	.75	SN74195N	1.49
SN7442N	.59	SN7512N	.75	SN74196N	1.49
SN7443N	1.10	SN7513N	.99	SN74197N	1.25
SN7444N	1.10	SN7514N	3.25	SN74198N	1.25
SN7445N	.89	SN7515N	3.49	SN74199N	.89
SN7446N	.79	SN7516N	3.49	SN74200N	.89
SN7447N	.69	SN7517N	.99	SN74201N	.89
SN7448N	.79	SN7518N	1.56	SN74202N	3.95
SN7449N	.20	SN7519N	1.29	SN74203N	.89
SN7450N	.20	SN7520N	1.29	SN74204N	.89
SN7451N	.20	SN7521N	1.29	SN74205N	.89
SN7452N	.20	SN7522N	1.29	SN74206N	.89
SN7453N	.20	SN7523N	1.29	SN74207N	.89
SN7454N	.20	SN7524N	1.29	SN74208N	.89
SN7455N	.20	SN7525N	1.29	SN74209N	.89
SN7456N	.20	SN7526N	1.29	SN74210N	.89
SN7457N	.20	SN7527N	1.29	SN74211N	.89
SN7458N	.20	SN7528N	1.29	SN74212N	.89
SN7459N	.20	SN7529N	1.29	SN74213N	.89
SN7460N	.20	SN7530N	1.29	SN74214N	.89
SN7470N	.29	SN7531N	.79	SN74215N	.89

OK

DIP/C INSERTION TOOL WITH PIN STRAIGHTENER

Inserts both 14 and 18 pin packages. Narrow profile permits work on closely spaced items. Pin straightener built into handle.

Part No.	Function	Price
INS-1416	14 pin CMOS safe	\$3.49
MOS-2428	24 pin CMOS safe	7.95
MOS-40	36 pin CMOS safe	7.95

Vacuum Vise

Vacuum-based light-duty vise for small components and assemblies. ABS construction. 1 1/2" jaws, 1 1/2" travel. Can be permanently installed.

VV-1.....\$3.49


Wire Wrapping Kit WK-2

Contains WSU-30 wrap tool, 50 feet of Kynar 30 AWG white wire, 50 pieces each pre-stripped wire in 1", 2" and 4" lengths, stripped 1" both ends.

WK-2.....\$12.95


Part No.	Function	Price
7065PI	CMOS Precision Timer	14.95
7065EV/KIT*	Stopwatch Chip, XTL	22.95
7105CPL	3 1/2 Digit A/D (LCD Drive)	16.95
7105EV/KIT*	IC, Circuit Board, Display	34.95
7107CPL	3 1/2 Digit A/D (LCD Drive)	15.95
7107EV/KIT*	IC, Circuit Board, Display	28.95
7115CPL	3 1/2 Digit A/D LED Dis. H.L.D.	18.95
7117CPL	3 1/2 Digit A/D LED Dis. H.L.D.	17.95
7201IDR	Low Battery Volt Indicator	2.25
7205IPG	CMOS LED Stopwatch/Timer	12.95
7205EV/KIT*	Stopwatch Chip, XTL	15.95
7205CJPE	Tone Generator	5.15
7205CEV/KIT*	Tone Generator Chip, XTL	9.50
7207APD	Oscillator Controller	6.95
7207AEV/KIT*	Freq. Counter Chip, XTL	17.95
7208IPD	Seven Decade Counter	3.95
7209IPD	4 Func. CMOS Stopwatch CKT	13.95
7215IPG/KIT*	4 Func. Stopwatch Chip, XTL	19.95
7215AIPD	8-Digit Univ. Counter C.A.	32.00
7215CJL	8-Digit Freq. Counter C.A.	26.95
7215DIPD	8-Digit Freq. Counter C.C.	21.95
7217IPD	4-Digit LED Up/Down Counter	12.95
7218CJL	8-Digit Univ. LED Drive	10.95
7218AIPD	LED 4 1/2 Digit Up/Down Counter DRI	11.25
7218CJL	8-Digit Univ. Counter C.A.	31.95
7225AEV/KIT*	5 Function Counter Chip, XTL	74.95
7240IPE	CMOS Bin Prog. Timer/Counter	4.95
7242IPE	CMOS Divide-by-256 RC Timer	2.05
7260IPE	CMOS BCD Prog. Timer/Counter	5.95
7260IPE	CMOS BCD Prog. Timer/Counter	5.25
7555IPE	CMOS 555 Timer (8 pin)	1.45
7555IPE	CMOS 555 Timer (4 pin)	2.20
7611BCPA	CMOS Op Amp Comparator	5M 2.25
7612BCPA	CMOS Op Amp Ext. Cmr.	5M 2.95
7621BCPA	CMOS Dual Op Amp Comp.	5M 3.95
7631CCPE	CMOS Tri Op Amp Comp.	10M 5.35
7641CCPD	CMOS Quad Op Amp Comp.	10M 7.50
7650CCPD	CMOS Quad Op Amp Comp.	10M 7.50
7650CCPD	Voltage Converter	2.95
8038CCPD	Waveform Generator	4.95
8048CCPE	Monolithic Logarithmic Amp	21.50
8111CPL	500pp Band - G.P. Volt Ref. Diode	2.50
8211CPL	Volt Ref/Indicator	2.50
8212CPL	Volt Ref/Indicator	2.50

DISCRETE LEDS			
XC556R .300" red	5/51	MV50 .085" red	6/51
XC556G .300" green	4/51	XC209R .125" red	5/51
XC556Y .300" yellow	4/51	XC209G .125" green	4/51
XC556C .300" clear	4/51	XC209Y .125" yellow	4/51
XC22R .200" red	5/51	XC526R .185" red	5/51
XC22G .200" green	4/51	XC526G .185" green	4/51
XC22Y .200" yellow	4/51	XC526Y .185" yellow	4/51
MV10B .170" red	4/51	XC526C .185" clear	4/51



6 VOLT MINI LAMP
- INCANDESCENT -

800-147 Clear w/5" leads 8/51
80620 Red w/10" leads 9/51

 XC556 RED, METAL
800-147 Clear w/5" leads 8/51
RL-2 \$3.89 ea. or 3/51

C.A. - Common Anode			C.C. - Common Cathode		
Type	Polarity	Ht Price	Type	Polarity	Ht Price
MAN 1	C.A.-red	.270 2.95	DLG507	C.A.-green	.500 1.25
MAN 2	SX7 D.M.-red	.300 4.95	DL704	C.C.-red	.300 1.25
MAN 3	C.C.-red	.125 .25	DL707	C.A.-red	.300 1.25
MAN 52	C.A.-green	.300 1.25	DL728	C.C.-red	.500 1.49
MAN 54	C.C.-green	.300 1.25	DL750	C.A.-red	.600 1.49
MAN 71	C.A.-red	.300 .75	DL746	C.A.-red ± 1	.630 1.49
MAN 72	C.A.-red	.300 .75	DL747	C.A.-red	.600 1.49
MAN 74	C.C.-red	.300 1.25	DL750	C.A.-orange	.800 1.49
MAN 82	C.A.-yellow	.300 .49	DL0847	C.C.-orange	.800 1.49
MAN 84	C.C.-yellow	.300 .99	DL0850	C.C.-orange	.800 1.49
MAN 3620	C.A.-orange ± 1	.300 .49	DL139B	C.C.-red	.110 .35
MAN 3630	C.C.-orange ± 1	.300 .99	FND368	C.C. ± 1	.367 .75
MAN 3640	C.C.-orange	.300 .99	FND359	C.C.	.357 .75
MAN 4610	C.A.-orange	.400 .99	FND503	C.C. (FND500)	.500 .99
MAN 6610	C.A.-orange-DD	.560 .99	FND507	C.C. (FND501)	.500 .99
MAN 6630	C.A.-orange ± 1	.560 .99	HDS3P-3403	C.A.-red	.800 1.50
MAN 6640	C.C.-orange-DD	.560 .99	HDS3P-3403	C.C.-red	.800 1.50
MAN 6650	C.C.-orange ± 1	.560 .99	5082-7751	C.A., R.H.D.-red	.430 1.25
MAN 6660	C.A.-orange	.560 .99	5082-7760	C.A., R.H.D.-red	.430 1.25
MAN 6710	C.A.-red-DD	.560 .99	5082-7700	4x1 sig. dig. RHD	.600 22.00
MAN 6750	C.C.-red ± 1	.560 .99	5082-7302	4x1 sig. dig. LHD	.600 22.00
MAN 6780	C.C.-red	.560 .99	5082-7304	Overrange, chr.(±1)	.600 19.95
DLO304	C.C.-orange	.300 1.25	4N28	Photo Xsistor Opto-Isol.	.99
DLO307	C.C.-orange	.300 1.25	LIT-1	Photo Xsistor Opto-Isol.	.69
DLG500	C.C.-green	.500 1.25	MOC310	Optically Isolated Triac Driver	1.25

SOCKETS

Test Sockets

RECEPTACLES

ZERO INSERTION FORCE

- * Nickel Boron Plating
- * G.F. PSF Plastic Body
- * For testing IC's
- * Wire Wrap Contacts

Part No.	Pins	Price	Part No.	Pins	Price
214-3339	14 pin	6.95	222-3343	22 pin	9.95
216-3340	16 pin	5.49	224-3344	24 pin	9.75
218-3341	18 pin	7.95	226-3345	26 pin	11.95
220-3342	20 pin	8.95	240-3346	40 pin	12.95

LOW PROFILE (TIN) SOCKETS

Part No.	Pins	Price	Part No.	Pins	Price
1-24	24	.49	50-100	100	.50
8 pin LP	.17	.12	14 pin ST	.27	.25
14 pin LP	.20	.19	16 pin ST	.30	.27
16 pin LP	.22	.21	18 pin ST	.35	.32
20 pin LP	.34	.32	24 pin ST	.49	.45
22 pin LP	.37	.36	26 pin ST	.59	.55
24 pin LP	.38	.37	36 pin ST	1.39	1.26
26 pin LP	.40	.39	40 pin ST	1.59	1.45
36 pin LP	.60	.59			
40 pin LP	.63	.62			

SOLDERTAIL (GOLD) STANDARD

Part No.	Pins	Price	Part No.	Pins	Price
1-24	24	.49	50-100	100	.50
8 pin SG	.34	.33	14 pin WW	.69	.73
14 pin SG	.49	.45	16 pin WW	.79	.73
16 pin SG	.54	.49	18 pin WW	.89	.81
20 pin SG	.59	.49	20 pin WW	1.19	.98
22 pin SG	.62	.59	22 pin WW	1.49	1.23
24 pin SG	.79	.75	24 pin WW	1.39	1.26
26 pin SG	1.10	1.00	26 pin WW	1.69	1.53
36 pin SG	1.65	1.40	36 pin WW	2.19	1.99
40 pin SG	1.75	1.59	40 pin WW	2.29	2.09

WIRE WRAP SOCKETS (GOLD) LEVEL #3

Part No.	Pins	Price	Part No.	Pins	Price
1-24	24	.49	50-100	100	.50
8 pin WW	.79	.73	14 pin WW	.69	.73
14 pin WW	.79	.73	16 pin WW	.79	.73
16 pin WW	.89	.81	18 pin WW	.89	.81
20 pin WW	1.19	.98	20 pin WW	1.19	.98
22 pin WW	1.49	1.23	22 pin WW	1.49	1.23
24 pin WW	1.39	1.26	24 pin WW	1.39	1.26
26 pin WW	1.69	1.53	26 pin WW	1.69	1.53
36 pin WW	2.19	1.99	36 pin WW	2.19	1.99
40 pin WW	2.29	2.09	40 pin WW	2.29	2.09


74C			
74C00	.39	74C221	1.95
74C02	.39	74C240	2.25
74C04	.39	74C244	2.25
74C08	.39	74C373	2.49
74C10	.39	74C374	2.49
74C12	.39	74C375	2.49
74C15	.39	74C376	2.49
74C16	.39	74C377	2.49
74C18	.39	74C378	2.49
74C19	.39	74C379	2.49
74C20	.39	74C380	2.49
74C21	.39	74C381	2.49
74C23	.39	74C382	2.49
74C24	.39	74C383	2.49
74C25	.39	74C384	2.49
74C26	.39	74C385	2.49
74C27	.39	74C386	2.49
74C28	.39	74C387	2.49
74C29	.39	74C388	2.49
74C30	.39	74C389	2.49
74C31	.39	74C390	2.49
74C32	.39	74C391	2.49
74C33	.39	74C392	2.49
74C34	.39	74C393	2.49
74C35	.39	74C394	2.49
74C36	.39	74C395	2.49
74C37	.39	74C396	2.49
74C38	.39	74C397	2.49
74C39	.39	74C398	2.49

DIGITAL RESEARCH: PARTS

"TOP QUALITY PARTS FOR LESS"

9 Watt Stereo Amplifier

Brand New!



6⁵⁰

Fantastic!

One of the neatest items we have come up with. Operates on 8 to 20V. A.C. or D.C. (on board diodes).

- Separate tone control pots
- Balance control
- Volume control

Separate inputs for phono, radio, recorder, etc. Separate jack for head phones.

Replace your car stereo amp. Easy hook up — approximately 10 min. with our "how to" instructions.

Transformer for above — \$3.50

Universal Timer Kit

NEW!

- ★ Adjustable from 1 sec. to 1 hr.
- ★ Control up to 1 amp
- "Turn Things On or Off"


Kit includes all parts necessary to build this exciting kit.

Uses: Children's T.V. programs - Darkroom exposures - Amateur 10 min. I.D.er - Egg Timer - Intermittent Windshield Wiper. Absolutely endless uses.

Complete kit including power supply, p.c. board - DPDT relay, and all parts to make timer operational.

8⁹⁵

Video Game Board



4⁴⁵

3 for 12⁰⁰

Hockey • Tennis • Handball

- General Instruments AY3-8500
- Features Exciting Sounds
- On Screen Scoring
- Speed & Paddle Controls
- 1 or 2 Players
- Works on 8-15 Volts D.C.

Each board comes with RF Modulator (Ch. 3 or 4) and schematic. The only parts needed to complete game are speaker, 2-1 Meg Pots & Switches.

IC Specials!

LM1889-2²⁵

MC1310-1⁸⁰

LM3820 - A.M. Radio on a chip w/specs.



2/1⁰⁰

16 Pin Header



4/1⁰⁰

Power Transistor TO220 Case

3/1¹⁰



1 Amp 30 Watts 100 Volt
TIP 30C (PNP)
TIP 29C (NPN)

Gold Wire Wrap Sockets

Not Cheap Gold Inlay as Sold By Others.

Super 3 Level Gold Wire Wrap.

14 Pin - 10/3⁹⁵, 25/8⁷⁵

16 Pin - 10/4⁹⁵, 25/11²⁵



Video Paddle Controls

2 for 1⁰⁰

1 Meg

Can be used with game board above.



Voltage Regulator

LM309K

1⁰⁰



5 Volt - 1 Amp Regulator
TO3 Case. Super Special!

Sprague RFI Filter 3⁶⁵ or 3/9⁰⁰

Perfect for Computers, or anything that needs to be "glitch" free. By the #1 name in filtering, Sprague. JN17-5109B. Has I.E.C. Power Line Connector. 2x3 Amp. 115/220 VAC 60 Hz. 2 1/2" x 2 1/2" x 3" deep.

Switch Banks



- Non Canceling
- DPDT-PC or Solder
- Switches Easily Removed
- Push On/Push Off
- THAT'S INCREDIBLE!

2⁵⁰

Transformer

32VCT @ 1amp

6V @ 1amp

3²⁵

Measures:

2" x 2 1/4" x 2 1/4"

2 3/8" Mounting Centers

Rectifier Diode IN4007

11/1⁰⁰



1000 Volts, 1 Amp
DO-41 Case • Prime • Long Lead • Marked.

RCA Triac

79^c

5 for 3⁵⁰



T2800M-TO220 Case
6 Amp 600 Volt

JFET OP AMP

Super High Input Impedance (10¹² OHMS) — High Frequency Response. TO 4 MHZ. Large DC Voltage Gain 106 DB — New generation OP-AMP with Vastly Superior Features!

LF356BH - 75^c or 3/2⁰⁰

Micro Mini Toggle Switch

99^c

6 for 5⁰⁰



SPDT • Made in USA with Hardware

IF YOU DON'T HAVE CATALOG #81-05, YOU BETTER WRITE TODAY!

TERMS:

Add 50¢ postage, we pay balance. Orders under \$15 add 75¢ handling. No C.O.D. We accept Visa, MasterCard and American Express cards. Tex. Res. add 5% Tax. Foreign orders (Canada 10%) add 20% P & H.


• VISA • MASTERCARD • AMERICAN EXPRESS •

Digital Research: Parts

P.O. Box 401247 • Garland, Texas 75040

(214) 271-2461

VAK-1 MOTHERBOARD



We also carry:

SYM-1	\$229 ⁰⁰
AIM-65 w/1K	389 ⁰⁰
AIM-65 w/4K	439 ⁰⁰

We also do custom hardware and software for the 6502 microprocessor

PRICE: \$139⁰⁰

Call or write for shipping charges and our complete catalog.

The VAK-1 was specifically designed for use with the KIM-1, SYM-1 and the AIM 65 Microcomputer Systems. The VAK-1 uses the KIM-4* Bus Structure, because it is the only popular Multi-Sourced bus whose expansion boards were designed specifically for the 6502 Microprocessor.


SPECIFICATIONS:

- Complete with rigid CARD-CAGE
- Assembled (except for card-cage). Burned in and tested.
- All IC's are in sockets
- Fully buffered address and data bus
- Uses the KIM-4* Bus (both electrical Pin-out and card size) for expansion board slots
- Provides 8 slots for expansion boards on 1" centers to allow for wire-wrap boards
- Designed for use with a Regulated Power Supply (such as our VAK-EPS) but has provisions for adding regulators for use with an unregulated power supply.
- Provides separate jacks for one audio-cassette, TTY and Power Supply.
- Board size: 14.5 in. Long x 11.5 in. Wide x 8 in. High
- Power requirements; 5V.DC @ 0.2 Amps.

*KIM-4 is a product of MOS Technology/C.B.M.

 **ENTERPRISES**
INCORPORATED ✓52

2951 W. Fairmount Avenue
Phoenix, AZ 85017
(602) 265-7564



QUEST

P.O. Box 44305
Santa Clara, CA 95054

Will calls: 2322 Walsh Ave.
ELECTRONICS
(408) 988-1640 TWX 910-338-2139


Same day shipment. First line parts only. Factory tested.
Guaranteed money back. Quality IC's and other components at factory prices.

INTEGRATED CIRCUITS

7400TTL	1M20K-5	1.35	CD4006	2.50	2141 4500s	4.00	
7400N	19	LM320K-12	1.35	CD4027	56	4116 2000s	3.95
7402N	20	LM320K-15	1.35	CD4028	85	84116 2000s	18.40
7404N	21	LM320K-18	1.35	CD4030	45	MM5280	3.00
7405N	22	LM320K-20	1.35	CD4030	45	MM5280	3.00
7410N	23	LM320K-12	1.35	CD4035	1.00	MM5220	9.95
7414N	24	LM320K-15	1.35	CD4040	1.35	MM5330	5.94
7420N	25	LM320K-18	1.35	CD4042	85	PD411D-3	4.00
7422N	26	LM320K-20	1.35	CD4043	85	PD411D-4	5.00
7430N	27	LM320K-12	1.35	CD4044	85	PD411D-5	5.00
7442N	28	LM320K-15	1.35	CD4046	1.67	4200A	9.95
7445N	29	LM320K-18	1.35	CD4049	45	82525	2.90
7447N	30	LM320K-20	1.35	CD4050	60	81102A	1.50
7448N	31	LM320K-15	1.35	CD4051	1.13	H00165-5	6.95
7450N	32	LM320K-18	1.35	CD4052	1.62	MM521700	6.50
7474N	33	LM320K-20	1.35	CD4053	71	GIAY3500-1	9.95
7475N	34	LM320K-12	1.35	CD4056	85	MM52751A	9.95
7485N	35	LM320K-15	1.35	CD4058	900	3500	3.50
7489N	36	LM320K-18	1.35	CD4059	40	4100	10.00
7490N	37	LM320K-12	1.35	CD4061	45	416	16.00
7492N	38	LM320K-15	1.35	CD4062	45		
7493N	39	LM320K-18	1.35	CD4063	45		
7494N	40	LM320K-20	1.35	CD4064	45		
74100N	1.35	LM379	5.00	CD4076	1.45		
74107N	1.35	LM380N	1.00	CD4078	40		
74121N	34	LM381	1.60	CD4081	45		
74123N	35	LM382	1.60	CD4082	35		
74125N	36	LM383	1.60	CD4083	35		
74126N	37	LM384	1.60	CD4084	35		
74127N	38	LM385	1.60	CD4085	35		
74128N	39	LM386	1.60	CD4086	35		
74129N	40	LM387	1.60	CD4087	35		
74130N	1.20	LM733N	85	CD4088	1.00	MM5280	3.00
74131N	1.20	LM734N	85	CD4089	1.00	MM5280	3.00
74132N	1.20	LM735N	85	CD4090	1.00	MM5280	3.00
74133N	1.20	LM736N	85	CD4091	1.00	MM5280	3.00
74134N	1.20	LM737N	85	CD4092	1.00	MM5280	3.00
74135N	1.20	LM738N	85	CD4093	1.00	MM5280	3.00
74136N	1.20	LM739N	85	CD4094	1.00	MM5280	3.00
74137N	1.20	LM740N	85	CD4095	1.00	MM5280	3.00
74138N	1.20	LM741N	85	CD4096	1.00	MM5280	3.00
74139N	1.20	LM742N	85	CD4097	1.00	MM5280	3.00
74140N	1.20	LM743N	85	CD4098	1.00	MM5280	3.00
74141N	1.20	LM744N	85	CD4099	1.00	MM5280	3.00
74142N	1.20	LM745N	85	CD4100	1.00	MM5280	3.00
74143N	1.20	LM746N	85	CD4101	1.00	MM5280	3.00
74144N	1.20	LM747N	85	CD4102	1.00	MM5280	3.00
74145N	1.20	LM748N	85	CD4103	1.00	MM5280	3.00
74146N	1.20	LM749N	85	CD4104	1.00	MM5280	3.00
74147N	1.20	LM750N	85	CD4105	1.00	MM5280	3.00
74148N	1.20	LM751N	85	CD4106	1.00	MM5280	3.00
74149N	1.20	LM752N	85	CD4107	1.00	MM5280	3.00
74150N	1.20	LM753N	85	CD4108	1.00	MM5280	3.00
74151N	1.20	LM754N	85	CD4109	1.00	MM5280	3.00
74152N	1.20	LM755N	85	CD4110	1.00	MM5280	3.00
74153N	1.20	LM756N	85	CD4111	1.00	MM5280	3.00
74154N	1.20	LM757N	85	CD4112	1.00	MM5280	3.00
74155N	1.20	LM758N	85	CD4113	1.00	MM5280	3.00
74156N	1.20	LM759N	85	CD4114	1.00	MM5280	3.00
74157N	1.20	LM760N	85	CD4115	1.00	MM5280	3.00
74158N	1.20	LM761N	85	CD4116	1.00	MM5280	3.00
74159N	1.20	LM762N	85	CD4117	1.00	MM5280	3.00
74160N	1.20	LM763N	85	CD4118	1.00	MM5280	3.00
74161N	1.20	LM764N	85	CD4119	1.00	MM5280	3.00
74162N	1.20	LM765N	85	CD4120	1.00	MM5280	3.00
74163N	1.20	LM766N	85	CD4121	1.00	MM5280	3.00
74164N	1.20	LM767N	85	CD4122	1.00	MM5280	3.00
74165N	1.20	LM768N	85	CD4123	1.00	MM5280	3.00
74166N	1.20	LM769N	85	CD4124	1.00	MM5280	3.00
74167N	1.20	LM770N	85	CD4125	1.00	MM5280	3.00
74168N	1.20	LM771N	85	CD4126	1.00	MM5280	3.00
74169N	1.20	LM772N	85	CD4127	1.00	MM5280	3.00
74170N	1.20	LM773N	85	CD4128	1.00	MM5280	3.00
74171N	1.20	LM774N	85	CD4129	1.00	MM5280	3.00
74172N	1.20	LM775N	85	CD4130	1.00	MM5280	3.00
74173N	1.20	LM776N	85	CD4131	1.00	MM5280	3.00
74174N	1.20	LM777N	85	CD4132	1.00	MM5280	3.00
74175N	1.20	LM778N	85	CD4133	1.00	MM5280	3.00
74176N	1.20	LM779N	85	CD4134	1.00	MM5280	3.00
74177N	1.20	LM780N	85	CD4135	1.00	MM5280	3.00
74178N	1.20	LM781N	85	CD4136	1.00	MM5280	3.00
74179N	1.20	LM782N	85	CD4137	1.00	MM5280	3.00
74180N	1.20	LM783N	85	CD4138	1.00	MM5280	3.00
74181N	1.20	LM784N	85	CD4139	1.00	MM5280	3.00
74182N	1.20	LM785N	85	CD4140	1.00	MM5280	3.00
74183N	1.20	LM786N	85	CD4141	1.00	MM5280	3.00
74184N	1.20	LM787N	85	CD4142	1.00	MM5280	3.00
74185N	1.20	LM788N	85	CD4143	1.00	MM5280	3.00
74186N	1.20	LM789N	85	CD4144	1.00	MM5280	3.00
74187N	1.20	LM790N	85	CD4145	1.00	MM5280	3.00
74188N	1.20	LM791N	85	CD4146	1.00	MM5280	3.00
74189N	1.20	LM792N	85	CD4147	1.00	MM5280	3.00
74190N	1.20	LM793N	85	CD4148	1.00	MM5280	3.00
74191N	1.20	LM794N	85	CD4149	1.00	MM5280	3.00
74192N	1.20	LM795N	85	CD4150	1.00	MM5280	3.00
74193N	1.20	LM796N	85	CD4151	1.00	MM5280	3.00
74194N	1.20	LM797N	85	CD4152	1.00	MM5280	3.00
74195N	1.20	LM798N	85	CD4153	1.00	MM5280	3.00
74196N	1.20	LM799N	85	CD4154	1.00	MM5280	3.00
74197N	1.20	LM800N	85	CD4155	1.00	MM5280	3.00
74198N	1.20	LM801N	85	CD4156	1.00	MM5280	3.00
74199N	1.20	LM802N	85	CD4157	1.00	MM5280	3.00
74200N	1.20	LM803N	85	CD4158	1.00	MM5280	3.00
74201N	1.20	LM804N	85	CD4159	1.00	MM5280	3.00
74202N	1.20	LM805N	85	CD4160	1.00	MM5280	3.00
74203N	1.20	LM806N	85	CD4161	1.00	MM5280	3.00
74204N	1.20	LM807N	85	CD4162	1.00	MM5280	3.00
74205N	1.20	LM808N	85	CD4163	1.00	MM5280	3.00
74206N	1.20	LM809N	85	CD4164	1.00	MM5280	3.00
74207N	1.20	LM810N	85	CD4165	1.00	MM5280	3.00
74208N	1.20	LM811N	85	CD4166	1.00	MM5280	3.00
74209N	1.20	LM812N	85	CD4167	1.00	MM5280	3.00
74210N	1.20	LM813N	85	CD4168	1.00	MM5280	3.00
74211N	1.20	LM814N	85	CD4169	1.00	MM5280	3.00
74212N	1.20	LM815N	85	CD4170	1.00	MM5280	3.00
74213N	1.20	LM816N	85	CD4171	1.00	MM5280	3.00
74214N	1.20	LM817N	85	CD4172	1.00	MM5280	3.00
74215N	1.20	LM818N	85	CD4173	1.00	MM5280	3.00
74216N	1.20	LM819N	85	CD4174	1.00	MM5280	3.00
74217N	1.20	LM820N	85	CD4175	1.00	MM5280	3.00
74218N	1.20	LM821N	85	CD4176	1.00	MM5280	3.00
74219N	1.20	LM822N	85	CD4177	1.00	MM5280	3.00
74220N	1.20	LM823N	85	CD4178	1.00	MM5280	3.00
74221N	1.20	LM824N	85	CD4179	1.00	MM5280	3.00
74222N	1.20	LM825N	85	CD4180	1.00	MM5280	3.00
74223N	1.20	LM826N	85	CD4181	1.00	MM5280	3.00
74224N	1.20	LM827N	85	CD4182	1.00	MM5280	3.00
74225N	1.20	LM828N	85	CD4183	1.00	MM5280	3.00
74226N	1.20	LM829N	85	CD4184	1.00	MM5280	3.00
74227N	1.20	LM830N	85	CD4185	1.00	MM5280	3.00
74228N	1.20	LM831N	85	CD4186	1.00	MM5280	3.00
74229N	1.20	LM832N	85	CD4187	1.00	MM5280	3.00
74230N	1.20	LM833N	85	CD4188	1.00	MM5280	3.00
74231N	1.20	LM834N	85	CD4189	1.00	MM5280	3.00
74232N	1.20	LM835N	85	CD4190	1.00	MM5280	3.00
74233N	1.20	LM836N	85	CD4191	1.00	MM5280	3.00
74234N	1.20	LM837N	85	CD4192	1.00	MM5280	3.00
74235N	1.20	LM838N	85	CD4193	1.00	MM5280	3.00
74236N	1.20	LM839N	85	CD4194	1.00	MM5280	3.00
74237N	1.20	LM840N	85	CD4195	1.00	MM5280	3.00
74238N	1.20	LM841N	85	CD4196	1.00	MM5280	3.00
74239N	1.20	LM842N	85	CD4197	1.00	MM5280	3.00
74240N	1.20	LM843N	85	CD4198	1.00	MM5280	3.00
74241N	1.20	LM844N	85	CD4199	1.00	MM5280	3.00
74242N	1.20	LM845N	85	CD4200	1.00	MM5280	3.00
74243N	1.20	LM846N	85	CD4201	1.00	MM5280	3.00
74244N	1.20	LM847N	85	CD4202	1.00	MM5280	3.00
74245N	1.20	LM848N	85	CD4203	1.00	MM5280	3.00
74246N	1.20	LM849N	85	CD4204	1.00	MM5280	3.00
74247N	1.20	LM850N	85	CD4205	1.00	MM5280	3.00
74248N	1.20	LM851N	85	CD4206	1.00	MM5280	3.00
74249N	1.20	LM852N	85	CD4207	1.00	MM5	

Better Products,

JADE Double-D™ Get the Inside Track



S-100 bus compatible • Reads and writes single or double density • Density is software selectable • CP/M® 2.2 compatible in single or double density • Controls up to four 5-1/4" or 8", single or double-sided drives • Single or double-sided drives may be mixed in the same system • On-board Z-80A to assure reliable operation • EIA level serial printer interface on board, baud rates to 9600 (perfect for despooling operations) • 2K of RAM on-board • Uses IBM standard formats • Designed to meet IEEE signal disciplines • Works with 8080, 8085, and Z-80 CPU's • 4-layer PC board with internal power and ground planes provides very stable, low-noise operation.

IOD-1200B Bare board	\$59.95
IOD-1200K Kit	\$299.95
IOD-1200A A & T for 8"	\$375.95
IOD-1205A A & T for 5 1/4"	\$395.00
SFC-58001200E DD boot PROM	\$20.00
SFC-59002001F CP/M 2.2 for DD ..	\$150.00

JADE Memory Bank™ 8 or 16 Bit Dynamic Memory

New, from JADE (naturally), an IEEE S-100 64K dynamic memory that looks toward the future. • IEEE S-100 standard pinout and signal discipline • Expandable to 16 Megabytes via switchable port OR extended address lines • 8 or 16 bit words, automatically, depending on the type of CPU on the bus • 4-layer PC board for extremely low-noise operation.


The new JADE Memory Bank™ is one of the safest places you can store your valuable program information. With its on-board refresh controller, this board allows DMA operations without regard to time factors. It will run reliably at any system clock rate up to 6 MHz—because it is clocked with the system clock itself (no one-shots are used for timing operations). Its unique IEEE design enables it to switch from a 64K by 8-bit board to a 32K by 16-bit board automatically (responds to IEEE's 16 Rqst line and, if enabled, replies with 16 Grant).

On-board M1 wait-state generator allows the use of slower memory, and a unique on-board precharge extender makes this board run reliably with any manufacturer's 4116 memory chips.

Compatible with Cromemco and other CPU systems — features enough optional strapping to enable it to run with any Z-80/Z8000 system.

MEM-99730B Bare Board	\$49.95
MEM-99730K Kit, no RAM	\$199.95
MEM-16730K 16K kit	\$219.95
MEM-32731K 32K kit	\$239.95
MEM-48732K 48K kit	\$259.95
MEM-64733K 64K kit	\$279.95
Assembled & Tested	add \$50.00

JADE ✓48 The Big Z™ Z-80A Based CPU




S-100 bus compatible • Switch selectable 2 or 4 MHz operation • Serial I/O port • Accommodates a 2708, 2716, or 2732 EPROM in shadow mode allowing full use of 64K RAM • MWRITE signal is generated automatically if used without front panel • On-board 8251 USART controls serial port at baud rates from 75 to 9600 baud • Switch selectable 1K, 2K, or 4K boundary fully buffered • Power-on jump to EPROM

CPU-30201K Kit	\$139.95
CPU-30201A A & T	\$189.95
CPU-30200B Bare board	\$35.00

Memory Chips on Sale

	1-9	10-24	25-49	50+
2114L 4 MHz	3.35	2.99	2.75	2.49
2708 2 MHz	4.90	3.90	3.45	2.90
2532 2 MHz	24.90	19.90	15.90	12.90
2716 2 MHz	8.90	7.45	6.45	5.75
2716 4 MHz	19.90	15.45	13.45	11.75
2732 2 MHz	24.90	19.90	15.90	12.90
2732 4 MHz	39.90	29.90	24.90	19.90
2758 2 MHz	6.90	6.25	5.50	4.50
4116 200 ns	3.25	2.99	2.49	1.99
4164 200 ns	28.90	24.90	22.90	19.90

JADE Disk Sub-Systems Shugart, Siemens, Qume



Handsome metal cabinet with proportionally balanced air flow system • Rugged dual drive power supply • Power cable kit • Power switch, line cord, fuse holder, cooling fan • Never-Mar rubber feet • All necessary hardware to mount 2-8" disk drives, power supply, and fan • Does not include signal cable

Dual 8" Subassembly Cabinet

END-000420 Bare cabinet	\$59.95
END-000421 Cabinet kit	\$225.00
END-000431 A & T	\$359.95


8" Disk Drive Subsystems

Single Sided, Double Density	
END-000423 Kit w/2 FD100-8Ds ..	\$975.00
END-000424 A & T w/2 FD100-8Ds	\$1175.00
END-000433 Kit w/2 SA-801Rs ...	\$999.95
END-000434 A & T w/2 SA-801Rs	\$1195.00

8" Disk Drive Subsystems Double Sided, Double Density

END-000426 Kit w/2 DT-8s	\$1475.00
END-000427 A & T w/2 DT-8s ...	\$1675.00
END-000436 Kit w/2 SA-851Rs ..	\$1495.00
END-000437 A & T w/2 SA-851Rs	\$1695.00

JADE S.P.I.C. Our "SPICy" New I/O Board



New, from JADE, one of the most advanced, technologically sophisticated Serial/Parallel Interrupt Controller systems in the world. On a single IEEE S-100 standard board, JADE has packed two bi-directional parallel ports with full handshaking, four serial channels (asynchronous, IBM-compatible bi-synch, synchronous, HDLC/SDLC) with complete modem control lines, and 16 counter-timer channels.

Utilizing the highly advanced Zilog peripheral chips, (Z-80 SIO, PIO & CTCs), the SPIC board is fully programmable to serve as the foundation for a multi-user multi-tasking system. Although the board can be operated in an 8080/8085 system, we recommend its use with a Z-80/Z8000 system utilizing the powerful Z-80/Z8000 interrupt Mode 2. Each of the seven Z-80 peripheral chips can generate its own interrupt vector, with daisy-chain priority levels. Each counter-timer channel can be programmed to monitor an interrupt vector line on the S-100 bus, to serve as an interval timer or real-time clock, and to operate as a software controllable baud rate generator. Each SIO channel can be driven independently with separate Tx/Rx clocks for each channel, so your peripherals can have varied baud rates, from 110 to 76,800 baud

In addition, this board can serve as a data concentrator link to an IBM, DEC, or Data General mainframe computer, utilizing a high-speed serial channel that is programmable to virtually any protocol.

IOI-1045B Bare board & manual	\$49.95
IOI-1045K Kit, standard	\$179.95
IOI-1045A A & T, standard	\$239.95
IOI-1046K Kit w/full chip set	\$219.95
IOI-1046A A & T w/full chip set ...	\$299.95

Jade Business Software


Now, for the first time, at an amazingly low price, CP/M and SDOS users can get an affordable business software package. Just look at these programs! All come complete with basic code (written to run under CBASIC I), for easy customizing and modification. All software is self-documenting. The package price includes a word-processing system. When printed on the system's printer, all files with the extension xxxTOT. constitute a complete manual. No manuals are supplied with the package other than as they appear on the disks. All software is supplied on 8" premium quality JADE Diskettes. Software sold as is. (Sorry, but at these low prices we can not offer our usual friendly support and handholding.)

Includes; General Ledger, Payroll, Invoicing, Inventory Control, Accounts Receivable, Cash Disbursements, Fixed Assets, Cash Receipts, & Mailing List Management.

Special Package Price \$249.95

Lower Prices,

Printers



BEST BUY in PRINTERS - Epson

MX-70 132 column, 80 CPS, 5 x 7 dot matrix, adjustable tractor feed, & graphics

PRM-27070 List \$459 **\$399.95**

MX-80 132 column, 80 CPS, bi-directional/logic seeking printing, 9 x 9 dot matrix, adjustable tractor feed, & 64 graphics characters

PRM-27080 List \$645 **\$474.95**

MX-80FT same as MX-80 with friction feed and full graphics added

PRM-27082 List \$745 **\$574.95**

MX-100 233 column, correspondence quality, ultra-high resolution graphics, up to 15" paper, friction feed & removable/adjustable tractor feed, 18 x 18 dot matrix, 80 CPS, programmable forms handling

PRM-27100 List \$945 **\$795.00**

PRA-27084 Serial interface **\$69.95**

PRA-27088 Serial intf & 2K buffer .. **\$144.95**

PRA-27081 Apple card **\$74.95**

PRA-27082 Apple cable **\$22.95**

PRA-27086 IEEE 488 card **\$52.95**

PRA-27087 TRS-80 cable **\$32.95**

PRA-27085 Graftax II **\$95.00**

PRA-27083 Extra ribbon **\$14.95**

SPINWRITER - NEC

65 cps, bi-directional, letter quality printer with deluxe tractor mechanism, both parallel and serial interfaces on-board, 16K buffer, ribbon, print thimble, graphics, micro-space justification, data cable, and self test/diagnostic ROM.

PRD-55511 without 16K buffer ... **\$2795.00**

PRD-55512 with 16K buffer **\$2895.00**

Accessories for TRS-80

DISK DRIVES for TRS-80

23% more storage, 8 times faster, 40 track with free patch, 120 day warranty.

MSM-12410C Save \$125.00 !!! **\$325.00**

8" DISK DRIVES for MODEL II

2 double density drives with cabinet, power supply, & cables

END-000433 Kit **\$1050.00**

END-000434 Assembled **\$1250.00**

WCA-5036A Cable (required) **\$29.95**

16K Atari ... \$359.95

ATARI 800 - Atari

Complete personal computer with high resolution color graphics, built-in RF modulator, 4 controller ports, internal speaker, 16K RAM & 8K ROM

SYO-2080A 16K Atari 800 **\$759.95**

Atari 800 with 32K of RAM **\$799.95**

Atari 800 with 48K of RAM **\$849.95**

SYO-2040A 16K Atari 400 **\$359.95**

MSM-330810 Disk drive **\$595.00**

MSM-330815 Dual drive **\$1395.00**

IOX-5050A 850 interface **\$199.95**

MEX-16853K 16K RAM module **\$69.95**

SFI-241011005 Visicalc **\$184.95**

Accessories for Apple



16K MEMORY UPGRADE

Add 16K of RAM to your TRS-80, Apple, or Exidy in just minutes. We've sold thousands of these 16K RAM upgrades which include the appropriate memory chips (as specified by the manufacturer), all necessary jumper blocks, fool-proof instructions, and our 1 year guarantee.

MEX-16100K TRS-80 kit **\$25.00**

MEX-16101K Apple kit **\$25.00**

MEX-16102K Exidy kit **\$25.00**

16K RAM Card - Microsoft

(There is life after 48K)

MEX-16300A A & T **\$174.95**

Z-80* CARD for APPLE

Two computers in one, Z-80 & 6502, more than doubles the power & potential of your Apple, includes Z-80* CPU card, CP M 2.2, & BASIC-80

CPX-30800A A & T **\$279.95**

APPLE CLOCK - Cal Comp Sys

Real time clock w/battery back-up

IOK-2030A A & T **\$109.95**

DISK DRIVE for APPLE

5 1/4" disk drive with controller for your Apple

MSM-12310C with controller **\$475.00**

MSM-123101 w/out controller **\$375.00**

8" DRIVES for APPLE

Controller, DOS, two 8" double density drives, cabinet, power supply, & cables

Special Package Price Kit **\$1399.95**

PRINTER INTERFACE - C.C.S.

Centronics type I/O card w/ firmware

IOI-2041A A & T **\$99.95**

AIO, ASIO, APIO - S.S.M.

Parallel & serial interface for your Apple (see Byte pg 11)

IOI-2050K Par & Ser kit **\$139.95**

IOI-2050A Par & Ser A & T **\$169.95**

IOI-2052K Serial kit **\$89.95**

IOI-2052A Serial A & T **\$99.95**

IOI-2054K Parallel kit **\$69.95**

IOI-2054A Parallel A & T **\$89.95**

A488 - S.S.M.

IEEE 488 controller, uses simple basic commands, includes firmware and cable, 1 year guarantee, (see April Byte pg 11)

IOX-7488A A & T **\$399.95**

CPS MULTICARD - Mtn. Computer

Three cards in one! Real time clock, calendar, serial interface, & parallel interface - all on one card.


IOX-2300A A & T **\$229.95**

VISICALC - Personal Sftwr

The ultimate program for your Apple II

SFA-24101005M Complete package **\$139.95**

Single Board Computers



AIM-65 - Rockwell

6502 computer with alphanumeric display, printer, & keyboard, and complete instructional manuals

CPK-50165 1K AIM **\$424.95**

CPK-50465 4K AIM **\$499.95**

SFK-74600008E 8K BASIC ROM ... **\$99.95**

SFK-64600004E 4K assembler ROM **\$84.95**

PSX-030A Power supply **\$64.95**

ENX-000002 Enclosure **\$54.95**

4K AIM, 8K BASIC, power supply, & enclosure

Special package price **\$675.00**

Z-80* STARTER KIT - SD Systems

Complete Z-80* computer with RAM, ROM, I O, display, keyboard, manual, and kluge area.

CPS-30010K Kit **\$369.95**

CPS-30010A A & T **\$459.95**

SYM-1 - Synertek Systems

Single board computer with 1K of RAM, 4K of ROM, key-pad, LED display, 20ma & cassette interface on board.

CPK-50020A A & T **\$249.95**

Video Terminals

VIEWPOINT - ADDS

Detachable keyboard, serial RS232C interface, baud rates from 110 to 19,200, auxiliary serial output port, 24 x 80 display, tiltable screen, international character set

VDT-501210 Sale Priced **\$639.95**

TELEVIDEO 950

Detachable keyboard, split screen with line lock, etched CRT, programmable function keys, on-screen status line, buffered auxiliary port, 14 x 10 dot matrix, self test, serviced nationwide by General Electric

VDT-901250 List \$1195.00 **\$995.00**

Video Monitors

Leedex / Amdek

Reasonably priced video monitors

VDM-801210 Video 100 12" B&W .. **\$149.95**

VDM-801230 Video 100-80 12" B&W **\$189.95**

VDM-801250 12" Green Phosphor **\$189.95**

VDC-801310 13" Color I **\$399.95**

13" COLOR MONITOR - Zenith

The hi res color you've been promising yourself

VDC-201301 **\$449.00**

12" GREEN SCREEN - NEC

20 MHz, P31 phosphor video monitor with audio, exceptionally high resolution - A fantastic monitor at a very reasonable price

VDM-651200 12" monitor **\$259.95**

EPROM Erasers

EPROM ERASERS

L.S. Engineering UV eraser for up to 48 EPROMs

XME-3200 A & T **\$39.99**


Spectronics hi intensity industrial eraser

XME-3100 Without timer **\$69.50**

XME-3101 With timer **\$94.50**

Faster Service.

S-100 PROM Boards



PB-1 - S.S.M.

2708, 2716 EPROM board with built-in programmer

MEM-99510K Kit	\$154.95
MEM-99510A A & T	\$219.95

PROM-100 - SD Systems

2708, 2716, 2732, 2758, & 2516 EPROM programmer

MEM-99520K Kit	\$219.95
MEM-99520A Jade A & T	\$269.95

EPROM BOARD - Jade

16K or 32K uses 2708's or 2716's, 1K boundary

MEM-16230K Kit	\$79.95
MEM-16230A A & T	\$119.95

S-100 Video

VB-3 - S.S.M.

80 characters x 24 lines expandable to 80 x 48 for a full page of text, upper & lower case, 256 user defined symbols, 160 x 192 graphics matrix, memory mapped, has key board input.

IOV-1095K 4 MHz kit	\$349.95
IOV-1095A 4 MHz A & T	\$439.95
IOV-1096K 80 x 48 upgrade	\$39.95

VDB-8024 - SD Systems

80 x 24 I/O mapped video board with keyboard I/O, and on-board Z-80A*.

IOV-1020K Kit	\$399.95
IOV-1020A Jade A & T	\$459.95

VIDEO BOARD - Jade

64 characters x 16 lines, 7 x 9 dot matrix, full upper/lower case ASCII character set, numbers, symbols, and greek letters, normal/reverse/blinking video, S-100.

IOV-1050K Kit	\$99.95
IOV-1050A A & T	\$125.00
IOV-1050B Bare board	\$29.95

Motherboards

ISO-BUS - Jade

Silent, simple, and on sale - a better motherboard

6 Slot (5 1/4" x 8")

MBS-061B Bare board	\$19.95
MBS-061K Kit	\$39.95
MBS-061A A & T	\$49.95

12 Slot (9 3/4" x 8")

MBS-121B Bare board	\$29.95
MBS-121K Kit	\$69.95
MBS-121A A & T	\$89.95

18 Slot (14 1/2" x 8")

MBS-181B Bare board	\$49.95
MBS-181K Kit	\$99.95
MBS-181A A & T	\$139.95

Mainframes

MAINFRAME - Cal Comp Sys

12 slot S-100 mainframe with 20 amp power supply


ENC-112105 Kit	\$379.95
ENC-112106 A & T	\$409.95

DISK MAINFRAME - N.P.C.

Holds 2 8" drives and a 12 slot S-100 system. Attractive metal cabinet with 12 slot motherboard & card cage, power supply, dual fans, lighted switch, and other professional features

ENS-112320 with 25 amp p.s.	\$699.95
-----------------------------	----------

S-100 Memory



EXPANDORAM II - S D Systems

4 MHz RAM board expandable from 16K to 64K

MEM-16630K 16K kit	\$275.95
MEM-32631K 32K kit	\$295.95
MEM-48632K 48K kit	\$315.95
MEM-64633K 64K kit	\$335.95
Assembled & tested	add \$50.00

64K RAM - Calif Computer Sys

4 MHz bank port / bank byte selectable, extended addressing, 16K bank selectable, PHANTOM line allows memory overlay, 8080 / Z-80 / front panel compatible.

MEM-64565A A & T	\$575.00
------------------	----------

32K STATIC RAM - Jade

2 or 4 MHz expandable static RAM board uses 2114L's

MEM-16151K 16K 4 MHz kit	\$169.95
MEM-32151K 32K 4 MHz kit	\$299.95
Assembled & tested	add \$50.00

16K STATIC RAM - Mem Merchant

4 MHz 16K static RAM board, IEEE S-100, bank selectable, Phantom capability, addressable in 4K blocks, "disable-able" in 1K segments, extended addressing, low power

MEM-16171A A & T	\$174.95
------------------	----------

S-100 Disk Controller

DOUBLE DENSITY - Cal Comp Sys

5 1/4" and 8" disk controller, single or double density, with on-board boot loader ROM, and free CP/M 2.2* and manual set.

IOD-1300A A & T	\$369.95
-----------------	----------

VERSAFLOPPY II - SD Systems

New double density controller for both 8" & 5 1/4"

IOD-1160K Kit	\$339.95
IOD-1160A A & T	\$379.95

Disk Drives

8" DISK DRIVES

Highly reliable double density floppy disk drives

Shugart 801R single sided, double density

MSF-10801R SA-801R	\$425.00
Special Sale Price	2 for \$790.00

Shugart 851R double sided, double density

MSF-10851R SA-851R	\$595.00
Special Sale Price	2 for \$1150.00

Siemens FDD100-8D2 single sided, double density

MSF-201120 6 mo warranty	\$385.00
Special sale price	2 for \$750.00

Qume Datatrak 8 double sided, double density

MSF-750080 SA-851R compatible	\$599.95
Special sale price	2 for \$1160.00

JADE DISK PACKAGE


Double density controller, two 8" double density floppy disk drives, CP/M 2.2 (configured for controller), hardware and software manuals, boot PROM, cabinet, power supply, fan, & cables

Special Package Price Kit	\$1395.00
---------------------------	-----------

5 1/4" Diskettes Box of 10	\$22.00
----------------------------	---------

8" Diskettes Box of 10	\$24.00
------------------------	---------

S-100 CPU



CB-2 Z-80 CPU - S.S.M.

2 or 4 MHz Z-80 CPU board with provision for up to 8K of ROM or 4K of RAM on board, extended addressing, IEEE S-100, front panel compatible.

CPU-30300K Kit	\$239.95
CPU-30300A A & T	\$299.95

2810 Z-80* CPU - Cal Comp Sys

2 1/4 MHz Z-80A* CPU with RS-232C serial I/O port and on-board MOSS 2.2 monitor PROM, front panel compatible.

CPU-30400A A & T	\$269.95
------------------	----------

SBC-200 - SD Systems

4 MHz Z-80* CPU with serial & parallel I/O ports, up to 8K of on-board PROM, software programmable baud rate generator, 1K of on-board RAM, Z-80 CTC.

CPC-30200K Kit	\$339.95
CPC-30200A Jade A & T	\$399.95

S-100 I/O

I/O-4 - S.S.M.

2 serial I/O ports plus 2 parallel I/O ports

IOI-1010K Kit	\$179.95
IOI-1010A A & T	\$249.95
IOI-1010B Bare board	\$35.00

Novation Cat Modem

(We have only 265

available at this special price)



IOM-5200A List price \$189.95	\$139.95
-------------------------------	----------

D-CAT 300 baud, direct connect modem

IOM-5201A Special sale price	\$189.00
------------------------------	----------

AUTO-CAT Auto answer/originate, direct connect

IOM-5230A Special sale price	\$239.95
------------------------------	----------

Place Orders Toll Free

Continental U.S. Inside California

800-421-5500 800-262-1710

For Technical Inquiries or Customer Service call:

213-973-7707

JADE Computer Products

4901 W. Rosecrans, Hawthorne, Ca 90250

TERMS of SALE: Cash, checks, credit cards, or Purchase Orders from qualified firms and institutions.

Minimum Order \$15.00. California residents add 6% tax. Minimum shipping & handling charge \$3.00.

Pricing & availability subject to change

Why use their flexible discs:

Ampex, Athana, BASF, Caelus, Control Data, Dysan, IBM, Inmac, K-Line, Maxell, Nashua, Scotch, Shugart, Syncom, 3M, Verbatim or Wabash

when you could be using

MEMOREX

for as low as \$1.99 each?

Find the flexible disc you're now using on our cross reference list... then write down the equivalent Memorex part number you should be ordering.

Product Family	Product Description	Memorex Part Number (3201-)	CE quant. 100 price per disc (\$)	Ampex	Athana	BASF	Caelus	Dysan	IBM	K-Line	Maxell	Nashua	Scotch 3M	Shugart	Syncom	Verbatim	Wabash	Inmac	Control Data
Flexible Disc 1x	IBM Compatible (128 B/S, 26 sectors)	3060	2.19	SFD-111110	473071	53428	CM-F11	800506	2305830	40013	FD-1128	FD-1	740-0	S/A-100	15002	FD34-1000	F111111X	7870-K	421802
	IBM Compatible (128 B/S, 26 sectors) w/ W.P.N.	3062	2.24	—	—	—	—	—	—	—	—	—	740-0	—	—	—	—	—	—
	IBM Compatible (128 B/S, 26 sectors) w/ W.P.N. & Hub ring	3064	2.55	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	IBM Compatible (128 B/S, 26 sectors) REVERSIBLE	1729	3.35	SFD-113110	473072	54431	—	—	—	40015	—	FD-2	740-2-0	—	15150	FD34-2000	F171111X	7860-K	—
	IBM System 6 Compatible	3066	2.19	—	473077	54561	—	800509	1669959	40014	—	—	740-0-088	—	15003	FD60-1000	F116111X	7861-K	—
	IBM Compatible (256 B/S, 15 sectors)	3109	2.19	SFD-111210	473073	—	—	800584	2305845	40040	—	—	740-3600	—	15005	FD36-1000	F112111X	7869-K	—
	IBM Compatible (512 B/S, 8 sectors)	3110	2.19	—	473074	—	—	800585	1669954	40044	—	—	—	—	15004	FD60-1000	F113111X	7869-K	—
	Shugart Compatible, 32 hard sector	3015	2.19	SFD-211010	470901	53802	CM-F21	101/1	—	40016	—	FD-132	740-32	S/A-101	15025	FD32-1000	—	7860-K	421322
	Shugart Compatible, 32 hard sector REVERSIBLE	3025	3.35	SFD-213010	—	—	—	—	—	40017	—	—	740-3-32	—	15151	FD32-2000	—	7860-K	—
	Wang Compatible, 32 hard sector w/Hub ring	3087	2.50	—	—	54491	—	—	—	—	—	—	740-33RM	—	—	—	F37A411X	—	—
Flexible Disc 1d	CPT 8000 Compatible	3045	2.79	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	IBM Compatible (128 B/S, 26 sectors)	3090	2.95	SFD-121010	474071	54568	—	3740/1D	—	40047	FD-1128/M2100	FD-1D	741-0	—	—	FD34-8000	F131111X	7857-K	423002
	Soft Sector (128 B/S, 26 sectors) REVERSIBLE	3093	3.99	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	Shugart Compatible, 32 hard sector	3091	2.95	SFD-221010	470801	54596	—	101/1D	—	40024	FD-1320	—	741-32	S/A-103	15075	FD32-8000	F33A410X	7887-K	423332
	Wang Compatible, 32 hard sector REVERSIBLE	3094	3.99	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
Flexible Disc 2x	Wang Compatible, 32 hard sector w/Hub ring	3088	3.20	—	—	—	—	—	—	—	—	—	—	—	—	—	F22A411X	—	—
	Soft Sector (Unformatted)	3101	3.84	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	Soft Sector (128 B/S, 26 sectors)	3113	3.84	—	—	54426	—	800814	1766870	—	—	—	—	S/A-150	15153	FD10-4026	F121111X	—	—
	Soft Sector (256 B/S, 15 sectors)	3106	3.84	—	473477	54226	—	800815	2736700	40043	FD-256D	—	742-0	—	15154	FD10-4015	F122111X	7856-K	424612
	32 Hard Sector	3108	3.84	—	—	—	—	—	—	—	FD-32	—	—	—	—	—	—	—	—
Flexible Disc 2d	Soft Sector (Unformatted)	3102	3.49	—	473485	—	—	DY-150	—	40028	FD-256D	FD-20	743-0	—	15103	OD34-4001	—	—	425002
	Soft Sector (128 B/S, 26 sectors)	3115	3.49	—	—	—	—	—	—	—	—	—	—	S/A-150	—	—	—	—	—
	Soft Sector (128 B/S, 26 sectors)	3103	3.49	—	473471	54235	—	800817	1766872	40019	FD-256D	—	743-0-256	—	15101	OD34-4025	F144111X	7856-K	425602
	Soft Sector (512 B/S, 15 sectors)	3114	3.49	—	473472	54473	—	800818	1690044	40039	—	—	743-0-512	—	15100	OD34-4015	F145111X	—	425612
	Soft Sector (1024 B/S, 8 sectors)	3104	3.49	—	473473	54485	—	800819	1690045	40020	—	—	743-0-1024	—	15102	OD34-4008	F147111X	7859-K	425622
	32 Hard Sector	3105	3.49	SFD-321010	470851	—	—	101/2D	—	40021	FD-320	—	743-32	S/A-151	15125	OD32-4000	F34A411X	7881-K	425322
	Burroughs B-80 Compatible 32 Hard Sector	3092	3.49	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	Soft Sector (1024 B/S, 8 sectors) w/ Hub Ring	3116	3.75	—	—	—	—	—	—	—	—	—	—	—	—	—	F34A611X	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
Flexible Disc FD	Memorex 651 or Equiv. Drive Compatible	30712003	2.95	—	470851	—	CM-F31	FDV	—	40002	—	FD-165	511-0	—	15026	FD65-1000	F61A111X	7910	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
Mini Flexible Disc 1x	Soft Sector (Unformatted)	3401	1.99	—	475001	54256	—	104/1	—	40500	MD1	MD 1	744-0	S/A-104	15300	MD25-01	M11A211X	7897	441002
	10 Hard Sector	3403	1.99	—	475010	54257	—	107/1	—	40501	—	MD 110	744-10	S/A-107	15325	MD25-10	M41A211X	7898	441102
	16 Hard Sector	3405	1.99	—	475016	54258	—	105/1	—	40502	MD1	MD 118	744-18	S/A-105	15326	MD25-18	M51A211X	7899	441162
	Soft Sector (Unformatted) W/Hub Ring	3431	2.19	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	10 Hard Sector, w/Hub Ring	3433	2.19	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
Mini Flexible Disc 1d	16 Hard Sector, w/Hub Ring	3435	2.19	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	Soft Sector	3417	2.24	—	—	54648	—	104/1D	—	—	—	—	—	—	—	—	—	—	—
	10 Hard Sector	3418	2.24	—	—	54649	—	107/1D	—	—	—	—	—	—	—	—	—	—	—
	Double-Density Media	3419	2.24	—	—	54652	—	105/1D	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
Mini Flexible Disc 2d	Soft Sector	3421	2.74	—	—	54654	—	104/2D	—	—	MD2-D	—	745-0	S/A-154	—	MD55-01	—	—	—
	10 Hard Sector	3423	2.74	—	—	54657	—	107/2D	—	—	—	—	745-10	S/A-157	—	MD55-10	—	—	—
	Double-Density Media	3425	2.74	—	—	54630	—	105/2D	—	—	MD2-D	—	745-18	S/A-155	—	MD55-18	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—

Memorex Flexible Discs...The Ultimate in Memory Excellence

Quality

Memorex means quality products that you can depend on. Quality control at Memorex means starting with the best materials available. Continual surveillance throughout the entire manufacturing process. The benefit of Memorex's years of experience in magnetic media production, resulting, for instance, in proprietary coating formulations. The most sophisticated testing procedures you'll find anywhere in the business.

100 Percent Error Free

Each and every Memorex Flexible Disc is certified to be 100 percent error free. Each track of each flexible disc is tested, individually, to Memorex's stringent standards of excellence. They test signal amplitude, resolution, low-pass modulation, overwrite, missing pulse error and extra pulse error. They are torque-tested, and competitively tested on drives available from almost every major drive manufacturer in the industry including drives that Memorex manufactures. Rigid quality audits are built into every step of the manufacturing process and stringent testing result in a standard of excellence that assures you, our customer, of a quality product designed for increased data reliability and consistent top performance.

Customer-Oriented Packaging

Memorex's commitment to excellence does not stop with a quality product. They are proud of their flexible discs and they package them with pride. Both their packaging and their labeling have been designed with your ease of identification and use in mind. The desk-top box containing ten discs is convenient for filing and storage. Both box labels and jacket labels provide full information on compatibility, density, sectoring, and record length. Envelopes with multi-language care and handling instructions and color-coded removable labels are included. A write-protect feature is available to provide data security.

Full One Year Warranty — Your Assurance of Quality

Memorex Flexible Discs will be replaced free of charge by Memorex if they are found to be defective in materials or workmanship within one year of the date of purchase. Other than replacement, Memorex will not be responsible for any damages or losses (including consequential damages) caused by the use of Memorex Flexible Discs.

Quantity Discounts Available

Memorex Flexible Discs are packed 10 discs to a carton and 10 cartons to a case. Please order only in increments of 100 units for quantity 100 pricing. We are also willing to accommodate your smaller orders. Quantities less than 100 units are available in increments of 10 units at a 10% surcharge. Quantity discounts are also available. Order 500 or more discs at the same time and deduct 1%; 1,000 or more saves you 2%; 2,000 or more saves you 3%; 5,000 or more saves you 5%; 10,000 or more saves you 7%; 25,000 or more saves you 8%; 50,000 or more saves you 9% and 100,000 or more discs earns you a 10% discount off our super low quantity 100 price. Almost all Memorex Flexible Discs are immediately available from CE. Our warehouse facilities are equipped to help us get you the quality product you need, when you need it. If you need further assistance to find the flexible disc that's right for you, call the Memorex compatibility hotline. Dial 800-538-8080 and ask for the flexible disc hotline extension 0997. In California dial 800-672-3525 extension 0997.

Buy with Confidence


To get the fastest delivery from CE of your Memorex Flexible Discs, send or phone your order directly to our Computer Products Division. Be sure to calculate your price using the CE prices in this ad. Michigan residents please add 4% sales tax. Written purchase orders are accepted from approved government agencies and most well rated firms at a 10% surcharge for net 10 billing. All sales are subject to availability. All sales are final. Prices, terms and specifications are subject to change without notice. Out of stock items will be placed on backorder automatically unless CE is instructed differently. International orders are invited with a \$20.00 surcharge for special handling in addition to shipping charges. All shipments are F.O.B. Ann Arbor, Michigan. No COD's please. Non-certified and foreign checks require bank clearance.

Mail orders to: Communications Electronics, Box 1002, Ann Arbor, Michigan 48106 U.S.A. Add \$8.00 per case or partial-case of 100 8-inch discs or \$6.00 per case of 100 5 1/4-inch mini-discs for U.S.P.S. ground shipping and handling in the continental U.S.A. If you have a Master Charge or Visa card, you may call anytime and place a credit card order. Order toll-free in the United States. Call anytime 800-521-4414. If you are outside the U.S. or in Michigan, dial 313-994-4444. Dealer inquiries invited. All order lines at Communications Electronics are staffed 24 hours.

Copyright ©1981 Communications Electronics™



Order Toll-Free!
(800) 521-4414




For Data Reliability—Memorex Flexible Discs

C COMMUNICATIONS ELECTRONICS™

Computer Products Division

854 Phoenix □ Box 1002 □ Ann Arbor, Michigan 48106 U.S.A.
Call TOLL-FREE (800) 521-4414 or outside U.S.A. (313) 994-4444

INTELLIGENT VIDEO I/O FOR S-100 BUS



VIO-X

The VIO-X Video I/O Interface for the S-100 bus provides features equal to most intelligent terminals both efficiently and economically. It allows the use of standard keyboards and CRT monitors in conjunction with existing hardware and software. It will operate with no additional overhead in S-100 systems regardless of processor or system speed.

Through the use of the Intel 8275 CRT controller with an onboard 8085 processor and 4K memory, the VIO-X interface operates independently of the host system and communicates via two ports, thus eliminating the need for host memory space. The screen display rate is effectively 80,000 baud.

The VIO-X1 provides an 80 character by 25 line format (24 lines plus status line) using a 5 × 7 character set in a 7 × 10 dot matrix to display the full upper and lower case ASCII alphanumeric 96 printable character set (including true descenders) with 32 special characters for escape and control characters. An optional 2732 character generator is available which allows an alternate 7 × 10 contiguous graphics character set.



Distributed by:

The VIO-X2 also offers an 80 character by 25 line format but uses a 7 × 7 character set in a 9 × 10 dot matrix allowing high-resolution characters to be used. This model also includes expanded firmware for block mode editing and light pen location. Contiguous graphics characters are not supported.

Both models support a full set of control characters and escape sequences, including controls for video attributes, cursor location and positioning, cursor toggle, and scroll speed. An onboard Real Time Clock (RTC) is displayed in the status line and may be read or set from the host system. A checksum test is performed on power-up on the firmware EPROM.

Video attributes provided by the 8275 in the VIO-X include:

- FLASH CHARACTER
- INVERSE CHARACTER
- UNDERLINE CHARACTER or
- ALT. CHARACTER SET
- DIM CHARACTER

The above functions may be toggled together or separately.


The board may be addressed at any port pair in the IEEE 696 (S-100) host system. Status and data ports may be swapped if necessary. Inputs are provided for parallel keyboard and for light pen as well as an output for audio signalling. The interrupt structure is completely compatible with Digital Research's MP/M ®.

Additional features include:

- HIGH SPEED OPERATION
- PORT MAPPED IEEE S-100 INTERFACE
- FORWARD/REVERSE SCROLL or
- PROTECTED SCREEN FIELDS
- CONVERSATIONAL or BLOCK MODE (opt)
- INTERRUPT OPERATION
- CUSTOM CHARACTER SET
- CONTROL CHARACTERS
- ESCAPE CHARACTER COMMANDS
- INTELLIGENT TERMINAL EMULATION
- TWO PAGE SCREEN MEMORY

VIO-X1 - 80 × 25 5 × 7 A & T **\$295.00**
Conversational Mode

VIO-X2 - 80 × 25 7 × 7 A & T **\$345.00**
Conversational & Block Modes



VIO-X S-100 I/O INTERFACE


285

WW COMPONENT SUPPLY INC. 1771 JUNCTION AVENUE • SAN JOSE, CA 95112 • (408) 295-7171

DIGITAL RESEARCH COMPUTERS

(214) 271-3538

32K S-100 EPROM CARD NEW!



\$79.95
KIT

USES 2716's
Blank PC Board - \$34
ASSEMBLED & TESTED
ADD \$30

SPECIAL: 2716 EPROM's (450 NS) Are \$9.95 Ea. With Above Kit.

KIT FEATURES:

1. Uses +5V only 2716 (2Kx8) EPROM's.
2. Allows up to 32K of software on line!
3. IEEE S-100 Compatible.
4. Addressable as two independent 16K blocks.
5. Cromemco extended or Northstar bank select.
6. On board wait state circuitry if needed.
7. Any or all EPROM locations can be disabled.
8. Double sided PC board, solder-masked, silk-screened.
9. Gold plated contact fingers.
10. Unselected EPROM's automatically powered down for low power.
11. Fully buffered and bypassed.
12. Easy and quick to assemble.

32K SS-50 RAM

\$329⁰⁰ KIT

For 2MHZ
Add \$10

Blank PC Board
\$50

For SWTPC
6800 - 6809 Buss

Support IC's
and Caps
\$19.95

Complete Socket Set
\$21.00

Fully Assembled,
Tested, Burned In
Add \$30

NEW!

At Last! An affordable 32K Static RAM with full 6809 Capability.

FEATURES:


1. Uses proven low power 2114 Static RAMS.
2. Supports SS50C - EXTENDED ADDRESSING.
3. All parts and sockets included.
4. Dip Switch address select as a 32K block.
5. Extended addressing can be disabled.
6. Works with all existing 6800 SS50 systems.
7. Fully bypassed. PC Board is double sided, plated thru, with silk screen.

16K STATIC RAM KIT-S 100 BUSS

PRICE CUT!

\$169⁹⁵ KIT

FOR 4MHZ
ADD \$10



KIT FEATURES:

1. Addressable as four separate 4K Blocks.
2. ON BOARD BANK SELECT circuitry. (Cromemco Standard!). Allows up to 512K on line!
3. Uses 2114 (450NS) 4K Static RAMs.
4. ON BOARD SELECTABLE WAIT STATES.
5. Double sided PC Board, with solder mask and silk screened layout. Gold plated contact fingers.
6. All address and data lines fully buffered.
7. Kit includes ALL parts and sockets.
8. PHANTOM is jumpered to PIN 67.
9. LOW POWER: under 1.5 amps TYPICAL from the +8 Volt Buss.
10. Blank PC Board can be populated as any multiple of 4K.

BLANK PC BOARD W/DATA-\$33

LOW PROFILE SOCKET SET-\$12

SUPPORT IC'S & CAPS-\$19.95

ASSEMBLED & TESTED-ADD \$35

**OUR #1 SELLING
RAM BOARD!**


16K STATIC RAM SS-50 BUSS

PRICE CUT!

\$159 KIT

FULLY STATIC!

FOR 2MHZ
ADD \$10



FOR SWTPC
6800 BUSS!

ASSEMBLED AND
TESTED - \$35

KIT FEATURES:

1. Addressable on 16K Boundaries
2. Uses 2114 Static Ram
3. Fully Bypassed
4. Double sided PC Board. Solder mask and silk screened layout.
5. All Parts and Sockets included
6. Low Power: Under 1.5 Amps Typical

BLANK PC BOARD-\$35

COMPLETE SOCKET SET-\$12

SUPPORT IC'S AND CAPS-\$19.95

NEW! S-100 SOUND COMPUTER BOARD NEW!

At last, an S-100 Board that unleashes the full power of two unbelievable General Instruments AY3-8910 NMOS computer sound IC's. Allows you under total computer control to generate an infinite number of special sound effects for games or any other program. Sounds can be called in BASIC, ASSEMBLY LANGUAGE, etc.

KIT FEATURES:

- * TWO GI SOUND COMPUTER IC'S.
- * FOUR PARALLEL I/O PORTS ON BOARD.
- * USES ON BOARD AUDIO AMPS OR YOUR STEREO.
- * ON BOARD PROTO TYPING AREA.
- * ALL SOCKETS, PARTS AND HARDWARE ARE INCLUDED.
- * PC BOARD IS SOLDERMASKED, SILK SCREENED, WITH GOLD CONTACTS.
- * EASY, QUICK, AND FUN TO BUILD. WITH FULL INSTRUCTIONS.
- * USES PROGRAMMED I/O FOR MAXIMUM SYSTEM FLEXIBILITY.

Both Basic and Assembly Language Programming examples are included.

SOFTWARE:

SCL™ is now available! Our Sound Command Language makes writing Sound Effects programs a SNAP! SCL™ also includes routines for Register-Examine-Modify, Memory-Examine-Modify, and Play-Memory. SCL™ is available on CP/M compatible diskette or 2708 or 2716. Diskette-\$24.95 2708 - \$19.95 2716 - \$29.95. Diskette includes the source. EPROM'S ARE ORG at E000H.

COMPLETE KIT!

\$84⁹⁵

(WITH DATA MANUAL)

BLANK PC
BOARD W/DATA
\$31

SPECIAL PURCHASE!

UART SALE!

TR1602B - SAME AS TMS6011,
AY5-1013, ETC. 40 PIN DIP

TR1602B

\$2⁹⁵ EACH

4 For \$10⁰⁰

CRT CONTROLLER CHIP

SMC #CRT 5037. PROGRAMMABLE FOR 80 x 24, ETC. VERY RARE
SURPLUS FIND. WITH PIN OUT. \$12.95 EACH.

NEW! G.I. COMPUTER SOUND CHIP

AY3-8910. As featured in July, 1979 BYTE! A fantastically powerful Sound & Music Generator. Perfect for use with any 8 Bit Microprocessor. Contains: 3 Tone Channels, Noise Generator, 3 Channels of Amplitude Control. 16 bit Envelope Period Control, 2-8 Bit Parallel I/O. 3 D to A Converters, plus much more! All in one 40 Pin DIP. Super easy interface to the S-100 or other busses. **\$11.95** PRICE CUT!

SPECIAL OFFER: ~~\$14.95~~ each Add \$3 for 60 page Data Manual.

Digital Research Computers (OF TEXAS)

P.O. BOX 401565 • GARLAND, TEXAS 75040 • (214) 271-3538

TERMS: Add \$2.00 postage. We pay balance. Orders under \$15 add 75¢ handling. No C.O.D. We accept Visa and MasterCard. Tex. Res. add 5% Tax. Foreign orders (except Canada) add 20% P & H. Orders over \$50, add 85¢ for insurance.

ALL SALES ARE SUBJECT TO THE TERMS OF OUR 90 DAY LIMITED WARRANTY. A COPY OF THIS WARRANTY IS AVAILABLE FREE, ON REQUEST.

*TRADEMARK OF DIGITAL RESEARCH.


WE ARE NOT ASSOCIATED WITH DIGITAL RESEARCH OF CALIFORNIA, THE SUPPLIERS OF CPM SOFTWARE.

NEW!

"THE BIG BOARD" OEM - INDUSTRIAL - BUSINESS - SCIENTIFIC SINGLE BOARD COMPUTER KIT! Z-80 CPU! 64K RAM!

NEW!

PARTIALLY ASSEMBLED KITS
For All Sockets Installed
And Soldered Add \$50.



THE FERGUSON PROJECT: Three years in the works, and maybe too good to be true. A tribute to hard headed, no compromise, high performance, American engineering! The Big Board gives you all the most needed computing features on one board at a very reasonable cost. The Big Board was designed from scratch to run the latest version of CP/M*. Just imagine all the off-the-shelf software that can be run on the Big Board without any modifications needed! Take a Big Board, add a couple of 8 inch disc drives, power supply, an enclosure, C.R.T., and you have a total Business System for about 1/3 the cost you might expect to pay.

\$649⁰⁰ **

(64K KIT
BASIC I/O)

SIZE: 8 1/2 x 13 1/4 IN.
SAME AS AN 8 IN. DRIVE.
REQUIRES: +5V @ 3 AMPS
+ 12V @ .5 AMPS.

FULLY SOCKETED!

FEATURES: (Remember, all this on one board!)

64K RAM

Uses industry standard 4116 RAM'S. All 64K is available to the user, our VIDEO and EPROM sections do not make holes in system RAM. Also, very special care was taken in the RAM array PC layout to eliminate potential noise and glitches.

Z-80 CPU

Running at 2.5 MHZ. Handles all 4116 RAM refresh and supports Mode 2 INTERRUPTS. Fully buffered and runs 8080 software.

SERIAL I/O (OPTIONAL)

Full 2 channels using the Z80 SIO and the SMC 8116 Baud Rate Generator. FULL RS232C. For synchronous or asynchronous communication. In synchronous mode, the clocks can be transmitted or received by a modem. Both channels can be set up for either data-communication or data-terminals. Supports mode 2 Int. Price for all parts and connectors: \$85.

BASIC I/O

Consists of a separate parallel port (Z80 PIO) for use with an ASCII encoded keyboard for input. Output would be on the 80 x 24 Video Display.

24 x 80 CHARACTER VIDEO

With a crisp, flicker-free display that looks extremely sharp even on small monitors. Hardware scroll and full cursor control. Composite video or split video and sync. Character set is supplied on a 2716 style ROM, making customized fonts easy. Sync pulses can be any desired length or polarity. Video may be inverted or true. 5 x 7 Matrix - Upper & Lower Case

FLOPPY DISC CONTROLLER

Uses WD1771 controller chip with a TTL Data Separator for enhanced reliability. IBM 3740 compatible. Supports up to four 8 inch disc drives. Directly compatible with standard Shugart drives such as the SA800 or SA801. Drives can be configured for remote AC off-on. Runs CP/M* 2.2.

TWO PORT PARALLEL I/O (OPTIONAL)

Uses Z-80 PIO. Full 16 bits, fully buffered, bi-directional. User selectable hand shake polarity. Set of all parts and connectors for parallel I/O: \$29.95

REAL TIME CLOCK (OPTIONAL)

Uses Z-80 CTC. Can be configured as a Counter on Real Time Clock. Set of all parts: \$14.95

SYSTEM COMPARISON

64K RAM KIT	\$370.00
80 x 24 Video Kit	365.00
Floppy Disk Controller Kit	235.00
Z-80 CPU Kit	185.95
SER & PAR. I/O	129.95
S-100 Mother Board	45.00
SUB TOTAL	\$1330.90

Talk about bangs per buck! The prices shown for \$100 kits were taken from the July 1980 BYTE. This will give some basis for comparison between the Big Board and a similar system implementation on the S100 Buss.

CP/M* 2.2 FOR BIG BOARD

The popular CP/M* D.O.S. modified by MICRONIX SYSTEMS to run on Big Board is available for \$150.00.

PC BOARD

Blank PC Board with Rom Set and Full Documentation.
\$199.00

PFM 3.0 2K SYSTEM MONITOR

The real power of the Big Board lies in its PFM 3.0 on board monitor. PFM commands include: Dump Memory, Boot CP/M*, Copy, Examine, Fill Memory, Test Memory, Go To, Read and Write I/O Ports, Disc Read (Drive, Track, Sector), and Search. PFM occupies one of the four 2716 EPROM locations provided.
Z-80 is a Trademark of Zilog.

Digital Research Computers

(OF TEXAS)

P.O. BOX 401565 • GARLAND, TEXAS 75040 • (214) 271-3538

TERMS: Shipments will be made approximately 3 to 6 weeks after we receive your order. VISA, MC, cash accepted. We will accept COD's (for the Big Board only) with a \$75 deposit. Balance UPS COD. Add \$3.00 shipping.

*TRADEMARK OF DIGITAL RESEARCH. NOT ASSOCIATED WITH DIGITAL RESEARCH OF CALIFORNIA, THE ORIGINATORS OF CPM SOFTWARE
**1 TO 4 PIECE DOMESTIC USA PRICE.

WAMECO

THE COMPLETE PC BOARD HOUSE

EVERYTHING FOR THE S-100 BUSS

- * **CPU-2** Z80 PROCESSOR BOARD ON BOARD ROM AND HARDWARE POWER ON JUMP.
PCBD \$35.95 KIT \$135.95
- * **MEM-3** 24 ADDRESS LINES EXPANDABLE IN 1K INCR. ADDRESSABLE IN 8K BLOCKS. BIDIRECTIONAL BUSSING.
PCBD \$ 42.95 KIT LESS RAM \$119.95
KIT WITH 2114L-4 \$475.95 KIT WITH 2114L-2 \$549.95
A&T WITH 2114L-4 \$505.95 A&T WITH 2114L-2 \$579.95
- * **FPB-1A** FRONT PANEL BOARD FOR 8080A AND Z80 SYSTEMS IMSAI COMPATIBLE.
PCBD \$56.95 KIT \$175.00
- * **MEM-2** 16K RAM 2114's. ADDRESSABLE IN 4K BOUNDARIES.
PCBD \$33.95 KIT (LESS RAMS) \$80.95
- * **EPM-2** 16/32K ROM USES 2716 OR 2708. ADDRESSABLE IN 4K BOUNDARIES.
PCBD \$33.95 KIT (LESS ROMS) \$74.95
- * **CPU-1** 8080A PROCESSOR BOARD WITH VECTOR INTERRUPT.
PCBD \$33.95 KIT \$124.95
- * **QMB-12** 13 SLOT MOTHER BOARD.
PCBD \$42.95 KIT \$125.95
- * **QMB-9** 9 SLOT MOTHER BOARD.
PCBD \$35.95 KIT \$109.95
- * **PTB-1** POWER SUPPLY AND TERMINATOR BOARD.
PCBD \$29.95 KIT \$49.95
- * **RTC-1** REAL TIME CLOCK BOARD WITH TWO INTERRUPTS.
PCBD \$29.95 KIT \$79.95
- * **MEM-1A** 8K RAM, USES 2102's.
PCBD \$33.95 KIT (LESS RAM) \$71.95
- * **IOB-1** I/O BOARD. ONE SERIAL, TWO PARALLEL WITH CASSETTE.
PCBD \$33.95
- * **FDC-1A** FLOPPY DISC CONTROLLER BOARD USES 1771.
PCBD \$45.95

FUTURE PRODUCTS: 80 CHARACTER VIDEO BOARD.
8 PARALLEL PORT I/O BOARD.

DEALER INQUIRIES INVITED, UNIVERSITY DISCOUNTS AVAILABLE
AT YOUR LOCAL DEALER



WAMECO, INC., P. O. BOX 877 • EL GRANADA, CA 94018 • (415) 728-9114



CALIFORNIA COMPUTER SYSTEMS

\$100

2032 32K STATIC RAM A & T.	
450 NSEC..\$579.00, 300 NSEC..\$585.00, 200 NSEC..\$629.00	
2116 16K STATIC RAM A & T.	
450 NSEC..\$285.00, 300 NSEC..\$289.00, 200 NSEC..\$329.00	
2065 64K DYNAMIC RAM A & T.	\$548.95
2200 S-100 MAIN FRAM A & T.	\$379.95
2422 FLOPPY DISC WITH CP/M 2.2™	\$329.95
2802 6502 PROCESSOR A & T.	\$282.95
2810A Z80 CPU A & T.	\$249.95
2710A 4 SERIAL 1/0 A & T.	\$291.95
2718A 2 SERIAL, 2 PARALLEL A & T.	\$305.95
2720A 4 PARALLEL A & T.	\$214.95
PROTO BOARDS WW	\$39.95, SOLDERTAIL \$29.95

APPLE PRODUCTS

7114A 12K ROM/PROM.	\$68.50
7424A CALENDAR/CLOCK.	\$106.95
7440A PROGRAMMABLE TIMER.	\$98.50
7470A A TO O CONVERTER	\$105.95
7490A GPIB (IE 488) INTERFACE.	\$265.95
7710A ASYNC SERIAL.	\$125.95
7712A SYNC SERIAL.	\$153.95
7720A PARALLEL STANDARD.	\$98.95
7720B PARALLEL CENTRONICS.	\$98.95
7811B ARITHMETIC PROCESSOR W/DISC.	\$342.95
7811C ARITHMETIC PROCESSOR W/ROM.	\$342.95
7500A WW BOARD.	\$22.95
7510A SOLDERTAIL BOARD	\$23.95

SOFTWARE

2610 CP/M™ MACRO ASSEMBLER ON DISK	\$76.95
2620 CP/M™ SYMBOLIC INSTRUCTION DEBUGGER	\$64.25
2630 CP/M™ TEXT FORMATER	\$64.25
2640 CP/M™ BACKGROUND PRINT UTILITY.	\$42.95

OTHER CCS PRODUCTS ARE AVAILABLE.
CALL FOR PRICE.



MICROCOMPUTER PRODUCTS

\$100 PRODUCTS

CB1A 8080 PROCESSOR PCBD	\$32.95
KIT	\$155.95, A & T \$215.95
CB-2 280 PROCESSOR BOARD.	
KIT	\$198.95, A & T \$269.95
VB1C 64 x 16 VIDEO, PCBD.	\$32.95
KIT	\$153.95, A & T \$199.95
VB2 64 x 16 VIDEO, PCBD	\$32.95
KIT	\$175.95, A & T \$234.95
VB3 80 CHARACTER VIDEO 4MHZ.	
KIT	\$345.95, A & T \$425.95
UPGRADE RAMS FOR VB-3	\$42.00
104 2 PARALLEL, 2 SERIAL, PCBD	\$32.95
KIT	\$155.95, A & T \$194.95
PB-1 2708, 2716 PROGRAMMER BOARD.	
KIT	\$135.95, A & T \$185.95
MB-10 16K STATIC RAM.	
KIT	\$299.95, A & T \$339.95

APPLE PRODUCTS

A488 IEEE 488 INTERFACE	\$399.95
A10 SERIAL/PARALLEL INTERFACE.	
KIT	\$125.95, A & T \$155.95
AS10 SERIAL I/O	
KIT	\$87.95, A & T \$97.95
API0 PARALLEL 10	
KIT (W/O CABLES) ... \$67.95, A & T (W/O CABLES) ... \$87.95	

OTHER SSM PRODUCTS ARE AVAILABLE.
CALL FOR PRICES.

MIKOS

MONDAY-FRIDAY, 8:00 TO 12:00, 1:00 TO 5:30
THURSDAYS, 8:00 TO 9:00 P.M.

(415) 728-9121

P.O. BOX 955 • EL GRANADA, CA 94018
PLEASE SEND FOR IC, XISTOR AND COMPUTER PARTS LIST

AUG. SPECIAL SALE ON PREPAID ORDERS

(CHARGE CARDS AND C.O.D. OR P.O. NOT AVAILABLE ON THESE OFFERS)

MEM-3 KIT LESS RAM	\$89.95
IOB-1 KIT	\$99.95

WMC inc. WAMECO INC.
BOARDS WITH MIKOS PARTS

MEM-3 32K STATIC RAM, PCBD.	\$36.95
KIT LESS RAM	\$95.95, A & T \$135.95

CPU-2 Z80 PROCESSOR, PCBD	\$32.95
KIT LESS ROM	\$109.95, A & T \$149.95

EPM-2 16K/32K EPROM, PCBD	\$32.95
KIT LESS ROM	\$65.95, A & T \$99.95

FPB-1 FRONT PANEL, PCBD	\$48.50
KIT	\$144.95, A & T \$184.95

CPU-1 8080 PROCESSOR, PCBD.	\$29.95
KIT	\$89.95, A & T \$129.95

QMB-12 13 SLOT MOTHER BOARD, PCBD	\$39.95
KIT	\$95.95, A & T \$135.95

OTHER WAMECO PRODUCTS ARE AVAILABLE.
CALL FOR PRICES.

MIKOS PARTS ASSORTMENTS ARE ALL FACTORY MARKED PARTS. KITS INCLUDE ALL PARTS LISTED AS REQUIRED FOR THE COMPLETE KIT LESS PARTS LISTED ALL SOCKETS INCLUDED

LARGE SELECTION OF LS TTL AVAILABLE.
PURCHASE \$50.00 WORTH OF LS TTL AND GET 10% CREDIT TOWARD ADDITIONAL PURCHASES. PREPAID ORDERS ONLY.

VISA or MASTERCARD: Send account number, interbank number, expiration date and sign your order. Approx. postage will be added. Check or money order will be sent post paid in U.S. If you are not a regular customer, please use charge, cashier's check or postal money order. Otherwise there will be a two-week delay for checks to clear. Calif. residents add 6% tax. Money back 30-day guarantee. We cannot accept returned IC's that have been soldered to. Prices subject to change without notice. \$10 minimum order. \$1.50 service charge on orders less than \$10.00.

PRINTERS

EPSON MX-80

Now in stock!
The MX-80 dot matrix printer. Unequalled Epson reliability. Has all the features of the MX-70 plus more power and extra functions.
CALL US

C-ITOH STARWRITER: LETTER QUALITY PRINTING FOR UNDER \$2000!


This daisywheel printer gives high quality at a low price. 25 cps. Parallel and serial interfaces available.
CALL

NEC SPINWRITER FROM THE FIRST NAME IN LETTER QUALITY PRINTERS/Compumart offers beautiful print quality with NEC Spinwriter Terminals. We carry all models from RO THRU KSR WITH NUMERIC KEYPAD—5510-5530. All versions give unsurpassed hard copy output!

CALL FOR PRICES

NEW INTEGRAL DATA'S 560 PRINTER/All the exciting features of the 400 series plus 14 1/2" paper capacity. 132 col. graphics printer.

IDS 445. Priced lower than the 440 and equipped with a better print head. With & w/o graphics.
IDS 460. Features include correspondence quality printing, high resolution graphics.
CALL FOR PRICES



CENTRONICS PRINTERS 3 SERIAL MODEL 737

The closest thing to letter quality print for under \$1000.
List \$1045 **SPECIAL \$795.**

737-1 Parallel Interface
List \$995 **SALE PRICE \$695.**

PLUS EXCITING REBATE OFFER ON CENTRONICS PRINTERS.

OMNI 810 PRINTER FROM TEXAS INSTRUMENTS **CALL US**

The 820 RO PACKAGE includes machine mounted paper tray and cable. A compressed print option and device forms control are standard features.

THE 820 KSR PACKAGE includes fully ASCII Keyboard plus all of the features of the RO.

CALL FOR PRICES

MONITORS TERMINALS

CLEARANCE ZENITH COLOR VIDEO MONITOR \$349.


SUPER SELLING TERMINALS FROM LEAR SIEGLER/We have the following Lear Siegler terminals in stock at prices too low to print! Call for quotes.

ADM-3A/Industry's favorite dumb terminal for some very smart reasons/ADM-3A + NEW from Lear Siegler. CALL!

IT IS HERE! It is the new Intermediate Terminal from Lear Siegler. CALL FOR DETAILS

SANYO MONITORS AT LOW COMPUMART PRICES/Sanyo's new line of CRT data display monitors are designed for the display of alphanumeric or graphic data.

9" SANYO B/W \$169. CALL
12" SANYO B/W CALL
12" SANYO W/ GREEN SCREEN CALL
13" SANYO COLOR CALL



NEC COLOR MONITOR/RECEIVER HIGH RESOLUTION/

Composite video using BNC connectors. 8-Pin connector for VCR/VTR video loop In/Out and television reception. **CALL US!**

Visit our giant

ANN ARBOR STORE

1250 North Main Street
Ann Arbor, Michigan

FREE CATALOGS

MICRO

Our complete line of micro-computers, accessories and peripherals.

DEC LSI-11

Systems configured and integrated with other manufacturers compatibles.

Send for them!

CALCULATORS MISC

HP-41C CALCULATORS

MEMORY MODULES for storing programs of up to 2000 lines of program memory.

"EXTRA SMART" CARD READER. Records programs and data back onto blank magcards.

THE PRINTER. Upper and lower case. High resolution plotting. Portable thermal operation.

APPLICATION MODULES

CALL FOR PRICES ON ALL

NEW SUPER 41-CV SYSTEMS with Quad RAMS built-in. Maximum memory on-board leaves slots open for Application Pacs and peripherals.

+ CARD READER + CARD READER + PRINTER

QUAD RAMS equivalent to four Memory Modules all packed into one.

CALL ON ALL

MATROX PRODUCTS/Compumart stocks the complete line.

CALL ON SPECS

DEC LSI-11/Compumart now offers the entire product line.


CALL FOR PRICES AND DELIVERY

NOVATION CAT ACOUSTIC MODEM Answer Originate.

CALL

NEW! D-CAT Direct Connect Modem from Novation.

CALL



NEW!

GILTRONIX RS 232 SWITCH/ The ultimate in flexibility. You can connect three peripherals to one computer or three computers to one peripheral. Switches the eight most important RS 232 signals.

CALL ON PRICE

DYSAN DISKETTES/Single side, single density. Hard or Soft Sector

\$5. ea.

MEMOREX 3401's/5 1/4 disks \$3.25
/with hub ring for Apple \$3.50

MEMORY INTEGRATED CIRCUITS/ Call for quantity discounts when ordering over 50 units. **CALL**

MOTOROLA 4116 (200 Nano-second Plastic) \$4.50

SYSTEMS SOFTWARE

ROM EXPANSION ACCESSORIES FOR AIM—

CALL SPECS AND PRICES

APPLE III IS IN STOCK/Apple III Information Analyst Package—

128K Apple III, Black and White Monitor 12", and information analyst software. **CALL**

TOP SOFTWARE PACKAGES FROM COMPUMART

VISICALC/FOR APPLE/FOR HP/FOR COMMODORE/FOR ATARI

SOFTWARE FROM APPLE/Apple Plot (the perfect graphic complement for Visicalc/Dow Jones News & Quotes/Apple Fortrom/Apple Writer/Pascal Language System/Controller Business System **CALL**

PERSONAL SOFTWARE/Visidex/VisiPlot/VisiTerm **CALL**

MUSE/Super Text **CALL**



MOUNTAIN COMPUTER/

Expansion accessories for Apple/Super Talker/The Music System/ROM plus board with Keyboard filter/ROM Writer/Clock Calendar/Atod and Dto A Converter/Clock for Apple/CPS Multifunction Board **CALL**

VIDEX/Video Term (80 col. x 24 line, 7x9 Matrix plug in compatible board for Apple II) w/wo graphics EPROM/SSM Serial & Parallel, Apple Interface/ABT's Numeric Key Plan/California Microcomputer Keyboard **CALL**

NEW!

VIC 20 PERSONAL COMPUTER FROM COMMODORE

\$299.

IMPORTANT ORDERING INFORMATION

CALL 800 343-5504 in Massachusetts (617) 491-2700, phones open from 8:30 a.m. to 7:00 p.m. Mon-Fri. 11:00 a.m. to 4:00 p.m. Sat.
PO's. Accepted from Dun & Bradstreet rated companies—shipment

contingent upon receipts of signed purchase order.

SALE PRICES. Valid for month of magazine date only—all prices subject to change without notice. Our Ann Arbor retail store is open 11:00 a.m. to 7:00 p.m. Tues-Fri. 10:00 a.m. to 5:00 p.m. on Saturdays

SYSTEMS APPLE II STARTER \$1895.

SAVE OVER \$200 ON OUR BEST SELLING APPLE SYSTEM/ System includes a 48K Apple II, Apple Disk, DOS 3.3 and Controller and a Sup R MOD RF Modulator. List \$2209.


EXCLUSIVE FOR THE APPLE: Magic Wand, Videx, Z-80 softcard (Requires 48K Apple and disk). COMPLETE SYSTEM \$925.

APPLE ACCESSORIES

CHOOSE FROM: Silentype Printer w/x face/Light Pen/Easy Writer (80 col. need a Videx)/Clock for Apple.

FROM MICROSOFT: 16K RAM Board/FORTRAN.

FROM COMPUTER STATION: Hi-Res Dump for 460 Printer.



OUR APPLE INVENTORY IS COMPLETE. WE'VE GOT IT ALL—CALL US FOR PRICES

SYSTEMS COMMODORE WORD PRO \$4695.

CRISP LETTER QUALITY OUTPUT UNSURPASSED EASE OF OPERATION

This Compumart/Commodore system includes a COMMODORE 8032 32K CPU, a 4040 DUAL DISK, a C-ITOH PRINTER and x/face and WORDCRAFT 80 (all cables included). List \$5385.

CALL FOR DETAILS AND LOW PRICES

A COMPLETE SYSTEM: includes a DUAL DISK DRIVE/TRACTOR PRINTER and an 80 COLUMN 32K CPU. No interfaces needed. Cables included. List \$3685.

COMPUMART \$3335.

SAVE \$200 ON COMMODORE ACCESSORIES WITH PURCHASE OF A 32K PET—SAVE \$100 WITH A 16K PET.

CHOOSE FROM: Visicalc/Word Pro 4/Wordcraft 80/Ozz the Information Wizard/Dow Jones Portfolio Mgmt System/Assembler Development Package.



SYSTEMS HP 83 BASIC \$4249.

This Basic System from Hewlett-Packard includes HP-83/ROM DRAWER/MASS STORAGE ROM/5 1/4" SINGLE MASTER FLEXIBLE DISK DRIVE/HP-1B INTERFACE MODULE/2 METER HP-1B CABLE.

SAVE \$400 ON HP-85 SERIES ACCESSORIES WITH THE PURCHASE OF AN HP-85.

CHOOSE FROM: PERIPHERALS; Disk Drives to Graphics Plotters ENHANCEMENTS: Basic Training/General Statistics/Financial Decision/Math/Linear Programming (\$95 EA.) ACCESSORIES: Enhancement ROMs/ROM drawer/Overhead Transparency Kit SUPPLIES: Plotter Pens/Tape Cartridges INTERFACE MODULES; HP-1B Interconnect Cables/Serial (RS-232C) Interface Module.



WE CARRY EVERY PERIPHERAL MADE FOR THE HP-85. CALL US FOR PRICES

SYSTEMS AIM 65 STARTER \$795.

FROM ROCKWELL

Our AIM Starter System for Educational & Laboratory use includes 4K AIM/BASIC & ROM/ASSEMBLER & ROM/POWER SUPPLY EG1 ENCLOSURE/CRAIG TAPE RECORDER.

ACCESSORIES FOR AIM STARTER: PL 65 High Level Language/Paper for the Aim (roll)/Rockwell's 4 slot Motherboard/

CALL



WE ALSO CARRY RM EXPANSION ACCESSORIES FOR THE AIM-65. CALL FOR SPECS AND PRICES



800-343-5504

IN MASS CALL 617-491-2700

Systems
Customized

COMPUMART

65 Bent Street, Dept 128,
PO Box 568, Cambridge, MA 02139

From THE LEADER...

We just might be the largest independent small systems dealer in the country. Here's why: COMPUMART has been serving the computer needs of industry since 1971.

We stock, for immediate shipment, only those products from the finest micro-computer manufacturers.

And any product, except software, can be returned within 10 days for a full refund—even if you just change your mind. We also honor all manufacturers' warranties. Our expert technicians will service any product we sell.

Call us for more information on products, product configuration and service. Our phones are open Monday thru Friday, 8:30 a.m. to 7:00 p.m. and Saturday 11:00 a.m. to 4:00 p.m.

We have a staff of highly knowledgeable sales people waiting to hear from you, and to help. Because service is what we're all about.

MICROCOMPUTING T.M. LIST OF ADVERTISERS

Reader Service Number	Page	Reader Service Number	Page	Reader Service Number	Page
121 A B Computers.....	143	339 End-of-File.....	155	* Mikos.....	191
91 Aardvark Technical Services.....	137	116 Epson America.....	52	255 Miller Microcomputer Services.....	123
232 Aardvark Technical Services.....	210	254 Erickson Communications.....	14	304 Mini Micro Mart.....	74
261 Ackerman Digital Systems, Inc.....	23	327 Essex Publishing.....	88	238 Mini Micro Mart.....	223
478 Action-Research Northwest.....	214	131 Fessenden Computer Service.....	155	226 Mini Micro Mart.....	225
393 Adventure International.....	54,55	191 Floppy Disk Service.....	29	50 Mini Micro Mart.....	224
311 Alpha Byte Stores.....	CIII	392 General Videotex Corp.....	23	391 Minis 'n Micros, Inc.....	72
249 American Software & Systems, Inc.....	153	22 Gimix, Inc.....	108	37 Mullen Computer Products.....	217
56 American Square Computers.....	199	301 Gimix, Inc.....	163	81 Multi Business Computer Systems.....	47
187 Ancie Labs.....	103	488 Gimix, Inc.....	206	381 Muse Software.....	126
477 Apple Computer, Inc.....	210	42 Godbout Electronics.....	176	* National Computer Shows.....	45
387 Apple Orchard.....	129	465 Grafix.....	206	378 Natural Language Systems.....	138
* Applied Analytics.....	73	5 Hanley Engineering.....	81	* Netronics R & D Ltd.....	38,122,209
494 Archives, Inc.....	204	243 Happy Hands.....	153	291 New England Business Service, Inc.....	201
471 Allen Ashley.....	208	236 Heath Company.....	34,35	286 Nibble.....	93
192 Audio Video Systems.....	72	265 Hobby Robotics.....	85	130 Olenky Brothers, Inc.....	145
193 Aurora Software.....	53	33 Human Engineered Software.....	206	89 Omega Sales Company.....	161
480 Aurora Systems, Inc.....	212	476 Image Computer Products.....	210	473 Omni Software Systems, Inc.....	212
96 Automated Equipment.....	77	223 Inmac.....	106	140 Omnitek Systems.....	127
55 Automated Simulations.....	49	Instant Software		482 On-Line Systems.....	215
468 Automated Simulations.....	208	400 Game Programs.....	221	310 Orange Micro.....	86
466 The Avalon Hill Game Company.....	212	401 New Products.....	82	329 Orion Software.....	168
490 Axiom Corporation.....	205	403 Master Directory.....	222	368 Osborne Computers.....	149
124 B.T. Enterprises.....	202	404 Climate Computer.....	215	172 Pacific Exchanges.....	71,92,145
469 BAYSIK Speech.....	210	75 Programmer's Kit.....	163,164,166,167,168,171	71 Pan American Electronics.....	132
256 The CPU Shop.....	125	485 Instructional Development Systems.....	198	472 Pegasus Software.....	212
79 C&S Electronics Mart Ltd.....	148	77 Intergrand Research Corp.....	46	1 Percom Data Company.....	CII
299 California Data Corp.....	170	496 Interaction Systems, Inc.....	204	266 Perry Oil & Gas.....	57
271 Cambridge Learning.....	102	264 Interactive Microware.....	206	303 Personal Computer Systems.....	44
170 Chips & Dale.....	127	73 Interactive Structures.....	139	481 Personal Software, Inc.....	214
28 Cleveland Consumer.....	63	235 Interlude.....	25	479 Professional Business Software, Inc.....	209
376 Communications Electronics.....	186	3 Intertec Data Systems.....	3	202 Progressive Computing.....	106
395 Compstat.....	104	126 J R Inventory Company.....	67	246 Quantum Information Systems.....	107
90 CompuCover.....	43	203 J.C. Datatron.....	112	44 Quest Electronics.....	182
43 Compumart.....	192,193	180 J.E.S. Graphics.....	46	30 RCA Solid State.....	15
42 CompuPro.....	176	92 J.P.C. Products.....	210	46 RKS Enterprises, Inc.....	212
147 CompuServe.....	111	48 Jade Computer Products.....	183,184,185	52 RNB Enterprises.....	181
58 The Computer Answer.....	112	41 Jameco Electronics.....	178,179	390 R.W. Electronics.....	136
320 Computer Case Company.....	66	* John Bell Engineering.....	101	101 Racet Computers.....	148
18 Computer Design Labs.....	21	464 John Bell Engineering.....	206	* Rainbow Computing.....	9
120 Computer Discount of America.....	62	247 Joe Computer.....	42	102 Rand's, Inc.....	156
370 Computer Dynamics.....	171	222 Kalglo Electronics.....	127	* Realty Software Company.....	72
341 Computer Exchange.....	213	Kilobaud Microcomputing		* Robotics Age Magazine.....	39
336 The Computerist, Inc.....	200	* Subscriptions.....	94,170	74 Rondure Company.....	83
362 Computer Plus.....	113	* "Moving".....	108	111 SZ Software Systems.....	168
346 Computer Sales & Service.....	92	* Manuscripts.....	172	146 Scelbi Publications.....	26
36 Computer Shopper.....	133	* University Microfilms.....	138	487 Seattle Computer Products.....	204
110 Computers, Peripherals Unltd.....	143	* Dealers.....	212	374 Select Information Systems, Inc.....	65
283 The Computer Stop.....	121	* Boxes.....	127	132 Sixty-eight Micro Journal.....	138
499 The Computer Stop.....	202	* Kilobaud Klassroom.....	83	* Snappware.....	140
105 The Computer Stop.....	203	* Books.....	173-175	385 Software Concepts.....	205
227 Computers Wholesale.....	120	289 KV-33 Corp.....	97	213 Software Consultants.....	163
176 Computer Trader.....	167	198 LNW Research.....	169	294 Software Review.....	165
467 Computerware.....	210	475 Lamar Instruments.....	215	306 Spectrum Software.....	139
6 Computronics, Inc.....	157	394 Laredo Systems, Inc.....	79	296 The Stocking Source.....	89
197 Compuware Corporation.....	166	355 Leading Edge Products.....	11	288 The Stocking Source.....	33
297 Concord Computer Products.....	190	23 Level IV Products, Inc.....	109	244 Sun Research.....	78
141 Custom Electronics.....	155	211 Lifeboat Associates.....	105	367 System Software Design, Inc.....	171
* Cybernetics, Inc.....	8	59 Lifeboat Associates.....	69	498 Systems Group.....	202
293 D & N Micro Products.....	104	373 Logical Devices, Inc.....	170	470 Systems Plus.....	208
210 Data Ed, Inc.....	27	316 MCP Computer Products.....	144	189 Tab Sales Company.....	58
484 Data Wholesale Corp.....	200	190 MI-8.....	164	* Taranto & Associates.....	13
63 Davis Systems, Inc.....	66	497 Magnolia Microsystems.....	204	233 Tarheel Software Systems.....	92
486 Digital Pathways, Inc.....	198	234 Magnolia Microsystems.....	166	139 Tecmar, Inc.....	47
* Digital Research Computers.....	188,189	483 Mendocino Software.....	208	493 Terrapin, Inc.....	200
* Digital Research Parts.....	180	161 Meta Technologies Corp.....	7	328 Texas Computer Systems.....	39
342 Digital Research, Inc.....	CIV	308 Micro 80, Inc.....	42	492 Total Digital Engineering.....	201
61 Digital Systems Engineering.....	88	* Micro Apple.....	218	118 Toxen Computer Systems.....	97
212 Digital Systems Engineering.....	150	108 Micro Architect.....	144	* VR Data Company.....	99
250 Discount Software Group.....	50	260 The Microcomputer Warehouse.....	58	495 VR Data Company.....	204
* Dosware, Inc.....	102	248 MicroDome.....	150	214 Van Horn Office Supply.....	100
34 Dr. Daley.....	32	100 Micro Management Systems.....	119	337 Vista Computer.....	41
87 Dwo Quong Fok Lok Sow.....	100	134 Micro Matrix.....	164	200 Votrax.....	17
491 E & L Instruments, Inc.....	201	68 Micromail.....	16	285 W. W. Components Supply.....	187
474 ESP Computer Resources.....	209	347 Micro Mint.....	207	* Wameco, Inc.....	191
82 Ecosoft.....	133	335 Micro Products Unlimited.....	92	* West Side Electronics.....	202
93 Electronic Specialists.....	217	* Microsette.....	29	284 White River Products.....	200
47 Electronic Systems.....	177	154 Micro Technology Unlimited.....	211	163 Wintek Corp.....	118
* Electrovalue Industrial.....	167	150 Midwest Computer Peripherals.....	141	122 World Wide Electronics.....	118
272 Ellis Computing.....	98	144 Midwest Scientific Instruments.....	114,115	489 Xerox Corporation.....	198

For further information from our advertisers, please use the Reader Service card.

*This advertiser prefers to be contacted directly.

LETTERS TO THE EDITOR

Force-feeding Education

The "Remarks" in the May 1981 issue caught my interest. I, too, have fond memories of high school and things have changed. I see this clearly since I taught mathematics on an intermediate and secondary level for the New York City Board of Education for two years. I am now teaching Computer Programming (BASIC, FORTRAN IV, and Pascal) to high school juniors and seniors.

You have outlined the problems in education well. The baby-sitting attitude in the public schools is abhorrent but true. I assure you, no one, teacher or otherwise, finds it particularly effective or rewarding to force people to learn.

We do have the responsibility of educating. This is especially important for those students who spend their most critical periods in grades one to 12. The question is how. I agree totally; the computer has come into education at a perfect time, but I maintain some intense reservations about computer-aided instruction which is teacher independent and home-based.

The unfortunate result of a student body separated and detached in the learning process would be the stunting of emotional and personal development. If the elements of interaction and communication are eliminated, the student may grow up feeling most comfortable only in front of a CRT.

I don't believe that the result would be more motivated children. Look back on your experiences in college. Although I am speaking about students whose age level is between six and 18, there is an analogy that can be drawn. What made the accounting course so uppermost in your mind? Where or from whom did the excitement come from? Was an honest concern about and interest in the students on the part of the teacher an ingredient in that positive experience?

I see a renaissance in education coming about. The advent of computer-aided instruction is responsible for this turning point. I am doing extensive research in this area and have implemented in-service workshops encouraging the use of computers not only in mathematics and science, but in languages (using speech synthesizing), history and English. Simulations and video disks will surely enhance and increase the amount of information retained by the student. Some other techniques will involve "live" photos and accurate graphics, along with background music and professional voice over-dubbing.

All in all, we should not force education.

Moving the students out of the schools will not ensure better behavior in society; it may only postpone and augment the problems in the long run. I firmly believe this, even after being assaulted twice in the public schools. Finally, with human example and intervention, these situations can be encountered and averted as soon as possible. The choice rests on a joint, concerted effort, on the part of the parents and schools.

One thing is for certain. With CAI, further developed systems, and more teachers involved in this progress, the renaissance in education is coming of age, regardless of how much time it will take, or the pain in the undertaking. That is why I foresee better schools, more effective teachers, and a raised level of learning. I am looking forward to the advances to be made by both teachers and Instant Software.

Paul S. Drago
St. Raymond High School for Boys
Bronx, NY

Wayne Green Replies

Your argument has merely proven my point.

The teacher I had for accounting had showmanship. We didn't really get to talk with him much or ask questions... it was all enthusiasm on his part and excitement. I find a similar enthusiasm from shows such as Connections, Freedom to Choose, etc. If we can get exciting people to put this stuff on video, using computers to match the speed of the teaching to the interest and intellect of the student, I think we would have a winner.

Your letter was most interesting. It's good to hear from the trenches.

Wayne Green

Inexpensive Word Processing

Craig Anderton ("In Search of the Processed Word," May 1981, p. 39) leaves the impression that a sophisticated word processing system, such as his, must cost at least \$10,000. Not so. Couple the new Osborne I, including its double density option, with one of several daisy-wheel printers selling for under \$2000, and you have a roughly comparable system, including the same software, for under \$4000.

I'm writing this letter on a used TRS-80 Mod I with Radio Shack's Daisywheel II printer operating under Scriptit enhanced with Acorn's Superscript. The cost is again under \$4000, including disk

drives. I suspect professionally useful word processing systems need no longer be as prohibitively expensive as Mr. Anderton's.

Stan Franklin
Memphis, TN

Response:

Your claim that a \$4000 Osborne-based system is equivalent to the system described in the article is stretching things. The Osborne can't do multi-user tasks (which mine has to, on occasion), nor is it easily expandable (I've upgraded my system several times since the article was written).

Craig Anderton
Redwood Valley, CA

Osborne the Obnoxious?

If "it was inevitable" that the Osborne I microcomputer would become a reality, I suppose it was also inevitable that the product introduction would be accompanied by a torrent of the usual self-righteous pomposity from Adam Osborne. Clearly, Osborne has every right to hype his micro-screened computer, but why does he make your readers suffer through a diatribe against the rest of the industry before getting to the system's features? Are we expected to buy an Osborne I because it can do something *better* than other systems on the market, or as simply a vote of support for the manufacturer's imagined "mandate"? Such "crust" deserves an award, but I haven't yet decided whether Mr. Osborne's complexion is better suited to a raspberry or a lemon pie!

Jack Carlson
Anaheim, CA

Osborne makes good reading. However, there is more to say about the Osborne I microcomputer than appears in the May 1981 issue of *Microcomputing*.

In size and weight the Osborne I is more similar to a portable sewing machine than to a briefcase. A more attractive package would be something like the HP-85 with a couple of the new Sony 3-1/2 inch floppy disk drives.

An 80-column external monitor will not be available for the Osborne I, but rather for a subsequent Osborne model.

Although Osborne touts compatibility and excoriates other manufacturers for their unique hardware and software designs, the Osborne I has its own hardware incompatibilities. The video output will not drive the standard monitor: you must

buy a unique Osborne monitor if you want a larger external display. The Osborne I printer interface is standard RS-232 (serial) or standard IEEE-488 (parallel). RS-232 is fine for expensive letter-quality printers but the standard microcomputer printer is a low-cost unit with a Centronics-compatible (not IEEE-488) parallel interface. The Centronics-compatible parallel interface has become the de facto standard microcomputer printer interface. IEEE-488 is an expensive parallel interface used primarily by industry in multiple instrument, control/measurement systems. Osborne espouses low cost hardware; he should have awarded himself a true White Elephant award for that IEEE-488 interface.

Other than that it looks like a good deal.

Robert C. Briggs
Mountain View, CA

The Letters Pour In

We are receiving a colossal number of letters from people who read my article in your magazine (May 1981). They are coming in at the rate of ten to 20 per day. That beats anything generated by publicity in any other magazine.

Adam Osborne
Hayward, CA

What else did you expect?—Editors.

More on CBASIC2

I'd like to make the following comments on the review of CBASIC2 by Bruce Evans in the May 1981 issue of *Microcomputing* (p. 254).

1. I agree with and wish to emphasize his comments about CP/M's ED editor. It is absolutely the worst I have ever used, and I have used several.

2. Evans must have never seen Microsoft BASIC, if he thinks CBASIC2 is the most extensive version of BASIC. Their BASIC 80 is at least as extensive (but it sure chews up a chunk of core).

3. Let me put one false statement to rest here and now. CBASIC2 *does not run faster than the usual BASICs!* The interpreter running on my TRS-80 Model I is faster! CBASIC2 is very slow, due to the fact (as Mr. Evans states) that it is not a true compiler. If you want to see a really fast BASIC, try Microsoft's BASIC Compiler. It also has the advantage that you can run your software on the interpreter first to remove all the bugs before compiling *one time*.

4. His comments about string manipulations are true, except for one problem. There is a MID\$ function to pull pieces of strings out, so that these can be converted to real variables, but there is no easy way to reverse the process. That is, you cannot easily put real variables in the middle of a string.

Just as a side note, there is a version of CP/M and CBASIC2 available for the TRS-80 Model I. I know... I bought it. Only after this did I realize that there is no way you can effectively utilize it on this machine with 5-1/4 inch 35/40 track single density drives. CP/M and CBASIC2 require eight-inch drives with their resultant capacity, or double density small drives.

Charles Reeves, Jr.
Union Carbide
Oak Ridge, TN

Response:

I agree with Mr. Reeves's second point—Microsoft's BASIC-80 is very extensive. But it is also very expensive—almost three times as much as CBASIC2. I also agree with Mr. Reeves that BASIC-80, being an interpreter, chews up a lot of computer memory.

It is on point three that we differ. I must admit that when I went back to the benchmark programs in October 1977 *Kilobaud*, CBASIC2 took a bath on the simple programs. However, by the time I got to program four, CBASIC2 had quite an advantage over my older Processor Technology Extended Cassette BASIC and over my Micropolis Disk BASIC. In using these benchmark tests, there is some problem in deciding when to start timing. Previously, I had started the stopwatch when I pressed RETURN after typing RUN, but this is not valid with a CBASIC2 program, since after you enter "CRUN2 'filename'", you must wait while the run time interpreter is loaded, the program is loaded and the execution begun. This time overhead is ridiculous for a short benchmark program, but it is negligible for one that will run for hours.

Mr. Reeves's comments on Microsoft's BASIC Compiler are a little misleading. To write, run and debug your software on the interpreter and then compile it with the BASIC Compiler, you must have both sets of software, each of which costs over \$300. Mr. Reeves needs almost \$700 worth of software to do what CBASIC2 can handle for less than \$100. I shall put up with these slight limitations unless Mr. Reeves or Microsoft is willing to send me a complimentary copy of BASIC-80 and their BASIC Compiler!

Mr. Reeves's fourth point is correct. I had not yet run into this problem. It can be programmed around by using the LEFT\$ and RIGHT\$ functions to split the original variable into two separate ones. Create the new string by concatenating the third string variable between these two strings. I agree this is a nuisance but it is not insurmountable.

Mr. Reeves's "side note" only strengthens my belief that "toy" microcomputers have no place in business. I use a SOL-20 with a dual drive quad density Micropolis disk system. Each disk uses 77 tracks and can store 350K of data. For the same reason, I am typing this letter by hand—

the inexpensive letter-quality printers cannot handle business applications and I cannot yet cost-justify a "professional" daisywheel!

Bruce Evans, M.D.
Pickering, Ontario
Canada

Business Applications

Please accept my congratulations and best wishes for success in your new undertaking, *Desktop Computing*.

Martin Klaver, writing the June Perspectives, explained the problem beautifully—we need microcomputers for micro applications—and we need to be able to learn to use them quickly.

I have had an Apple II for about six months and have been trying to use it in connection with a real estate and related investment business. As a computer beginner, I'm having problems and I need help.

Please sign me up for *Desktop Computing*.

David S. Ailes
Winter Park, FL

No Longer Undocumented

Edwin Freed's article about "secret" Z-80 codes (April 1981, p. 58) was both interesting and instructive. Although the additional codes do not promise to revolutionize Z-80 programming, they may indeed be handy at times.

Tests run on my TRS-80 entirely confirm the accuracy of Mr. Freed's statements. He does not, however, deal specifically with one group of codes: the four-byte codes starting with DDCB or FDCB. The 62 documented codes in this group perform rotations, shifts and bit operations upon memory locations indicated by the IX or IY registers as offset by the value specified in the third byte of the code. The undocumented codes similarly use the IX or IY registers, with offset, as pointers to the memory locations affected, but, with the exception of the BIT instructions, they also load the results into a register.

For example, the code DDCB05C8 will set bit 1 of the memory location whose address is five greater than the contents of the IX register and will also load the resulting value into the B register. For this operation, which would normally require two separate instructions, I use the mnemonic BSET 1,(IX+5), the letter B indicating the register loaded.

The specific operations and the registers loaded by these codes may be determined readily by comparing the second and fourth bytes with the regular two-byte CB codes. Only in the case of the BIT operations is the indicated register left unloaded; thus the undocumented codes whose fourth byte is between 40 and 7F merely duplicate existing codes.

Even the RLO operation described by Freed is available: the code FDCB0937 (ARLO (IY + 09)) rotates the byte indicated by IY + 9 to the left, shifts a 1 into the low-order bit, and loads the result into the A register. Note that it would normally take three instructions to accomplish this result.

James Yowell Yelvington
Stillwater, OK

Califorina Dreaming

Here is one of those "I have never written a letter to the editor (all right, publisher) before" letters. This time I cannot restrain myself.

I have just finished reading Wayne Green's comments in the June issue. As one of the old-time followers (more than five years), I am distressed to hear of the poor showing that this industry is accused of giving. Sure, I was at the Faire and saw all that you saw but I ask you—is it fair to judge our entire industry on the basis of this small coterie of 32,000 isolated individuals?

No matter, I see further on that there is a serious article on the solid businesslike business of multitask systems. This will show them we have our act together! OOPS! As I peruse the lead photos of these two heavy duty and surely deadly serious computers I see screened right on the front panel that Action Computer Enterprise, Inc., believes that they are located in Pasadena, Califorina... CALIFORINA?

I hope that the article is great. I still can't read it through the tears in my eyes. Please, Lord, tell me that this is just the act of some misguided graphic artist retouching the print for greater clarity.

David Geo. Krauss
Menlo Park, CA

These are limited edition models. Act now while the supply lasts. Guaranteed to become a collector's item.—Editors

Passing the Buck

Recently I faced a problem using a C. Itoh 25 cps Starwriter with a California Computer Systems (CCS) Centronics parallel interface, and the Apple PIE Word Processor by Programma. It seems the customary control-I 80N command that was needed couldn't be entered except as text in the program.

To make a long story short, the driver program that was supplied with the CCS interface didn't cooperate with the C. Itoh printer. Talking to CCS put blame onto Apple PIE and C. Itoh; talking to Programma put blame onto CCS and C. Itoh; and, you guessed it, talking to C. Itoh put blame onto CCS and Apple PIE.

The solution to this problem is so fundamentally simple that it only needs nine

bytes instead of the usual 256 bytes for a driver. It involves storing the accumulator into the appropriate data address for that slot (\$C0n0, where n = slot + 8), loading the accumulator from the same address and then when the value is no longer the same, to return for the next character.

The program in Listing 1 is relocatable not only pagewise but wherever you have nine bytes to spare.

You can even take this one step further by replacing the 5623 PROMs that the CCS board has with a pair of 2112s (256 byte by four bit RAM). Just remember which 5623 is the high order and which is the low order so if you replace them the board will function properly.

A program like Apple PIE asks, by way of a SYSGEN Program, for the printer driver starting address. A slot number will automatically generate a \$Cn00, where n = slot number. You may assign this to any address in memory if you desire. If you install the RAMs then you would just BLOAD the driver into the \$Cn00 address. If not, then the proverbial \$300 is always there.

Mark Johnson
Schultz Systems, Inc.
Barnegat, NJ

A Different Approach

I have a few comments to add to the "North Star Quiz" which was in the June issue. I approached the problem of the exclamation point and PRINT commands differently, by modifying the command table in the BASIC itself. By changing the code for the exclamation point command from 146 to 130, when new programs are typed both the exclamation point and PRINT are stored as the same code and will therefore be listed as PRINT. However, to properly list a previous program which used the original 146 code, it has to remain in the command table unchanged also. For this patch to work properly, the PRINT must be first, the changed exclamation point second and the unchanged exclamation point last. They don't have to be the first three entries in the table, nor do they have to be adjacent, but they should be in this order. Since other data follows this table its size can't be changed.

I gained the extra two bytes by reducing SQRT to SQR and FREE to FRE. Looking over the table again I see that a better possibility would be to delete the square bracket. The only purpose of this in the table is to automatically convert an open bracket to an open parenthesis. Incidentally, Mr. Prisco left the FREE command out of his list; it is 216 decimal or D8 hex.

The command table starts at 3B65 hex or 15205 decimal in the single-density release four version. I don't know about the other versions, but it is easy to find by us-

```
]PRINTCHR$(9);"80N"
```

```
]CALL-151
```

```
*300L
```

```
0300- 8D A0 C0 STA $COAO
0303- AD A0 C0 LDA $COAO
0306- 30 FB BMI $0303
0308- 60 RTS
0309- 00 BRK
030A- 00 BRK
030B- 00 BRK
030C- 00 BRK
030D- 00 BRK
030E- 00 BRK
030F- 00 BRK
0310- 00 BRK
0311- 00 BRK
0312- 00 BRK
0313- 00 BRK
0314- 00 BRK
0315- 00 BRK
0316- 00 BRK
0317- 00 BRK
0318- 00 BRK
*D4F2G
```

```
]
```

```
]COAO IS THE APPROPRIATE DATA ADDRESS FOR SLOT # 2
```

Listing 1.

ing an ASCII dump routine such as the DA command in the North Star Monitor program. The code byte precedes each string.

About the only problem with this change is that an exclamation point in a REMark is also expanded to PRINT. This doesn't affect the running of the program, but it sure lists funny. Actually, Mr. Prisco's programs would do the same thing, but they could be rewritten easily to check for the REM code to ignore the rest of the line.

Another change that I made to the command table was to change EXAM and FILL to PEEK and POKE. There is no real advantage to this, but it gives some strange effects when listing a program that was entered without this patch. For example, the phrase FOR EXAMPLE comes out FOR PEEKPLE.

Larry Hudson
Ventura, CA



Xerox Desktop Computer Talking Telephone Terminal Micro Security Cabinet Apple/Turtle Interface

Desktop Computer and Word Processing System

A 64K desktop workstation that can be used as a word processing system, a business computer or both is available from Xerox Corporation, Office Products Division, 1341 West Mockingbird Lane, Dallas, TX 75247. The Xerox 820 can also be connected to the company's Ethernet local area communications network, which links different kinds of office equipment for high-speed exchange of information. As a word processor, the 820 is designed for organizations needing low-cost display systems. As a desktop computer, it is intended for small businesses and for professionals and managers in larger organizations. Appropriate software tailors the equipment for either function.

The system's standard disk storage has a capacity of about 45 pages of text. A larger disk unit, with a storage capacity of about 140 pages, is available as an option. The printer is a daisywheel Diablo 630, which prints bidirectionally at up to 40 characters per second. Xerox will provide the industry-compatible operating system software for the 820. Price of the desktop computer version, including display screen, keyboard and standard disk storage, is \$2995. As a word processing system, with the optional 40-cps daisywheel printer, price is \$5895. Software is priced separately. Reader Service number 489.

Intelligent Telephone Controller

The SLC-II is a serial line controller that combines



A telephone-based terminal operator from Digital Pathways.

microprocessor intelligence with voice synthesis capability. The SLC-II can automatically dial phone lines and talk in its electronically synthesized voice. Its vocabulary includes more than 300 words, the alphabet and numbers. The SLC-II will spell what it can't say. No software changes to the host computer's operating system are needed. The SLC-II connects between any computer and terminal to monitor the flow of messages. It can then be taught to initiate voice messages at specific time intervals—or upon recognition of certain messages moving from computer to terminal. The SLC-II can also listen and respond to incoming phone messages that originate at a remote terminal or are generated by a telephone keypad.

The SLC-II features automatic time and date entry with a day/month/year calendar. It also comes with built-in power backup via rechargeable batteries, an auto-dial/auto-answer modem, and 16K, 32K or 80K RAM. Priced at \$1975. Reader Service number 486.

Digital Pathways, Inc., 1260 L'Avenida, Mountain View, CA 94043.

Microcomputer System Security Cabinet

An attractive and practical microcomputer cabinet is available from Instructional Development Systems, 2927 Virginia Beach Blvd., Virginia Beach, VA 23452. Compatible systems include Apple II, Atari, Texas Instruments 99/4, Ohio Scientific, Sorcerer and other modular systems. The wood door provides maximum equipment security with two solid brass locks and a full piano hinge; the door opens to serve as a work table. The microprocessor and disk drive units slide out on tray rollers, providing easy access to components. Adequate space is provided for most 13-inch televisions or monitors; monitors are angled down for maximum screen visibility. The design of the cabinet assures a distance of approximately 24 inches from the user's eyes to the television screen, reducing the danger of radiation exposure, eye strain and fatigue.


Two minidisk storage compartments hold as many as 100



Xerox 820 information processor.

LOWEST PRICE - BEST QUALITY

NORTH STAR



North Star Horizon 2


2-5 1/4 Disk Drives
32K Double Den
Factory assem. & tested
Factory guaranteed
List \$3695

only **\$2697**

POWERFUL NORTH STAR BASIC FREE SUPERB FOR BUSINESS & SCIENCE

FACTORY ASSEMBLED & TESTED	LIST	ONLY
HORIZON-2-64K-DOUBLE DEN	\$4195	\$3062
HORIZON-2-32K-QUAD DENSITY	\$3995	\$2916
HORIZON-2-64K-QUAD	\$4495	\$3281
HORIZON RAM ASSM 16K = \$279		32K = \$479
HORIZON RAM ASSM 48K = \$679		64K = \$879
HORIZON DISK DRIVE SALE		
DOUB DEN	SAVE!	\$ 445
NORTH STAR HARD DISK 18 Mb	\$5375	\$3923
NORTH STAR TIME SHARING MULTI-USER		CALL

SUPERBRAIN ZENITH



SUPERBRAIN QD 64K

List \$3995 only \$2995



Z-89 48K

List \$2895 only \$2299

TERMINALS Z-19 \$725 INTERTUBE III only \$725

DYNABYTE COMPUTER—SAVE—PHONE

EPSON MX-80—PHONE

ANADIX 9501 \$1349

NEC PRINTER \$2639

TRACTOR,

THIMBLE,

RIBBON

DIP-81

\$395

TEC LETTER QUAL \$1599



InterSystems

ITHACA INTERSYSTEMS 2A



Z-80A CPU 4 MHz
64K Dynamic RAM
Front panel
V I/O—with interrupts
FDCII Disk Controller
20 slot motherboard


CALL FOR PRICE— TOO LOW TO ADVERTISE!

PASCAL/Z + THE FASTEST PASCAL \$375
Z-8000 & CACHE BIOS—POWERFUL—PHONE
8086 16 BIT CPU & SUPPORT CARD SEATTLE \$695
CALIFORNIA COMPUTER 2210A ONLY \$1795

MORROW 8" DISK

DISCUS 2D + CP/M® 600K ONLY \$929
DISCUS 2 + 2 + CP/M® 1.2 MEGA B. \$1240
ADD DRIVES 2D = \$650 2 + 2 = \$975
2D-DUAL + CP/M® ONLY \$1540

FREE MBASIC FROM MORROW!!



MORROW HARD DISK
26,000,000 BYTES!!
LIST \$4995 ONLY \$3919
CP/M® IS INCLUDED!

SAVE ON MEMORY AND PROGRAMS

SYSTEMS MEMORY 64K A & T 4mhz	\$590	WORD STAR	\$315
SYSTEM MEMORY 64K BANK SELECT	\$740	SPECTRUM	\$269
ITHACA MEMORY 8/16-bit 64K	\$845	COMPUPRO	SAVE
SEATTLE MEMORY 8/16 BIT 16K	\$249	EZ-CODER Translates English to BASIC	\$71
SSM KITS Z-80 CPU	\$221	ECOSOFT FULL ACCOUNTING PKG	\$355
VIDEO BRD V83 4Mhz	\$412	BOX OF DISKETTES	\$29
ANADIX PRINTER DP-9500-1	\$1349	SECRETARY WORD PROCESSOR	The Best! \$99
CAT NOVAION MODEM	\$169	GOFAST NORTH STAR BASIC	
ECONORAM 2A 8K ASSM	\$179	OPTIMIZER—FAST	\$71
NSSE 1-22 & P01 TERRIFIC PROGRAMS	ONLY \$10. EACH	Which Computers are BEST?	
NORTHWORD 329 MAILMAN \$246		BROCHURE	FREE
INFOMAN	\$411	North Star Documentation refundable	w/HRZ \$35

TARBELL COMPUTER-PHONE

AMERICAN SQUARE COMPUTERS BEATS ADV. PRICES

American ^{square} Computers ✓56

919-889-4577

KIVETT DR. JAMESTOWN N.C. 27282

919-883-1105

© CP/M is a registered trademark of Digital Research, Inc.

DISCOUNT

**Stock Computer Paper & Labels
Over 50 Items in Stock**

ITEMS IN STOCK

Stock Forms Blank or Green Bar
Statements
Index Cards
Pressure sensitive labels all sizes
Continuous #10 envelopes
Continuous Blank Letter Heads
Spacing charts & layout sheets
Forms rulers

Custom To Your Needs

Invoices
Shippers
Custom Checks
Custom Continuous Envelopes
& Letter Heads
Statements

Quantities Of 1000 Or More

Send Inquiries To:

WHITE RIVER PRODUCTS ✓ 284
P.O. BOX 604
MT. CLEMENS, MICHIGAN 48043

Name _____

Street _____ Phone _____

State _____ Zip _____

Type of Equipment _____

**FREE
SEND FOR
YOURS TODAY**

☐ Computer Package ☐ 81 Tax Guide
☐ Stock Price List

Are you playing with a full deck?



If you are holding an AIM, SYM, KIM, PET or OSI, then you need our 1981 Product Guide to fill your hand.

The Computerist deals only superior products:


- Dram Plus** — RAM, EPROM, Programmer and I/O.
- Video Plus** — Instant video up to 132 by 30, plus communication and keyboard ports.
- Mother Plus** — Supports multi-board expansion, cassette control and more.
- Proto Plus** — Add custom circuits easily.
- Power Plus** — Triple voltage supply.

Why stand when you can take a guaranteed hit?

For the best deal in town,
write or call for our free 1981 Product Guide

✓ 336

THE COMPUTERIST®
34 Chelmsford St., Chelmsford, MA 01824
(617) 256-3649



A wood storage cabinet from Instructional Development Systems will secure modular micro systems.

disks, or one storage compartment can be used to house a small line printer. The cabinet is solid wood with a formica veneer. Convection venting is included to cool system components. The cabinet comes fully assembled and ready to use. Priced at \$275. Reader Service number 485.

also features acoustic sound reduction, an internal power supply and new quick-load ribbons.


Sprint 9 is available with two different RO front panel configurations, limited or complete front panels, at either 45 or 55 cps. The Sprint 9/45 is \$2455 (\$100 less for a limited front panel); the 9/55 is \$2555 (\$100 less for limited front panel). Reader Service number 484.

Letter-Quality Printer


The Sprint 9 letter-quality daisywheel printer, from Data Wholesale Corp., 700 Whitney St., San Leandro, CA 94577, now offers an improved carriage drive mechanism. The micro-drive Kevlar belt enhances print quality and registration, and also makes steel carriage cables, pulleys and excessive service adjustments obsolete. The Sprint 9 has fewer parts, making it easier to service than previous Sprint products. The top cover has been totally redesigned for easier carriage access. The printer

Interface with a Turtle

Terrapin, Inc., 678 Massachusetts Ave., #205, Cambridge, MA 02139, now has a smart Terrapin-Apple interface for its robot, the Turtle. The interface lets the user control the Turtle from a high-level language (BASIC, Pascal, Logo) via simple I/O statements. It can be used at home or in the classroom for teaching, learning or just having fun. The smart interface includes a parallel port, a



Sprint 9 letter-quality printer from Data Wholesale.



The Terrapin Turtle can now be interfaced to an Apple microcomputer.

separate regulated current-limited power supply and interface software. The parallel port I/O card contains the interface software in ROM, and plugs into one of the Apple's peripheral interface connectors. The program in ROM initializes the I/O port, generates the appropriate bit pattern for a specific command, compares this with the previous command byte to determine which bits must be left on, and writes to the appropriate output port location. The interface software allows Turtle control commands to be sent directly to the Turtle. The assembled Terrapin Turtle costs \$599.95; kits are \$399.95. Interfaces are \$199.95. Reader Service number 493.

Biofeedback


The Biocom is a new peripheral from Total Digital Engineering, 210 Daniel Webster Highway, S. Nashua, NH 03060. Biocom measures your galvanic skin response (GSR) using two Velcro wrappers for your fingers (or one from each person at the end of a circle of

people holding hands). The user selects sample rate, sensitivity and how the readings are to be processed and presented. The readings are transmitted to your microcomputer, where, with the appropriate software, the readings will produce a GSR plot or act as a relaxation trainer, a computerized Ouija, a lie detector or a personal growth system.

Biocom is easily tied into your computer via an asynchronous RS-232 port. Software is supplied as BASIC listings, annotated to point out differences in the interpreters of different microcomputers. You can also buy software on cassette or diskette for \$15. The Biocom, with manual, listings and personal growth booklet, is \$125. Reader Service number 492.

Design Tool

The Pencil Box logic designer is a portable breadboarding instrument for designing logic circuits and includes an I/O port for microcomputer experiments. The



The Biocom biofeedback peripheral from Total Digital Engineering.

FREE Computer Forms Catalog

with 32 pages of continuous business forms for small computer systems

Send today for our NEW full color 32 page catalog with programming guides, prices and order forms for continuous checks, invoices, statements, envelopes, stock paper and labels.

- Quality products at low prices
- Available in small quantities
- Fast Service
- Money Back Guarantee
- Convenient TOLL-FREE ordering

Fast Service by mail or . . . PHONE TOLL FREE

1 + 800-225-9550

Mass. residents 1 + 800-922-8560

8:30 a.m. to 5:00 p.m. Eastern Time Monday — Friday


Please rush a new computer forms catalog to:	CODE 460
Name _____	
Company _____	
Street _____	
City, State and Zip _____	
Phone _____	
Computer make & model _____	

Nebs 291
Computer Forms
78 Hollis Street, Groton, Mass. 01471
A division of New England Business Service, Inc.

IT'S ABOUT TIME!

SUPERCLOCK II™

A COMPLETE
CLOCK/CALENDAR
SYSTEM FOR THE
APPLE II.



FEATURES:

- Timing from milliseconds to 99 years
- 12/24 Hour formats plus day of week
- Does not use C800-CFFF address space
- Automatic dating of files stored on disk
- Automatic updating of PASCAL's Filer
- Up to four software controlled interrupts
- Full battery operation for up to 10 years



SUPERCLOCK II COMPLETE SYSTEM \$159



TIME-CLOCK II program automatically keeps track of the time you spend on your computer for each job, client, program, etc. Then prints out a detailed report. Requires SUPERCLOCK II, Applesoft, and disk **\$30**

west side electronics

P.O. Box 636D, Chatsworth, CA 91311

Phone (213) 884-4794

All orders - add \$3.50 for postage, insurance, and handling (\$7.00 outside Continental USA). California residents add 6% sales tax. A 3% surcharge will be added to all credit card orders.

Apple, Apple II, and Applesoft are trademarks of Apple Computer, Inc.

MODEL III DISK DIRECTORY PROGRAM

Catalogue your Diskettes with this easy to use Catalogue program for Model III Disk systems. Can run on as little as a 32K 1 Drive system. Help you keep track of ALL of your programs.

ONLY \$19.95

MODEL III SPEED UP!

Load in the 500 Baud system tapes in 1/3 the time with copy III. This utility will read in your 500 baud system tapes. and then write them out at 1500 baud. This gives you backup protection as well as speeding up your tapes. A must for all Model III Cassette users!

ONLY \$14.95

B.T. Enterprises

171 Hawkins Road
Centereach, New York 11720


(516) 981-8568 (Voice)

(516) 588-5836 (Data)

MNET-70331, 105

NYS res. add appr. tax

Dealers Inquiries Welcome Add \$2.00 S & H



The Pencil Box from E & L Instruments.

Pencil Box incorporates major design needs in a molded plastic case with an integral hinged cover. It features a variable clock, two pulsers, eight LED readouts which also serve as a latched output port, eight logic-level switches which also serve as an input port and E & L SK-10 solderless breadboarding socket. Power is supplied by four 1.5 V batteries or an optional ac adapter. A Zener diode reduces the input voltage to 5 V for standard TTL work. The Pencil Box, assembled, is priced at \$99.50; kit is \$75.


E & L Instruments, Inc., 61 First St., Derby, CT 06418. Reader Service number 491.

RAM Card for Apple II

Computer Stop, 2545 W. 237th St., Suite L, Torrance, CA 90505, is offering the CS16K RAM card to increase Apple II memory. With 48K of RAM already in place, this new card increases capacity

Z-80 Processor Board

The CPC-2810 Z-80 processor board is now being offered by Systems Group, a division of Measurement Systems and Controls, Inc., 1601 Orange-wood, Orange, CA 92668. The board is designed specifically



Computer Stop's CS16K RAM card.

COMPUTER STOP

2545 W. 237 St. Torrance, CA. 90505

ORDER BY PHONE
MON.—SAT.
10-6

(213) 539-7670 PST
TELEX: 678401 TAB IRIN

LOWEST PRICES IN THE WEST, NORTH, SOUTH & EAST



APPLE /// OPTION A:	3850
APPLE /// 96K Information Analyst Package 12" B/W Monitor	
APPLE /// OPTION B:	4350
SAME AS OPTION A PLUS: DISK II for APPLE ///	
APPLE /// OPTION C:	4800
SAME AS OPTION A PLUS: DISK II FOR APPLE /// SILENTYPE Thermal Printer	

APPLE HARDWARE

Parallel Printer Interface Card	160
Communications Card	195
High Speed Serial Interface	175
Pascal Language System	425
Centronics Printer Interface	185
Applesoft Firmware Card	160
Integer Firmware Card	160
Disk][with Controller DOS 3.3	529
Disk][only	475
Graphics Tablet	625

OTHER HARDWARE

Alf Music Synthesizer (3 Voice)	245
9 voice	175
ABT Numeric Keypad	119
Micromodem][.....	295
Apple Clock	245
Rom Plus with Keyboard Filter	175
Introl/X-10 System	250
Romwriter	150
DoubleVision 80 x 24 Video Interface	295
CCS Arithmetic Processor	399
CCS Parallel Interface	119
16K Ram Card	145
Microworks DS-65 Digisector	339
SVA 8 inch Disk Controller	335
Sup-R-Mod	30
CCS Synchronous Serial Interface	159
CCS Asynchronous Serial Interface	159
Corvus 10 Meg. Hard Disk	4395
Corvus Constellation	595

MISCELLANEOUS/SUPPLIES

16K RAM (200-250 NS)	49
Verbatim Datalife Diskette (Box of 10)	30
Dysan Diskettes (Box of 5)	22
Apple Diskettes (Box of 10)	45
Verbatim Diskette Boxes (Holds 50 Disks)	18
Silentype Paper (Box of 10 rolls)	40



MONITORS/DISPLAYS

Leedex Video 100 12"	140
Sanyo 9" Monitor	195
KG-12C Green Phos. Monitor	275
Sanyo 12" Green Phosphor. Monitor	275
NEC 12" Green Phosphor. Monitor	275
Sanyo 12" B/W Monitor	250

PRINTERS

Apple Silentype with Interface	525
IDS445 (Paper Tiger) with Graphics	695
IDS460 with Graphics	1099
IDS560 with Graphics	1295
Centronics 737	895
NEC Spinwriter (RO, Serial)	2650

SOFTWARE

The Controller	525
Apple Post (Mailing List Program)	40
Easywriter Professional System	195
Apple Pie 2.0	95
DB Master Data Management	150
The Cashier	210
Apple Writer	65
Visicalc	125
CCA Data Management System	90
Full Screen Mapping for CCA DMS	59
Pascal Interactive Terminal Software (PITS)	29
Basic Interactive Terminal Software (BITS)	29
Data Capture	29
Data Factory DMS	95
Apple Plot	55
Apple Pilot	120
Magic Wand Word Processor (Needs Z-80 Softcard)	345
Dow Jones Portfolio Evaluator	45
Fortran	140


ORDERING INFORMATION: Phone orders invited using VISA, MASTERCARD or bank wire transfers. VISA & MC credit card service charge of 2%. Mail order may send charge card number (include expiration date), cashier's check, money order or personal check (allow 10 business days to clear). Please include a telephone number with all orders. Foreign orders (excluding Military PO's) add 5% for shipping. All funds must be in U.S. dollars (letters of credit permitted). Shipping, handling and insurance in U.S. add 2% (minimum \$4.00). California residents add 6% sales tax. Our low margins prohibit us to send COD or on purchase orders or open account (please send for written quotation). All equipment is subject to price change and availability. Equipment is new and complete with the manufacturer warranty. We do not guarantee merchantability of products sold. All returned equipment is subject to a 15% restocking fee. We ship most orders within 2 days.

WE ARE A MEMBER OF THE CHAMBER OF COMMERCE.

PLEASE SEND ORDERS TO:

COMPUTER STOP, 2545 W. 237 St., TORRANCE, CA 90505

RETAIL STORE PRICES MAY DIFFER FROM MAIL ORDER PRICES.



Systems Group Z-80 processor board.

for the S-100 bus, and is compatible with single-user, multi-user or networking systems. It features two or four serial I/O channels, software-selectable baud rates, two parallel I/O channels and eight vectorized, prioritized interrupts. The price is \$495. Reader service number 498.


Increase H/Z-89 Storage to 7.6 Megabytes

A new double-density disk controller for the Heath/Zenith-89 computer supports up to four eight-inch disk drives and four five-inch drives. These supplement the three five-inch drives supported by the existing Heath/Zenith controller. The new controller increases on-line access to 7.6M. It can handle any combination of industry-standard eight-inch drives and five-inch 40-track or 80-track drives in either single- or double-sided versions. The controller is priced at \$595, including CP/M 2.2 on either five-inch or eight-inch media.

Magnolia Microsystems, Inc., 2812 Thorndyke Ave., West, Seattle, WA 98199. Reader Service number 497.

Disk Storage for TRS-80 Model III

The Disk III, offered by VR Data, 777 Henderson Blvd., N-6, Folcroft Industrial Park, Folcroft, PA 19032, is a 5-1/4 inch disk storage subsystem for the Radio Shack TRS-80 Model III computer. It is fully compatible with the Model III hardware and software. The Disk III is calibrated, aligned, tested and burned-in prior to shipping. It can be installed by VR Data, or can be easily in-



VR Data's Disk III.



Archives III word processor/computer.

stalled by any mechanically inclined person with simple hand tools. The Disk III basic unit consists of controller, power supply, mounting bracket, one 40-track (6 ms) disk drive and associated cabling. Price is \$599. Reader Service number 495.

Static 64K RAM Uses 100 ns Chip

Seattle Computer Products, 1114 Industry Drive, Seattle, WA 98188, recently announced their SCP-110, a 64K IEEE S-100 memory card. It uses the 100 ns Intel 2167 16K static chip. The new chip allows memory management functions of offset and protection to be performed with the firm's 8 MHz 8086 CPU without a wait state. The card performs both eight-bit and 16-bit transfers, switching automatically. The chips are used in a power-down mode to minimize current. Power requirement for an active board is 1.6

A at 8 V, while an inactive card uses 0.8 A. The card uses 24-bit addressing; the upper eight can be disabled. Price is \$1295. Reader Service number 487.


More Available Memory

The Archives III word processor/computer offers greater storage capacity than previous models. The Archives III features a Tandon double-sided disk drive and a Seagate 5M 5-1/4 inch Winchester disk drive. Total storage will be 5.75M. The unit is priced at \$8500.


Archives Inc., 404 West 35th St., Davenport, IA 52806. Reader Service number 494.

Touch-Sensitive Add-On for Lear Siegler Terminal


Interaction Systems, Inc., 24 Munroe St., Newtonville,



Double-density disk controller from Magnolia Microsystems.



Static RAM card from Seattle Computer Products.




Interaction Systems' TK-242 touch-sensitive add-on kit for the ADM-42.

MA 02160, is offering its Model TK-242 touch-sensitive add-on kit, designed for use with the Lear Siegler ADM-42 CRT terminal. The kit provides the video display terminal with a human interface that is easy to use. The touch-sensitive feature lets the terminal respond to the touch of the finger on data displayed on the CRT screen. The kit consists of a glass touch-sensitive faceplate that overlays the terminal's CRT monitor, an electronics board and mounting bracket which fit inside the CRT monitor housing and interconnecting cables and mounting

clamps. The price is \$995. Reader Service number 496.

Apple-Compatible Printer

IMP2-Apple, a low-cost impact printer designed to operate with Apple microcomputers, is being offered by Axiom Corporation, 5932 San Fernando Road, Glendale, CA 91202. IMP2-Apple is equipped with both friction and tractor feed. This versatile printer enhances the Apple's capabilities by providing extra features, such as lowercase



Axiom IMP2-Apple printer.

SPECIAL DELIVERY

WORDPROCESSING - POWER - for the TRS-80®

"...If you're presently looking for a mailing list processor, this represents the current state of the art."
80 MICROCOMPUTING - 80 REVIEWS - JULY 1980

MAILFORM is data entry at its best, just fill in the form! **FAST, EASY** to use functions include: search, sort, extract, page forward and back. 'Transparent cursor', insert/delete characters, and **MORE!**

MAILRITE prints 'personalized' form letters by inserting information from **MAILFORM** into **Electric Pencil®**, **Scriptit®**, or **BASIC** text files. Print letters, labels, even envelopes! Boldface, underscore, change margins, pause, print 'unprintable' characters, and **MORE!**

XTRA! includes: **MAILFORM**; **MAILRITE** - with capability of printing variable text from a 'key' file; **MAILABEL** - 1, 2, 3, or 4 across label printer; and **MAILSORT** - sort a full 40 track double density data diskette in only 48K!

ALL MACHINE LANGUAGE means unsurpassed SPEED, RELIABILITY & EASE OF USE

For VISA, Master Card & COD orders only

Call NOW - TOLLFREE

(800) 824-7888

ASK FOR OPERATOR 203

California (800) 852-7777

Hawaii & Alaska (800) 824-7919

For more information call (214) 233-3998

(Requires min 32K single disk drive)

FOR THE MODEL I & III
SPECIAL DELIVERY\$125
XTRA SPECIAL DELIVERY ..\$199

FOR THE MODEL II
SPECIAL DELIVERY\$199
(Requires Mod II DOS version 2.0)

TRS-80 is a registered trademark of Tandy Corp.



software concepts

13534 Preston Rd. Suite 142
Dallas, Texas 75240

Dealer Inquiries invited

Printer interface from John Bell Engineering.

characters. IMP2-Apple is compatible with Pascal. It is priced at \$895. Reader Service number 490.

Parallel Printer Interface

John Bell Engineering, 700 Warrington Ave., Redwood City, CA 94063, is announcing a parallel printer interface to interface your Apple II microcomputer to Centronics-compatible printers. This board features on-board ROM compatible with Applesoft and Integer BASIC (Pascal disk available separately), has

all the commands of the Apple printer interface and has an additional command for graphics. The price is \$79.95, assembled and tested, or \$69.95 for the kit. Reader Service number 464.

Super Expansion Board for OSI

The Super Expansion Board (SEB) is a high resolution color graphics/memory expansion board for the Ohio Scientific Superboard II/Challenger 1P computers. The SEB incorporates the following features on a 10×12-inch board: 16K memory expansion, 11 software-selectable display modes with graphics resolution of up to 256×192, up to eight user-selectable colors, 6K display memory and eight-bit parallel port with handshake. The SEB is designed to mount/connect directly to the computer without any user modifications. It is available assembled and tested for \$249, or as a bare board with documentation for \$59.


Grafix, 911 Columbia Ave.,
N. Bergen, NJ 07047. Reader
Service number 465.

RAM Board with Backup Power Supply

Gimix, Inc., 1337 West 37th Place, Chicago, IL 60609, announces their new 64K CMOS static RAM board with battery backup for the SS50/C bus. This board is compatible with any of the 6800/6809 DMA techniques. They are

guaranteed for 2 MHz operation with no wait states or clock stretching required. Low power CMOS RAM requires 250 mA at 8 V for a fully-populated 64K board. It is non-volatile, using an on-board nickel-cadmium battery. The board retains data even with system power removed. With the battery fully charged, the contents of the memory remain intact for a minimum of 21 days.

The Gimix board is priced at \$1088.64. Reader Service number 488.



A new static RAM board from Gimix, Inc.

**MORE SOFTWARE TOOLS
FROM HES FOR YOUR 8K PET™**

by Jay Balakrishnan

HESEDIT: change 22 lines of data by merely overtyping and insert, delete, and even duplicate lines—all at once! Scroll forwards or backwards by any amount — it's also easy to edit files bigger than your memory. Why code a program to maintain each file? Use HESEDIT for mailing lists, notes or prepare assembler source for HESBAL. All keys repeat. FAST — written in BASIC and assembler. **ONLY \$12.95**

6502 ASSEMBLER PACKAGE: HESBAL, a full-featured assembler with over 1200 bytes free (8K) & HESEdit; for less than \$25! HESBAL is *THE* best 8K assembler available: it uses only 1 tape or disk, yet includes variable symbol sizes, pseudo-opcodes, over 25 error messages and more than 70 pages of documentation.

ONLY \$23.95

HESLISTER: formats multi-statement line BASIC programs, shows logic structure (disk reqd.) \$9.95

GUARANTEED to load or replaced FREE
Order from your dealer or direct from us
Plus \$1.50 Postage (our doc. is heavy!)

Disk - Add \$3 • Calif Res. - 6% Sales Tax

HES Human Engineered Software
3748 Inglewood Blvd. Room 11
Los Angeles, California 90066

24 HOURS – (213) 398-7259

Dealer inquiries welcomed

IS YOUR STRIP CHART RECORDER OUTSTRIPPING YOU?
ARE YOU INUNDATED WITH UNDATA?
ARE YOUR CONTROL APPLICATIONS OUT OF CONTROL?
Then you need **ADRIAD**™

MAPPAE

0 0

THE small laboratory computer system with LARGE capabilities from Interactive Microware, Inc.

APPLAB HARDWARE PACKS MORE POWER . . . for collecting data and controlling your laboratory instruments. It includes a 12-bit analog **input**, a 12-bit analog **voltage output**, 8 digital **sense inputs**, 8 digital **control outputs**, a 32-bit **real-time clock** and two 16-bit **timers/counters** . . . ALL ON A SINGLE APPLE INTERFACE CARD!

QUICKI/O SOFTWARE MAKES IT EASY . . . **Simple commands** in BASIC give you control of all hardware features of APPLAB. **Sample programs** and **easy-to-use manuals** will enable you to start using your APPLAB system right away. Additional **software for laboratory applications** is available at extra cost. A complete **self-test diagnostic program** is included to assure you that all of the hardware is working properly and accurately.

MAKE APPLAB YOUR LAB PARTNER!

- A** • **Saves time** by eliminating manual calculations.
- P** • Is **easy-to-use** because the manuals and software are complete and well written.
- P** • **Saves money** by adding convenience and utility to older instruments.
- L** • Has a **great memory** to store and organize experimental data.
- A** • Is **versatile**; it works with many different instruments.
- B** • Is **more accurate** than reading a meter or chart recording.
- Is **fully supported** by a dedicated team of scientists.

GREAT PRICE/PERFORMANCE . . . The APPLAB **Add-on Package** with interface card, cables, self-test module, QUICK/O™ software and manuals is available today for **ONLY \$495.**

Put a **complete, reliable computer system** in your laboratory **FOR ONLY \$3595**, including a 48K APPLE II+ computer, disk drive, graphics/text printer, video monitor and APPLAB Add-on Package.

Send for **FREE** hardware and software brochures or enclose \$10 for complete manuals. **For fastest service**, call in your VISA/MasterCard order **NOW**. Dealer inquiries invited!



INTERACTIVE MICROWARE, INC. ✓264
P.O. Box 771, Dept. K State College, PA 16801
CALL (814) 238-8294 for IMMEDIATE ACTION

DEALER DIRECTORY

El Monte, CA

Ohio Scientific specialist in the San Gabriel Valley serving greater Los Angeles. Full product line on display. Specializing in business computers. In-house service. Custom programming. Terminals. Printers. Open Mon-Sat, 9 AM-7 PM. **Computer & Video, 3380 Flair Dr., Suite 207, El Monte, CA 91731, 572-7292.**

Riverside, CA

Visit our Computer Support Center for the Inland Empire's largest selection of ICs, books and computer accessories. Open daily. Check our prices and friendly service. **Inland Electro-Mart, 8624 California Ave., Riverside, CA 92504. 687-3776.**

San Jose, CA

New and used computer products—specializing in S-100 boards, printers, drives, chassis and complete systems, as well as supplies and parts—Imjai, Tandon, Diablo—5000 sq. ft. **W/W Component Supply, Inc., 1771 Junction Ave., San Jose, CA 95112.**

Sarasota, FL

Your personal and business computer store for Dynabyte, Vector, HP-85, Atari and Epson. Structured Systems and Micro-Pro software. Computer furniture and books by Osborne or Hayden. Sales, service and supplies. **Computer Crossroads, 3800 S. Tamiami Trail, Sarasota, FL 33579, 349-0200.**

Tampa, FL

Apple Computer sales and service. S-100 boards from SSM, Godbout, Thinker Toys, California Computer Systems. Computer books and magazines. **AMF Microcomputer Center, Inc., 11158 N. 30th Street, Tampa, FL 33612, 971-4072, 977-0708.**

Aurora, IL

Microcomputer systems for home or business; peripherals, software, books & magazines. Apple, Hewlett-Packard Series 80 Systems, HP Calculators, IDS, Qume, Starwriter printers. **Farnsworth Computer Center, 1891 N. Farnsworth Ave., Aurora, IL 60505, 851-3888.**

Chicago, IL

Computer Hardware/Specialists for home and business. Largest selection of computer books, magazines and copyrighted software in Illinois. Experienced factory-trained service department. Feature Apple, Alpha Microsystems and Hewlett-Packard calculators and accessories. **Data Domain of Schaumburg, 1612 E. Algonquin Rd., Schaumburg, IL 60195, 397-8700.**

Chicago, IL

Brand new lowest prices, never undersold, postpaid in USA—Teletype 43 keyboard printers, Okidata & Integral Data printers, SS-50 bus computers, peripherals & business software. **Data Mart, 914 East Waverly Street, Arlington Heights, IL 60004, 398-8525.**

Herington, KS

Hardware support. Maintenance and service for all microcomputers and peripherals. Kits assembled or debugged. Radio Shack (mods OK) repaired. Quality work, fast turnaround and reasonable cost. **Prairie Micro Clinic, Box 325, Herington, KS 67449, 258-2179.**

Garden City, MI

Books, magazines, hardware and software for Apple, North Star, TRS-80 and PET. **Computer Center, 28251 Ford Rd., Garden City, MI 48135, 425-2470.**

Hannibal, MO

Ohio Scientific products, modifications, service, software. 8" disk for CIP, C4P. Process control specialist. **E&I Technical Service, 5300 Paris Gravel Road, Hannibal, MO 63401, 248-0084.**

River Edge, NJ

Discount software—up to 25% off business, utility, recreational, educational and home programs. Apple, Atari, TRS-80 and PET. Atari computers always on sale. **Software City, 111 Grand Ave., River Edge, NJ 07661.**

Chautauqua, NY

Retail book store featuring the Disassembled Handbook for TRS-80 Volumes 1, 2, 3. English, German & French language editions. 9 AM-5 PM weekdays. Come and visit us. **Richcraft Computer Book Store, 1 Wahmeda Ave., Chautauqua, NY 14722, 753-2654.**

Portland, OR

Ohio Scientific specialists for business and personal computers. Local service. Terminals, printers, custom programming. Full OSI product line on display! 10 AM to 6 PM M-F. **Fial Computer, 11266 SE 21st Ave., Milwaukie, OR 97222, 654-9574.**

Montreal, Quebec


We do expert service on all microcomputers and peripherals, (CRT, printer, floppy disk) North Star, Hazeltine, Cromemco, Centronics, Shugart, Siemens, Apple, TRS, Epson, S-100. **Montreal Data Centre, 120 Ricard, Legardeur, Montreal, Quebec. 585-8801.**

Spokane, WA

SS-50 Users: Expand present system to maximum or build from ground up. We provide PCBs for motherboards, interfaces, etc. Write for specs and information. **Quality Research Company, PO Box 7207, Spokane, WA 99207.**

Dealers: Listings are \$15 per month in prepaid quarterly payments, or one yearly payment of \$150, also prepaid. Ads include 25 words describing your products and services plus your company name, address and phone. (No area codes or merchandise prices, please.) Call Marcia at 603-924-7138 or write *Kilobaud Microcomputing*, Ad Department, Peterborough, NH 03458.

"THIS IS DIGITALKER*" OUT 127,0



(As featured in
Byte June 81)

This is all it takes to say this or 143 other expressions with MICRO-MOUTH*. Absolutely no software drivers or subroutines to load. MICROMOUTH*, the latest Circuit Cellar project can be used as an emergency annunciator, as an aid for the handicapped, for process control and automatic monitoring, and to add new dimensions to computer games.

Sample phrases that can be programmed are:
"THE TIME IS 4 HOURS 23 MINUTES... (BEEP)"
"NUMBER 4 IS 3.47 VOLTS"
"THE SPEED IS 100 METERS A SECOND... SLOW DOWN"
Thousands of expressions can be added by changing the ROM chips.

MICROMOUTH* is plug compatible with APPLE II and TRS-80* computers. Directions are included for S100, H8 and parallel port operation. *DIGITALKER is a trademark of National Semiconductor Corp.

Complete Kit (as shown) \$120.00
Assembled and tested:
Apple II.....\$150.00
TRS-80 Model I w/power supply, case, cable.....\$175.00
TRS-80 Model III.....\$200.00

*MICROMOUTH is a trademark of Micromint Inc

The MicroMint Inc. ✓347
917 Midway
Woodmere, NY 11598
Dealer inquiries invited.



To order call:
1-800-645-3479
In N.Y. 516-374-6793



CP/M Disk Catalog Model III Development System Apple Accounting and Data Management Pascal Billing System TRS-80 Voice Synthesizer

CP/M Disk Catalog System

Master Disk Catalog comprises three assembly-language programs for CP/M-based systems. This system will maintain a record of the files from your disks on a single catalog disk. Comments and dates which you have inserted in programs can also be recorded on the catalog disk. It will locate a particular document in word processing applications, and help you keep track of data files or the various stages of program development. The disk catalog can be searched for all occurrences of particular file names, for text in your comments or for dates. File names and disk names can include CP/M wildcard characters.

Master Disk Catalog is available on single-density eight-inch disk for \$35.

Mendocino Software, PO Box 1564, Willits, CA 95490. Reader Service number 483.

PDS for TRS-80

The PDS assembly-language development system is now fully operational under

TRSDOS for the Radio Shack TRS-80 Model III computer. PDS includes a relocating macro assembler, linkage editor/linking loader, string-oriented text editor, interactive editor/assembler, trace debug/monitor, disk disassembler and several utilities which extend the power of TRSDOS. The relocating macro assembler and linkage editor support modular program development: large programs can be developed in independent, easily manageable segments which can be linked together for execution. Program segments can be chained together at the source level or linked together at object level. Commonly used program segments, once assembled, can be used thereafter without reassembly. Extensive conditional arithmetic and string operations let you develop sophisticated macro libraries to create a high-level macro language or to cross assemble programs for any of the commonly available processors.

Program modules can be modified, assembled and checked in seconds with the interactive editor/assembler. Debugging is aided by single-step trace capability, with full

display of registers, flag status and the mnemonics of the instruction just executed and the next instruction to be executed. Both assemblers use an extension of the Intel instruction set. The PDS development system is available on five-inch double-density disk with documentation for \$99.

Allen Ashley, 395 Sierra Madre Villa, Pasadena, CA 91107. Reader Service number 471.

Apple Accounting Module

Systems Plus, 3975 East Bayshore, Palo Alto, CA 94303, is introducing an additional module to the Apple Accounting Plus II software package. An inventory module with purchasing brings the total number of modules available to four, including General Ledger, Accounts Receivable, Accounts Payable and now Inventory with Purchasing. The inventory-purchasing module is integrated with General Ledger. It supports four different costing methods—Standard, Weighted Average, Lifo and Fifo. It al-

so maintains a master parts list, offers eight-character alphanumeric part identification and 100 product groups. The module prints purchase orders and maintains on-order quantities, and it supports inventory to allow for receipts, issues and adjustments. It maintains a complete audit trail of all inventory transactions for the current month.

The inventory-purchasing module generates full inventory reporting. Reader Service number 470.

Overland Role-Playing Game

A new EPYX role-playing fantasy is available from Automated Simulations, Inc., PO Box 4247, Mountain View, CA 94040. The player has 21 game days (about half an hour playing time) to find the Dragon's Eye, a magical jewel hidden somewhere in one of seven provinces. He chooses his role from 16 characters, each with a unique set of magical abilities—healing, flying, time travel, teleport. He takes his choice of four swords, bow and arrow or magic bolt. The

screen displays a detailed map of the provinces and the location, strength and health of the character. When a monster is encountered, animated battle graphics display the action between player and beast. The player must confront dragons, bats, vampires, ghosts, golems, serpents, skeletons and other adversaries. He can fight with sword or bow, or cast a magic spell.

The Dragon's Eye on cassette for the PET (32K) or on disk for the Apple (48K, AppleSoft in ROM) is \$24.95. Reader Service number 468.

Data Management For the Apple

ESP dataKEYper is a data management system for the experienced data processor or the beginner who does occasional programming. It is menu-driven and tutorial. The system creates, changes, searches, sorts and lists data files. Its screen formatting flexibility lets you tailor the input screen definition to suit your application. The dataKEYper then becomes a tool to help you build your special system.

The package is designed to operate on an Apple II+ (48K) and is compatible with Corvus, eight-inch Sorrento Valley and 5-1/4-inch disk drives. The system to run on the Corvus hard disk is priced at \$449. The floppy disk version is \$99.

ESP Computer Resources, Inc., 9 Ash St., Hollis, NH 03049. Reader Service number 474.

Pascal Billing System for the Apple II

The SoftCare medical billing system, which has been operating on minis and many Z-80 systems, is now available on the Apple II. SoftCare prepares patient bills and insurance claims, including Medicare and MediCal, for single or shared-practice doctor offices. Accounts receivable are maintained for patient and insurance carrier, and transaction detail is retained to permit tracking of individual claims.

SoftCare accounts for partial payment of claims, write-offs and secondary insurance carriers.

Little or no operator training is needed. The fill-in-the-blank screen formats are self-explanatory. SoftCare guides the operator and does error checking as information is being entered. Moving from one function to another can be done at any time, from anywhere on the screen, using function keys shown on the screen. Patient files are updated as transactions are entered, so that bills and claims can be prepared on demand and reports can be run at any time. SoftCare can use patient names as a key, so that ID numbers are not required. The unique "browsing" capability lets you quickly and easily inquire and page through the files for access to up-to-date information. Set-up parameters tailor SoftCare to the doctor's practice. Procedure and diagnosis codes are user defined, with no limit on the number in the system.

SoftCare, written in UCSD Pascal, runs on the Apple II with Pascal language card and eight-inch disk drives or the Corvus hard disk. The price of SoftCare is \$1995.

Professional Business Software, Inc., 119 Fremont St., San Francisco, CA 94105. Reader Service number 479.

Software for the TRS-80 Voice Synthesizer

Sayit adds voice output to BASIC programs on the TRS-80 Model I with the Radio Shack Voice Synthesizer. The program (5.5K of machine code) relocates itself in high memory of a 16K or larger machine without upsetting any installed custom drivers. It adds a SAY command which makes the synthesizer say string expressions, numeric expressions or any combination of the two. Simultaneous depression of the RTY keys will cause the current SAY statement to be spoken by the synthesizer.

The voice synthesizer is programmed using English letters. Normal English spelling will often be correctly pro-

FOR ONLY \$129.95 Learn Computing From The Ground Up

Build a Computer kit that grows with you, and can expand to 64K RAM, Microsoft BASIC, Text Editor/Assembler, Word Processor, Floppy Disks and more.

EXPLORER/85

Here's the low cost way to learn the fundamentals of computing, the all-important basics you'll need more and more as you advance in computer skills. For just \$129.95 you get the advanced-design Explorer/85 motherboard, with all the features you need to learn how to write and use programs. And it can grow into a system that is a match for any personal computer on the market. Look at these features: 8085 Central Processing Unit, the microprocessor "heart" of the Explorer/85. (Join the millions who will buy and use the 8085/8085 this year alone). . . Four 8-bit bus one-to-one input/output ports from which you can input and output your programs, as well as control exterior switches, relays, lights, etc. . . a cassette interface that lets you store and reload programs you've learned to write . . . a deluxe 2,000 byte operating system/monitor makes it easy to learn computing in several important ways: • It allows simpler, faster writing and entering of programs • It permits access by you to all parts of the system so you can check on the status of any point in the program • It allows tracing each program step by step, with provision for displaying all the contents of the CPU (registers, flags, etc.) . . . and it does much more!

You get all this in the starting level (Level A) of the Explorer/85 for only \$129.95. Incredible! To see just plug in your 8VDC power supply and terminal or keyboard/display — if you don't have them, see our special offers below.

Level A computer kit (Terminal Version) . . . \$129.95 plus \$3 P&H*
Level A kit (Hex Keypad/Display Version) . . . \$129.95 plus \$3 P&H*

LEVEL B — This "building block" converts the motherboard into a two-slot S100 bus (industry standard) computer. Now you can plug in any of the hundreds of S100 cards available.
Level B kit . . . \$49.95 plus \$2 P&H*
Level B kit . . . \$49.95 plus \$2 P&H*
Level B kit . . . \$49.95 plus \$2 P&H*
Level B kit . . . \$49.95 plus \$2 P&H*

LEVEL C — Add still more computing power, this "building block" mounts directly on the motherboard and expands the S100 bus to six slots.
Level C kit . . . \$39.95 plus \$2 P&H*
Level C kit . . . \$39.95 plus \$2 P&H*
Level C kit . . . \$39.95 plus \$2 P&H*
Level C kit . . . \$39.95 plus \$2 P&H*

LEVEL D — When you reach the point in learning that requires more memory, we have two choices: either add 4K of a memory directly on the motherboard, or add a disk of 64K of memory by means of a single S100 card, our famous "JAWS".

Level D kit (CHECK ONE) . . . \$49.95 plus \$2 P&H*
Level D kit (CHECK ONE) . . . \$49.95 plus \$2 P&H*
Level D kit (CHECK ONE) . . . \$49.95 plus \$2 P&H*
Level D kit (CHECK ONE) . . . \$49.95 plus \$2 P&H*

LEVEL E — An important "building block" it activates the 8K ROM/EPROM space on the motherboard. Now just plug in our 8K Microsoft BASIC or your own custom programs.

Level E kit . . . \$5.95 plus 50¢ P&H*
Level E kit . . . \$5.95 plus 50¢ P&H*
Level E kit . . . \$5.95 plus 50¢ P&H*
Level E kit . . . \$5.95 plus 50¢ P&H*

Microsoft BASIC — It's the language that allows you to talk English to your computer. It is available three ways:
8K cassette version of Microsoft BASIC (requires Level B and 12K of RAM minimum; we suggest a 16K S100 "JAWS" — see above) . . . \$64.95 postpaid.
8K ROM version of Microsoft BASIC (requires Level B and 8K of RAM; just plug into your Level E socket) . . . \$64.95 postpaid.
8K ROM version of Microsoft BASIC (requires Level B and 8K of RAM; just plug into your Level E socket) . . . \$64.95 postpaid.

We suggest either the 4K Level D RAM expansion or a 16K S100 "JAWS". . . \$99.95 plus \$2 P&H*
Disk version of Microsoft BASIC (requires Level B, 32K of RAM, floppy disk controller, 8" floppy disk drive) . . . \$325 postpaid.

TEXT EDITOR/ASSEMBLER — The editor/assembler is a software tool (a program) designed to simplify the task of writing programs. As your programs become longer and more complex, the assembler can save you many hours of programming time. This software includes an editor program that enters the programs you write, makes changes, and saves the programs on cassettes. The assembler performs the clerical task of translating symbolic code into the computer-readable object code. The editor/assembler program is available either in cassette or a ROM version.

Editor/Assembler (Cassette version; requires Level B and 8K (min.) of RAM — we suggest 16K "JAWS" — see above) . . . \$59.95 plus \$2 P&H*
Editor/Assembler (ROM version; supplied on an S100 card; requires Level B and 4K RAM (min.) — we suggest either Level D or 16K "JAWS") . . . \$99.95 plus \$2 P&H*

8" FLOPPY DISK — A remarkable "building block." Add our 8" floppy disk when you need faster operation, more convenient program storage, perhaps a business application, and access to the literally thousands of programs and program languages available today. You simply plug them into your Explorer/85 disk system — it accepts all IBM-formatted CP/M programs.

8" Floppy Disk Drive . . . \$499.95 plus \$12 P&H*
Floppy Controller Card . . . \$199.95 plus \$2 P&H*
Disk Drive Cabinet & Power Supply . . . \$69.95 plus \$3 P&H*
Drive Cables (set up for two drives) . . . \$25.00 plus \$1.50 P&H*

CP/M 2.2 Disk Operating System; includes Text Editor/Assembler, dynamic debugger, and other features that give your Explorer/85 access to thousands of existing CP/M-based programs. . . \$150.00 postpaid.

NEED A POWER SUPPLY? Consider our AP-1. It can supply all the power you need for a fully expanded Explorer/85 (note: disk drives have their own power supply). Plus the AP-1 fits neatly into the attractive Explorer steel cabinet (see below).

AP-1 Power Supply kit (6V @ 5 amps) in deluxe steel cabinet . . . \$39.95 plus \$2 P&H*
NEED A TERMINAL? We offer you choices: the least expensive one is our Hex Keypad/Display kit that displays the information on a calculator-type screen. The other choice is our ASCII Keyboard/Computer Terminal kit, that can be used with either



1. Plug in Netronic's Hex Keypad/Display
2. Add Level B to convert to 8085 (you own custom circuit (prototyping area))
3. Add 4K RAM
4. Plug in Level E here; accepts Microsoft BASIC or Editor/Assembler in ROM
5. Add two S100 boards
6. Add your own custom circuit (prototyping area)
7. Connect terminal

a CRT monitor or a TV set (if you have an RF modulator).
Hex Keypad/Display kit . . . \$69.95 plus \$2 P&H*
ASCII Keyboard/Computer Terminal kit featuring a full 128 character set, u.k. case, full cursor control, 75 ohm video output, convertible to baudot output, selectable baud rate, RS 232-C or 20 mA I/O, 32 or 64 character by 16 line formats . . . \$149.95 plus \$3 P&H*

Steel Cabinet for ASCII Keyboard/Terminal . . . \$19.95 plus \$2.50 P&H*
RF Modulator kit (allows you to use your TV set as a monitor) . . . \$8.95 postpaid.
12" Video Monitor (10MHz bandwidth) . . . \$139.95 plus \$3 P&H*
Deluxe Steel Cabinet for the Explorer/85 . . . \$49.95 plus \$3 P&H*
Fan for cabinet . . . \$15.00 plus \$1.50 P&H*



ORDER A SPECIAL-PRICE EXPLORER/85 PAK — THERE'S ONE FOR EVERY NEED.

Beginner Pak (Save \$20.00) — You get Level A (Terminal Version) with Monitor Source Listing (\$25 value) AP-1, 5-amp. power supply, Intel 8085 User Manual . . . (Reg. \$199.95) SPECIAL \$169.95 plus \$4 P&H*
Experimenter Pak (Save \$53.40) — You get Level A (Hex Keypad/Display Version) with Hex Keypad/Display, Intel 8085 User Manual, Level A Hex Monitor Source Listing, and AP-1, 5-amp. power supply . . . (Reg. \$279.95) SPECIAL \$226.55 plus \$6 P&H*

Special Microsoft BASIC Pak (Save \$103.00) — You get Levels A (Terminal Version), B, D (4K RAM), E, 8K Microsoft in ROM, Intel 8085 User Manual, Level A Monitor Source Listing, and AP-1, 5-amp. power supply . . . (Reg. \$430.70) SPECIAL \$327.70 plus \$7 P&H*

Add a Rom-Version Text Editor/Assembler (Requires Levels B and D or S100 Memory) . . . \$99.95 plus \$2 P&H*

Starter 8" Disk System — Includes Level A, B floppy disk controller, one CDC 8" disk-drive, two-drive cable, two S100 connectors; just add your own power supplies, cabinets and hardware . . . (Reg. \$1065.00) SPECIAL \$999.95 plus \$13 P&H*
32K Starter System, \$1049.95 plus \$13 P&H*
48K Starter System, \$1149.95 plus \$13 P&H*
64K Starter System, \$1249.95 plus \$13 P&H*

Add to any of above Explorer steel cabinet, AP-1 5-amp. power supply, Level C with two S100 connectors, disk drive cabinet and power supply, two S-D connectors for connecting your printer and terminal . . . (Reg. \$225.95) SPECIAL \$199.95 plus \$3 P&H*

Complete 64K System, Wired & Tested . . . \$1650.00 plus \$2 P&H*
Special Complete Business Software Pak (Save \$625.00) — Includes CP/M 2.2 Microsoft BASIC, General Ledger, Accounts Receivable, Accounts Payable, Payroll Package . . . (Reg. \$1325) SPECIAL \$699.95 postpaid.

*P&H stands for "postage & insurance." For Canadian orders, double this amount.

Continental Credit Card Buyers Outside Connecticut:

TO ORDER
Call Toll Free:
800-243-7428 KB8

To Order From Connecticut, or For Technical Assistance, Call (203) 354-9375

CP/M is a reg. trademark of Digital Research

★ (Clip and mail entire ad) ★

SEND ME THE ITEMS CHECKED ABOVE
Total Enclosed (Conn. Residents add sales tax): \$
Paid by:

☐ Personal Check ☐ Cashier's Check/Money Order
☐ VISA ☐ MASTER CARD (Bank No. _____)

Acct. No. _____ Exp. Date _____

Signature _____

Print Name _____

Address _____

City _____

State _____ Zip _____

NETRONICS Research & Development Ltd.
333 Litchfield Road, New Milford, CT 06776

TRS-80 ADVENTURES FOR 16K COLOR 80

Extended color or Level II BASIC

ESCAPE FROM MARS — You are stranded on Mars and somewhere in the Martian city are the parts you need to repair your ship. Our best adventure for new adventurers.

TREK ADVENTURE — You will recognize the spaceship this takes place on. The crew has left—for good reason—but they forgot you—and the "Orbit is Decaying." Almost as good as being there.

PYRAMID — Our most advanced and challenging adventure, this takes place in our own special ancient pyramid. The builders were as nasty as pyramid builders usually are, and ransacking this one is a dangerous job.

ADVENTURES are all written in BASIC, all come with listings, and each sells for \$14.95.

ARCADE AND THINKING GAMES

16K and extended or level II BASIC

TIME TREK, REAL TIME REAL GRAPHICS TREK. See the torpedoes fly and the Klinskons explode. No more scrolling displays, no more turn taking. — This one has real time and real displays. In BASIC — for 16K level II or extended color BASIC. \$14.95.

STARFIGHTER — This one man space war game pits you against spacecruisers, battlewagons, and one man fighters. You have the view from your cockpit window, a working instrument panel, and your wits. Another real time goody.

BATTLEFLEET — This grown-up version of Battleship is the toughest thinking game available on 80 computers. There is no luck involved as you seek out the 80's hidden fleet. This is a topographical toughie. \$9.95.


SLASHBALL — A two player game of strategy and skill, this is like nothing you have ever seen before. This takes fast fingers, quick wits and concentration. Playable from age 6 to 65, it is a good family game. \$9.95.



FREE CATALOG

AARDVARK-80 ✓ 232

2352 S. Commerce, Walled Lake, MI 48088
(313) 669-3110



Two new utilities from Image Computer Products.

nounced. Soundspelling can be used to force correct pronunciation; for example, the word BASIC sounds better soundspelled BAYSIK. Stress can be added within words to make them sound even better —BAY!SIK. For maximum precision, an optional symbol set based on the International Phonetic Alphabet can be used. The program also provides a talking keyboard which echoes each key struck. This feature is useful for teaching touch-typing or where visual feedback of key-presses is not possible. Sayit and manual are priced at \$125.

BAYSIK Speech, Suite 289, 1259 El Camino Real, Menlo Park, CA 94025. Reader Service number 469.

Apple 2D-3D Graphics

A software program that brings professional multidimensional graphics capability to Apple II personal computers is offered by Apple Computer, Inc., 10260 Bandley Drive, Cupertino, CA 95014. AppleGraphics II is a versatile programming tool designed to help you prepare computer programs which generate two-dimensional and three-dimensional graphics. It lets you see a multidimensional object from any angle. Programs developed using AppleGraphics II can be used by architects to design buildings, by drafting professionals to prepare plans and by scientists to conduct experiments. You can also call up a full-

screen view of any portion of a drawing, with no degradation of picture quality, for detailed study. For demanding applications requiring high-resolution hard copy, the AppleGraphics and Apple II system can be used with the most advanced plotters; AppleGraphics supports device-independent graphics protocol.

Requires 48K Apple II, video display and disk drive. Priced at \$95. Reader Service number 477.

Space Games for the Color Computer

Computerware, Box 668, 1512 Encinitas Blvd., Encinitas, CA 92024, is offering Color Invaders on cassette for the Radio Shack Color Computer. This game puts you at the controls of the space tank, where you fire at stellar ships and invading critters. Invading ships burst in air with explosive sound. Alien critters march across the screen, drop their bombs and scream with pain when you zap them. Each of the eight levels of play further complicates the game, to keep the beginner going and challenge the expert.


Color Invaders is priced at \$19.95, and requires use of the Radio Shack Power Pack. Reader Service number 467.

Utility Programs for The Apple II

Disk Fixer and Monitor Extender are machine-language programs which enable the

JPC PRODUCTS FOR

6800 COMPUTERS



High Performance Cassette Interface

- **FAST** - 4800 Baud Loads 4K in 8 Seconds!
- **RELIABLE** - Error Rate Less Than 1 in 10⁸ Bytes.
- **CONVENIENT** - Plugs Directly Into The SWTPC.
- **PLUS** - A Fully Buffered 8 Bit Output Port Provided.
- **LOW COST** - \$59.95 For Complete Kit.
- **OPTIONAL** - CFM/3 File Manager.

Manual & Listing \$19.95
(For Cassette Add) \$ 6.95

TERMS: CASH, MC or VISA;

Shipping & Handling \$3.00



JPC PRODUCTS CO.

Phone (505) 294-4623

✓ 92

12021 Paisano Ct.

Albuquerque, N.M. 87112

80 COLUMN GRAPHICS



The image on the screen was created by the program below.

```

10 VISMEM: CLEAR
20 P=160: Q=100
30 XP=144: XR=1.5*3.1415927
40 YP=56: YR=1: ZP=64
50 XF=XR/XP: YF=YF/YR: ZF=XR/ZP
60 FOR ZI=-Q TO Q-1
70 IF ZI<-ZP OR ZI>ZP GOTO 150
80 ZT=ZI*XP/ZP: ZZ=ZI
90 XL=INT(.5+SQR(XP*XP-ZT*ZT))
100 FOR XI=-XL TO XL
110 XT=SQR(XI*XI+ZT*ZT)*XF: XX=XI
120 YY=(SIN(XT)+.4*SIN(3*XT))*YF
130 GOSUB 170
140 NEXT XI
150 NEXT ZI
160 STOP
170 X1=XX+ZZ+P
180 Y1=YY+ZZ+Q
190 GMODE 1: MOVE X1,Y1: WRPIX
200 IF Y1=0 GOTO 220
210 GMODE 2: LINE X1,Y1-1,X1,0
220 RETURN
    
```

The Integrated Visible Memory for the PET has now been redesigned for the new 12" screen 80 column and forthcoming 40 column PET computers from Commodore. Like earlier MTU units, the new K-1008-43 package mounts inside the PET case for total protection. To make the power and flexibility of the 320 by 200

bit mapped pixel graphics display easily accessible, we have designed the Keyword Graphic Program. This adds 45 graphics commands to Commodore BASIC. If you have been waiting for easy to use, high resolution graphics for your PET, isn't it time you called MTU?

K-1008-43M Manual only \$10 (credited toward purchase)

k-1008-43 Complete ready to install package \$495

Mastercharge and Visa accepted


Write or call today for our full line catalog describing all MTU 6502 products, including our high speed 8" Floppy Disk Controller for up to 4 megabytes of PET storage.

✓ 154


Micro Technology Unlimited
 2806 Hillsborough Street
 P.O. Box 12106
 Raleigh, NC 27605, U.S.A.
 (919) 833-1458

NOW 80 COLUMN PETS CAN HAVE MTU HIGH RESOLUTION GRAPHICS

Kill Surges Like Lightning!




Permanent protection for small computers, communications, medical and other sensitive electronic equipment. Surge Sentry works in parallel with the power line to shunt destructive power surges in picoseconds! Triggers at 10% above the nominal peak voltage.

At \$89.50, it's less than the cost of a service call. Easy to install for immediate protection. Several models to choose from to fit your specific application. For details and a free brochure, call or write:

**RKS
ENTERPRISES, INC.** ✓ 46

208 Mount Hermon Rd. #2
Scott's Valley, CA 95066
(408) 438-5760 **Dealer inquiries invited.**



DEALERS... SELL

kilobaud
MICROCOMPUTING

Selling Kilobaud MICROCOMPUTING, the most complete journal of microcomputing, brings the computer enthusiast through your door. Once he's in your store, you can sell him anything.

For information on selling Kilobaud MICROCOMPUTING, call 603-924-7296 and speak with Ginie Boudrieau, our bulk sales manager, or write to her at Kilobaud Microcomputing, Route 101 and corner of Elm St. Peterborough, NH 03458

Our dealers are telling us that Kilobaud MICROCOMPUTING is the hottest-selling computer magazine on the newsstand, so call today and join the ranks of dealers who make money with KM.

kilobaud
MICROCOMPUTING
80 PINE STREET PETERBOROUGH NH 03458

experienced programmer to manipulate, protect and display data. Disk Fixer provides easy access to either 13- or 16-sector formatted disks on either the track or sector level. The user is allowed sector-by-sector access to named files. Sector information can be displayed in hex, ASCII or a mixture of both. Price is \$29.95.

Monitor Extender is a handy programming tool that enhances the capabilities of the Apple II monitor ROMs. Memory can be displayed in ASCII or binary. A range of memory can be disassembled into an ASCII file in memory, creating a labelled file that can be used for assembler source code. Monitor Extender is \$19.95.

Image Computer Products, 615 Academy Drive, Northbrook, IL 60062. Reader Service number 476.

Word Processing Program

The Executive Secretary word processor, from Aurora Systems, Inc., 2040 E. Washington Ave., Madison, WI 53704, runs on Apple II with Applesoft and disk drives, any lowercase adapter or 80-column video board and shift key modification. It features versatile pagination and header printing, global search and replace, file merge and unmerge, block operations (move, transfer and delete) and spooling. It has a built-in card file system. The Executive Secretary interfaces with Data Factory, On-Line Database, Information Master and VisiCalc files. It provides automatic tabbing, dynamic text reformatting, immediate mode configuration for display screen, number of disk drives and printer, and it interfaces with CCS clock board for time stamping of documents. It also provides a built-in interface to D. C. Hayes Micromodem. Executive Secretary is priced at \$250. Reader Service number 480.

Programming Aid For North Star

Info-System lets you develop your own software without

any programming experience. All instructions are screen prompted. Just follow the cursor—your program is set up for you automatically. Info-System creates and initializes all files for you. All files can be updated, changed or deleted at your command. You can design the format for your printed reports. All information can be directed to the screen or to the printer. The system is flexible and easy to use. Info-System is written in North Star BASIC and requires 24K and two disk drives. Price is \$95.

Omni Software Systems, Inc., 146 North Broad St., Griffith, IN 46319. Reader Service number 473.

A BASIC Compiler For OSI

FBASIC runs under the OS-65D3 operating system, with full access to all system facilities. FBASIC is a super-fast integer subset of OSI/Microsoft BASIC which is well suited to systems-level programming. It produces stand-alone 6502 machine-code modules. Features include user-definable array locations, WHILE loops, GOTOs and GOSUBs to absolute addresses and direct access to registers. It also links compiled modules to the OSI interpreter. The FBASIC compiler is disk based and can produce programs larger than available memory. Requires 48K of memory. Available on eight-inch floppy disk for \$155.

Pegasus Software, PO Box 10014, Honolulu, HI 96816. Reader Service number 472.

Computer Epic

Empire of the Overmind is a computer fantasy game set in an ancient world where time has no meaning and the good King Alcazar ruled his kingdom nobly. Alas, one day a gray cloud settled upon Alcazar and his ministers were corrupted. The Overmind is the archvillain of the game. The Overmind is part machine, part spirit of evil, a dark angel striking terror into the heart of any foolhardy adventurer who dares to rectify the havoc he has wrought. The



Compare!

APPLE II PLUS:

16K
48K
64K

Apple III

All are 1981 models with Apple RAM. 64K unit is 48K unit with Microsoft 16K RAM board. 48K and 64K units include Applesoft and Integer BASIC's when used with DISK II.

HARDWARE for Apple II/II+

Disk II & 3.3 Controller
Disk II
Micro Sci A70 for Apple II
286K 5" Drive
3.3/Pascal/CPM Controller

SAVE
\$499 23%
\$439 16%
\$499 16%
\$79 20%

SAVE
\$1049 22%
\$1099 29%
\$1269 27%
Call



MONITORS:

Sanyo 9" B&W
12" B&W
12" Green
13" Color
13" Green
NEC 12" Green
RF Modulator, M&R
Serial/Parallel Interface, SSM AIO
Serial Interface Card, CCS
Parallel Interface Card, CCS
Apple IEEE Card

SAVE
\$169 30%
\$249 21%
\$299 21%
\$449 20%
\$225 21%
\$25 38%
\$159 20%
\$129 35%
\$99 37%
\$339 25%

80 Column Video Cards:

Apple Smartterm
Videx, Videoterm
Apple Clock/Calendar Card

\$299 17%
\$249 18%
\$239 15%

PRINTERS:

Apple Silentype w/Interface
Centronics 737
737 Interface & cable
Epson MX 80
MX 80 Interface & cable
Epson MX 100
MX100 Interface & cable
Apple Graphics Tablet

\$499 22%
\$759 26%
\$169 25%
\$475 27%
\$95 15%
Call
Call
Call
\$695 13%
\$249 28%
\$159 20%
\$299 23%
\$25 45%
\$39 33%

Microsoft:
Z80 Softcard
16K RAM Card
Hayes Micromodem II™
10 Memorex 5" Diskettes
10 Maxell 5" Diskettes

SOFTWARE for Apple II/II+

Language/Pascal System
DOS 3.3
Apple Writer
The Controller
Apple Pilot
DOS Tool Kit
Apple Fortran
Apple Plot
Tax Planner
Visicalc 3.2
Visicalc 3.3

SAVE
\$379 24%
\$49 20%
\$59 21%
\$495 21%
\$119 27%
\$59 22%
\$149 25%
\$49 30%
\$99 33%
\$119 21%
\$159 20%

Copy II Plus: Bit copy program.
COPY II PLUS by Central Point Software.
Will copy most protected programs for your backup in 45 seconds. \$39.95

MICROSOFT: (all disk)
Typing Tutor
Adventure
Fortran - 80
A.L.D.S.
BASIC Compiler
Olympic Decathlon


\$14 30%
\$23 24%
\$149 25%
\$110 10%
\$299 25%
\$19 24%

INSOFT:

ALD System II
TransFORTH II
Accounting Software

\$110 10%
\$110 10%
\$365 66%

NO SALES TAX



Computer Exchange

P.O. BOX 1380
JACKSONVILLE, OR 97530
TOLL FREE (800) 547-1289

TECHNICAL & OREGON: (503) 899-7297

Apple computer
Sales and Service

IMPORTANT NOTE:
We are an authorized dealer and repair center and will repair all Apple equipment regardless of where you purchased it, in or out of warranty. Normally our turnaround time on repairs is 24 hours. Call before sending equipment.



Above prices for mail orders only. Our store showroom is 126 N.E. "F" St., Grants Pass, OR. Store prices, which include software service, differ from mail order prices. No mail order sales at store. CALL ORDER DESK.

ORDERING INFORMATION: Minimum order \$100. Money Orders, Cashier Checks or Bank Wires Welcomed. Visa and MC orders add 3%. Personal checks accepted (allow up to 20 days to clear). Add 3% for shipping, handling and insurance. UPS ground is standard. Add 4% total for UPS Blue or 10% total for US Parcel Post. Include your telephone number. No COD's. Prices subject to change without notice. Order desk hours are 9 to 6 PDT, 10 to 3 Saturdays.

References:

We have been an Apple dealer since 1978. Our bank reference is First Interstate Bank (503) 776-5620. We belong to the Chamber of Commerce (503) 772-6293.

Save.

CLUB NOTES

The Apple Guild

The Apple Guild for Apple users and owners supports a sophisticated, computerized, telecommunication system (617-767-1303); maintains a collection of hard-copy material and software at its Apple Resource Center located at Massasoit Community College (Brockton, MA); and publishes a quarterly journal. Membership requests and other inquiries should be sent to: PO Box 371, Weymouth, MA 02188.

Micropolis User's Group

The Micropolis User's Group (MUG) is entering its second year of service offering its members a monthly newsletter, discounts, library disks and vendor and membership directories. For further information, contact Buzz Rudow, Micropolis User's Group, 604 Springwood Circle, Huntsville, AL 35803. 205-883-2621.

Malibu Printers

Anyone owning a Malibu printer and wishing to join a user's group should contact Tom Wade, 6030 Fennell Ave., San Diego, CA 92114. The purpose of the club is to facilitate communication with the manufacturer and to exchange ideas, fonts and complaints.

New RI Club

Apple users will be interested to note that a new computer club is forming in Rhode Island. The club will publish the National Apple Newsletter for owners and users of Apple II or Apple II+ computer systems. For further information, contact Scott Summer, 27 Leicester Way, Pawtucket, RI 02860.

OSI User's Group of Southern Ontario

The OSI User's Group of Southern Ontario has recently released its meeting schedule for 1981/2. The group will meet Sept. 5, Dec. 5, March 6 and June 5. For more information call Dr. N. Solntseff or Mr. C. Bryce, Unit for Computer Science, McMaster University, Hamilton, Ontario L8S 4K1 Canada (416-525-9140, ext. 4689 or 2065).

Homebrew Computer Club of Europe

The first East-European micro club, called the Homebrew Computer Club of Europe, has been founded for producers and users of 6800, 6809, Z-80, 8080, 8085, 6502 and F8 micros. For further information contact Dr. Endre Simonyi, 19 Trencsenyi, Budapest, H-1125, Hungary (0361 369183).

rhyme of Overmind tells the story of Alcazar's downfall and gives the player clues to guide the play. Empire of the Overmind cassettes for TRS-80 Model II, Apple II and Atari 800 are \$30; disks are \$35.

The Avalon Hill Game Company, 4517 Hartford Road, Baltimore, MD 21214. Reader Service number 466.

Apple Interactive Data Analysis

AIDA is a full-featured statistical analysis system for the Apple II, designed to perform data manipulation and statistical analyses needed in academic and marketing research. The program builds self-descriptive data files on the disk, then recalls variables by a virtual memory process as they are referenced by the user. Up to 11,000 data points can reside in memory at one time, allowing a maximum of over 4000 cases in analysis. Subsetting, transformation, missing data and case weights are supported.

Statistics include mean, variance, distributions, histograms, two-way tables (with chi-square), Pearson and rank correlation, pair and standard t-tests, ANOVA and multiple linear regression. It uses provisional means algorithms for accuracy of variances and cross-products, and computes significance levels. Data can be input from data files or through an enter and verify routine. Requires 48K with Applesoft and one disk drive. Price is \$235.

Action-Research Northwest, 11442 Marine View Drive,

SW, Seattle, WA 98146. Reader Service number 478.

Business Software

Four new software packages for business use have been introduced by Personal Software, Inc., 1330 Bordeaux Drive, Sunnyvale, CA 94086. VisiPlot is a high-resolution plotting and graphics package; VisiDex is a flexible personal information system; the VisiTrend/VisiPlot program combines VisiPlot graphics with a program for time-series manipulation, trend forecasting and descriptive statistics; and the VisiTerm program enables a personal computer to communicate with mainframes and micros.

A major feature of the programs is the ability to pass information between programs. VisiPlot and VisiTrend can share data directly with the recently updated VisiCalc program. Using VisiTerm as a terminal, program files from VisiCalc, VisiPlot and VisiTrend/VisiPlot, or files created with VisiDex, can be sent between computers over phone lines or other connections.

All four programs operate on the Apple II and Apple II+ with 48K, and are 16-sector compatible, with or without Apple's Language System. VisiDex and VisiTerm require one disk drive. VisiPlot and VisiTrend/VisiPlot require two disk drives and Applesoft BASIC. Prices are: \$199.95 for VisiDex; \$179.95 for VisiPlot; \$259.95 for VisiTrend/VisiPlot; and \$149.95 for VisiTerm. Reader Service number 481.

CORRECTIONS

Zoltan Szepesi of Pittsburgh, PA, has noted two line corrections to the program listing in "The Fifteen Puzzle" (February 1981, p. 114). Line 5080 should read:



```
5080 IF A(X)=16 THEN S=S+1
```

Also, the following two statements should be added to the program to prevent a jump from the last block of a row to the first block of the next row and vice versa:

```
7012 IF (X=4 OR X=8 OR X=12) AND
A(X+1)=16 THEN RETURN
7013 IF (X=5 OR X=9 OR X=13) AND
A(X-1)=16 THEN RETURN
```

* * * * *

The subscription price of a year of *Kilobaud Microcomputing* as printed in the May 1981 issue (p. 210) is incorrect. *Kilobaud Microcomputing* still costs \$25 for one year.



SALES VS OPERATING INCOME

Sample printout from the VisiPlot and VisiTrend/VisiPlot programs, two of Personal Software's new business packages.

Applesoft Compiler

Expediter II provides an easy means to translate Applesoft BASIC programs into machine language. The compiled version will run from two to 20 times faster. All features of Applesoft are fully supported, including high resolution graphics, shape tables, low resolution graphics, defined functions and DOS commands. There is no additional BASIC syntax to learn, and most compilations can be performed with one simple command.

The Expediter II compiler makes extensive use of pre-existing routines within the Applesoft ROM; this minimizes the memory required by compiled machine code. Applesoft programs can be compiled to reside at any location in memory, so multiple Applesoft programs can overlay each other and use the compiled Applesoft programs as subroutines. Comprehensive statistics are generated at compile times such as total memory requirement and starting address of the com-

iled machine code for each line of the Applesoft program. Price is \$99.95.

On-Line Systems, 36575 Mudge Ranch Road, Coarsegold, CA 93614. Reader Service number 482.

Integrated Circuit Info on Your Apple

Lamar Instruments, 2107 Artesia Blvd., Redondo Beach, CA 90278, has a new program that will quickly provide engineers, technicians and computer hobbyists with needed information. Chips contain pinouts and truth tables, where applicable, for over 100 TTL and CMOS integrated circuits. Any of these can be displayed in less than three seconds, using Apple's high-speed 6502 machine-language search routines. New pinouts and truth tables are easily added to the existing list using examples provided in the program. Chips is available on floppy disk for the Apple II or the Apple II+ for \$49.95. Reader Service number 475.

Storm Coming?

How many times have your plans revolved around the weather? Now you can turn your TRS-80 into a weather forecaster, and stop getting caught in the rain!!

CLIMATE-COMP was created by National Weather Service Meteorologist, author and editor David Carman.

THE WEATHER FORECASTER program will give you a short range forecast for your area. Enter a few simple measurements, easily obtained from newspapers or the U.S. Weather Service, to receive a short range forecast for the next six hours.

THE WEATHER PLOT program is the result of years of carefully collected data. At your command are records, charts, graphs, facts and figures on local weather for every major city in the United States. Choose your area of the country and the data files will release a flood of information. Each city is listed with its monthly rainfall, monthly and yearly average temperature, average wind speed, snowfall, heating and cooling degree days, annual average sunshine, humidity and record-breaking temperatures.

CLIMATE COMP for all the information you need to know what the weather has in store for you.

Cassette based: system requires 16K, level II, Pkg. no. 0102R \$19.95. Disk based: system requires 32K one disk drive, Pkg. no. 0316RD \$24.95.

TO ORDER: Contact your local Instant Software dealer. If these programs are unavailable, call toll-free 1-800-258-5473

* A trademark of Tandy Corporation

Instant Software™

PETERBOROUGH, N.H. 03458

✓333

CLASSIFIEDS

Classified advertisements are intended for use by persons desiring to buy, sell or trade used computer equipment. No commercial ads are accepted.

Two sizes of ads are available. The \$5 box allows up to 5 lines of about 35 characters per line, including spaces and punctuation. The \$10 box allows up to 10 lines. Minimize use of capital letters to save space. No special layouts allowed. Payment is required in advance with ad copy. We cannot bill or accept credit.

Advertising text and payment must reach us 60 days in advance of publication (i.e., copy for March issue, mailed in February, must be here by Jan. 1). The publisher reserves the right to refuse questionable or inapplicable advertisements. Mail copy with payment to: **Classifieds, Kilobaud Microcomputing, Peterborough NH 03458.** Do not include any other material with your ad as it may be delayed.

Hardly-used Hayes Micromodem for Apple. Like new! Only \$285. Still has unused warranty card! Also Centronics 737, like new, only \$700. For \$85 more you can have the Apple interface & cable. Howard Rothman, 218 Huntington Road, Bridgeport, CT 06608. 203-333-6436.

For Sale: TRS-80 and interface video display and all conn. 16K, Level II, manuals, extras. Like new \$900. W. Wright, 6362 San Diego Ave., Riverside, CA 92506. 714-781-5863, wk. ends.

Three 8K S-100 memory boards. \$125 each. For information on these quality S-100 boards contact: Richard A. Bockholt, 13275 South Street, Draper, UT 84020. 572-0590.

IBM/ESCON Selectric typewriter (correcting, w/legal keyboard) both 8 months old. Factory installed RS232C interface w/backspace and tab. In new condition, just too slow for my purpose. \$1600. J. Turner, 309 Mac Corkle Ave., Saint Albans, WV 25177. 304-776-3675.

Axiom printer, Model EX801P (parallel). Great, trouble-free printers; new, in original boxes, my project cancelled. \$425 each, or all four (4) \$1600. J. Turner, 309 Mac Corkle Ave., St. Albans, WV 25177. 304-776-3675.

For Sale: 8 Godbout 8K Econoram II \$43 each postpaid. Hazeltine 2000 CRT \$500 FOB. Compucolor 8001, 19" CRT, 8 colors, 192x160 resolution, large keyboard with numeric pad, cursor control, BASIC, \$1200 FOB. Make offer. D. G. Kissinger, School of Health, Loma Linda Univ., Loma Linda, CA 92350. 714-796-7272.

For Sale: Complete system. IMSAI 8080 computer with 64K memory, Lear Siegler ADM-3 terminal, and Altair disk drive. Good condition. Best offer. Jim Fritz, 1413 Harmony Lane, Annapolis, MD 21401. 301-757-7019.

For Sale: LA-36 Decwriter, excel. cond., RS-232 or current loop: \$790. ASR-38 Teletype, good cond.: \$225. KSR-38 Teletype, fair cond.: \$175. UDS type 202 modems: \$95. Optical paper tape reader, make an offer. Documentation but not shipping included in all prices. D. Monroe, 426 Maquan St., Hanson, MA 02341. Call 617-293-2885, weekends best.

Exatron stringy floppies for TRS-80. Two for sale. Both like new. Complete setup. Owner's manual, cable, 15 blank tapes. \$150 each. Jane Caldwell, 411 Rembert St., Demopolis, AL 36732. 205-289-0756.

For sale—Zenith/Heath H-11 system, 64K RAM, two eight-inch floppy drives, HT-11 and Pascal software. Fully DEC PDP-11/03 compatible. \$4200. 215-248-0439, evenings.

For sale: ASR-33 teletype with stand and service manuals. Reads and punches paper tape. Good condition. \$200 plus shipping. Dick Carney, 1927 Dewey, Bartlesville, OK 74003. 918-336-3731.

For Sale: One set *Kilobaud Microcomputing* issues #1-52, missing #14. All in excellent shape. Best offer. S. Alter, 105 Southgate Circle, Massapequa Park, NY 11762.


For Sale: Heavy duty IBM Selectric I/O terminal (GTE Novar). Very good working condition: includes manuals. \$275. Call Jim at 617-692-7541.

For Sale: Exidy Sorcerer—32K RAM (includes all hardware schematics), some software, two cassette recorders and interfacing. Video 100 (12") monitor. Basic ROMpac and EPROMs for assembler pac. \$850. Contact Al Schmidt, Rt. #3, Box 206, Oswego, IL 60543. 312-554-3044.

For Sale: Texas Instruments 990/4 computer floppy development system. Includes dual 8-inch floppy disk drives, 990/4 CPU, 810/4 printer, bell data set interface, two TMS 1000 incircuit emulators with debug, 9900 time share pers. module & paper tape reader, and power basic module. Orig. val. \$24,000; asking \$12,000 or best offer. Contact: Howard Morrison, Marvin Glass & Associates, 815 North LaSalle Street, Chicago, IL 60610. 312-664-8855.

For Sale: SWTP 6800 computer 28K PR40 printer, 7mp boards, CT64 term Sanyo mon—AC30& CIS30+ interfaces. Extras—CPU board w/Z-80 chip; 6809 CPU board (Per-com); SWTBUG-RT68 mon., S32 blank memory board (SWTP). Best offer over \$600. 301-367-2760, after 5 pm. C. N. Harrid, PO Box 3021, Baltimore, MD 21229.

For Sale: Digital group Z-80 system, 34K (expand to 50K by adding chips), TVC-F video readout and cassette interface, 4 parallel and 4 serial ports, dual 8-inch floppy-disk system, MCOS, FORTRAN, Maxi-BASIC, Z-80 assembler, Sargon chess, text editor & formatter. Documentation on all hardware and software. Selectric terminal (not working). \$3500 or best offer. DeWayne Smith, 714-792-2703 or 714-793-2853 (work). Redlands, CA.



"Well, there goes the neighborhood."

Computer Arts Festival

The Personal Computer Arts Festival, held in conjunction with the Personal Computing '81 Show at the Philadelphia Civic Center, Aug. 28-30, will feature technical sessions, demonstrations and exhibits, as well as the annual computer music concert and computer graphics film/video show. Computer musicians and artists who would like to speak, exhibit or perform at the festival should contact PCAF '81, Box 1954, Philadelphia, PA 19105.

National Computer Shows

The National Computer Shows has announced its fall schedule of trade and public expositions for manufacturers, OEMs, distributors, dealers and retailers selling small, medium and large computers for business, industry, government and education. The shows feature office systems, data and word processing equipment, telecommunications equipment, electronic typewriters, computers for scientific and engineering applications, microcomputers, computer graphics, computer peripherals, accessories, supplies and software. The shows are: the Second Annual Midwest Computer Show, Sept. 10-13, at Chicago's McCormick Place; the Second Annual Mid-Atlantic Computer Show, Sept. 24-27, at Washington's DC Armory; the Third Annual Northeast Computer Show, Oct. 15-18, at Boston's Hynes Auditorium; and the Southeast Computer Show, Oct. 29-Nov. 1, at the Atlanta Civic Center. Contact the National Computer Shows, 824 Boylston St., Chestnut Hill, MA 02167, 617-739-2000.

Software Info '81

Software Info '81, the National Software Package Conference and Exposition, will be held Sept. 14-17 at Chicago's Merchandise Mart Expocenter. Software product exhibits, seminars and speeches are slated. For more information, contact Software Info, 1730 N. Lynn St., Suite 400, Arlington, VA 22209, 703-521-6209.

Personal Computer Show

The 4th Personal Computer World Show will be held at the Cunard Hotel, Hammersmith, London, from Sept. 10-12. Further information can be obtained by writing Timothy Collins, Personal Computer World Show, 11 Manchester Square, London W1E 2QZ.

IEEE Computer Society Conference

"Productivity—An Urgent Priority" is the theme of the IEEE Computer Society Compcon Fall '81 to be held Sept. 14-17 at the Capital Hilton Hotel, Washington, DC. Contact Compcon Fall '81, PO Box 639, Silver Spring, MD 20901, 301-589-3386.

Electronic Learning Conference

The Association of Media Producers will spotlight electronic learning in a conference scheduled for Sept. 23-25 in Washington, DC. "Technology Revolution: Education And Training" will focus on microcomputers, cable TV and video disks or tapes. For information, call the AMP at 202-857-1195.

Ham/Computerfest

The 1981 Golden Spread Hamfest and Convention, sponsored by the Panhandle ARC and the High Plains TRS-80 User's Group will be held Aug. 7, 8 and 9 at the Student Activities Center of West Texas State University in Canyon, TX. Amateur events include commercial displays, swapfest, ARES, station operating demonstration, Navy and Army MARS meetings, ARRL forum, TRS-80 user's group meeting and technical sessions. For further information, contact Carl Holtman, High Plains TRS-80 User's Group, PO Box 30546, Amarillo, TX 79120.

Midwest Computer Show

The Second Annual Midwest Computer Show & Office Equipment Exposition will be held Thursday-Sunday, Sept. 10-13, 1981, at Chicago's McCormick Place. The show features hardware, software and supplies for business, education, government, home and office use, plus office systems and office equipment. For more information, contact National Computer Shows, 824 Boylston St., Chestnut Hill, MA 02167 (617-739-2000).

Mid-Atlantic Computer Show

The Second Annual Mid-Atlantic Computer Show & Office Equipment Exposition will be staged Thursday-Sunday, Sept. 24-27, 1981, at the Washington DC Armory/Starplex. Exhibits will include hardware, software and supplies for business, education, government, home and office use, plus office systems and office equipment. The show is produced by National Computer Shows, 824 Boylston St., Chestnut Hill, MA 02167, 617-739-2000.

Software Symposium

Queue's second annual Educational Software Symposium is set for Oct. 15-16 at the Stouffer's Inn in White Plains, NY. The symposium will feature education software from dozens of publishers on display for review and purchase. There will also be a wide variety of seminars, panels and user interest group meetings on such topics as designing educational software, evaluating educational software, computers in the elementary classroom, computers in various curriculum, including math, science, English and foreign language. Registration is \$45 in advance, \$55 at the door. Contact Monica Kantrowitz, President, Queue, Inc., 5 Chapel Hill Drive, Fairfield, CT 06432.

Computers and Medicine

Computers in Ambulatory Medicine is the topic of the Joint Annual Conference of the Society for Advanced Medical Systems and the Society for Computer Medicine, Oct. 31-Nov. 1 at the Washington Sheraton, Washington, DC. Selected contributed papers, topic oriented sessions, basic and advanced tutorials on fundamentals of medical computing. Fee is \$115 members, \$165 non-members. For information write SCM, 9650 Rockville Pike, Bethesda, MD 20014, or call 301-530-7120.

Computers for Lawyers

"Legal Info," the first national conference and exposition dedicated to automating legal information systems, is scheduled for Dec. 1-3 at the Shoreham Hotel in Washington, DC. For more information, write "Legal Info," 1730 North Lynn St., Suite 400, Arlington, VA 22209, or call 703-521-6209.

RIT Courses for Deaf

Rochester Institute of Technology (RIT) will offer two computer courses for deaf adults this summer through the National Technical Institute for the Deaf (NTID). Introduction of Data Processing will be offered Aug. 3-7. Advanced Data Processing will be offered Aug. 10-14. For more information contact Donald Beil, NTID Data Processing Dept., Rochester Institute of Technology, One Lomb Memorial Drive, Rochester, NY 14623, or call 716-475-6373 (voice or TTY).

MICRO QUIZ

(from page 8)

Answer: ECCS

right\$ ("NECSL",3) = "CSL"
B\$ = left\$ ("CSL",2) = "CS"
C\$ = mid\$ ("NECSL",2,2) = "EC"
B\$ = "EC" + "CS" = "ECCS"

**DISK DRIVE WOES?
PRINTER INTERACTION?
MEMORY LOSS?
ERRATIC OPERATION?**

Don't Blame The Software!



Power Line Spikes, Surges & Hash could be the culprit! Floppies, printers, memory & processor often interact! Our patented ISOLATORS eliminate equipment interaction AND curb damaging Power Line Spikes, Surges and Hash.

Pat. #4,259,705

- ISOLATOR (ISO-1) 3 filter isolated 3-prong sockets; integral Surge/Spike Suppression; 1875 W Maximum load, 1 KW load any socket \$62.95
- ISOLATOR (ISO-2) 2 filter isolated 3-prong socket banks; (6 sockets total); integral Spike/Surge Suppression; 1875 W Max load, 1 KW either bank \$62.95
- SUPER ISOLATOR (ISO-3), similar to ISO-1 except double filtering & Suppression \$94.95
- ISOLATOR (ISO-4), similar to ISO-1 except unit has 6 individually filtered sockets \$106.95
- SUPER ISOLATOR (ISO-11) similar to ISO-2 except double filtering & Suppression \$94.95
- CIRCUIT BREAKER, any model (add-CB) Add \$ 8.00
- CKT BRKR/SWITCH/PILOT (-CBS) Add \$16.00

AT YOUR DEALERS

Master-Card, Visa, American Express
Order Toll Free 1-800-225-4876
(except AK, HI, PR & Canada)

ESP Electronic Specialists, Inc. ✓ 93

171 South Main Street, Natick, Mass. 01760

Technical & Non-800: 1-617-655-1532

BRAND NAME BARGAIN

32K S-100 STATIC RAM \$399 (lists \$559)

These are ultra high speed operation / low power consumption boards with extended addressing & bank select.... we think we've lucked into the S-100 value of the year.

Recently a leading manufacturer of static memory for S-100 systems received a batch of electrically perfect 32K static RAM boards with some minor cosmetic defects. We were in the right place at the right time and bought the entire lot.

We're offering these memories in kit form with all components (SOCKETS ALREADY SOLDERED IN PLACE) and complete documentation.

Insert the ICs into the appropriate sockets, solder in a few other parts - and you're up and running. Best of all, you'll have the same reliable, ultra-high speed, fully static, and low power performance you've come to expect from the boards made by this prominent company.

Don't miss out on the memory deal of the year
these are limited quantity, first-come-first-served.

**FOR MORE INFORMATION
CALL (415) 783-2866**

TODAY!!!

S-100 EXTENDER/ LOGIC PROBE

\$59 Kit, \$79 Assembled/Tested.


- **New** interlaced ground and signal traces, improves performance, reduces noise, with the new high clock frequency boards
- **New** brighter display, makes this very handy logic probe easier to use
- **New** proposed IEEE buss edge connector label, with all the fine quality documentation you expect with Mullen kits.
- High quality FR-4 board is double sided with plated thru holes and solder-masked for easy kit assembly
- Gold on all mating connector surfaces for better electrical contact
- Formed connector leads for easy scope probe attachment
- Jumper links in power lines makes current measurement and fusing easy
- Large "kluge" area lets you build and test your own circuits

MULLEN COMPUTER PRODUCTS, BOX 6214, HAYWARD, CA 94544
OR PHONE (415) 783-2866. VISA/MASTERCARD ACCEPTED.
INCLUDE \$1.50 FOR SHIPPING & HANDLING. CALIFORNIA RESIDENTS ADD TAX.

✓ 37

MULLEN Computer Products

GET MORE OUT OF YOUR APPLE WITH MICRO^{on} the APPLE



MICRO/Apple

Over 30 Apple Programs on Diskette — For
Less Than \$1.00 Apiece! No Need to Type
In Hundreds of Lines of Code!

224-page book and diskette \$24.95*

* Add \$2.00 for surface shipping.
Massachusetts residents add 5% for sales
tax.

MICRO's new book for Apple II users lets you

- Speed up programming in Applesoft and Integer BASIC!
- Add Apple II Plus editing features — at no cost!
- Round and format numbers accurately in business applications!
- Get lowercase letters and punctuation into Applesoft strings — at no cost!
- Do a shape table easily and correctly!
- Play the hit game "Spelunker"!
- And much, much more!

With MICRO/Apple 1, the first volume in our new series, you receive

- 30 choice articles from MICRO, The 6502 Journal (1977-80), complete with listings, all updated by the authors or MICRO staff,

plus

- 38 tested programs on diskette (13 sector, 3.2 DOS format, convertible to 3.3).

Ask for MICRO/Apple at your computer store or

Call Toll-free 800-227-1617, Ext. 564

In California, call 800-772-3545, Ext. 564

VISA and Mastercard Accepted

MICRO

P.O. Box 6502

Chelmsford, Massachusetts 01824

CP/M Primer Real-Time Programming Program Structure and Design Computers Can Make You Rich The Book of Apple Software

CP/M Primer

Stephen M. Murtha & Mitchell Waite
Howard W. Sams & Co., Inc.
Indianapolis, IN, 1980
Paperback, 92 pp., \$11.95

Digital Research has provided the microcomputer world with an eminently successful software product in the CP/M operating system. Everything the CP/M user needs to know about the system is contained in the set of manuals included with the software. Unfortunately, those manuals are not organized or written in a manner understandable to the novice programmer or computer user. As more and more inexperienced personal computer users are acquiring CP/M-based machines, there is a need for a guide to CP/M that is understandable by the beginner.

The *CP/M Primer* is an outstanding example of how to write a technical book for the beginner. It guides the reader step by step through the subject, explaining what CP/M is and how to use it.

As the authors point out, *CP/M Primer* does not replace the Digital Research manuals. Some topics, such as modifying the system for a specific hardware environment or the use of the PUN: and RDR: devices, are not even covered. But these topics are for the more advanced programmer, who will be able to find all the additional information he needs in the more detailed manuals. Where the *CP/M Primer* does not include all these details, references are made to the appropriate sections of the Digital Research manuals.

What the novice user has always needed is a guide to using CP/M written for normal mortals, as opposed to expert programmers. While all the cutesy cartoons in this book don't do much to achieve that

goal, the more technically correct diagrams and simulated CRT screen displays certainly do. The friendly, informal tone of the text makes the reading easier, without detracting one bit from technical accuracy.

This brings up a very important point: accuracy. In past book reviews in *Microcomputing* I have blasted other publications as being worthless or insulting to the reader. These judgments are made primarily on the basis of the percentage of misinformation contained in a book, which I find inexcusable.

"Refreshingly enjoyable" is, therefore, the feeling generated by reviewing *CP/M Primer*. While it is readable and understandable, this book is also incredibly accurate. To achieve such accuracy, the authors had to know their subject intimately. They also had to be talented at presenting a technical subject in such a well-organized and readable manner.

What Stephen Murtha and Mitchell Waite present so accurately are all the instructions you will need to operate a computer running CP/M. Quite often you will use the operating system only for its file-handling capabilities, running BASIC or some other higher-level language. The first five chapters cover all the information you will need to make full use of CP/M at this level.

When you are ready to go on to assembly-language programming, chapters 6 through 8 will guide you through operating the editor, assembler and debugger included with CP/M. (You will not be able to learn assembly-language programming from these chapters alone, however. For that you will also need a book like Intel's *8080 Assembly Language Programming*

Manual that will tell you what all the microprocessor instructions will do.) The *CP/M Primer* will tell you how to enter and edit your source program, assemble it and debug the resulting machine-language program. Chapter 8, on the DDT debugger, is one of the highlights of the book, explaining a difficult subject completely and concisely.

Some more intricate insights into the internal structure of CP/M are included in an appendix, where such details belong. The appendix mentions the differences between versions 1.4 and 2.0. Again, the superb organization of topics and clarity of the presentation provide the reader with a framework on which to hang the numerous details he will have to dig out of the turbid Digital Research manuals.

This book was written to fill a real need and it fills that need more than adequately. It is accurate, readable, understandable and indispensable. Don't stay home without it.

Ken Barbier
Borrego Springs, CA

Home Computers Can Make You Rich

Joe Weisbecker
Hayden
Rochelle Park, NJ, 1980
Paperback, \$6.50, 122 pp.

Of the hundreds of thousands of today's microcomputerists, a healthy majority probably entered the field with the vague idea that somehow there was money to be made with small computers. At least I did; and when I spotted this paperback on my local bookstore's shelf I bought it, albeit

with mixed feelings of optimism and skepticism. I was neither disappointed nor surprised.

After an introductory overview of the microcomputer industry, Weisbecker devotes a chapter to some useful considerations on making money. He warns of pitfalls and failure-prone behavior patterns, and he describes what he calls "luck management," a way of optimizing one's chances to succeed. But the big message of this chapter bears repeating here:

If you are going to sell products, sell services, or create new ones, there are two basic principles you should know about:

1. Find a need and fill it at a reasonable cost.
2. Never overestimate the intelligence of your customers.

The next chapter, on resources, discusses books, magazines, stores, clubs, user groups and shows which the reader can use for basic education and for sources of money-making ideas. A few specific book and magazine titles on computers are suggested, as are several key reference aids for authors.

The real meat of the book is contained in the middle chapters entitled "Writing for Money," "Creating and Selling Programs," "Services for Sale" and "Use Your Imagination." In these pages Weisbecker gives advice and suggestions on a wide range of concerns: writing nontechnical vs software/construction articles; royalty agreements vs outright sale of programs; marketing programs through hardware manufacturers vs software and magazine publishers. I found especially apt his ideas on operating a microcomputer rental service for students, for use at parties, or for merchant displays.

The final three chapters cover various topics, but are all strongly profit-oriented. In "Invent Your Way to Success," the author discusses at some length his own favorite way of making money with computers. "Making Your Money Grow" urges the reader toward stock market investment of profits (earned, of course, by implementing the book's ideas), using the microcomputer to maximize return. In "Working at Home," equipment, supplies and reference books for the home-based office are discussed briefly, and the undeniable need for self-discipline is stressed.

The book is by no means flawless. I found several distracting typographical errors—none, however, that distorted meanings. The section on opportunities for computer consultants is of questionable utility. What qualified consultant would feel the need to read this kind of book? Also, it seemed to me unnecessary to advise a hardware hacker to get himself a soldering iron. These are mere quibbles, to be sure. What is more serious is that a book about making money doesn't have a chapter on simple bookkeeping. Perhaps one or more of the suggested readings covers this subject, but I'd like to see the topic covered in this book.

Yes, I was skeptical that this book would deliver on its promise. It certainly is not a

detailed, foolproof, get-rich-quick scheme. But, the book is well worth its modest price. Weisbecker has covered thoroughly, if not exhaustively, the many broad categories of money-making activities, and within those categories he has suggested specific applications quite imaginatively. Few will become suddenly wealthy as a result of reading this book, but there are plenty of ideas here to point a self-starter in the right direction. As the author says, "Think of the current phase of the microcomputer industry as your opportunity to develop the skills that can make really big money for you in the future."

Dennis C. Cullinan
East Lansing, MI

Real-Time Programming with Microcomputers

Ronald C. Turner
Lexington Books
D. C. Heath & Co., 1978
Hardcover, 168 pp.

Ronald Turner set out to accomplish quite a task: to write a book that spans the "no-man's land" between the separate worlds of the hardware designer and the software designer. Although this book might not be the ultimate text in that area, I feel Turner has accomplished his goal quite admirably. Better yet, his writing is concise, understandable and often humorous, so it reads well whether you are a professional or a hobbyist.

This book is about interface software drivers. Real-time in the text refers to events requiring attention from the microcomputer but occurring asynchronously with the internal timing of the microcomputer. Please note that you will find no fancy programming gimmicks in this book. Instead, emphasis is put on structured, easy to read and easy to modify code.

The microprocessor used in the examples is the 8080, and code examples in PL/M are used where advantageous. Before all of you who use processors other than the 8080 wander on to the next review, let me state that this is not a programming manual for that microprocessor. Its instruction set is examined, but only as a means to discover ways to manipulate data.

Topics covered include choosing between a polled or interrupt-driven system, establishing a communications protocol between the microcomputer and peripheral devices, data manipulation and control of program flow. Special emphasis is placed on establishing a concise system of communication between devices and tightly structured (therefore easily modified) program blocks in these discussions.

The last section of the book deals with top-down program design, and has practical exercises in designing software for dedicated real-time systems. Three gener-

al-information appendices and answers to selected questions in the book are also included at the end.

This book should be valuable to anyone, regardless of their chosen family of microprocessor devices. I say this because of the impact Turner has had on my programming style. I find that since reading his book, problems in programming I/O drivers for my 6502 are much more easily broken down into solvable steps. This book would be a good addition to the library of anyone who is involved in writing peripheral-driving software.

Thomas Franks
Wadsworth, OH

Techniques of Program Structure and Design

Edward Yourdon
Prentice-Hall, Inc.
Englewood Cliffs, NJ
Hardcover, 364 pp., \$24.95

It's a dry, academic-sounding title, but thanks to the author the content is readable, entertaining and informative. This is a practical book, punctuated with humor and anecdotes, that reveals the mysteries of structured programming. It assumes that the reader is basically familiar with computer hardware and various programming languages (i.e., assembler, Fortran, COBOL, PL/1, ALGOL). However, you don't have to have an in-depth knowledge of all these languages to appreciate the book. The author is not concerned with language syntax and mechanics but with the frame of mind and concepts required for structured programming.

The elements of good programming—top-down design, modular programming, and simplicity and clarity of design—are discussed at length. After presenting the theory and techniques of structured programming, the author looks at the flip side of writing programs—getting them to work. A key device to prevent errors in the first place is antibugging. This "refers to the philosophy of writing programs in such a way to make bugs less likely to occur—and when they do occur (which is inevitable) to make them more noticeable to the programmer and the user."


The final two sections are entitled "Program Testing Concepts" and "Debugging Concepts and Techniques." They lay the groundwork for an organized, problem-solving approach to programming and debugging. The author humorously notes that:

Tracking down a program bug is much like tracking down the murderer in an Agatha Christie mystery: Where massive manhunts and brute-force techniques of the local police force fail, the hero, M. Hercule Poirot, succeeds by employing the "little gray cells."

This book is not a beginner's programming tutorial, nor is it written specifically for the microcomputer hobbyist. But even if you're a neophyte programmer, you'll find it worthwhile to be exposed to these

GO BOLDLY...

Where No TRS-80* Program Has Gone Before!



ANGER IN ORBIT

DATE: 28.02.2047
LOCATION: 270 million miles from Terra
MISSION: Maintaining Terra's Space Lanes

Briefing will follow;
1.1 Your mission is to destroy any asteroids in your sector and to prevent alien spacecraft from infiltrating the Terran Defense Network.
1.2 Your ship is armed with an anti-matter cannon. You can shoot large asteroids, but this turns them into many smaller asteroids, each capable of destroying your ship.
1.3 In addition, alien ships can make in-

stantaneous hyperspace jumps into your area and start firing on your ship.
1.4 You'll need lightning reflexes and nerves of steel to survive Danger In Orbit. We have no use for non-survivors!


Danger In Orbit, a real-time, machine-language game, features variable levels of difficulty, superb high-speed graphics, sound effects and automatic score keeping. (T1 or T2)

Order No. 0237R
\$14.95 Tape.
Order No. 0247RD
\$19.95 Disk.

BALL TURRET GUNNER

For years the Petro Resource Conglomerate has attacked our photon collection stations and strangled our deep-space trade routes. The PRC Exonerator Class light fighters (code name: Gnat) have been their main weapon. Now you can strike back, by joining the Ball Turret Gunner Service.


Imagine yourself at the control console of an LW-1417 Stratoblazer (Type B Strategic Laser Weapon). Your Hindsight Director informs you that a Gnat fighter is coming in for an attack. You pivot your gigawatt laser turret until you can see the target on your monitor. The Range Indicator shows him coming in fast. The Targeting Computer studies his course and speed as your finger tenses over the firing key. You know you'll have only a fraction of a second in which to react. The Gnat fighter's evasive maneuvers cause him to dance in your sights. Suddenly,



you see the FIRE Command and you react instinctively. Your laser beam lashes out and reduces the Gnat to an expanding ball of ionized gas. Mission accomplished!

Ball Turret Gunner, with your choice of multiple levels of difficulty, optional sound effects and superb graphics, is more than just a game. It's an adventure. Experience it! (T1)


Order No. 0051R \$9.95.



ALIEN ATTACK FORCE

The INVADERS are coming! Earth's defenses are dead except for your Laser base. Your assignment is to destroy the approaching INVADERS before they destroy Earth. Before Earth's sensors failed, they detected 550 armed invaders in space, speeding toward us in 10 attack formations of 55 in each group. The sensors detected four different types of attack craft: Large, Medium, Small, and short profile craft which is the most difficult to destroy. If you cannot stop these space attackers they will stop Earth... for good. (T1)

Order No. 0240R \$9.95.



COSMIC PATROL

WARNING: PLAYERS OF THIS GAME SHOULD BE PREPARED FOR A STATE OF REALISM HITHERTO UNAVAILABLE ON THE TRS-80

Skilled players soon master many difficult computer games, but COSMIC PATROL is in a world all its own. The challenge intensifies! Supporting graphics and sound (optional) make each encounter an exciting new experience. It all adds up to a Super 3-S package... skill, sight and sound.

Scenario: The Cosmic Patrol program puts you in the command chair of a small interstellar patrol craft. Your mission is to defend Terran space and prey on the Que-lon supply ships which carry essential parts and lubricants for that implacably hostile robotic force. The drone freighters

are fairly easy pickings for the accomplished starship pilot, but beware of the I-Fighter escorts. They're armed, fast and piloted by intelligent robots linked to battle computers. They never miss.

The Cosmic Patrol program is not just another search and destroy game. With its fast, real-time action, impressive sound option and superb graphics, this machine-language program is the best of its genre.

Don't keep putting quarter after quarter into arcade games or spending big bucks for video game cartridges. Get Cosmic Patrol from Instant Software—and get the best for less! (T1 or T2)

Order No. 0223R
\$14.95 Tape.
Order No. 0224RD
\$19.95 Disk.

TO ORDER

See Your Local Instant Software Dealer or Call
Toll-Free 1-800-258-5473
(Orders Only)
In NH dial 1-603-924-7296

Instant Software™

PETERBOROUGH, N.H. 03458

400

(T1) = TRS-80 Model 1, Level II, 16K RAM.

(T2) = TRS-80 Model 1, Level II 16K, expansion interface 16K + 1 disk drive.

ideas before you get caught up in sloppy habits. Those already into their programming careers will find this book a valuable introduction to the programming concepts of the 80s.

Fred La Point
Lansdale, PA

The Book of Apple Computer Software

James Sadler and Jeffrey Stanton
The Book Company
Softcover, \$19.95, 243 pp.

One of the toughest tasks that a computer hobbyist has is choosing software. Hundreds of different programs are released each month—from games to business applications. Most people cannot take the time to evaluate these new programs, let alone the thousands of programs currently written. For the Apple owner this task has been made easier with *The Book* by James Sadler and Jeffrey Stanton.

The editors have done a noteworthy job of rating and describing the software available for the Apple II. The book is divided into eight sections, five of which deal with program reviews. These sections are Games and Entertainment, Education, Business and Utilities. Each section is further subdivided with the software logically grouped under their own

heading. The other sections deal with how the software was rated, software under review and new products which may be evaluated at a future time.

Software ratings are the most important part of the book. Software is rated on a scale of 10 to 100, 10 being unacceptable, and 100 superior. The rating criteria used are what you would use if you went to a computer store to purchase the software. Ease of use, documentation and reliability are all used to evaluate the software, and these factors are also listed in the review, scored from 10 to 100.

One of the more interesting ratings is the price/usefulness ratio. The reviewers attempt to answer the question, can "a fair program from a vendor priced at \$7.95 be a better value than only a slightly better program of the same type from another vendor priced at \$24.95." This rating can be especially useful when looking at similar programs. In my opinion, the price/usefulness ratio is one of the most important aspects of this book.

Another nice feature is the comparison charts for word processing and assembler programs. A quick glance will list all the major features of the application rated side by side. These charts can be very helpful in selecting application software when there are many features.

The major problem with all books of this type is staying up to date. The editors

have found a way around this problem by offering quarterly updates. This service costs \$15 a year.

On the negative side, the book is full of typos. Whole pages are duplicated within the book, often one right after another. Another flaw is the way the programs are reviewed. The reader is given a list of judging criteria, but nowhere is it mentioned if similar programs were tested against one another. Just as important, no qualifications are given of the reviewers. This may not be important for game programs, but can be critical for business applications where a poorly evaluated program, by an unqualified individual, may cause a company to lose a substantial amount of money.

I have mixed feelings about this book. It is very convenient to have a book that contains a review of almost all current Apple software. The quarterly updates are most appreciated in keeping *The Book* current. On the other hand, \$34.95 for this book (\$19.95 for the book, \$15 for the updates) seems a bit much. There are just too many typos for a book at this price.

If keeping abreast with software is important to you, then buy *The Book*. I don't think that you will find as many programs rated and organized in any other book or magazine.

Robert J. Flynn
Riverdale, IL

GET ORGANIZED

With These Utility Programs From Instant Software

FIND IT QUICK

Put an end to the Misplaced Information Syndrome! Here is a reliable, fast, subject-oriented information locator—**FIND IT QUICK!** This information indexing and retrieval system is versatile and flexible—the ideal tool for doctors, lawyers, engineers, businessmen, educators, anyone who needs to locate information.

Designed with a journal/magazine format, FIQ is versatile enough to be used to store and retrieve any type of reference information including client lists, vendor advertisements, report bibliographies and more—even poems and famous quotations. Subjects can be indexed or called according to author, journal and date or by up to nine keywords that you determine. Keywords can be used singly or in combination during the search routines.

FIQ can be used by anyone. It requires no special skill, just the ability to type. Ar-

ticle references to be stored can be pre-selected and then entered into the system by a secretary or assistant. The contents of entire file cabinets can even be indexed and stored!

FIND IT QUICK requires a minimum system consisting of a TRS-80 Model I Level II with 16K of RAM, an Expansion Interface with 16K of RAM and at least one disk drive. Up to 1080 items can be stored on one data disk. Instant Software's Tiny DOS operating system is included on the program disk so that you can use the program without fuss or bother.

Make your computer work like your own personal librarian with **FIND IT QUICK**. Can you afford to wait another day?


Order No. 0258RD \$49.95. Disk

MASTER DIRECTORY

The **MASTER DIRECTORY** is a disk file storage program that reads the files on all your disks and stores the file names and extensions and even records the free space on each disk. All you have to do is number the disks in your library and the **MASTER DIRECTORY** will keep track of their contents. You can read the names, displayed alphabetically, search the **DIRECTORY** for file names and extensions, delete disks and search for free space. You can store 5000 files or 320 disks, whichever comes first.

Your disk storage problems are over now that the **MASTER DIRECTORY** is here. This package requires the following minimum system:

1. A TRS-80 Level II with 16K RAM.
2. An Expansion Interface.
3. One (or more) disk drives.




Order No. 5005RD (disk-based version)
\$29.95

TO ORDER:

SEE YOUR LOCAL
INSTANT SOFTWARE DEALER
OR CALL TOLL-FREE
1-800-258-5473

Instant Software™

PETERBOROUGH, N.H. 03458



16K Static Ram Board from Memory Merchants

- Low power 16K Static RAM (2114)
- Extended address - 24 bit
- Four independent 4 K blocks
- Bank select logic
- Runs with:
2 Mhz 8080, 4 Mhz Z80, 5 Mhz 8085

One of the 4K has "windowing" capability — any or all of the 1K sub-blocks may be removed from the memory block.

POWER:
5 v. (nominal 8V on S-100 bus)

ORGANIZATION:
Dip switch selection allows independent placement of any of the 4K blocks to any 4K boundary.
Dip switch control of windows.

BANK SELECT:
DIP switch array allows bank select port to be placed anywhere in I/O space. Jumper slide allows complete flexibility in choosing enable/disable within bank select port. DIP switch selection allows board to be enabled or disabled on power-on reset.

EXTENDED ADDRESS:
Independent DIP switch allows board to be addressed in any of the 256 64K extended address pages.

PHANTOM DISABLE/ENABLE:
Via DIP switch.

SPEED:
300 ns low power 2114 1Kx4 static memory chips. Compatible with 4 Mhz Z80, 5 Mhz 8085, and 2 Mhz 8080's.

DESIGN FEATURES:
Low power Schottky TTL circuitry. All input and outputs fully buffered. Meet specifications of IEEE 696 (S-100 standard).

CIRCUIT BOARD:
Highest quality FR4 epoxy glass material, solder mask, legend. Fully socketed.
Fully assembled and tested, with extended burn in. Serialized board.

WARRANTY
Extended warranty 6 months, no repair; instant replacement.

only \$189

The Best Prices and Deliveries

CALIFORNIA COMPUTER
64K Dynamic RAM
ONLY \$499

SYSTEM DESIGN
(Formerly Measurement Systems & Controls)
64K Dynamic RAM

DM6400 List \$795 **SPECIAL \$599**
DMB6400 w/Bank Select Special
List \$995 **SPECIAL \$799**
Cromix adapter for above \$44

Mini Micro Mart, Inc.

1618 James Street, Syracuse, NY 13203
(315) 422-4467 TWX 710-541-0431

Computers, Disk Systems

ZENITH | data systems



Z89-FA
List \$2895
OUR PRICE
\$2395



Z-89GA
List \$2595, Less Disk \$2149
A-87 Two Drive
Minifloppy System List \$1195. \$989
Z-47DA \$3695
8" Two Megabyte Disk System
List \$3695 \$3059

INTERSYSTEMS

formerly ITHACA AUDIO


The new Series II CPU Board features a 4 MHz Z-80A CPU and a full-feature front panel. 20-slot actively terminated motherboard, with 25 amp power supply (50/60 Hz operation, incl. 68 cfm fan). DPS-1.

CALL



COMPLETE SYSTEM with InterSystem 64K RAM, I/O Board and double density disk controller board. Full 1-year warranty.

CALL



NEW! CROMEMCO SYSTEM ZERO/D

A complete 64K Computer with Double Density Disk Controller List \$2995


OUR PRICE \$2545

Companion Disk drive for above —
Quad Density — Total of 780 Kilobytes of storage on the two drives. List \$1295

OUR PRICE \$1099

Only \$3644 for a complete 64K Disk System

SUPERBRAIN[®] By INTERTEC



64K Double or Quad Density units available. Uses two Z-80 CPU's. Commercial-type terminal with 12" monitor. Dual double density minifloppies. Over 350 kilobytes of storage (twice that with quad density drives). Two serial RS232 ports, I/O ports standard. Expandable with optional S-100 interface. Comes with CP/MTM 2.2 operating system. MiniMicroMart can supply a wide range of CP/M development and application software.

w/64K Double Density, List \$3495 .. **\$2869**
w/64K Quad Density, List \$3995. **\$3395**



**HEWLETT
PACKARD
HP-41CV**
\$259.



DYNABYTE DB 8/1



DB 8/1-64 — 64K RAM SYSTEM WITH Z80 CPU and 2 serial and 1 parallel I/O.
List \$3395, Disc. \$2850 **OUR PRICE \$2795**



**HEWLETT
PACKARD HP-85A**

Desk-Top
Computer
List
\$3250




\$2749

F.O.B. shipping point. All prices subject to change and all offers subject to withdrawal without notice. Advertised prices are for prepaid orders. Credit card and C.O.D. 2% higher. C.O.D. may require deposit.

MORROW THINKER TOYS[®] DISCUS M26[™]

26 megabytes of formatted storage
List \$4,995

\$4,199




THINKER TOYS[®] DISK SYSTEMS

Now includes CP/M[®] 2.2

Discus 2D, List \$1199 **\$998**
Discus 2D, dual-drive, List \$1994 \$1669
Discus 2 + 2, A&T, List \$1549 \$1299
Dual Discus 2 + 2, A&T, List \$2748 \$2299

All Morrow floppy disks include CP/M[®] 2.2 and Microsoft Basic 80

MORROW



List \$3695

DISCUS M-10
10 Megabyte
Wirchester

OUR PRICE

\$3095

NEW! CROMIX FROM CROMEMCO

A New UNIX Like
Disk Operating System,
With true multi-user,
multi-tasking capabilities

List \$295 **OUR PRICE \$249**

NEW! DOUBLE DENSITY CONTROLLER BOARD FROM CROMEMCO

With built-in diagnostics

16 FDC Controller, List \$595 **OUR PRICE \$505**


— WRITE FOR FREE CATALOG —

Mini Micro Mart, Inc. 1618 James Street, Syracuse, NY 13203
(315) 422-4467 TWX 710-541-0431

Terminals and Printers



data systems
Z19 Video Terminal



List \$995

OUR PRICE
\$799

Limited Time


Intertec

NEW INTERTUBE III

List \$995 **ONLY \$749**

12" display, 24 x 80 format, 18-key numeric keypad, 128 upper/lower case ASCII characters. Reverse video, blinking, complete cursor addressing and control. Special user-defined control function keys, protected and unprotected fields. Line insert/delete and character insert/delete editing, eleven special line drawing symbols.

TELEVIDEO TVI-912C



Upper and lower case, 15 baud rates: 75 to 19,000 baud, dual intensity, 24 x 80 character display, 12 x 10 resolution. Numeric pad. Programmable reversible video, auxiliary port, self-test mode, protect mode, block mode, tabbing, addressable cursor. Microprocessor controlled, programmable underline, line and character insert/delete. "C" version features typewriter-style keyboard. List \$950

CALL FOR PRICE


920C (with 11 function keys, 6 edit keys and 2 transmission mode keys, List \$1030

CALL FOR PRICE

950C List \$1195 **CALL FOR PRICE**

HAZELTINE 1500

Call
For
Price



1410 w/numeric keypad, List \$900 **CALL**
1420 w/lower case and numeric pad . . . **CALL**
1510, List \$1395 **CALL**
1520, List \$1650 **CALL**

SOROC



IQ-120

List \$995

SPECIAL

\$729

IQ135
\$749

IQ-140 List \$1495
SPECIAL \$1149

CENTRONICS PRINTERS

NEW 730, parallel, friction, tractor \$599
NEW 737 parallel, friction, tractor \$799
779-2 w/tractor (same as TRS-80 Line
Printer I), List \$1350 \$799
704-9 RS232 180CPS \$1595
704-11 Parallel 180CPS \$1695

NEC SPINWRITER™




Terminal/Keyboard as well as
RO Printer Only models available.

CALL FOR PRICES!

Above prices reflect a 2% cash discount (order prepaid prior to shipment). Add 2% to prices for credit card orders, C.O.D.'s, etc. Prices are f.o.b. shipping point. Prices are subject to change and offers subject to withdrawal without notice. **WRITE FOR FREE CATALOG.**

PAPER TIGER®




IDS 445 PAPER TIGER \$698
IDS 445G PAPER TIGER
Buffer w/graphics option, incl. buffer . . . \$789
NEW IDS 460/560

QUALITY PRINTING AT MATRIX
SPEED — LOGIC SEEKING
PROPORTIONAL SPACING

w/auto test justification

NEW IDS PAPERTIGER 460 List \$1295 . . \$1099
NEW IDS PAPERTIGER 460G List \$1394 . \$1149
NEW IDS 560G List \$1794 \$1499
TRS-80 cable \$45

TI-810



TI-810 Basic Unit, \$1895 **\$1595**
TI-810 w/full ASCII (Lower case), vertical
forms control, and compressed print . **\$1795**
TI-820w/lower case List \$1995 \$1645
TI-820w/full ASCII, forms control,
compressed print List \$2150 . \$1795
TI-745 Complete printing terminal
with acoustic coupler, List \$1695 . . . **\$1399**

ANADEx

DP9500 / DP9501 PRINTERS

DP-9500, List \$1650 **\$1349**

DP-9501, List \$1650 **\$1349**

ANADEx DP-8000

80-Col. Dot Matrix. **\$849**

OKIDATA

Microline 80 List \$599 **ONLY \$499**

Tractor Feed Option **\$109**

Serial interface **\$ 99**

Microline 82 List \$799 \$679

Microline 83 List \$1260 \$1069

AXIOM IMP I **\$699**

Epson MX-80 List \$645 **\$499**

MiniMicroMart, Inc.

1618 James Street, Syracuse NY 13203 (315) 422-4467 TWX 710-541-0431



The STD Bus Is Coming!

Will It Replace The S-100?

Back in mid-1978, Mostek Corp. and Pro-log Corp. devised an industrial approach to the booming microprocessor world to satisfy a need. That need was for standardization of the several powerful microprocessors that had become prolific in industrial control and application. The concept was so well defined, so inflexible, that it created its own flexibility at the system level.

With standardization, no longer did small companies worry about boards from different sources not playing together. With few exceptions, the mix-and-match of a wide variety of boards became possible. Almost overnight, sources of peripheral and special function cards became available to the harried microprocessor engineer.

CPU cards included the Z-80, 8085, 8080, 6800 and 6809 as the most popular. Although memory cards are necessarily limited by their small size (4.5 x 6.5 inches), 32K and even 48K cards became available. Density is certain to increase with the coming new families of RAM, and even bubble memory is not far in the future.

The STD Challenge

The STD Manufacturer's Group (STDMG) is a voluntary industry association whose purpose is to try and maintain order, and promote and preserve the STD bus concept. Over 30 manufacturers belong, and there are estimates of over 100 sources of STD bus products.

There have been several feeble attempts to introduce STD boards to the hobbyist with notably poor response. S-100 has a strong foothold, especially with the hardware-oriented hobbyist. Other bus systems have their followings, and the STD bus will have a difficult job becoming accepted in the home and

small-business computer markets.

Nevertheless, the movement is underway. A lot of engineers have built home systems with the STD bus after becoming familiar with it either through working with it or through the trade journals. A few manufacturers are starting to package complete systems. The first came with the manufacturer's development software; now most offer CP/M.

The problem STD manufacturers face is quantity. Board sales lend themselves best to OEM volumes with lots of follow-on orders. Manufacturers have just not been interested in catering to the hobbyist market.

The STD bus has no growth potential and will always be an eight-bit bus. The boards are basically limited to one function per board, causing a multitude of boards to be needed for a complete sys-

tem. The manufacturers are reluctant to become involved in the hobbyist market.

But the scene is about to change. As more and more STD bus systems become available, the hobbyist and small-business users will become prime targets. The ease of use and versatility have no parallel with any other system. Mail-order houses and dealers will be able to offer custom systems to fit anyone's needs and growth plans. Designers and tinkerers may try their hand with specialty cards with little worry that their efforts will be limited only to their systems. Users won't be continually modifying to make their new gizmo board play.

No doubt about it, the STD bus is coming, and those who want a versatile, easy-to-use family of cards had better take a hard look at all the STD bus has to offer. The wait will be well worth it. □

Q C MicroSystems
PO Box 401326
Garland, TX 75040
214-343-1282

STD Z-80 system with
eight-inch drives and CP/M 2.2

Intelligence Systems Limited
124 South Delaware St.
Indianapolis, IN 46204
317-631-5514

STD Z-80 or 6809 system with
eight-inch drives and Flex 3.0 and CP/M 2.2

Micro/Sys
1353 Foothill Blvd.
La Canada, CA 91011
213-790-7957

STD Z-80 or 8085 system with
eight-inch drive and CP/M 2.2

Mostek
1215 West Crosby Road
Carrollton, TX 75006
214-323-6000

STD Z-80 system with
eight-inch drives and FLP-80/MDX

For those with TRS-80 systems:

XITEX Corp.
9861 Chartwell Drive
Dallas, TX 75243
214-349-2490

TRS-80 to STD bus interface card

Don Langford is an engineer who resides at 3915 Brookline Circle, Huntsville, AL 35810.

Some companies now offering STD bus systems.

NEVER UNDER\$OLD.

Thats right. If you can find a lower price in this magazine WE WILL BEAT IT! Period.*

S-100 HARDWARE

SD SYSTEMS	
Versa Floppy I kit	\$259
Versa Floppy II kit	\$349
ExpandoRam II kit	\$249
ITHICA INTERSYSTEMS	\$CALL
ALTOS	\$CALL
NORTHSTAR	\$CALL

SUPPLIES

Verbatim Datalife Diskettes	
MD525-01,10,16	\$26.50
FD34-9000	\$30.00
FD34-8000	\$44.00

Avery Tabulables	
5,000 3 1/2 X 15/16	\$18.75
3,000 3 1/2 X 15/16	\$14.25
1,000 3 1/2 X 15/16	\$8.15

UARCO Paper (prices are FOB S.P.)	
9 1/2 X 11, 15 or 18 Lb.	\$25.95
14 7/8 X 11, 15 or 18 Lb.	\$35.00

SOFTWARE

Microsoft Basic-80	\$299
Microsoft Basic Compiler	\$319
Microsoft Fortran-80	\$399
Magic Wand	\$275
Apple Visicalc	\$113
Pickles and Trout CP/M®	\$175

APPLE HARDWARE

Microsoft Z-80 Softcard	\$259
Microsoft Ramcard	\$170
SSM AIO A&T	\$165
SYMTEC Apple Light Pen	\$219

MOUNTAIN HARDWARE:

Super Talker	\$270
ROMWRITER	\$157
INTROL/X-10	\$180
ROMPLUS+	\$162
MUSICSYSTEM	\$499
Apple Clock	\$252
Lobo Drive	\$CALL
Videx 80 x 24	\$299
Andromeda	\$170
M & R Sup-R-Term	\$299
Enhancer	\$100
NEC Green Monitor	\$240
Sanyo Green Monitor	\$240
D.C. Hayes Micromodem	\$299

CALIFORNIA COMPUTER


SYSTEMS
See our full page ad in this magazine.

PRINTERS

EPSON MX-80	CALL
MX-80 Graphics ROM	CALL
NEW EPSON MX-80 TF	CALL
Okidata Microline 80	\$415
Okidata Microline 82	\$625
Okidata Microline 83	\$899
IDS Paper Tiger 460G	\$1050
Anadex DP-9000,1	\$1195
Anadex DP-9500,1	\$1295
Centronics 737	\$689
NEC Spinwriter	\$CALL
NEC w/ Sellum Option	\$CALL
C. Itoh Starwriter 25 cps	\$1440
C. Itoh Starwriter 45 cps	\$1770
Diablo 630	\$2195
Malibu 165	\$1995
Malibu 200	\$CALL
MPI 88G	\$495

TRS-80 HARDWARE

TRS-80's	\$CALL
Micropolis 77 track	\$399
Percom Doubler	\$199
Percom Separator	\$27
Orchestra 80	\$79



**ALPHA
BYTE
STORES**

311

5115 Douglas Fir Road • Suite B • Calabasas, CA 91302

*Include \$2.00 shipping and handling on all orders. Visa and Master Card accepted. Never undersold offer applies only to items currently deliverable from other retail vendors at advertised price. All never undersold offers good as supply lasts. Please add \$2.00 for all COD orders. Please call for items not listed. We gladly answer any questions on all of our hardware, software, and supply needs. Quantity discounts available. School purchase orders accepted. Please remember to figure competitors shipping and handling charges when arriving at never undersold price.

(213) 883-8594



If you write software, write Digital Research.

We can help you bring your products to market.

Independent Software Vendors (ISV's) are the key to solving the software crunch in the 1980's. To help you bring your products to market, Digital Research introduces the ISV Support Plan — designed to assist you in:

Developing Your Product

- ☐ With the fast and powerful PL/I-80™ Programming System
- ☐ ISV Seminars covering high level applications programming

Getting Established in Your Market

ISV Seminars cover:

- ☐ Designing a marketing strategy
- ☐ Advertising
- ☐ Writing Manuals
- ☐ Assuring software security
- ☐ Supporting and updating products

On-Going Support Includes:


- ☐ Legal and technical information
- ☐ Distribution channels
- ☐ Printing facilities
- ☐ Free product listing in our Applications Software Catalog

All this plus the world's largest software marketplace — the CP/M® customer base.

So why do it alone? Write Digital Research. We'll send you our free brochure detailing the ISV Support Plan.

 **DIGITAL RESEARCH®**

P.O. Box 579
Pacific Grove, CA 93950
(408) 649-3896
TWX 910 360 5001



```
COMPILATION OF: LOAN:
mt:
proc options(main);
dcl
  m fixed binary;
  y fixed binary;
  P fixed decimal(11,2);
  PMT fixed decimal(6,2);
  i fixed decimal(4,2);
do while('1'b);
  put skip list('Principal ');
  set list(P);
  put list('Interest ');
  set list(i);
  put list('Payment ');
  set list(PMT);
  m = 0;
  y = 0;
  do while (P > 0);
    if mod(m,12) = 0 then
      put skip list('Year',y);
      m = m + 1;
      put skip list(m,P);
      P = P + round(i * P / 1200, 2);
      put list(PMT);
      P = P - PMT;
    end;
  end;
end;
end PMT;

IE = 01BA
EA = 003C
MS = 3C86
MPILATION
```

Handwritten notes on the document:

- do y =
- if P < PMT - 1
PMT = P